

بسم الله الرحمن الرحيم



جامعة بوليتكنك فلسطين

COURSE PROJECT

Course: Microprocessor and systems interfacing
Dr. Elayan Abugharbyeh

Group 1:

Osama Rafat Shawabkeh 231027

Zaid Adnan Qabaja 237539

Almotasembelah Yousef Shehada 231164

Bashar Abdullah Maree 231159

Memory Map:

Because Memory Foldback is not allowed, we have assumed that the A12 line is set to 1 in case of 4k RAMs.

1- Two 8k EPROM chips:

1- EPROM 1:

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	0	0	1	1	1	1	1	1	1	1	1	1	1	1	1

EPROM1 Address Range: (8000H – 9FFFH)

2- EPROM 2:

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	0	1	1	1	1	1	1	1	1	1	1	1	1	1	1

EPROM2 Address Range: (A000H – BFFFH)

2- Two 4k RAM chips:

1- RAM 1:

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	1	0	1	1	1	1	1	1	1	1	1	1	1	1	1

RAM1 Address Range: (D000H – DFFFH)

2- RAM 2:

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0

A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1

RAM2 Address Range: (F000H – FFFFH)

