YEAR 10 PHYSICS, AQA GCSE, LESSON 11 OF 12


ELECTRIC CIRCUITS

LESSON 11 POWER AND ENERGY TRANSFER

Which transfers more energy: a 3 kW kettle boiling for 3 minutes, or a 10 W LED lamp left on for 5 hours?

IN THIS LESSON YOU WILL

- describe power as the energy transferred per second
- use $E = P\,t$, $P = V\,I$ and $P = I^2\,R$ with the right units
- describe the energy transfers in everyday appliances
- choose the right equation for a question



NAME _____ CLASS _____

TEACHER _____ TARGET GRADE _____

START HERE

HOW THIS BOOKLET WORKS

This is the booklet for **Lesson 11** of the Electric Circuits unit. It builds on the lessons before it; the "Do now" questions and the quick answers at the back help you check what you remember. Keep it: it is your classwork book *and* your revision guide.

DO NOW
Quick questions from earlier lessons. Remembering again is what makes it stick.

LEARN IT
Explanations and diagrams. Fill in the slide examples with your teacher, then try "Your turn" alone.

TRY IT
Practice that builds up: first with support, then on your own. Quick checks from the slides follow some lessons.

LAB
Record measurements from a virtual lab or a required practical.

EXAM CORNER
An AQA-style question with a tip on how the marks are given.

REVISE IT
Summary, cover-and-answer questions and an "I can" check to colour in.

! **Revising at home?** (1) Read the Learn it pages. (2) Cover them and answer the "Cover the page" questions in Revise it. (3) Check with the quick answers at the back.

THE ROUTE THROUGH THE UNIT (THIS LESSON IS HIGHLIGHTED)

01 Complete circuits and symbols

02 Current and charge

03 Potential difference

04 Resistance and V = I R

05 Resistance of a wire RP

06 Series and parallel circuits

07 Resistors in series and parallel RP

08 I–V graphs

09 Investigating I–V characteristics RP

10 Thermistors, LDRs and sensors

11 Power and energy transfer
Power, E = P t, P = V I, P = I² R, energy transfers in appliances

12 Mains, safety and the National Grid

Lesson

11 POWER AND ENERGY TRANSFER

AQA Combined 6.2.4.1–6.2.4.2; Physics 4.2.4.1–4.2.4.2

BIG QUESTION **Which transfers more energy: a 3 kW kettle boiling for 3 minutes, or a 10 W LED lamp left on for 5 hours?**

BY THE END YOU CAN

- describe power as the energy transferred per second
- use E = P t, P = V I and P = I² R with the right units
- describe the energy transfers in everyday appliances
- choose the right equation for a question

power | **watt (W)** | **kilowatt (kW)** | **energy transferred** | **power rating**

RETRIEVE

DO NOW

From earlier lessons. No notes!

1
5.0 C passes through a 12 V lamp. How much energy is transferred?

2
2.0 A flows for 1 minute. How much charge flows?

3
What is the resistance of a heater with 230 V across it and 5.0 A through it?

EXPLAIN

HOW FAST IS ENERGY TRANSFERRED?

Power is the **energy transferred per second**. It is measured in **watts (W)**: 1 W = 1 J per second. A 2000 W (2 kW) kettle transfers 2000 J of energy every second.

APPLIANCE	TYPICAL POWER	ENERGY TRANSFERRED EACH SECOND
LED lamp	10 W	10 J
Laptop	60 W	60 J
Hairdryer	1.2 kW = 1200 W	1200 J
Kettle	2.2 kW = 2200 W	2200 J
Electric shower	9 kW = 9000 W	9000 J


Every appliance transfers energy electrically from the mains to other energy stores: a kettle to the **thermal store** of the water; a hairdryer's fan to **kinetic** energy and its heater to thermal; a phone charger to the **chemical store** of the battery.

E = P t

energy transferred = power × time

E in joules (J), P in watts (W), t in seconds (s)

Convert kW → W (× 1000) and minutes or hours → seconds first.



WITH YOUR TEACHER SLIDE 45

A 2.0 kW kettle is on for 3.0 minutes. Calculate the energy transferred.

CONVERT

EQUATION

SUBSTITUTE

ANSWER

YOUR TURN

A 1.2 kW hairdryer is used for 10 minutes. Calculate the energy transferred.

CONVERT

EQUATION


SUBSTITUTE

ANSWER

P = V I

power = p.d. × current


P in watts (W), V in volts (V), I in amperes (A)



$$P = I^2 R$$

power = current² × resistance

P in watts (W), I in amperes (A), R in ohms (Ω)



WITH YOUR TEACHER SLIDE 44

A heater on the 230 V mains draws a current of 4.0 A. Calculate its power.

EQUATION

SUBSTITUTE

ANSWER

YOUR TURN

A toaster on the 230 V mains draws a current of 3.0 A. Calculate its power.

EQUATION

SUBSTITUTE

ANSWER

WITH YOUR TEACHER SLIDE 44

A current of 2.0 A flows through a 15 Ω resistor. Calculate the power.

EQUATION

SUBSTITUTE

ANSWER

YOUR TURN

A current of 1.5 A flows through a 40 Ω resistor. Calculate the power.

EQUATION

SUBSTITUTE

ANSWER

! In P = I² R, **square the current first**. Doubling the current makes the heating **four times** bigger: that is why cables carrying big currents get hot.

IF YOU KNOW…	USE
p.d. and current	P = V I
current and resistance	P = I² R
power and time	E = P t
charge and p.d.	E = Q V
current and time	Q = I t

PRACTISE

TRY IT

1 Answer the big question. Show both calculations.

2 SUPPORTED A 24 V lorry headlamp draws a current of 3.0 A. Calculate its power.

EQUATION	
SUBSTITUTE	
ANSWER	unit:

3 **SUPPORTED** An 8.5 kW electric shower runs for 6.0 minutes. Calculate the energy transferred in joules.

CONVERT	
EQUATION	
SUBSTITUTE	
ANSWER	unit:

4 **ON YOUR OWN** A current of 2.0 A flows through a 10 Ω resistor. Then the current is increased to 4.0 A. Calculate the power each time. What happens to the power when the current doubles?

5 **ON YOUR OWN** A device transfers 240 J of energy when 40 C of charge flows through it. Calculate the p.d. across it.

6 **CHALLENGE** A lamp is rated 60 W, 230 V. Calculate the current through it and its resistance.

AQA-STYLE

EXAM CORNER

Write in full sentences. Show every step of a calculation.

> **Get the marks:** Write the power in watts before you substitute: 2.2 kW = 2200 W. Give answers to a sensible number of significant figures.

7 A 2.2 kW kettle runs on the 230 V mains. (a) Calculate the current through the kettle. (b) Calculate the energy transferred in 150 s. (c) A heater draws twice this current through the same resistance. How does its heating power compare? **[6 marks]**

REVIEW LATER

REVISE IT

Use this box after the lesson and before tests.

SUMMARY

- Power is energy transferred per second. 1 W = 1 J/s.
- **E = P t** (P in W, t in s).
- **P = V I** and **P = I² R**.
- Doubling the current through a resistor makes the heating 4 times bigger.
- Appliances transfer energy electrically to thermal, kinetic or chemical stores.

COVER THE PAGE AND ANSWER

1 What is power?

2 Convert 3.5 kW into watts.

3 Write two equations for electrical power.

4 Write the equation linking energy, power and time.

I CAN…

- describe power as energy transferred per second
- use E = P t with unit conversions
- use P = V I and P = I² R
- choose the right equation from the data given

REFERENCE

EQUATION TOOLKIT

The equations you have met so far. You will meet these one at a time. Learn each equation **in words** as well as symbols: AQA gives you an equation sheet in the exam (it does not include $R_{total} = R_1 + R_2$), but knowing the equations by heart makes every question faster.

$Q = I\,t$

Lesson 2

charge flow = current × time

C, A, s

Rearranged: I = Q ÷ t and t = Q ÷ I

$E = Q\,V$

Lesson 3

energy transferred = charge × p.d.

J, C, V

Rearranged: V = E ÷ Q and Q = E ÷ V

$V = I\,R$

Lesson 4

p.d. = current × resistance

V, A, Ω

Rearranged: I = V ÷ R and R = V ÷ I

$R_{total} = R_1 + R_2$

Lesson 6

total resistance in series

Ω

Rearranged: (series only)

$P = V\,I$

Lesson 11

power = p.d. × current

W, V, A

Rearranged: V = P ÷ I and I = P ÷ V

$P = I^2\,R$

Lesson 11

power = current² × resistance

W, A, Ω

Rearranged: R = P ÷ I² and I = √(P ÷ R)

$E = P\,t$

Lesson 11

energy transferred = power × time

J, W, s

Rearranged: P = E ÷ t and t = E ÷ P

FOUR STEPS FOR EVERY CALCULATION

1
Write down what you know, with units. Convert units first (minutes → seconds, kW → W, mA → A).

2
Write the equation you will use, in symbols.

3
Substitute the numbers, then rearrange if needed.


4
Give the answer with a unit. Ask: is it sensible?

CONVERT	HOW	EXAMPLE
minutes → seconds	× 60	3.0 min = 180 s
hours → seconds	× 3600	2.0 h = 7200 s
milliamps (mA) → amps (A)	÷ 1000	250 mA = 0.25 A
kilowatts (kW) → watts (W); kilohms (kΩ) → ohms (Ω)	× 1000	2.2 kW = 2200 W
kilovolts (kV) → volts (V)	× 1000	400 kV = 400 000 V


EQUATION TRIANGLES: HELP WITH REARRANGING

1. Cover the quantity you want to find.
2. The two left **side by side**? **Multiply** them.
3. One **above** the other? **Divide** the top by the bottom.


Example: to find I from Q = I t, cover I. Q is above t, so I = Q ÷ t. Triangles only help with rearranging: you still need to learn each equation. For P = I² R, the triangle gives I²; take the square root to find I.




Q = I t
Q = I × t
I = Q ÷ t
t = Q ÷ I




E = Q V
E = Q × V
Q = E ÷ V
V = E ÷ Q




V = I R
V = I × R
I = V ÷ R
R = V ÷ I



P = V I
P = V × I
V = P ÷ I
I = P ÷ V



P = I² R
P = I² × R
R = P ÷ I²
I² = P ÷ R, so I = √(P ÷ R)



E = P t
E = P × t
P = E ÷ t
t = E ÷ P

REFERENCE

KEY WORDS FROM THIS LESSON

Learn the meaning and spelling. In exams, precise words earn marks: say “p.d. across” and “current through”.

Power (P): Energy transferred per second. Unit: watt (W).

CHECK YOURSELF

QUICK ANSWERS

Answers to the “Do now” and “Cover the page” questions, so you can check yourself when revising. Answers to the longer questions are in your teacher's answer edition.

DO NOW

1. $E = Q\,V = 60$ J
2. $Q = 2.0 \times 60 = 120$ C
3. $R = 230 \div 5.0 = 46\ \Omega$

COVER THE PAGE

1. Energy transferred per second.
2. 3500 W
3. $P = V\,I$ and $P = I^2 R$
4. $E = P\,t$