

EXP-14- EMBEDDED C PROGRAM TO DISPLAY “HELLO WORLD” MESSAGE

CODE:

```
#include <reg51.h>

#include <stdio.h>

void main(void)
{
    SCON = 0x50;    // UART mode 1, 8-bit data, receiver enabled

    TMOD = 0x20;    // Timer 1, mode 2, 8-bit auto reload

    TH1 = 0xFD;     // 9600 baud rate

    TR1 = 1;        // Start Timer 1

    TI = 1;         // Set transmit interrupt flag

    while(1)
    {
        printf("Hello World!\n");
    }
}
```

CIRCUIT DIAGRAM:



