One ROM

Chip Type Specifications

This document provides detailed specifications for the different Chip types One ROM supports, and aims to support in future, including pinouts, control lines, and programming requirements.

One ROM firmware v0.8.1

8 November 2026

Built from one-rom 1b189260 · source `docs/CHIP-TYPES.md`

Copyright © 2026 Piers Finlayson <piers@piers.rocks> · MIT licence

https://onerom.org

Contents

24-pin Mask ROM Family (23xx) 4
28-pin Mask ROM Family (23xx) 4
32-pin Mask ROM Family (23xx) 5
24-pin EPROM Family (27xx) 5
28-pin EPROM Family (27xx) 5
32-pin EPROM Family (27xx) 6
40-pin EPROM Family (27xx) 6
24-pin EEPROM Family (28Cxx) 7
28-pin EEPROM Family (28Cxx) 7
32-pin EEPROM Family (28Cxx) 7
24-pin Bipolar PROM Family (HM76xx) 7
RAM Chips 8
Pin Function Comparison 8
- 24-pin Package 8
- 28-pin Package 9
- 32-pin Package 10
- 40-pin Package 11

Detailed Pinouts 12
- 2316 12
- 2332 13
- 2364 13
- 23128 13
- 23256 14
- 23QL384 14
- 23512 14
- 23QL512 15
- 231024 15
- 23C1001 15
- 23C1010 16
- 2704 16
- HM7641 17
- 2708 17
- 2716 17
- 28C16 18
- 6116 18
- 2732 19
- 2764 19
- 28C64 19

© 2026 Piers Finlayson · onerom.org · MIT licence

27128 20
27256 20
28C256 21
62256 21
27512 21
28C512 22
27C010 22
27C301 23
27C020 23
27C200 23
27C200Pin31NC 24
27C040 24
27C400 25
27C400Pin31A17 25
SST39SF040 25
27C080 26

© 2026 Piers Finlayson · onerom.org · MIT licence

This document provides detailed specifications for the different Chip types One ROM supports, and aims to support in future, including pinouts, control lines, and programming requirements.

The document is auto-generated from the json/chip-types.json configuration file. That file was created by researching datasheets for the various Chip types.

Some of the pin names have been modified from the datasheet values for consistency beween Chip types:

- /OE on 2704/2408 is called Program, but serves as /OE when in read mode. Other 27xx ROMs use /OE for that pin, hence the /OE name is used here.
- Similarly /CE on 2704/2708 ROMs is called /CS, but is called /CE for consistency with other ROM types.
- 23256/23512 chip select lines are often called CE/OE on datasheets, but are mask programmable to be active high or low, hence these are referred to within this doc as CS lines, like the other 23xx ROMs.
- Chips whose enables have a polarity fixed by the silicon use CE/OE where every enable is active low (the JEDEC convention followed by the 27xx and 28xx families). Where the enables are not all active low, CS lines are used instead: the HM7641 has CS1 and CS2 fixed active low, and CS3 and CS4 fixed active high. A leading `/` in the tables below indicates an active low line.

There are also some other inconsistencies between types:

- 2332's CS2 is pin 21 and pin 18 is A11. On the 2316, CS2 is pin 18, and CS3 pin 21.
- The 2332's A11 is pin18, but the 2732's A11 is pin 21.

24-pin Mask ROM Family (23xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
2316	9316, 9316A	2KB	11 (A0-A10)	CS1 (pin 20), CS2 (pin 18), CS3 (pin 21)	None	✓
2332	9332, 4732	4KB	12 (A0-A11)	CS1 (pin 20), CS2 (pin 21)	None	✓
2364	4764, MCM68764, MCM68A764, MCM68364, MCM68A364, MM52164, MK36000	8KB	13 (A0-A12)	CS1 (pin 20)	None	✓

28-pin Mask ROM Family (23xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
23128	HN613128P	16KB	14 (A0-A13)	CS1 (pin 20), CS2 (pin 22), CS3 (pin 27)	None	✓
23256		32KB	15 (A0-A14)	CS1 (pin 20), CS2 (pin 22)	None	✓

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
23QL384		48KB	16 (A0-A15)	CS1 (pin 22)	None	✓
23512		64KB	16 (A0-A15)	CS1 (pin 20), CS2 (pin 22)	None	✓
23QL512		64KB	16 (A0-A15)	CS1 (pin 22)	None	✓
231024	TC531000, 23C1000, 23C1000A, MX23C1000	128KB	17 (A0-A16)	CS1 (pin 20)	None	✓

32-pin Mask ROM Family (23xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
23C1001	D23C1001	128KB	17 (A0-A16)	/CE (pin 22), CS1 (pin 31), CS2 (pin 30), /OE (pin 24)	None	✓
23C1010		128KB	17 (A0-A16)	/CE (pin 22), /OE (pin 24)	None	✓

24-pin EPROM Family (27xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
2704		512B	9 (A0-A8)	/CE (pin 18), /OE (pin 20)	VPP: pin 18 (Low during read); PE: pin 20 (Low during read)	✓
2708		1KB	10 (A0-A9)	/CE (pin 18), /OE (pin 20)	VPP: pin 18 (Low during read); PE: pin 20 (Low during read)	✓
2716		2KB	11 (A0-A10)	/CE (pin 18), /OE (pin 20)	VPP: pin 21 (VCC during read); PE: pin 20 (Low during read)	✓
2732	27C32	4KB	12 (A0-A11)	/CE (pin 18), /OE (pin 20)	VPP: pin 20 (Acts as /OE); PE: pin 18 (Low during read)	✓

28-pin EPROM Family (27xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
2764	27C64, 27LC64	8KB	13 (A0-A12)	/CE (pin 20), /OE (pin 22)	VPP: pin 1 (VCC during read); /PGM: pin 27 (High during read)	✓
27128	27C128, 27LC128	16KB	14 (A0-A13)	/CE (pin 20), /OE (pin 22)	VPP: pin 1 (VCC during read); /PGM: pin 27 (High during read)	✓

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
27256	27C256, 27LC256, 27SF256	32KB	15 (A0-A14)	/CE (pin 20), /OE (pin 22)	VPP: pin 1 (VCC during read); PE: pin 22 (Low during read)	✓
27512	27C512, 27LC512, 27SF512	64KB	16 (A0-A15)	/CE (pin 20), /OE (pin 22)	VPP: pin 22 (VCC during read); PE: pin 20 (Low during read)	✓

32-pin EPROM Family (27xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
27C010	27C1001, 27C1000A, 29F010, 39SF010, SST39SF010	128KB	17 (A0-A16)	/CE (pin 22), /OE (pin 24)	VPP: pin 1 (Don't care during read); /PGM: pin 31 (Don't care during read)	✓
27C301	27C1000, 27C100	128KB	17 (A0-A16)	/CE (pin 22), /OE (pin 2)	VPP: pin 1 (Don't care during read); /PGM: pin 31 (Don't care during read)	✓
27C020	27C2001, 39SF020, 29F020, SST39SF020	256KB	18 (A0-A17)	/CE (pin 22), /OE (pin 24)	VPP: pin 1 (Don't care during read); /PGM: pin 31 (Don't care during read)	✓
27C040	27C4001	512KB	19 (A0-A18)	/CE (pin 22), /OE (pin 24)	VPP: pin 1 (Don't care during read); /PGM: pin 22 (Acts as /OE)	✓
SST39SF040	39SF040, 29F040	512KB	19 (A0-A18)	/CE (pin 22), /OE (pin 24), /WRITE (pin 31)	None	✓
27C080	27C801	1MB	20 (A0-A19)	/CE (pin 22), /OE (pin 24)	VPP: pin 24 (Acts as /OE); /PGM: pin 22 (Acts as /OE)	✓

40-pin EPROM Family (27xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
27C200	HN62402	256KB	18 (A0-A17)	/BYTE (pin 31), /CE (pin 10), /OE (pin 12)	None	✓
27C200Pin31NC		256KB	18 (A0-A17)	/CE (pin 10), /OE (pin 12)	None	✓

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
27C400	AT27C400, M27C400, 23C4100, MX23C4100, TCS534200, 27C4100, MX27C4100, HN62404, HN62424, MB834200	512KB	19 (A0-A18)	/BYTE (pin 31), /CE (pin 10), /OE (pin 12)	VPP: pin 31 (Selects word size during read); /PGM: pin 10 (Acts as /OE)	✓
27C400Pin31A17		512KB	19 (A0-A18)	/CE (pin 10), /OE (pin 12)	None	✓

24-pin EEPROM Family (28Cxx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
28C16		2KB	11 (A0-A10)	/CE (pin 18), /OE (pin 20), /WRITE (pin 21)	None	✓

28-pin EEPROM Family (28Cxx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
28C64		8KB	13 (A0-A12)	/BUSY (pin 1), /CE (pin 20), /OE (pin 22), /WRITE (pin 27)	None	✓
28C256		32KB	15 (A0-A14)	/CE (pin 20), /OE (pin 22), /WRITE (pin 27)	None	✓

32-pin EEPROM Family (28Cxx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
28C512		64KB	16 (A0-A15)	/CE (pin 22), /OE (pin 24), /WRITE (pin 30)	None	✓

24-pin Bipolar PROM Family (HM76xx)

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
HM7641		512B	9 (A0-A8)	/CS1 (pin 21), /CS2 (pin 20), CS3 (pin 19), CS4 (pin 18)	None	✓

© 2026 Piers Finlayson · onerom.org · MIT licence

RAM Chips

Chip Type	Aliases	Size	Address Lines	Control Lines	Programming	Supported
6116	2016	2KB	11 (A0-A10)	/CE (pin 18), /OE (pin 20), /WRITE (pin 21)	None	✓
62256		32KB	15 (A0-A14)	/CE (pin 20), /OE (pin 22), /WRITE (pin 27)	None	×

Pin Function Comparison

24-pin Package

Pin	2316	2332	2364	2704	HM7641	2708	2716	28C16	6116	2732
1	A7	A7	A7	A7	A7	A7	A7	A7	A7	A7
2	A6	A6	A6	A6	A6	A6	A6	A6	A6	A6
3	A5	A5	A5	A5	A5	A5	A5	A5	A5	A5
4	A4	A4	A4	A4	A4	A4	A4	A4	A4	A4
5	A3	A3	A3	A3	A3	A3	A3	A3	A3	A3
6	A2	A2	A2	A2	A2	A2	A2	A2	A2	A2
7	A1	A1	A1	A1	A1	A1	A1	A1	A1	A1
8	A0	A0	A0	A0	A0	A0	A0	A0	A0	A0
9	D0	D0	D0	D0	D0	D0	D0	D0	D0	D0
10	D1	D1	D1	D1	D1	D1	D1	D1	D1	D1
11	D2	D2	D2	D2	D2	D2	D2	D2	D2	D2
12	GND	GND	GND	GND	GND	GND	GND	GND	GND	GND
13	D3	D3	D3	D3	D3	D3	D3	D3	D3	D3
14	D4	D4	D4	D4	D4	D4	D4	D4	D4	D4
15	D5	D5	D5	D5	D5	D5	D5	D5	D5	D5
16	D6	D6	D6	D6	D6	D6	D6	D6	D6	D6
17	D7	D7	D7	D7	D7	D7	D7	D7	D7	D7
18	CS2	A11	A11	/CE+VPP	CS4	/CE+VPP	/CE	/CE	/CE	/CE+PE
19	A10	A10	A10	VDD	CS3	VDD	A10	A10	A10	A10
20	CS1	CS1	CS1	/OE+PE	/CS2	/OE+PE	/OE+PE	/OE	/OE	/OE+VPP
21	CS3	CS2	A12	VBB	/CS1	VBB	VPP	/WRITE	/WRITE	A11
22	A9	A9	A9	GND	NC	A9	A9	A9	A9	A9

© 2026 Piers Finlayson · onerom.org · MIT licence

Pin	2316	2332	2364	2704	HM7641	2708	2716	28C16	6116	2732
23	A8	A8	A8	A8	A8	A8	A8	A8	A8	A8
24	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC

28-pin Package

Pin	23128	23256	23QL384	23512	23QL512	231024	2764	28C64	27128	27256	28C256	62256	27512
1	NC	NC	NC	A15	NC	A15	VPP	/BUSY	VPP	VPP	A14	A14	A15
2	A12	A12	A12	A12	A12	A12	A12	A12	A12	A12	A12	A12	A12
3	A7	A7	A7	A7	A7	A7	A7	A7	A7	A7	A7	A7	A7
4	A6	A6	A6	A6	A6	A6	A6	A6	A6	A6	A6	A6	A6
5	A5	A5	A5	A5	A5	A5	A5	A5	A5	A5	A5	A5	A5
6	A4	A4	A4	A4	A4	A4	A4	A4	A4	A4	A4	A4	A4
7	A3	A3	A3	A3	A3	A3	A3	A3	A3	A3	A3	A3	A3
8	A2	A2	A2	A2	A2	A2	A2	A2	A2	A2	A2	A2	A2
9	A1	A1	A1	A1	A1	A1	A1	A1	A1	A1	A1	A1	A1
10	A0	A0	A0	A0	A0	A0	A0	A0	A0	A0	A0	A0	A0
11	D0	D0	D0	D0	D0	D0	D0	D0	D0	D0	D0	D0	D0
12	D1	D1	D1	D1	D1	D1	D1	D1	D1	D1	D1	D1	D1
13	D2	D2	D2	D2	D2	D2	D2	D2	D2	D2	D2	D2	D2
14	GND	GND	GND	GND	GND	GND	GND	GND	GND	GND	GND	GND	GND
15	D3	D3	D3	D3	D3	D3	D3	D3	D3	D3	D3	D3	D3
16	D4	D4	D4	D4	D4	D4	D4	D4	D4	D4	D4	D4	D4
17	D5	D5	D5	D5	D5	D5	D5	D5	D5	D5	D5	D5	D5
18	D6	D6	D6	D6	D6	D6	D6	D6	D6	D6	D6	D6	D6
19	D7	D7	D7	D7	D7	D7	D7	D7	D7	D7	D7	D7	D7
20	CS1	CS1	A15	CS1	A15	CS1	/CE	/CE	/CE	/CE	/CE	/CE	/CE+PE
21	A10	A10	A10	A10	A10	A10	A10	A10	A10	A10	A10	A10	A10
22	CS2	CS2	CS1	CS2	CS1	A16	/OE	/OE	/OE	/ OE+PE	/OE	/OE	/ OE+VPP
23	A11	A11	A11	A11	A11	A11	A11	A11	A11	A11	A11	A11	A11
24	A9	A9	A9	A9	A9	A9	A9	A9	A9	A9	A9	A9	A9
25	A8	A8	A8	A8	A8	A8	A8	A8	A8	A8	A8	A8	A8
26	A13	A13	A13	A13	A13	A13	NC	NC	A13	A13	A13	A13	A13

© 2026 Piers Finlayson · onerom.org · MIT licence

Pin	23128	23256	23QL384	23512	23QL512	231024	2764	28C64	27128	27256	28C256	62256	27512
27	CS3	A14	A14	A14	A14	A14	/ PGM	/ WRITE	/PGM	A14	/WRITE	/ WRITE	A14
28	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC

32-pin Package

Pin	23C1001	23C1010	28C512	27C010	27C301	27C020	27C040	SST39SF040	27C080
1	NC	NC	NC	VPP	VPP	VPP	VPP	A18	A19
2	A16	A16	NC	A16	/OE	A16	A16	A16	A16
3	A15	A15	A15	A15	A15	A15	A15	A15	A15
4	A12	A12	A12	A12	A12	A12	A12	A12	A12
5	A7	A7	A7	A7	A7	A7	A7	A7	A7
6	A6	A6	A6	A6	A6	A6	A6	A6	A6
7	A5	A5	A5	A5	A5	A5	A5	A5	A5
8	A4	A4	A4	A4	A4	A4	A4	A4	A4
9	A3	A3	A3	A3	A3	A3	A3	A3	A3
10	A2	A2	A2	A2	A2	A2	A2	A2	A2
11	A1	A1	A1	A1	A1	A1	A1	A1	A1
12	A0	A0	A0	A0	A0	A0	A0	A0	A0
13	D0	D0	D0	D0	D0	D0	D0	D0	D0
14	D1	D1	D1	D1	D1	D1	D1	D1	D1
15	D2	D2	D2	D2	D2	D2	D2	D2	D2
16	GND	GND	GND	GND	GND	GND	GND	GND	GND
17	D3	D3	D3	D3	D3	D3	D3	D3	D3
18	D4	D4	D4	D4	D4	D4	D4	D4	D4
19	D5	D5	D5	D5	D5	D5	D5	D5	D5
20	D6	D6	D6	D6	D6	D6	D6	D6	D6
21	D7	D7	D7	D7	D7	D7	D7	D7	D7
22	/CE	/CE	/CE	/CE	/CE	/CE	/CE+/PGM	/CE	/CE+/PGM
23	A10	A10	A10	A10	A10	A10	A10	A10	A10
24	/OE	/OE	/OE	/OE	A16	/OE	/OE	/OE	/OE+VPP
25	A11	A11	A11	A11	A11	A11	A11	A11	A11
26	A9	A9	A9	A9	A9	A9	A9	A9	A9
27	A8	A8	A8	A8	A8	A8	A8	A8	A8

© 2026 Piers Finlayson · onerom.org · MIT licence

Pin	23C1001	23C1010	28C512	27C010	27C301	27C020	27C040	SST39SF040	27C080
28	A13	A13	A13	A13	A13	A13	A13	A13	A13
29	A14	A14	A14	A14	A14	A14	A14	A14	A14
30	CS2	NC	/WRITE	NC	NC	A17	A17	A17	A17
31	CS1	NC	NC	/PGM	/PGM	/PGM	A18	/WRITE	A18
32	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC	VCC

40-pin Package

Pin	27C200	27C200Pin31NC	27C400	27C400Pin31A17
1	NC	NC	A18	NC
2	A8	A8	A8	A8
3	A7	A7	A7	A7
4	A6	A6	A6	A6
5	A5	A5	A5	A5
6	A4	A4	A4	A4
7	A3	A3	A3	A3
8	A2	A2	A2	A2
9	A1	A1	A1	A1
10	/CE	/CE	/CE+/PGM	/CE
11	GND	GND	GND	GND
12	/OE	/OE	/OE	/OE
13	D0	D0	D0	D0
14	D8	D8	D8	D8
15	D1	D1	D1	D1
16	D9	D9	D9	D9
17	D2	D2	D2	D2
18	D10	D10	D10	D10
19	D3	D3	D3	D3
20	D11	D11	D11	D11
21	VCC	VCC	VCC	VCC
22	D4	D4	D4	D4
23	D12	D12	D12	D12
24	D5	D5	D5	D5

© 2026 Piers Finlayson · onerom.org · MIT licence

Pin	27C200	27C200Pin31NC	27C400	27C400Pin31A17
25	D13	D13	D13	D13
26	D6	D6	D6	D6
27	D14	D14	D14	D14
28	D7	D7	D7	D7
29	A0+D15	A0+D15	A0+D15	A0+D15
30	GND	GND	GND	GND
31	/BYTE	NC	/BYTE+VPP	A18
32	A17	A17	A17	A17
33	A16	A16	A16	A16
34	A15	A15	A15	A15
35	A14	A14	A14	A14
36	A13	A13	A13	A13
37	A12	A12	A12	A12
38	A11	A11	A11	A11
39	A10	A10	A10	A10
40	A9	A9	A9	A9

Detailed Pinouts

2316 - 2KB mask ROM with 3 configurable CS lines

Package: 24-pin DIP
Capacity: 2048 bytes
Control: 3 configurable CS lines

Function	Pins	Notes
Address (A0-A10)	8,7,6,5,4,3,2,1,23,22,19	11 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
CS1	20	Configurable polarity
CS2	18	Configurable polarity
CS3	21	Configurable polarity
VCC	24	+5V
GND	12	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

2332 - 4KB mask ROM with 2 configurable CS lines

Package: 24-pin DIP
Capacity: 4096 bytes
Control: 2 configurable CS lines

Function	Pins	Notes
Address (A0-A11)	8,7,6,5,4,3,2,1,23,22,19,18	12 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
CS1	20	Configurable polarity
CS2	21	Configurable polarity
VCC	24	+5V
GND	12	0V

2364 - 8KB mask ROM with 1 configurable CS line

Package: 24-pin DIP
Capacity: 8192 bytes
Control: 1 configurable CS line

Function	Pins	Notes
Address (A0-A12)	8,7,6,5,4,3,2,1,23,22,19,18,21	13 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
CS1	20	Configurable polarity
VCC	24	+5V
GND	12	0V

23128 - 16KB mask ROM with 3 configurable CS lines

Package: 28-pin DIP
Capacity: 16384 bytes
Control: 3 configurable CS lines

Function	Pins	Notes
Address (A0-A13)	10,9,8,7,6,5,4,3,25,24,21,23,2,26	14 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
CS1	20	Configurable polarity
CS2	22	Configurable polarity
CS3	27	Configurable polarity
VCC	28	+5V
GND	14	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

23256 - 32KB mask ROM with 2 configurable CS lines

Package: 28-pin DIP
Capacity: 32768 bytes
Control: 2 configurable CS lines

Function	Pins	Notes
Address (A0-A14)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,27	15 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
CS1	20	Configurable polarity
CS2	22	Configurable polarity
VCC	28	+5V
GND	14	0V

23QL384 - A composite ROM type, serving a combined 23256 and 23128 for the Sinclair QL, with a single configured CS line and is de-selected when A14 & A15 are both high

Package: 28-pin DIP
Capacity: 49152 bytes
Control: 1 configurable CS line

Function	Pins	Notes
Address (A0-A15)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,27,20	16 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
CS1	22	Configurable polarity
VCC	28	+5V
GND	14	0V

23512 - 64KB mask ROM with 2 configurable CS lines

Package: 28-pin DIP
Capacity: 65536 bytes
Control: 2 configurable CS lines

Function	Pins	Notes
Address (A0-A15)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,27,1	16 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
CS1	20	Configurable polarity
CS2	22	Configurable polarity
VCC	28	+5V
GND	14	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

23QL512 - A composite ROM type, serving two combined 23256s for the Sinclair QL, with a single configured CS line at pin 22, and A15 at pin 20 instead of pin 1

Package: 28-pin DIP
Capacity: 65536 bytes
Control: 1 configurable CS line

Function	Pins	Notes
Address (A0-A15)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,27,20	16 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
CS1	22	Configurable polarity
VCC	28	+5V
GND	14	0V

231024 - 128KB mask ROM with 1 configurable CS line

Package: 28-pin DIP
Capacity: 131072 bytes
Control: 1 configurable CS line

Function	Pins	Notes
Address (A0-A16)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,27,1,22	17 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
CS1	20	Configurable polarity
VCC	28	+5V
GND	14	0V

23C1001 - 128KB mask programmed ROM with fixed active-low CE/OE, plus 2 programmable CS lines

Package: 32-pin DIP
Capacity: 131072 bytes
Control: 2 configurable CS lines, /CE, /OE

Function	Pins	Notes
Address (A0-A16)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,2	17 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
CS1	31	Configurable polarity
CS2	30	Configurable polarity
/OE	24	Active low
VCC	32	+5V

© 2026 Piers Finlayson · onerom.org · MIT licence

Function	Pins	Notes
GND	16	0V

23C1010 - 128KB mask ROM with fixed active-low CE/OE

Package: 32-pin DIP
Capacity: 131072 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A16)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,2	17 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	24	Active low
VCC	32	+5V
GND	16	0V

2704 - 512B EPROM with multiple supply voltages

Package: 24-pin DIP
Capacity: 512 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A8)	8,7,6,5,4,3,2,1,23	9 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
/CE	18	Active low
/OE	20	Active low
VPP	18	Low during read during read
PE	20	Low during read during read
VCC	24	+5V
VDD	19	+12V
VBB	21	-5V
GND	12	0V
GND	22	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

HM7641 - 512B bipolar PROM with three-state outputs and four fixed-polarity chip selects

Package: 24-pin DIP
Capacity: 512 bytes
Control: /CS1, /CS2, CS3, CS4

Function	Pins	Notes
Address (A0-A8)	8,7,6,5,4,3,2,1,23	9 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
/CS1	21	Active low
/CS2	20	Active low
CS3	19	Active high
CS4	18	Active high
VCC	24	+5V
GND	12	0V

2708 - 1KB EPROM with multiple supply voltages

Package: 24-pin DIP
Capacity: 1024 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A9)	8,7,6,5,4,3,2,1,23,22	10 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
/CE	18	Active low
/OE	20	Active low
VPP	18	Low during read during read
PE	20	Low during read during read
VCC	24	+5V
VDD	19	+12V
VBB	21	-5V
GND	12	0V

2716 - 2KB EPROM with fixed active-low CE/OE

Package: 24-pin DIP
Capacity: 2048 bytes
Control: /CE, /OE

© 2026 Piers Finlayson · onerom.org · MIT licence

Function	Pins	Notes
Address (A0-A10)	8,7,6,5,4,3,2,1,23,22,19	11 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
/CE	18	Active low
/OE	20	Active low
VPP	21	VCC during read during read
PE	20	Low during read during read
VCC	24	+5V
GND	12	0V

28C16 - 2KB EEPROM with fixed active-low CE/OE

Package: 24-pin DIP
Capacity: 2048 bytes
Control: /CE, /OE, /WRITE

Function	Pins	Notes
Address (A0-A10)	8,7,6,5,4,3,2,1,23,22,19	11 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
/CE	18	Active low
/OE	20	Active low
/WRITE	21	Active low
VCC	24	+5V
GND	12	0V

6116 - 2KB (2048 x 8-bit) Static RAM with fixed active-low CE/OE/WE

Package: 24-pin DIP
Capacity: 2048 bytes
Control: /CE, /OE, /WRITE

Function	Pins	Notes
Address (A0-A10)	8,7,6,5,4,3,2,1,23,22,19	11 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
/CE	18	Active low
/OE	20	Active low
/WRITE	21	Active low
VCC	24	+5V
GND	12	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

2732 - 4KB EPROM with fixed active-low CE and shared OE/VPP

Package: 24-pin DIP
Capacity: 4096 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A11)	8,7,6,5,4,3,2,1,23,22,19,21	12 address lines
Data (D0-D7)	9,10,11,13,14,15,16,17	8 data lines
/CE	18	Active low
/OE	20	Active low
VPP	20	Acts as /OE during read
PE	18	Low during read during read
VCC	24	+5V
GND	12	0V

2764 - 8KB EPROM with fixed active-low CE/OE

Package: 28-pin DIP
Capacity: 8192 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A12)	10,9,8,7,6,5,4,3,25,24,21,23,2	13 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
/CE	20	Active low
/OE	22	Active low
VPP	1	VCC during read during read
/PGM	27	High during read during read
VCC	28	+5V
GND	14	0V

28C64 - 8KB EEPROM with fixed active-low CE/OE

Package: 28-pin DIP
Capacity: 8192 bytes
Control: /BUSY, /CE, /OE, /WRITE

Function	Pins	Notes
Address (A0-A12)	10,9,8,7,6,5,4,3,25,24,21,23,2	13 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines

© 2026 Piers Finlayson · onerom.org · MIT licence

Function	Pins	Notes
/BUSY	1	Active low
/CE	20	Active low
/OE	22	Active low
/WRITE	27	Active low
VCC	28	+5V
GND	14	0V

27128 - 16KB EPROM with fixed active-low CE/OE

Package: 28-pin DIP
Capacity: 16384 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A13)	10,9,8,7,6,5,4,3,25,24,21,23,2,26	14 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
/CE	20	Active low
/OE	22	Active low
VPP	1	VCC during read during read
/PGM	27	High during read during read
VCC	28	+5V
GND	14	0V

27256 - 32KB EPROM with fixed active-low CE/OE

Package: 28-pin DIP
Capacity: 32768 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A14)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,27	15 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
/CE	20	Active low
/OE	22	Active low
VPP	1	VCC during read during read
PE	22	Low during read during read
VCC	28	+5V
GND	14	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

28C256 - 32KB EEPROM with fixed active-low CE/OE

Package: 28-pin DIP
Capacity: 32768 bytes
Control: /CE, /OE, /WRITE

Function	Pins	Notes
Address (A0-A14)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,1	15 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
/CE	20	Active low
/OE	22	Active low
/WRITE	27	Active low
VCC	28	+5V
GND	14	0V

62256 - 32KB (32768 x 8-bit) Static RAM with fixed active-low CE/OE/WE

Package: 28-pin DIP
Capacity: 32768 bytes
Control: /CE, /OE, /WRITE

Function	Pins	Notes
Address (A0-A14)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,1	15 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
/CE	20	Active low
/OE	22	Active low
/WRITE	27	Active low
VCC	28	+5V
GND	14	0V

27512 - 64KB EPROM with fixed active-low CE/OE

Package: 28-pin DIP
Capacity: 65536 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A15)	10,9,8,7,6,5,4,3,25,24,21,23,2,26,27,1	16 address lines
Data (D0-D7)	11,12,13,15,16,17,18,19	8 data lines
/CE	20	Active low
/OE	22	Active low

© 2026 Piers Finlayson · onerom.org · MIT licence

Function	Pins	Notes
VPP	22	VCC during read during read
PE	20	Low during read during read
VCC	28	+5V
GND	14	0V

28C512 - 64KB EEPROM with fixed active-low CE/OE

Package: 32-pin DIP
Capacity: 65536 bytes
Control: /CE, /OE, /WRITE

Function	Pins	Notes
Address (A0-A15)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3	16 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	24	Active low
/WRITE	30	Active low
VCC	32	+5V
GND	16	0V

27C010 - 128KB EPROM with fixed active-low CE/OE

Package: 32-pin DIP
Capacity: 131072 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A16)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,2	17 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	24	Active low
VPP	1	Don't care during read during read
/PGM	31	Don't care during read during read
VCC	32	+5V
GND	16	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

27C301 - 128KB EPROM with fixed active-low CE/OE

Package: 32-pin DIP
Capacity: 131072 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A16)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,24	17 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	2	Active low
VPP	1	Don't care during read during read
/PGM	31	Don't care during read during read
VCC	32	+5V
GND	16	0V

27C020 - 256KB EPROM with fixed active-low CE/OE

Package: 32-pin DIP
Capacity: 262144 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A17)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,2,30	18 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	24	Active low
VPP	1	Don't care during read during read
/PGM	31	Don't care during read during read
VCC	32	+5V
GND	16	0V

27C200 - 0.25MB mask programmed EPROM with fixed active-low CE/OE

Package: 40-pin DIP
Capacity: 262144 bytes
Control: /BYTE, /CE, /OE

Function	Pins	Notes
Address (A0-A17)	29,9,8,7,6,5,4,3,2,40,39,38,37,36,35,34,33,32	18 address lines
Data (D0-D15)	13,15,17,19,22,24,26,28,14,16,18,20,23,25,27,29	16 data lines

© 2026 Piers Finlayson · onerom.org · MIT licence

Function	Pins	Notes
/BYTE	31	Active low
/CE	10	Active low
/OE	12	Active low
VCC	21	+5V
GND	11	0V
GND	30	0V

27C200Pin31NC - 0.25MB EPROM with pin 31 unused and no /BYTE, as the Amiga A500 rev 5 PCB wires it

Package: 40-pin DIP
Capacity: 262144 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A17)	29,9,8,7,6,5,4,3,2,40,39,38,37,36,35,34,33,32	18 address lines
Data (D0-D15)	13,15,17,19,22,24,26,28,14,16,18,20,23,25,27,29	16 data lines
/CE	10	Active low
/OE	12	Active low
VCC	21	+5V
GND	11	0V
GND	30	0V

27C040 - 512KB EPROM with fixed active-low CE/OE

Package: 32-pin DIP
Capacity: 524288 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A18)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,2,30,31	19 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	24	Active low
VPP	1	Don't care during read during read
/PGM	22	Acts as /OE during read
VCC	32	+5V
GND	16	0V

© 2026 Piers Finlayson · onerom.org · MIT licence

27C400 - 0.5MB EPROM with fixed active-low CE/OE

Package: 40-pin DIP
Capacity: 524288 bytes
Control: /BYTE, /CE, /OE

Function	Pins	Notes
Address (A0-A18)	29,9,8,7,6,5,4,3,2,40,39,38,37,36,35,34,33,32,1	19 address lines
Data (D0-D15)	13,15,17,19,22,24,26,28,14,16,18,20,23,25,27,29	16 data lines
/BYTE	31	Active low
/CE	10	Active low
/OE	12	Active low
VPP	31	Selects word size during read during read
/PGM	10	Acts as /OE during read
VCC	21	+5V
GND	11	0V
GND	30	0V

27C400Pin31A17 - 0.5MB EPROM with A17 on pin 31 and no /BYTE, as the Amiga A500 rev 5 PCB wires it

Package: 40-pin DIP
Capacity: 524288 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A18)	29,9,8,7,6,5,4,3,2,40,39,38,37,36,35,34,33,32,31	19 address lines
Data (D0-D15)	13,15,17,19,22,24,26,28,14,16,18,20,23,25,27,29	16 data lines
/CE	10	Active low
/OE	12	Active low
VCC	21	+5V
GND	11	0V
GND	30	0V

SST39SF040 - 512KB flash with fixed active-low CE/OE and different pinout to 27C040

Package: 32-pin DIP
Capacity: 524288 bytes
Control: /CE, /OE, /WRITE

Function	Pins	Notes
Address (A0-A18)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,2,30,1	19 address lines

© 2026 Piers Finlayson · onerom.org · MIT licence

Function	Pins	Notes
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	24	Active low
/WRITE	31	Active low
VCC	32	+5V
GND	16	0V

27C080 - 1MB EPROM with fixed active-low CE/OE

Package: 32-pin DIP
Capacity: 1048576 bytes
Control: /CE, /OE

Function	Pins	Notes
Address (A0-A19)	12,11,10,9,8,7,6,5,27,26,23,25,4,28,29,3,2,30,31,1	20 address lines
Data (D0-D7)	13,14,15,17,18,19,20,21	8 data lines
/CE	22	Active low
/OE	24	Active low
VPP	24	Acts as /OE during read
/PGM	22	Acts as /OE during read
VCC	32	+5V
GND	16	0V

© 2026 Piers Finlayson · onerom.org · MIT licence