



Standalone Operation (SPI_MODE=GND)

CFG6/En
 GND -> Driver enabled
 Vio -> Driver disabled
 Open -> Driver enabled with ramp down from 100% to 34% after about 3s

CFG2	CFG1	Steps	Interpolation	Chopper Mode
GND	GND	1	No	spreadCycle
GND	Vio	2	No	spreadCycle
GND	Open	2	Yes to 256	spreadCycle
Vio	GND	4	No	spreadCycle
Vio	Vio	16	No	spreadCycle
Vio	Open	4	Yes to 256	spreadCycle
Open	GND	16	Yes to 256	spreadCycle
Open	Vio	4	Yes to 256	stealthChop
Open	Open	16	Yes to 256	stealthChop

Released under the Creative Commons
 Attribution Share-Alike License
<http://creativecommons.org/licenses/by-sa/4.0/>
 Designed by Stephan Watterott (Watterott electronic)
 Based on the Trinamic TMC2100-BOB

www.watterott.com

SilentStepStick-TMC2130_v10

06.03.2016 21:57

Sheet: 1/1

OSHW

Watterott



Component Side View
(Bottom)

