

# Engineering Science Data Booklet

## National 4/5

For use in National Qualification Courses  
leading to the 2014 examinations and beyond.

Publication date: 2019  
Publication code: BB6707  
ISBN: 978 1 85969 699 6

Published by the Scottish Qualifications Authority  
The Optima Building, 58 Robertson Street, Glasgow G2 8DQ  
Lowden, 24 Wester Shawfair, Dalkeith, Midlothian EH22 1FD

[www.sqa.org.uk](http://www.sqa.org.uk)

*The information in this publication may be reproduced in support of SQA qualifications. If it is reproduced, SQA should be clearly acknowledged as the source. If it is to be used for any other purpose, then written permission must be obtained from SQA. It must not be reproduced for trade or commercial purposes.*

© Scottish Qualifications Authority 2019

## Contents

|                               |     |
|-------------------------------|-----|
| Preface                       | 2   |
| Quantities, symbols and units | 3   |
| Decimal prefixes              | 4   |
| Relationships                 | 4-5 |
| Symbols for flowcharts        | 6   |

## Preface

This data booklet is intended for use by candidates in examinations in Engineering Science at National 5. It may also be used as a reference for assignments at National 4 and National 5. It is recommended that candidates should become familiar with the contents of the data booklet through use in undertaking Units of these Courses.

It should be noted that the range of data contained in the booklet has been limited to the concepts which may be assessed through written question papers. This range should be supplemented by other resource material as necessary during the course, eg by using data sheets. However, should any additional information (or data not included in this booklet) be required in an examination, such information will be included in the question paper.

Teachers/lecturers should note that all of the material contained in this booklet is likely to be examined at some time. With regard to tables of information, not every entry in a table will necessarily be involved in examination questions.

From the variety of data offered in this booklet, candidates will be expected to demonstrate the ability to select appropriate information or formulae.

## Quantities, Symbols and Units

| Quantity                      | Symbol         | Unit                                 | Abbreviation                      |
|-------------------------------|----------------|--------------------------------------|-----------------------------------|
| distance                      | d,x            | metre                                | m                                 |
| height                        | h              | metre                                | m                                 |
| length                        | l              | metre                                | m                                 |
| diameter                      | d              | metre                                | m                                 |
| radius                        | r              | metre                                | m                                 |
| area                          | A              | square metre                         | m <sup>2</sup>                    |
| circumference                 | C              | metre                                | m                                 |
| time                          | t              | second                               | s                                 |
| speed, velocity               | v              | metre per second                     | ms <sup>-1</sup>                  |
| mass                          | m              | kilogram                             | kg                                |
| force                         | F              | newton                               | N                                 |
| gravitational acceleration    | g              | metre per second per second          | ms <sup>-2</sup>                  |
| work done                     | E <sub>w</sub> | joule                                | J                                 |
| energy                        | E              | joule                                | J                                 |
| power                         | P              | watt                                 | W                                 |
| torque                        | T              | newton metre                         | Nm                                |
| efficiency                    | η              | -                                    | -                                 |
| pressure                      | P              | newton per square metre (pascal)     | Nm <sup>-2</sup> (Pa)             |
| temperature                   | T              | kelvin, celsius                      | K, °C                             |
| specific heat capacity        | c              | joule per kilogram per degree kelvin | Jkg <sup>-1</sup> K <sup>-1</sup> |
| voltage, potential difference | V              | volt                                 | V                                 |
| current                       | I              | ampere (amp)                         | A                                 |
| resistance                    | R              | ohm                                  | Ω                                 |
| frequency                     | f              | hertz                                | Hz                                |
| rotational speed              | n              | revolutions per minute               | revs min <sup>-1</sup>            |
|                               |                | revolutions per second               | revs sec <sup>-1</sup>            |
| stress                        | σ              | newton per square metre (pascal)     | Nm <sup>-2</sup> (Pa)             |
| strain                        | ε              |                                      |                                   |

## Decimal Prefixes

| Prefix | Symbol | Multiplying factor |
|--------|--------|--------------------|
| peta   | P      | $10^{15}$          |
| tera   | T      | $10^{12}$          |
| giga   | G      | $10^9$             |
| mega   | M      | $10^6$             |
| kilo   | k      | $10^3$             |
| milli  | m      | $10^{-3}$          |
| micro  | $\mu$  | $10^{-6}$          |
| nano   | n      | $10^{-9}$          |
| pico   | p      | $10^{-12}$         |

## Relationships

### Energy and power

|                   |                                                                                                                                    |                                                         |
|-------------------|------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------|
| Potential energy  | $E_p = mgh$                                                                                                                        | $g = 9.8 \text{ ms}^{-2}$ (to 2 significant figures)    |
| Kinetic energy    | $E_k = \frac{1}{2}mv^2$                                                                                                            |                                                         |
| Heat energy       | $E_h = cm\Delta T$                                                                                                                 | $c_{\text{water}} = 4180 \text{ Jkg}^{-1}\text{K}^{-1}$ |
| Electrical energy | $E_e = VIt$                                                                                                                        |                                                         |
| Work done         | $E_w = Fd$                                                                                                                         |                                                         |
| Power             | $P = \frac{E}{t}$                                                                                                                  |                                                         |
| Electrical power  | $P = VI = \frac{V^2}{R} = I^2R$                                                                                                    |                                                         |
| Mechanical power  | $P = Fv$                                                                                                                           | $P = 2\pi nT$ (n= no of revs per second)                |
| Efficiency        | $\eta = \frac{\text{Energy}_{\text{out}}}{\text{Energy}_{\text{in}}} = \frac{\text{Power}_{\text{out}}}{\text{Power}_{\text{in}}}$ |                                                         |

## Mechanisms

Velocity ratio  $VR = \frac{\text{speed of input}}{\text{speed of output}}$

$$\text{Input speed} \times \text{input size} = \text{output speed} \times \text{output size}$$

Torque  $T = Fr$

Circumference of circle  $C = \pi d$

Moment of force  $M = Fx$  (x is perpendicular distance)

Principle of moments  $\Sigma M = 0$

$$\Sigma \text{ clockwise moments} = \Sigma \text{ anti-clockwise moments}$$

Conditions of equilibrium  $\Sigma F_h = 0 \quad \Sigma F_v = 0 \quad \Sigma M = 0$

## Pneumatic Systems

Pressure, force and area  $P = \frac{F}{A}$

Area of circle  $A = \pi r^2 \quad A = \frac{\pi d^2}{4}$

## Structures

Stress  $\sigma = \frac{F}{A}$

Strain  $\epsilon = \frac{\Delta l}{l}$

## Electrical and electronic

Ohm's Law  $V = IR$

Resistors in series  $R_t = R_1 + R_2 + R_3 + \dots$

Resistors in parallel  $\frac{1}{R_t} = \frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_3} + \dots$



2 resistors in parallel  $R_t = \frac{R_1 R_2}{(R_1 + R_2)}$

Kirchhoff's 1st law (parallel branch)  $I_t = I_1 + I_2 + I_3 + \dots$

Kirchhoff's 2nd law (series circuit)  $V_t = V_1 + V_2 + V_3 + \dots$

Voltage Divider  $\frac{V_1}{V_2} = \frac{R_1}{R_2}$

## Symbols for Flowcharts

|                      |                                                                                     |                                                                                                                                                |
|----------------------|-------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| Terminator symbol    |    | Used for the start and end of a main program or sub-procedure.                                                                                 |
| Line symbol          |    | Shows the direction of program flow. For flow down or to the right, an arrow is not needed. For flow upwards or to the left, arrows are added. |
| Input/Output         |    | Used to control outputs or to show that data is being received.                                                                                |
| Process symbol       |    | Used for operations which take place within the microcontroller, for example a delay.                                                          |
| Decision symbol      |  | Program flow is determined by a “yes” or “no” answer to the question in the box.                                                               |
| Sub procedure symbol |  | Used to call a sub-procedure.                                                                                                                  |

[END OF DATA BOOKLET]

**Published:** August 2019

**Change since last published:**

Page 3: Symbol for circumference changed from 'c' to 'C' (correcting error)

Page 3: Symbol for strain changed from 'ε' to 'Ε' (correcting error)

Page 5: Value for  $\pi$  removed (use scientific calculator for this value)