


These output pins are the values of the x, y and z acceleration after the first order 500Hz low pass filter.


Top Level[1B], Filter[4D]
Top Level[1B], Filter[4B]
Top Level[1B], Filter[4A]

RAW-X
RAW-Y
RAW-Z

0.01uF capacitor is used in parallel with 10uF capacitor for decoupling, which reduces noise from the power supply.




3.3V power is supplied from the microcontroller. Voltage should range from 1.8V - 3.6V, ideally being 3V.



This subcircuit is used for the self-test routine. ST-CTRL is a GPIO pin from the ESP32. When ST-CTRL is high, the p-channel MOSFET stays closed, and the ADXL's self-test is not activated. When ST-CTRL goes to 0V (GND), the p-channel MOSFET opens, sending the 3.3V power supply into the ADXL's ST pin. The change in ADXL output should be -1.31g in the X-axis, +1.31g in the Y-axis, and +2.22g in the Z-axis.

This represents the pins on the ADXL that aren't connected to anything.



Title			ADXL335 Interface
Size	Number	Revision	
A	LUM-2026-SCH-002	v1.0	
Date:	5/22/2026	Sheet 2 of	9
File:	C:\Users\...\Accelerometer.SchDoc	Drawn By:	Leo Chinchilla