

Composing layers

Project: Image-pattern Network Investigation

1. Recall and choose your starting point

Try the recall before opening notes. Then use a different colour or a labelled second line to correct your explanation.

Activation functions

Without opening the old lesson, explain one key idea from Activation functions. Give an example and a mistake that the idea helps you avoid.

My remembered idea, example and correction

Dot products and weighted sums

Without opening the old lesson, explain one key idea from Dot products and weighted sums. Give an example and a mistake that the idea helps you avoid.

My remembered idea, example and correction

2. Practise with fading help

Use W2: Repair a dimension mismatch for Composing layers. Record the answer once; the lesson and workbook refer to the same attempt.

Given inputs · Procedure I chose · Middle steps · Result and check

Given inputs: _____

Procedure I chose: _____

Middle steps: _____

Result and check: _____

The step I completed without help, and the hint I needed

3. Individual reasoning check

Use the worked case for Composing layers. Proposed explanation: “The second hidden unit receives the first hidden unit output”. Decide whether this explanation is supported. Point to the step or supplied fact that decides; explain your repair if needed.

My explanation before partner discussion

4. Independent transfer case

Independent case: Compose a new network independently

A new model takes $[u, v]$. Compute $a = \text{ReLU}(u + v - 3)$, $b = \text{ReLU}(u - v)$, then $q = a + 2b - 1$. Trace both inputs $[2, 1]$ and $[1, 2]$, including scores before ReLU. Apply class 1 when $q \geq 0$. State the hidden and output vector sizes.

My independent explanation, trace and limits

Attempt this case before feedback. Record any help. Earlier examples below are further practice; a case already practised with feedback cannot establish fresh transfer.

5. W1 Trace the second worked case

For $x = [1, 3]$, write both scores, both ReLU activations and y using the lesson model.

My reasoning and evidence

6. W2 Repair a dimension mismatch

A revised hidden layer returns $[h_1, h_2, h_3]$. The output layer still has weights $[2, -1]$. Explain the mismatch and what must be specified before calculation.

My reasoning and evidence

7. W3 Use a revealing order check

Compare hidden vectors for $x = [4, 1]$ and $x = [3, 0]$. Which input reveals a bug that swaps h_1 and h_2 but keeps output weights unchanged? Give correct and swapped outputs for that input.

My reasoning and evidence

8. W4 Compose a new network independently

A new model takes $[u, v]$. Compute $a = \text{ReLU}(u + v - 3)$, $b = \text{ReLU}(u - v)$, then $q = a + 2b - 1$. Trace both inputs $[2, 1]$ and $[1, 2]$, including scores before ReLU. Apply class 1 when $q \geq 0$. State the hidden and output vector sizes.

My reasoning and evidence

9. W5 Explain information loss

Use the lesson model to verify h and y for $[0, 1]$ and $[0, 2]$. Could a fixed later layer receiving only h distinguish the two original inputs?

My reasoning and evidence

10. Project checkpoint and reflection

Add a labelled composing layers evidence sheet to Image-pattern Network Investigation. Show how you can trace how one layer supplies the next layer inputs. Use the supplied fictional case and keep its inputs, intermediate steps, calculation or prediction, and limitation. Connect this record to last week's record; a matching answer without a trace is insufficient.

My project change, supporting evidence and remaining limit

11. Feedback, return check and learning record

Evidence · My record

Evidence: Worked alone / hint / model

My record: _____

Evidence: First step I repaired and why

My record: _____

Evidence: New case checked later; date and result

My record: _____

Evidence: What I can now explain without notes

My record: _____

Evidence: One remaining question

My record: _____

Revisit this idea with your teacher after a delay. Familiarity is different from explaining and using it on a changed case.

12. Pictorial case practice: Composing layers

Compose two hidden detectors before one output instead of skipping a layer.

For input $[u, v]$, $h1 = \text{ReLU}(u-2)$, $h2 = \text{ReLU}(v-1)$, $y = h1 - h2$. Input $[4, 3]$.

All inputs and outcomes in this worked example are invented classroom data; no real model run is claimed.

Composing layers

Start with the supplied facts

Follow each arrow. Ask which fact allows the next step.



1. First hidden unit

$u-2=2$, so $h1=2$.



2. Second hidden unit

$v-1=2$, so $h2=2$.



3. Compose output

$y=2-2=0$; the output uses activated hidden values, not raw inputs.

CHANGE ONE THING

Change only v from 3 to 1.

Explain the changed result using the matching lesson.

What intermediate value explains the changed output? Point to the relevant step in the picture, then write the changed result and the rule or evidence that supports it.

My picture-based explanation and changed-case prediction

Support used: alone / hint / worked example. This record is practice evidence.

Project connection: For your Image-pattern Network Investigation, save the input, procedure, observed result and limitation of this check. Label this worked example as practice; use a different, previously unreviewed case when checking independent understanding.