<u>Peer Assessments (https://class.coursera.org/exdata-032/human_grading/)</u> / Course Project 1
<u>Help Center (https://accounts.coursera.org/i/zendesk/courserahelp?return_to=https://learner.coursera.help/hc)</u>

due in 5day 24h
Submission Phase
1. Do assignment ☐ (/exdata-032/human_grading/view/courses/975127/assessments/3/submissions)
Evaluation Phase
2. Evaluate peers
Results Phase
3. See results
■ In accordance with the Honor Code, I certify that my answers here are my own work, and that I have appropriately acknowledged all external sources (if any) that were used in this work.
Save draft Submit for grading

Introduction

This assignment uses data from the <u>UC Irvine Machine Learning Repository</u> (http://archive.ics.uci.edu/ml/), a popular repository for machine learning datasets. In particular, we will be using the "Individual household electric power consumption Data Set" which I have made available on the course web site:

- Dataset: <u>Electric power consumption</u>
 (https://d396qusza40orc.cloudfront.net/exdata%2Fdata%2Fhousehold_power_consumption.zip)
 [20Mb]
- **Description**: Measurements of electric power consumption in one household with a one-minute sampling rate over a period of almost 4 years. Different electrical quantities and some sub-metering values are available.

The following descriptions of the 9 variables in the dataset are taken from the <u>UCI web site</u> (https://archive.ics.uci.edu/ml/datasets/Individual+household+electric+power+consumption):

1. **Date**: Date in format dd/mm/yyyy

- 2. **Time**: time in format hh:mm:ss
- 3. Global_active_power: household global minute-averaged active power (in kilowatt)
- 4. Global reactive power: household global minute-averaged reactive power (in kilowatt)
- 5. Voltage: minute-averaged voltage (in volt)
- 6. **Global_intensity**: household global minute-averaged current intensity (in ampere)
- 7. **Sub_metering_1**: energy sub-metering No. 1 (in watt-hour of active energy). It corresponds to the kitchen, containing mainly a dishwasher, an oven and a microwave (hot plates are not electric but gas powered).
- 8. **Sub_metering_2**: energy sub-metering No. 2 (in watt-hour of active energy). It corresponds to the laundry room, containing a washing-machine, a tumble-drier, a refrigerator and a light.
- 9. **Sub_metering_3**: energy sub-metering No. 3 (in watt-hour of active energy). It corresponds to an electric water-heater and an air-conditioner.

Loading the data

When loading the dataset into R, please consider the following:

- The dataset has 2,075,259 rows and 9 columns. First calculate a rough estimate of how much memory the dataset will require in memory before reading into R. Make sure your computer has enough memory (most modern computers should be fine).
- We will only be using data from the dates 2007-02-01 and 2007-02-02. One alternative is to read the data from just those dates rather than reading in the entire dataset and subsetting to those dates.
- You may find it useful to convert the Date and Time variables to Date/Time classes in R using the strptime() and as.Date() functions.
- Note that in this dataset missing values are coded as ?

Making Plots

Our overall goal here is simply to examine how household energy usage varies over a 2-day period in February, 2007. Your task is to reconstruct the following plots below, all of which were constructed using the base plotting system.

First you will need to fork and clone the following GitHub repository: https://github.com/rdpeng/ExData_Plotting1 (https://github.com/rdpeng/ExData_Plotting1)


For each plot you should

- Construct the plot and save it to a PNG file with a width of 480 pixels and a height of 480 pixels.
- Name each of the plot files as plot1.png, plot2.png, etc.
- Create a separate R code file (plot1.R, plot2.R, etc.) that constructs the corresponding plot, i.e. code in plot1.R constructs the plot1.png plot. Your code file **should include code for reading** the data so that the plot can be fully reproduced. You must also include the code that creates the PNG file.
- Add the PNG file and R code file to the top-level folder of your git repository (no need for separate sub-folders)


When you are finished with the assignment, push your git repository to GitHub so that the GitHub version of your repository is up to date. There should be four PNG files and four R code files, a total of eight files in the top-level folder of the repo.

The four plots that you will need to construct are shown below.


Plot 1




Plot 2





Plot 3




Plot 4









Reviewing the Assignments

Keep in mind this course is about exploratory graphs, understanding the data, and developing strategies. Here's a good quote from a swirl lesson about exploratory graphs: "They help us find patterns in data and understand its properties. They suggest modeling strategies and help to debug analyses. We DON'T use exploratory graphs to communicate results."

The rubrics should always be interpreted in that context.

As you do your evaluation, please keep an open mind and focus on the positive. The goal is not to deduct points over small deviations from the requirements or for legitimate differences in implementation styles, etc. Look for ways to give points when it's clear that the submitter has given a good faith effort to do the project, and when it's likely that they've succeeded. Most importantly, it's okay if a person did something differently from the way that *you* did it. The point is not to see if someone managed to match your way of doing things, but to see if someone objectively accomplished the task at hand.

To that end, keep the following things in mind:

DO

- · Review the source code.
- Keep an open mind and focus on the positive.≤/li>
- When in doubt, err on the side of giving too many points, rather than giving too few.
- Ask yourself if a plot might answer a question for the person who created it.
- Remember that not everyone has the same statistical background and knowledge.

DON'T:

- Deduct just because you disagree with someone's statistical methods.
- Deduct just because you disagree with someone's plotting methods.
- Deduct based on aesthetics.

	I	≔	1 2 3	% Link	<code></code>	Math		Edit: Rich	~	Pre
-		, olu-	atio =	/foodba	ok op 4	ho ob	ove work			
							ut during the evaluation phase.			
	140									
		Was	a va	lid GitHul	b URL co	ntainin	g a git repository submitted?			
		-					NOT submitted (or URL is broken) to a GitHub repository			
						▼				
100							J			

Note: this section can only be filled out during the evaluation phase. Please examine the plot files in the GitHub repository. Do the plot files appear to be of the correct graphics file format? **0 points**: No, at least one of the files appears to be in the wrong format 1 point: Yes, all of the files appear to be in the correct format Please view the image file for Plot 1 from the GitHub repository. Does the plot appear correct? 0 points: No, the plot appears incorrect in at least 1 major discrepancy from the reference plot (e.g. wrong data), or at least 2 minor discrepancies (e.g. x-label is incorrect, title is incorrect), or the plot was not viewable 1 point: The plot is mostly correct with at most one minor discrepancy from the reference plot Please evaluate the code for Plot 1, but do not run the code on your computer. Does the code appear to create the plot reference plot given in the assignment? **0 points**: The code does not create the reference plot, or is not viewable/present in repository 1 point: The code is mostly correct, but does not reproduce the reference plot exactly **2 points**: The code reproduces the reference plot exactly Please view the image file for Plot 2 from the GitHub repository. Does the plot appear correct? 0 points: No, the plot appears incorrect in at least 1 major discrepancy from the reference plot (e.g. wrong data), or at least 2 minor discrepancies (e.g. x-label is incorrect, title is incorrect), or the plot was not viewable 1 point: The plot is mostly correct with at most one minor discrepancy from the reference

	•
	evaluate the code for Plot 2, but do not run the code on your computer. Does the opear to create the plot reference plot given in the assignment?
0 point	s: The code does not create the reference plot, or is not viewable/present in
-	:: The code is mostly correct, but does not reproduce the reference plot exactly s: The code reproduces the reference plot exactly
	•
correct	view the image file for Plot 3 from the GitHub repository. Does the plot appear
0 point plot (e.gincorre	ss: No, the plot appears incorrect in at least 1 major discrepancy from the reference g. wrong data), or at least 2 minor discrepancies (e.g. x-label is incorrect, title is ct), or the plot was not viewable :: The plot is mostly correct with at most one minor discrepancy from the reference
0 point plot (e.gincorrect 1 point	s: No, the plot appears incorrect in at least 1 major discrepancy from the reference g. wrong data), or at least 2 minor discrepancies (e.g. x-label is incorrect, title is ct), or the plot was not viewable
O point plot (e.gincorrect f point plot Please	s: No, the plot appears incorrect in at least 1 major discrepancy from the reference g. wrong data), or at least 2 minor discrepancies (e.g. x-label is incorrect, title is ct), or the plot was not viewable
O point plot (e.g incorrec 1 point plot Please code ap 0 point reposite 1 point	s: No, the plot appears incorrect in at least 1 major discrepancy from the reference g. wrong data), or at least 2 minor discrepancies (e.g. x-label is incorrect, title is ct), or the plot was not viewable the plot is mostly correct with at most one minor discrepancy from the reference evaluate the code for Plot 3, but do not run the code on your computer. Does the opear to create the plot reference plot given in the assignment?

correct?	e image file for Plot 4 from the GitHub repository. Does the plot appear
plot (e.g. wrong incorrect), or th	the plot appears incorrect in at least 1 major discrepancy from the reference of data), or at least 2 minor discrepancies (e.g. x-label is incorrect, title is the plot was not viewable of is mostly correct with at most one minor discrepancy from the reference
	•
	e the code for Plot 4, but do not run the code on your computer. Does the create the plot reference plot given in the assignment?
repository 1 point: The co	code does not create the reference plot, or is not viewable/present in ode is mostly correct, but does not reproduce the reference plot exactly code reproduces the reference plot exactly
	•
the work. Point	space below to provide constructive feedback to the student who submitted out the submission's strengths as well as areas in need of improvement. You his space to explain your grading decisions.

☐ In accordance with the Honor Code, I certify that my answers here are my own work, and that I have appropriately acknowledged all external sources (if any) that were used in this work.

Save draft

Submit for grading