

Never connect a Uno pin straight to the CC1101: 5 V can damage it.


Put C1 and C2 at the CC1101 VCC and GND pins.

ANT: 315 MHz antenna, or a 23.8 cm wire on modules with a solder pad.

GDO0 and GDO2 stay unconnected: this build only transmits.

Opening the serial port resets a Uno, and the sketch then forgets the fireplace state.





Bench build. The level shifter is required: the CC1101 is not 5 V tolerant. Not yet built.

rileyschuit/Proflame2-Remote

Sheet: /
File: uno_cc1101.kicad_sch

Title: Arduino Uno R3 + CC1101 fireplace remote (serial only)

Size: A4	Date:	**Rev: 0.1**
KiCad E.D.A. 9.0.8		Id: 1/1