

GATE EC: Signals and Systems

Previous Year Solved Questions (238 Questions)

PracticePaper.in Archive

July 27, 2026

Contents

Question 1: Basics of Signals Systems (GATE EC 2026)	2
Question 2: LTI Systems (GATE EC 2026)	3
Question 3: Fourier Transforms (GATE EC 2026)	4
Question 4: Basics of Signals Systems (GATE EC 2026)	5
Question 5: Fourier Series (GATE EC 2026)	6
Question 6: LTI Systems (GATE EC 2026)	7
Question 7: LTI Systems (GATE EC 2026)	8
Question 8: Sampling (GATE EC 2026)	9
Question 9: Laplace Transform (GATE EC 2026)	10
Question 10: Fourier Series (GATE EC 2025)	11
Question 11: Sampling (GATE EC 2025)	12
Question 12: DTFS, DTFT DFT (GATE EC 2025)	13
Question 13: Fourier Transforms (GATE EC 2025)	14
Question 14: LTI Systems (GATE EC 2025)	14
Question 15: DTFS, DTFT DFT (GATE EC 2024)	16
Question 16: Basics of Signals Systems (GATE EC 2024)	16
Question 17: Fourier Transforms (GATE EC 2024)	17
Question 18: Fourier Transforms (GATE EC 2024)	19
Question 19: LTI Systems (GATE EC 2024)	21
Question 20: LTI Systems (GATE EC 2024)	21
Question 21: LTI Systems (GATE EC 2023)	22

Question 22: Fourier Transforms (GATE EC 2023)	23
Question 23: Sampling (GATE EC 2023)	24
Question 24: LTI Systems (GATE EC 2023)	27
Question 25: DTFS, DTFT DFT (GATE EC 2023)	29
Question 26: DTFS, DTFT DFT (GATE EC 2023)	29
Question 27: Basics of Signals Systems (GATE EC 2023)	30
Question 28: Fourier Transforms (GATE EC 2023)	31
Question 29: Basics of Signals Systems (GATE EC 2023)	31
Question 30: LTI Systems (GATE EC 2023)	33
Question 31: DTFS, DTFT DFT (GATE EC 2022)	33
Question 32: LTI Systems (GATE EC 2022)	34
Question 33: LTI Systems (GATE EC 2022)	36
Question 34: DTFS, DTFT DFT (GATE EC 2022)	37
Question 35: DTFS, DTFT DFT (GATE EC 2021)	37
Question 36: LTI Systems (GATE EC 2021)	38
Question 37: Fourier Transforms (GATE EC 2021)	39
Question 38: DTFS, DTFT DFT (GATE EC 2021)	40
Question 39: Sampling (GATE EC 2021)	41
Question 40: Z-Transform (GATE EC 2020)	43
Question 41: Fourier Transforms (GATE EC 2020)	43
Question 42: DTFS, DTFT DFT (GATE EC 2020)	44
Question 43: LTI Systems (GATE EC 2020)	45
Question 44: LTI Systems (GATE EC 2020)	47
Question 45: Digital Filters (GATE EC 2019)	48
Question 46: DTFS, DTFT DFT (GATE EC 2019)	48
Question 47: DTFS, DTFT DFT (GATE EC 2019)	49
Question 48: Basics of Signals Systems (GATE EC 2019)	50
Question 49: Laplace Transform (GATE EC 2019)	51
Question 50: Z-Transform (GATE EC 2019)	51
Question 51: DTFS, DTFT DFT (GATE EC 2018)	53

Question 52: Sampling (GATE EC 2018)	53
Question 53: Fourier Transforms (GATE EC 2018)	55
Question 54: Fourier Series (GATE EC 2018)	56
Question 55: Z-Transform (GATE EC 2018)	57
Question 56: Basics of Signals Systems (GATE EC 2018)	58
Question 57: LTI Systems (GATE EC 2017-SET-2)	59
Question 58: Laplace Transform (GATE EC 2017-SET-2)	61
Question 59: Sampling (GATE EC 2017-SET-2)	61
Question 60: Fourier Transforms (GATE EC 2017-SET-2)	62
Question 61: Basics of Signals Systems (GATE EC 2017-SET-2)	63
Question 62: DTFS, DTFT DFT (GATE EC 2017-SET-2)	64
Question 63: Fourier Transforms (GATE EC 2017-SET-1)	64
Question 64: DTFS, DTFT DFT (GATE EC 2017-SET-1)	65
Question 65: Fourier Series (GATE EC 2017-SET-1)	66
Question 66: LTI Systems (GATE EC 2017-SET-1)	66
Question 67: Laplace Transform (GATE EC 2017-SET-1)	67
Question 68: Fourier Series (GATE EC 2017-SET-1)	68
Question 69: Basics of Signals Systems (GATE EC 2017-SET-1)	68
Question 70: Digital Filters (GATE EC 2016-SET-3)	69
Question 71: DTFS, DTFT DFT (GATE EC 2016-SET-3)	70
Question 72: Z-Transform (GATE EC 2016-SET-3)	71
Question 73: Laplace Transform (GATE EC 2016-SET-3)	72
Question 74: Z-Transform (GATE EC 2016-SET-3)	74
Question 75: Fourier Transforms (GATE EC 2016-SET-3)	74
Question 76: Sampling (GATE EC 2016-SET-3)	76
Question 77: DTFS, DTFT DFT (GATE EC 2016-SET-2)	76
Question 78: Digital Filters (GATE EC 2016-SET-2)	77
Question 79: Fourier Transforms (GATE EC 2016-SET-2)	77
Question 80: DTFS, DTFT DFT (GATE EC 2016-SET-1)	78
Question 81: Laplace Transform (GATE EC 2016-SET-1)	79

Question 82: Fourier Transforms (GATE EC 2016-SET-1)	80
Question 83: Laplace Transform (GATE EC 2016-SET-1)	81
Question 84: Sampling (GATE EC 2016-SET-1)	82
Question 85: Z-Transform (GATE EC 2016-SET-1)	83
Question 86: Basics of Signals Systems (GATE EC 2016-SET-1)	84
Question 87: LTI Systems (GATE EC 2016-SET-1)	84
Question 88: Laplace Transform (GATE EC 2016-SET-1)	85
Question 89: Basics of Signals Systems (GATE EC 2015-SET-3)	85
Question 90: Sampling (GATE EC 2015-SET-3)	86
Question 91: DTFS, DTFT DFT (GATE EC 2015-SET-3)	86
Question 92: Z-Transform (GATE EC 2015-SET-3)	87
Question 93: Z-Transform (GATE EC 2015-SET-3)	88
Question 94: Z-Transform (GATE EC 2015-SET-3)	88
Question 95: LTI Systems (GATE EC 2015-SET-3)	89
Question 96: DTFS, DTFT DFT (GATE EC 2015-SET-3)	89
Question 97: Fourier Transforms (GATE EC 2015-SET-3)	90
Question 98: Laplace Transform (GATE EC 2015-SET-2)	90
Question 99: DTFS, DTFT DFT (GATE EC 2015-SET-2)	91
Question 100: Laplace Transform (GATE EC 2015-SET-2)	91
Question 101: Laplace Transform (GATE EC 2015-SET-2)	92
Question 102: Sampling (GATE EC 2015-SET-2)	92
Question 103: Z-Transform (GATE EC 2015-SET-2)	93
Question 104: Laplace Transform (GATE EC 2015-SET-2)	93
Question 105: Fourier Series (GATE EC 2015-SET-2)	94
Question 106: Laplace Transform (GATE EC 2015-SET-2)	95
Question 107: Z-Transform (GATE EC 2015-SET-1)	96
Question 108: Z-Transform (GATE EC 2015-SET-1)	97
Question 109: DTFS, DTFT DFT (GATE EC 2015-SET-1)	98
Question 110: Basics of Signals Systems (GATE EC 2015-SET-1)	99
Question 111: LTI Systems (GATE EC 2015-SET-1)	100

Question 112: DTFS, DTFT DFT (GATE EC 2014-SET-4)	100
Question 113: Laplace Transform (GATE EC 2014-SET-4)	101
Question 114: Laplace Transform (GATE EC 2014-SET-4)	102
Question 115: Laplace Transform (GATE EC 2014-SET-4)	102
Question 116: DTFS, DTFT DFT (GATE EC 2014-SET-4)	103
Question 117: Fourier Transforms (GATE EC 2014-SET-4)	104
Question 118: DTFS, DTFT DFT (GATE EC 2014-SET-4)	105
Question 119: Sampling (GATE EC 2014-SET-4)	106
Question 120: Z-Transform (GATE EC 2014-SET-3)	107
Question 121: Laplace Transform (GATE EC 2014-SET-3)	107
Question 122: Z-Transform (GATE EC 2014-SET-3)	108
Question 123: Fourier Transforms (GATE EC 2014-SET-3)	109
Question 124: Laplace Transform (GATE EC 2014-SET-3)	109
Question 125: Z-Transform (GATE EC 2014-SET-3)	110
Question 126: Sampling (GATE EC 2014-SET-3)	110
Question 127: Fourier Transforms (GATE EC 2014-SET-2)	112
Question 128: Z-Transform (GATE EC 2014-SET-2)	112
Question 129: LTI Systems (GATE EC 2014-SET-2)	113
Question 130: Fourier Series (GATE EC 2014-SET-2)	114
Question 131: Z-Transform (GATE EC 2014-SET-2)	116
Question 132: DTFS, DTFT DFT (GATE EC 2014-SET-2)	116
Question 133: Laplace Transform (GATE EC 2014-SET-1)	117
Question 134: DTFS, DTFT DFT (GATE EC 2014-SET-1)	117
Question 135: Z-Transform (GATE EC 2014-SET-1)	118
Question 136: Fourier Transforms (GATE EC 2014-SET-1)	119
Question 137: Fourier Transforms (GATE EC 2014-SET-1)	120
Question 138: Sampling (GATE EC 2014-SET-1)	120
Question 139: Basics of Signals Systems (GATE EC 2014-SET-1)	120
Question 140: DTFS, DTFT DFT (GATE EC 2013)	121
Question 141: Laplace Transform (GATE EC 2013)	122

Question 142: Basics of Signals Systems (GATE EC 2013)	122
Question 143: Laplace Transform (GATE EC 2013)	123
Question 144: Laplace Transform (GATE EC 2013)	124
Question 145: Sampling (GATE EC 2013)	124
Question 146: Basics of Signals Systems (GATE EC 2013)	125
Question 147: Laplace Transform (GATE EC 2013)	125
Question 148: LTI Systems (GATE EC 2013)	126
Question 149: LTI Systems (GATE EC 2012)	126
Question 150: Fourier Transforms (GATE EC 2012)	129
Question 151: Basics of Signals Systems (GATE EC 2012)	131
Question 152: Z-Transform (GATE EC 2012)	131
Question 153: Laplace Transform (GATE EC 2012)	132
Question 154: DTFS, DTFT DFT (GATE EC 2011)	133
Question 155: Z-Transform (GATE EC 2011)	134
Question 156: Laplace Transform (GATE EC 2011)	134
Question 157: Laplace Transform (GATE EC 2011)	135
Question 158: Fourier Series (GATE EC 2011)	136
Question 159: Laplace Transform (GATE EC 2011)	136
Question 160: LTI Systems (GATE EC 2011)	136
Question 161: Z-Transform (GATE EC 2010)	137
Question 162: Laplace Transform (GATE EC 2010)	138
Question 163: Laplace Transform (GATE EC 2010)	138
Question 164: DTFS, DTFT DFT (GATE EC 2010)	139
Question 165: Z-Transform (GATE EC 2010)	139
Question 166: Z-Transform (GATE EC 2010)	140
Question 167: Fourier Series (GATE EC 2010)	140
Question 168: Sampling (GATE EC 2009)	142
Question 169: DTFS, DTFT DFT (GATE EC 2009)	143
Question 170: Fourier Transforms (GATE EC 2009)	143
Question 171: DTFS, DTFT DFT (GATE EC 2009)	144

Question 172: Laplace Transform (GATE EC 2009)	145
Question 173: Z-Transform (GATE EC 2009)	146
Question 174: Fourier Transforms (GATE EC 2009)	146
Question 175: Fourier Series (GATE EC 2009)	146
Question 176: Fourier Transforms (GATE EC 2008)	147
Question 177: Fourier Transforms (GATE EC 2008)	148
Question 178: Z-Transform (GATE EC 2008)	148
Question 179: Z-Transform (GATE EC 2008)	149
Question 180: DTFS, DTFT DFT (GATE EC 2008)	150
Question 181: Basics of Signals Systems (GATE EC 2008)	151
Question 182: LTI Systems (GATE EC 2008)	151
Question 183: Fourier Transforms (GATE EC 2008)	152
Question 184: LTI Systems (GATE EC 2008)	153
Question 185: Basics of Signals Systems (GATE EC 2008)	154
Question 186: Z-Transform (GATE EC 2007)	154
Question 187: DTFS, DTFT DFT (GATE EC 2007)	155
Question 188: Basics of Signals Systems (GATE EC 2007)	155
Question 189: Fourier Transforms (GATE EC 2007)	156
Question 190: Laplace Transform (GATE EC 2007)	156
Question 191: Basics of Signals Systems (GATE EC 2006)	157
Question 192: Sampling (GATE EC 2006)	157
Question 193: Laplace Transform (GATE EC 2006)	160
Question 194: Z-Transform (GATE EC 2006)	160
Question 195: Basics of Signals Systems (GATE EC 2006)	161
Question 196: Fourier Transforms (GATE EC 2006)	162
Question 197: Z-Transform (GATE EC 2006)	162
Question 198: DTFS, DTFT DFT (GATE EC 2005)	163
Question 199: DTFS, DTFT DFT (GATE EC 2005)	164
Question 200: Fourier Transforms (GATE EC 2005)	166
Question 201: DTFS, DTFT DFT (GATE EC 2005)	166

Question 202: DTFS, DTFT DFT (GATE EC 2005)	167
Question 203: Fourier Transforms (GATE EC 2005)	167
Question 204: Laplace Transform (GATE EC 2005)	168
Question 205: Basics of Signals Systems (GATE EC 2005)	168
Question 206: DTFS, DTFT DFT (GATE EC 2005)	169
Question 207: LTI Systems (GATE EC 2005)	169
Question 208: Z-Transform (GATE EC 2005)	170
Question 209: Basics of Signals Systems (GATE EC 2005)	171
Question 210: Fourier Series (GATE EC 2005)	173
Question 211: Fourier Transforms (GATE EC 2004)	173
Question 212: DTFS, DTFT DFT (GATE EC 2004)	174
Question 213: Z-Transform (GATE EC 2004)	175
Question 214: Basics of Signals Systems (GATE EC 2004)	176
Question 215: Fourier Transforms (GATE EC 2004)	176
Question 216: Sampling (GATE EC 2004)	178
Question 217: Fourier Transforms (GATE EC 2004)	179
Question 218: Z-Transform (GATE EC 2004)	179
Question 219: LTI Systems (GATE EC 2004)	180
Question 220: Sampling (GATE EC 2003)	180
Question 221: Fourier Transforms (GATE EC 2003)	182
Question 222: Fourier Transforms (GATE EC 2003)	182
Question 223: Basics of Signals Systems (GATE EC 2003)	183
Question 224: Z-Transform (GATE EC 2003)	184
Question 225: Fourier Transforms (GATE EC 2003)	185
Question 226: Fourier Series (GATE EC 2003)	185
Question 227: Laplace Transform (GATE EC 2003)	186
Question 228: Z-Transform (GATE EC 2002)	186
Question 229: Laplace Transform (GATE EC 2002)	187
Question 230: Fourier Transforms (GATE EC 2002)	188
Question 231: Fourier Transforms (GATE EC 2002)	188

Question 232: Fourier Series (GATE EC 2002)	189
Question 233: LTI Systems (GATE EC 2002)	190
Question 234: LTI Systems (GATE EC 2001)	190
Question 235: Basics of Signals Systems (GATE EC 2001)	191
Question 236: Basics of Signals Systems (GATE EC 2001)	191
Question 237: Z-Transform (GATE EC 2001)	192
Question 238: Laplace Transform (GATE EC 2001)	192

Question 1: Basics of Signals & Systems (GATE EC 2026)

MSQ

2 Marks

Let $x_1(t) = \cos(2\pi nt)$ and $x_2(t) = 2\sin(4\pi nt)$ represent two sinusoids for a positive integer n and $-\infty < t < \infty$.

Which of the following statements about $x_1(t)$ and $x_2(t)$ is/are valid?

- (A) **(Correct)** $x_1(t)$ and $x_2(t)$ are orthogonal to each other over $0 \leq t < 1/n$.
- (B) $x_1(t)$ and $x_2(t)$ are orthonormal to each other over $0 \leq t < 1/n$.
- (C) **(Correct)** $x_2(t)$ is a harmonic of $x_1(t)$.
- (D) **(Correct)** $x_1(t)$ and $x_2(t)$ are non-orthogonal to each other over $0 \leq t < 1/(2n)$.

Correct Answer: (A, C, D)

Detailed Solution – Question 1

Given, $x_1(t) = \cos(2\pi nt)$ and $x_2(t) = 2\sin(4\pi nt)$
where n is a positive integer.

For $x_1(t)$, the frequency is: $f_1 = n$

For $x_2(t)$, the frequency is: $f_2 = 2n$

Thus, $f_2 = 2f_1$

Hence, $x_2(t)$ is the second harmonic of $x_1(t)$.

Therefore, **option (C) is correct.**

Now check orthogonality over $0 \leq t < \frac{1}{n}$.

Two signals are orthogonal if:

$$\int_0^{1/n} x_1(t)x_2(t), dt = 0$$

Substituting,

$$\int_0^{1/n} \cos(2\pi nt) \cdot 2\sin(4\pi nt), dt$$

Using identity,

$$2\sin A \cos B = \sin(A+B) + \sin(A-B)$$

we get,

$$2\cos(2\pi nt)\sin(4\pi nt) = \sin(6\pi nt) + \sin(2\pi nt)$$

$$\text{Hence, } \int_0^{1/n} [\sin(6\pi nt) + \sin(2\pi nt)] dt$$

Both sine terms integrate to zero over the interval $0 \leq t < \frac{1}{n}$. Therefore,

$$\int_0^{1/n} x_1(t)x_2(t), dt = 0$$

Hence, the signals are orthogonal over $0 \leq t < \frac{1}{n}$.

Therefore, **option (A) is correct.**

Now check orthonormality.

For orthonormal signals, each signal must have unit energy over the interval.

Energy of $x_1(t)$:

$$\int_0^{1/n} \cos^2(2\pi nt), dt \neq 1$$

Hence, the signals are not normalized. Therefore, **option (B) is incorrect.**

Now check option (D).

Over $0 \leq t < \frac{1}{2n}$,

$$\int_0^{1/(2n)} x_1(t)x_2(t), dt \neq 0$$

Thus, the signals are non-orthogonal over this interval.

Therefore, **option (D) is correct.**

Correct Options: (A), (C), and (D).


Question 2: LTI Systems (GATE EC 2026)

MCQ

2 Marks

Consider the discrete time system (S) with input $x[n]$ and output $y[n]$ as shown in the Figure. The two sub-systems represented by their impulse responses $h_1[n]$ and $h_2[n]$ are linear and time invariant.

Which of the following statements is necessarily TRUE?



- (A) S is causal.
- (B) **(Correct)** S is linear and time invariant.
- (C) S is linear and time varying.
- (D) S is non-linear.

Correct Answer: (B)

Detailed Solution – Question 2

From the figure: $x[n]$ is the input. The system has two paths:

Upper path: $x[n] \rightarrow h_1[n] \rightarrow \Sigma$

Lower path: $x[n] \rightarrow z^{-1} \rightarrow (-)\Sigma \rightarrow h_2[n] \rightarrow z^{-1} \rightarrow \Sigma$

The right summing junction combines the upper (positive) and lower (negative, delayed) signals to produce $y[n]$.

Step 1: Analyse the lower branch

The lower sub-system receives $x[n] - x[n-1]$ (difference, which is a linear time-invariant operation) and passes it through $h_2[n]$, then delays by z^{-1} . All operations (delay, difference, convolution with $h_2[n]$) are LTI.

Step 2: Output equation

$$y[n] = (x[n] * h_1[n]) - (x[n-1] * h_2[n-1])$$

Both terms are linear functions of $x[n]$, and all shifts are fixed. The overall system S is a linear combination of LTI subsystems, S is also **Linear and Time Invariant**.

Question 3: Fourier Transforms (GATE EC 2026)

MCQ

2 Marks

Consider a real baseband signal $x(t) = e^{-2t}$, for t (in seconds) ≥ 0 .

If 99% of energy of $x(t)$ lies within B Hz, then which of the following options is TRUE for the value of B ?

- (A) $B > 1$ kHz
- (B) **(Correct)** $63/\pi$ Hz $< B < 64/\pi$ Hz
- (C) $126/\pi$ Hz $< B < 128/\pi$ Hz
- (D) $B < 1$ Hz

Correct Answer: (B)

Detailed Solution – Question 3

Step 1: Fourier Transform of the signal

The Fourier Transform of $e^{-at}u(t)$ is

Here, $a = 2$. Therefore,

$$X(f) = \frac{1}{2+j2\pi f}$$

Magnitude squared is

$$|X(f)|^2 = \frac{1}{4 + 4\pi^2 f^2}$$

Step 2: Total energy of the signal

Total energy is $E = \int_{-\infty}^{\infty} |X(f)|^2 df$

Substituting, $E = \int_{-\infty}^{\infty} \frac{df}{4 + 4\pi^2 f^2}$

Simplifying, $E = \frac{1}{4} \int_{-\infty}^{\infty} \frac{df}{1 + \pi^2 f^2}$

Using the standard result, we get $E = \frac{1}{4}$

Step 3: Energy within bandwidth B

Required condition:

$$\int_{-B}^B |X(f)|^2 df = 0.99E$$

Substituting values,

$$\int_{-B}^B \frac{df}{4 + 4\pi^2 f^2} = 0.99 \times \frac{1}{4}$$

Simplifying,

$$\int_{-B}^B \frac{df}{1 + \pi^2 f^2} = 0.99$$

Using symmetry,

$$2 \int_0^B \frac{df}{1 + \pi^2 f^2} = 0.99$$

Integrating, $\frac{2}{\pi} \tan^{-1}(\pi B) = 0.99$

Hence, $\tan^{-1}(\pi B) = 0.495\pi$

Now,

$$0.495\pi \approx 1.555$$

Since $\tan(1.555) \approx 63.7$,

$$\pi B \approx 63.7$$

Therefore,

$$B \approx \frac{63.7}{\pi}$$

Question 4: Basics of Signals & Systems (GATE EC 2026)

MCQ

2 Marks

Consider a real signal $x(t)$, $-\infty < t < \infty$, such that

$x(t) = 0$ for $t < 0$, $x(t) = 2$ for $0 \leq t < 1$ and $x(t) = 0$ for $t \geq 1$.

Let $E[x(t)] = \int_{-\infty}^{\infty} [x(t)]^2 dt$.

Which of the following options correctly represents the ratio,

$$E[x(t)]/E[3x(-3t+5)]?$$

(A) 3

(B) 1

(C) (Correct) $1/3$

(D) $1/9$

Correct Answer: (C)

Detailed Solution – Question 4

Given:

$x(t) = 0$ for $t < 0$; $x(t) = 2$ for $0 \leq t < 1$; $x(t) = 0$ for $t \geq 1$

$$E[x(t)] = \int_{-\infty}^{\infty} [x(t)]^2, dt$$

Step 1: Compute $E[x(t)]$

$$E[x(t)] = \int_0^1 (2)^2, dt = 4 \times 1 = 4$$

Step 2: Analyze $g(t) = 3x(-3t + 5)$

$$E[g(t)] = \int_{-\infty}^{\infty} [3x(-3t + 5)]^2, dt = 9 \int_{-\infty}^{\infty} [x(-3t + 5)]^2, dt$$

Let $u = -3t + 5 \Rightarrow du = -3, dt \Rightarrow dt = \frac{du}{3}$ (with $\frac{1}{3}$ scaling):

$$= 9 \cdot \frac{1}{3} \int_{-\infty}^{\infty} [x(u)]^2, du = 3 \cdot E[x(t)] = 3 \times 4 = 12$$

Step 3: Compute ratio

$$\frac{E[x(t)]}{E[3x(-3t+5)]} = \frac{4}{12} = \frac{1}{3}$$

Question 5: Fourier Series (GATE EC 2026)

MCQ

2 Marks

The continuous time signal $x(t)$ is real, periodic with period T and satisfies the Dirichlet conditions.

The Fourier series representation of $x(t) = \sum_{n=-\infty}^{\infty} a_n e^{j(2\pi n t/T)}$ and $x(t)$ satisfies the following:
 $x(t - T/2) = -x(t)$.

For any integer m , which of the following options is correct?

(A) (Correct) $a_{2m} = 0$

(B) $a_{2m} = 1$

(C) $a_{2m} = a_{2m+1}$

(D) $a_{2m} = -1$

Correct Answer: (A)

Detailed Solution – Question 5

Given:

$x(t)$ is real, periodic with period T , satisfying:

$$x\left(t - \frac{T}{2}\right) = -x(t) \quad (\text{half-wave symmetry})$$

Fourier series: $x(t) = \sum_{n=-\infty}^{\infty} a_n e^{j2\pi n t/T}$

Step 1: Effect of half-wave symmetry on Fourier coefficients

Compute the Fourier coefficient a_n :

$$a_n = \frac{1}{T} \int_0^T x(t) e^{-j2\pi n t/T} dt$$

Under the substitution $t \rightarrow t + T/2$:

$$a_n = \frac{1}{T} \int_0^T x\left(t + \frac{T}{2}\right) e^{-j2\pi n(t+T/2)/T} dt$$

$$= e^{-j\pi n} \cdot \frac{1}{T} \int_0^T x\left(t + \frac{T}{2}\right) e^{-j2\pi n t/T} dt$$

Using $x\left(t + \frac{T}{2}\right) = -x(t)$ (from given symmetry, replacing $t \rightarrow t + T/2$):

$$a_n = e^{-j\pi n} \cdot (-a_n) = (-1)^n \cdot (-a_n)$$

Step 2: Determine which coefficients survive

$$a_n = -(-1)^n a_n$$

For **even** n : $a_n = -a_n \Rightarrow a_n = 0$

For **odd** n : $a_n = +a_n$ (no constraint, coefficients can be nonzero)

Conclusion:

For any integer m , $a_{2m} = 0$ (all even-indexed Fourier coefficients are zero). Only odd harmonics exist in the spectrum.

Question 6: LTI Systems (GATE EC 2026)

MCQ

1 Mark

The relation between the input current (I) and the output voltage (V) of a circuit is governed by the equation: $C \frac{dV}{dt} = I(t) - m(t)$. The circuit is excited by $I(t) = q\delta(t)$, where q is a real valued constant. V at $t = 0^-$ is V_0 .

Which of the following is an equivalent representation of the above case?

- (A) **(Correct)** $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = V_0 + q/C$
- (B) $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = V_0 + q/C + m(t = 0^-)$
- (C) $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = V_0 - q/C + m(t = 0^-)$
- (D) $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = q/C$

Correct Answer: (A)

Detailed Solution – Question 6

Given:

$$C \frac{dV}{dt} = I(t) - m(t), \quad I(t) = q\delta(t), \quad V(0^-) = V_0$$

Step 1: Effect of impulse current

$I(t) = q\delta(t)$ acts instantaneously at $t = 0$. Integrating both sides from 0^- to 0^+ :

$$C[V(0^+) - V(0^-)] = q - 0 \Rightarrow V(0^+) = V_0 + \frac{q}{C}$$

Step 2: For $t > 0$

The impulse is gone, so:

$$C \frac{dV}{dt} = -m(t), \quad V(0^-) \rightarrow V(0^+) = V_0 + \frac{q}{C}$$

The equivalent representation treats the initial condition as updated by the impulse:

$$C \frac{dV}{dt} = -m(t), \quad \text{with } V(t = 0^-) = V_0 + \frac{q}{C}$$

Question 7: LTI Systems (GATE EC 2026)

MCQ

1 Mark

The response of a discrete time system $y[n]$ obeys the following relation:

$$y[n] = \frac{5}{6}y[n-1] - \frac{1}{6}y[n-2] + x[n]$$

The input to the system is $x[n] = \delta[n] - \frac{1}{3}\delta[n-1]$.

Which of the following options is TRUE for $y[n]$?

- (A) **(Correct)** Stable and causal response
- (B) Stable and non-causal response
- (C) Unstable and causal response
- (D) Unstable and non-causal response

Correct Answer: (A)

Detailed Solution – Question 7

Given Difference Equation:

$$y[n] = \frac{5}{6}y[n-1] - \frac{1}{6}y[n-2] + x[n]$$

Input signal:

$$x[n] = \delta[n] - \frac{1}{3}\delta[n-1]$$

To determine the nature of the response, we analyze the system poles.

Taking Z-transform of the system equation under zero initial conditions,

$$Y(z) = \frac{5}{6}z^{-1}Y(z) - \frac{1}{6}z^{-2}Y(z) + X(z)$$

Rearranging terms,

$$Y(z) \left(1 - \frac{5}{6}z^{-1} + \frac{1}{6}z^{-2}\right) = X(z)$$

Hence, the transfer function is

$$H(z) = \frac{Y(z)}{X(z)} = \frac{1}{1 - \frac{5}{6}z^{-1} + \frac{1}{6}z^{-2}}$$

Multiplying numerator and denominator by z^2 ,

$$H(z) = \frac{z^2}{z^2 - \frac{5}{6}z + \frac{1}{6}}$$

The characteristic equation is

$$z^2 - \frac{5}{6}z + \frac{1}{6} = 0$$

Factorizing,

$$\left(z - \frac{1}{2}\right) \left(z - \frac{1}{3}\right) = 0$$

Therefore, the poles are

$$z = \frac{1}{2}, \quad z = \frac{1}{3}$$

Since both poles lie inside the unit circle, the system is **stable**.

Also, the output depends only on present and past values:

$$x[n], \quad y[n-1], \quad y[n-2]$$

Hence, the system is **causal**

Question 8: Sampling (GATE EC 2026)

MCQ

1 Mark

Two analog signals $x_1(t)$ and $x_2(t)$ (t in second) are sampled at a rate $F_s = 40$ Hz, where

$$x_1(t) = \cos(20\pi t), t \geq 0, \text{ and } x_2(t) = \cos(100\pi t), t \geq 0.$$

The first ten samples (starting from $t = 0$) are considered for the analysis.

Which of the following statements is TRUE?

- (A) All of the first three samples of $x_1(t)$ are greater than the corresponding samples of $x_2(t)$.
- (B) All of the last three samples of $x_1(t)$ are greater than the corresponding samples of $x_2(t)$.
- (C) All of the samples of $x_2(t)$ are greater than the corresponding samples of $x_1(t)$.
- (D) **(Correct)** All of the fourth to seventh samples of $x_1(t)$ are equal to the corresponding samples of $x_2(t)$.

Correct Answer: (D)

Detailed Solution – Question 8

Given:

Sampling frequency:

$$f_s = 40 \text{ Hz}$$

Signal 1:

$$x_1(t) = \cos(20\pi t)$$

Signal 2:

$$x_2(t) = \cos(100\pi t)$$

The sampling interval is

Therefore,

$$T_s = \frac{1}{40} \text{ sec}$$

The sampled signals are obtained at

$$t = nT_s = \frac{n}{40}, \quad n = 0, 1, 2, \dots$$

Step 1: Samples of $x_1(t)$

$$\begin{aligned} x_1[n] &= \cos\left(20\pi \frac{n}{40}\right) \\ &= \cos\left(\frac{n\pi}{2}\right) \end{aligned}$$

Thus, the sequence becomes

$$1, 0, -1, 0, 1, 0, -1, 0, 1, 0, \dots$$

Step 2: Samples of $x_2(t)$

$$\begin{aligned} x_2[n] &= \cos\left(100\pi \frac{n}{40}\right) \\ &= \cos\left(\frac{5n\pi}{2}\right) \end{aligned}$$

Using periodicity of cosine,

$$\cos\left(\frac{5n\pi}{2}\right) = \cos\left(\frac{n\pi}{2}\right)$$

Hence,

$$x_2[n] = x_1[n]$$

Therefore, all corresponding samples of the two sequences are equal.

In particular, the fourth to seventh samples are equal.

Question 9: Laplace Transform (GATE EC 2026)

MCQ

1 Mark

The Laplace Transform of the signal $x(t) = u(t-2) * (t \cdot u(t))$ is given by which of the following expressions?

[Note: "*" represents convolution operator]

- (A) $\frac{e^{-2s}}{s^2(s-2)}$
- (B) $\frac{e^{-2(s-2)}}{s^3}$
- (C) $\frac{se^{-2s}}{(s-2)^2}$
- (D) **(Correct)** $\frac{e^{-2s}}{s^3}$

Correct Answer: (D)

Detailed Solution – Question 9

Given:

$$x(t) = u(t - 2) * (tu(t))$$

where $*$ denotes convolution.

Using the convolution property of Laplace Transform,

$$\mathcal{L}\{f(t) * g(t)\} = F(s)G(s)$$

So,

$$X(s) = \mathcal{L}\{u(t - 2)\} \times \mathcal{L}\{tu(t)\}$$

Step 1: Laplace Transform of $u(t - 2)$

Using the standard formula,

For $a = 2$,

$$\mathcal{L}\{u(t - 2)\} = \frac{e^{-2s}}{s}$$

Step 2: Laplace Transform of $tu(t)$

Using the standard result,

Therefore,

$$\mathcal{L}\{tu(t)\} = \frac{1}{s^2}$$

Step 3: Apply convolution property

$$X(s) = \frac{e^{-2s}}{s} \times \frac{1}{s^2}$$

Hence,

$$X(s) = \frac{e^{-2s}}{s^3}$$

Question 10: Fourier Series (GATE EC 2025)

MSQ

2 Marks

Let $f(t)$ be a periodic signal with fundamental period $T_0 > 0$. Consider the signal $y(t) = f(\alpha t)$, where $\alpha > 1$.

The Fourier series expansions of $f(t)$ and $y(t)$ are given by

$$f(t) = \sum_{k=-\infty}^{\infty} c_k e^{j\frac{2\pi}{T_0}kt} \quad \& \quad y(t) = \sum_{k=-\infty}^{\infty} d_k e^{j\frac{2\pi}{T_0}\alpha kt}$$

Which of following statement is/are TRUE?

- (A) **(Correct)** $c_k = d_k$ for all k
- (B) $y(t)$ is periodic with a fundamental period αT_0
- (C) $c_k = d_k/\alpha$ for all k
- (D) **(Correct)** $y(t)$ is periodic with a fundamental period T_0/α

Correct Answer: (A, D)

Detailed Solution – Question 10

Let the original signal $f(t)$ have period T_0 . Then:

$$f(t + T_0) = f(t)$$

Now consider the time-scaled signal:

$$y(t) = f(\alpha t) \text{ To find its period, assume } y(t + T) = y(t):$$

$$f(\alpha(t + T)) = f(\alpha t) \Rightarrow f(\alpha t + \alpha T) = f(\alpha t)$$

Since $f(t)$ is periodic with period T_0 , this implies:

$$\alpha T = T_0 \Rightarrow T = \frac{T_0}{\alpha} \text{ Therefore, } y(t) \text{ is periodic with fundamental period } \frac{T_0}{\alpha}$$

So, (D) is TRUE, and (B) is FALSE

Fourier Series Comparison: The Fourier series of $f(t)$ is:

$$f(t) = \sum_{k=-\infty}^{\infty} c_k e^{j \frac{2\pi}{T_0} k t} \text{ Now } y(t) = f(\alpha t) ?$$

$$y(t) = \sum_{k=-\infty}^{\infty} c_k e^{j \frac{2\pi}{T_0} k \alpha t} = \sum_{k=-\infty}^{\infty} d_k e^{j \frac{2\pi}{T_0/\alpha} k t}$$

Hence, $d_k = c_k$ for all k

So (A) is TRUE

(C) is FALSE

Question 11: Sampling (GATE EC 2025)

MCQ

2 Marks

Consider a continuous-time finite-energy signal $f(t)$ whose Fourier transform vanishes outside the frequency interval $[-\omega_c, \omega_c]$, where ω_c is in rad/sec.

The signal $f(t)$ is uniformly sampled to obtain $y(t) = f(t)p(t)$. Here,

$$p(t) = \sum_{n=-\infty}^{\infty} \delta(t - \tau - nT_s),$$

with $\delta(t)$ being the Dirac impulse, $T_s > 0$, and $\tau > 0$. The sampled signal $y(t)$ is passed through an ideal lowpass filter $h(t) = \omega_c T_s \frac{\sin(\omega_c t)}{\pi \omega_c t}$ with cutoff frequency ω_c and passband gain T_s .

The output of the filter is given by ----- .

(A) **(Correct)** $f(t)$ if $T_s < \pi/\omega_c$

(B) $f(t - \tau)$ if $T_s < \pi/\omega_c$

(C) $f(t - \tau)$ if $T_s < 2\pi/\omega_c$

(D) $T_s f(t)$ if $T_s < 2\pi/\omega_c$

Correct Answer: (A)

Detailed Solution – Question 11

We are given that $f(t)$ is bandlimited to $[-\omega_c, \omega_c]$, meaning its Fourier transform $F(j\omega)$ is zero outside this interval.

Step 1: Sampling process Sampling is done using the impulse train:

$$p(t) = \sum_{n=-\infty}^{\infty} \delta(t - \tau - nT_s)$$

Multiplying this with $f(t)$ gives:

$$y(t) = f(t) \cdot p(t) = \sum_{n=-\infty}^{\infty} f(\tau + nT_s) \cdot \delta(t - \tau - nT_s)$$

This means we are taking samples of $f(t)$ at times $t = \tau + nT_s$.

Step 2: Filtering with ideal LPF

The sampled signal $y(t)$ is passed through an ideal lowpass filter with impulse response:

$$h(t) = T_s \cdot \text{sinc}\left(\frac{\omega_c t}{\pi}\right)$$

The output of the system is:

$$z(t) = y(t) * h(t) = \sum_{n=-\infty}^{\infty} f(\tau + nT_s) \cdot h(t - \tau - nT_s)$$

Substitute $h(t)$:

$$z(t) = T_s \sum_{n=-\infty}^{\infty} f(\tau + nT_s) \cdot \text{sinc}\left(\frac{\omega_c(t - \tau - nT_s)}{\pi}\right)$$

This is the reconstruction formula for $f(t)$, but it appears to reconstruct $f(t - \tau)$ at first glance.

Step 3: Time-invariance and interpretation

Here's the key point: Even though the samples are taken at $t = \tau + nT_s$, the reconstruction system is linear and time-invariant. A shift in sampling time does not affect the shape of the reconstructed signal, because the sinc interpolation is symmetric and consistent.

Hence, the filter effectively undoes the delay, and we recover the original signal $f(t)$.

Step 4: Condition for perfect reconstruction

Perfect reconstruction using sinc interpolation is possible only if there is no aliasing, which happens when:

$$T_s < \frac{\pi}{\omega_c}$$

This is the Nyquist condition for bandlimited signals.

Question 12: DTFS, DTFT & DFT (GATE EC 2025)

MSQ

1 Mark

Let $x[n]$ be a discrete-time signal whose z -transform is $X(z)$.

Which of the following statements is/are TRUE?

- (A) The discrete-time Fourier transform (DTFT) of $x[n]$ always exists
- (B) The region of convergence (ROC) of $X(z)$ contains neither poles nor zeros
- (C) **(Correct)** The discrete-time Fourier transform (DTFT) exists if the region of convergence (ROC) contains the unit circle
- (D) **(Correct)** If $x[n] = \alpha \delta[n]$, where $\delta[n]$ is the unit impulse and α is a scalar, then the region of convergence (RoC) is the entire z -plane

Correct Answer: (C, D)

Detailed Solution – Question 12

- (A) The DTFT does not always exist. It exists only if the signal is absolutely summable: $\sum_{n=-\infty}^{\infty} |x[n]| < \infty$. So this statement is False.
- (B) The region of convergence (RoC) contains no poles, but it can include zeros (since zeros do not affect convergence). So this statement is False.
- (C) This is True. The DTFT of $x[n]$ exists iff the RoC of $X(z)$ includes the unit circle $|z| = 1$.
- (D) For $x[n] = \alpha\delta[n]$, the z -transform is $X(z) = \alpha$ (a constant), which is defined for all $z \in \mathbb{C}$. Hence, the RoC is the entire z -plane, so this is True.

Question 13: Fourier Transforms (GATE EC 2025)

MCQ

1 Mark

Consider a continuous-time, real-valued signal $f(t)$ whose Fourier transform $F(\omega) = \int_{-\infty}^{\infty} f(t) \exp(-j\omega t) dt$ exists.

Which one of the following statements is always TRUE?

- (A) **(Correct)** $|F(\omega)| \leq \int_{-\infty}^{\infty} |f(t)| dt$
- (B) $|F(\omega)| > \int_{-\infty}^{\infty} |f(t)| dt$
- (C) $|F(\omega)| \leq \int_{-\infty}^{\infty} f(t) dt$
- (D) $|F(\omega)| \geq \int_{-\infty}^{\infty} f(t) dt$

Correct Answer: (A)

Detailed Solution – Question 13

We are given that $F(\omega) = \int_{-\infty}^{\infty} f(t) e^{-j\omega t} dt$ exists.

This means that $f(t)$ is absolutely integrable, i.e., $\int_{-\infty}^{\infty} |f(t)| dt < \infty$.

To find a general bound on $|F(\omega)|$, we apply the triangle inequality for integrals:

$$|F(\omega)| = \left| \int_{-\infty}^{\infty} f(t) e^{-j\omega t} dt \right| \leq \int_{-\infty}^{\infty} |f(t) e^{-j\omega t}| dt = \int_{-\infty}^{\infty} |f(t)| dt$$

This inequality is always true.

Now check the options:

- (A) $|F(\omega)| \leq \int_{-\infty}^{\infty} |f(t)| dt$ – Correct
- (B) Strict inequality – not always true
- (C) Inequality involving $\int f(t) dt$ – this can be 0 for symmetric signals (e.g., odd functions), but $|F(\omega)|$ may be nonzero
- (D) Similar issue – not always true


Question 14: LTI Systems (GATE EC 2025)

MCQ

1 Mark

Consider the discrete-time system below with input $x[n]$ and output $y[n]$. In the figure, $h_1[n]$ and $h_2[n]$ denote the impulse responses of LTI Subsystems 1 and 2, respectively. Also, $\delta[n]$ is the unit impulse, and $b > 0$.

Assuming $h_2[n] \neq \delta[n]$, the overall system (denoted by the dashed box) is



- (A) linear and time invariant
- (B) linear and time variant
- (C) nonlinear and time invariant
- (D) **(Correct)** nonlinear and time variant

Correct Answer: (D)

Detailed Solution – Question 14

$$y_2[n] = \{y_1[n] + b\delta[n]\} * h_2[n]$$

$$\text{Output } y[n] = \{x[n] * h_1[n] + b\delta[n]\} * h_2[n] - b\delta[n]$$

$$y(n) = \underbrace{x[n] * h_1[n] * h_2[n]}_{\text{This is LTI}} + \underbrace{b h_2[n] - b\delta[n]}_{\text{N.L. terms}}$$

$$h_2[n] \neq \delta[n]$$

If we consider $h_2[n] = nu[n]$

$y[n]$ is variable function of time $\Rightarrow$ Time variant So, Non Linear & Time variant.

Question 15: DTFS, DTFT & DFT (GATE EC 2024)

NAT

2 Marks

The relationship between any N-length sequence $x[n]$ and its corresponding N-point discrete Fourier transform $X[k]$ is defined as

$$X[k] = F\{x[n]\}.$$

Another sequence $y[n]$ is formed as below

$$y[n] = F\{F\{F\{F\{x[n]\}\}\}\}$$

For the sequence $x[n] = \{1, 2, 1, 3\}$, the value of $Y[0]$ is _____

Detailed Solution – Question 15

$$y[n] = N^2 x[n]$$

$$y[n] = N^2 x[n]$$

$$\begin{aligned} Y[k]|_{K=0} &= \sum_{n=0}^3 y[n] = \sum_{n=0}^3 N^2 x[n] \\ &= N^2 [x[0] + x[1] + x[2] + x[3]] \\ &= (4)^2 [1 + 2 + 1 + 3] = 16 \times 7 = 112 \end{aligned}$$

$$y[n] = N^2 x[n] \quad \because N = 4$$

Question 16: Basics of Signals & Systems (GATE EC 2024)

MSQ

2 Marks

The radian frequency value(s) for which the discrete time sinusoidal signal $x[n] = A \cos(\Omega n + \pi/3)$ has a period of 40 is/are _____

(A) **(Correct)** 0.15π

(B) 0.225π

(C) **(Correct)** 0.3π

(D) **(Correct)** 0.45π

Correct Answer: (A, C, D)

Detailed Solution – Question 16

$$x[n] = A \cos \left[\Omega n + \frac{\pi}{3} \right]$$

$$N = 40$$

$$\Omega = ?$$

$$\frac{\Omega}{2\pi} = \frac{m}{N}$$

$$\frac{\Omega}{2\pi} = \frac{m}{40}$$

$$\Omega = m \cdot \frac{2\pi}{40} = \pi \cdot m(0.05)$$

$$\Omega = 0.05\pi$$

$$m = 1 \quad \Omega = 0.05\pi$$

$$m = 2 \quad \Omega = 0.10\pi$$

$$m = 3 \quad \Omega = 0.15\pi$$

$$m = 4 \quad \Omega = 0.20\pi$$

$$m = 5 \quad \Omega = 0.25\pi$$

$$m = 6 \quad \Omega = 0.30\pi$$

$$m = 7 \quad \Omega = 0.35\pi$$

$$m = 8 \quad \Omega = 0.40\pi$$

$$m = 9 \quad \Omega = 0.45\pi$$

Question 17: Fourier Transforms (GATE EC 2024)

MCQ

2 Marks

A continuous time signal $x(t) = 2 \cos(8\pi t + \pi/3)$ is sampled at a rate of 15 Hz. The sampled signal $x_s(t)$ when passed through an LTI system with impulse response

$$h(t) = \left(\frac{\sin 2\pi t}{\pi t} \right) \cos(38\pi t - \pi/2)$$

produces an output $x_0(t)$. The expression for $x_0(t)$ is -----

- (A) $15 \sin(38\pi t + \pi/3)$
- (B) $15 \sin(38\pi t - \pi/3)$
- (C) **(Correct)** $15 \cos(38\pi t - \pi/6)$
- (D) $15 \cos(38\pi t + \pi/6)$

Correct Answer: (C)

Detailed Solution – Question 17



$$x(t) = 2 \cos \left(8\pi t + \frac{\pi}{3} \right), \quad \omega_o = 8\pi$$

$$f_s = 15 \text{ Hz}$$

$$x(t) \rightarrow \text{sample } x_s(t) \rightarrow h(t)x_0(t)$$

$$\Rightarrow h(t) = \frac{\sin 2\pi t}{\pi t} \cos \left(38\pi t - \frac{\pi}{2} \right)$$

$$\text{Let } p(t) = \frac{\sin 2\pi t}{\pi t}$$



After sampling:

$$X_s(\omega) = f_s \sum_{n=-\infty}^{\infty} X(\omega - n\omega_s)$$

Frequency components present in sampler output $n\omega_s \pm \omega_o$

$$\omega_o, \omega_s + \pm\omega_o, 2\omega_s \pm \omega_o, \dots$$

$$8\pi, 30\pi \pm 8\pi, 60\pi \pm 8\pi, \dots$$

$$8\pi, 22\pi, 38\pi, 52\pi, 68\pi, \dots \text{ (rad/sec)}$$

System will pass '38π' component of input.

$$x_o(t) = 2 \times \frac{f_s}{2} \cos \left[38\pi t + \frac{\pi}{3} - \frac{\pi}{2} \right] = 15 \cos \left(38\pi t - \frac{\pi}{6} \right)$$





As per GATE official Answer Key-MTA

Question 18: Fourier Transforms (GATE EC 2024)

MCQ

2 Marks

Consider two continuous time signals $x(t)$ and $y(t)$ as shown below





If $X(f)$ denotes the Fourier transform of $x(t)$, then the Fourier transform of $y(t)$ is ----

- (A) $-4X(4f)e^{-j\pi f}$
- (B) **(Correct)** $-4X(4f)e^{-j4\pi f}$
- (C) $-\frac{1}{4}X(f/4)e^{-j\pi f}$
- (D) $-\frac{1}{4}X(f/4)e^{-j4\pi f}$



Correct Answer: (B)

Detailed Solution – Question 18

Given



Length of $x(t)$ is 1 and length of $y(t)$ is 4.



$$\therefore y(t) = -x\left(\frac{t-2}{4}\right)$$

$$y(t) = -x\left(\frac{t}{4} - \frac{2}{4}\right) = -x\left(\frac{t}{4} - \frac{1}{2}\right)$$

On taking Fourier transform, we get

$$x(t) \leftrightarrow X(f)$$

Question 19: LTI Systems (GATE EC 2024)

MSQ

1 Mark

For a causal discrete-time LTI system with transfer function

$$H(z) = \frac{2z^2+3}{(z+\frac{1}{3})(z-\frac{1}{3})}$$

which of the following statements is/are true?

- (A) **(Correct)** The system is stable.
- (B) The system is a minimum phase system.
- (C) **(Correct)** The initial value of the impulse response is 2.
- (D) **(Correct)** The final value of the impulse response is 0.

Correct Answer: (A, C, D)

Detailed Solution – Question 19

Given: $H(z) = \frac{2z^2+3}{(z+\frac{1}{3})(z-\frac{1}{3})}$

System is non-minimum phase system. Since zero are lying outside the unit circle.

Final value:

$$h(\infty) = \lim_{z \rightarrow 1} (z-1) \frac{2z^2+3}{(z+\frac{1}{3})(z-\frac{1}{3})} = 0$$

Initial value:

$$\begin{aligned} h(0) &= \lim_{z \rightarrow \infty} \frac{(2z^2+3)}{(z+\frac{1}{3})(z-\frac{1}{3})} = \lim_{z \rightarrow \infty} \frac{z^2 [2 + \frac{3}{z^2}]}{z^2 [1 + \frac{1}{3z}] [1 - \frac{1}{3z}]} \\ &= \lim_{z \rightarrow \infty} \frac{[2 + \frac{3}{z^2}]}{[1 + \frac{1}{3z}] [1 - \frac{1}{3z}]} = \frac{2}{1 \times 1} = 2 \\ |z| &= \frac{1}{3} = 0.33 \end{aligned}$$

$$z = -\frac{1}{3}, z = \frac{1}{3}$$

System is stable. Since | pole | < 1 i.e. pole are lying inside the unit circle.

Question 20: LTI Systems (GATE EC 2024)

MCQ

1 Mark

A causal and stable LTI system with impulse response $h(t)$ produces an output $y(t)$ for an input signal $x(t)$. A signal $x(0.5t)$ is applied to another causal and stable LTI system with impulse response $h(0.5t)$. The resulting output is -----

- (A) **(Correct)** $2y(0.5t)$
- (B) $4y(0.5t)$
- (C) $0.25y(2t)$

(D) $0.25y(0.25t)$

Correct Answer: (A)

Detailed Solution – Question 20

$$y(t) = x(t) * h(t)$$

$$x(t) \leftrightarrow X(\omega)$$

$$x(0.5t) \leftrightarrow 2X(2\omega)$$

$$h(0.5t) \leftrightarrow 2H(2\omega)$$

$$y(t) \leftrightarrow Y(\omega)$$

$$Y(\omega) \leftrightarrow X(\omega) \times H(\omega)$$

After scaling,

$$Y_1(\omega) = 2X(2\omega) \times 2H(2\omega)$$

$$= 4X(2\omega) \times H(2\omega) \text{ After taking inverser Fourier transform } y_1(t) = 2y(0.5t)$$


Question 21: LTI Systems (GATE EC 2023)

NAT

2 Marks

Let $X(t)$ be a white Gaussian noise with power spectral density $\frac{1}{2}$ W/Hz. If $X(t)$ is input to an LTI system with impulse response $e^{-t}u(t)$. The average power of the system output is ___ W. (Rounded off to two decimal place).

Detailed Solution – Question 21



$$h(t) = e^{-t}u(t)$$

Given: Input PSD

$$\Rightarrow S_x(f) = \frac{1}{2} \text{ W/Hz}$$

We know output PSD,

$$S_Y(f) = S_X(f)|H(f)|^2$$

$$S_Y(f) = \frac{1}{2}|H(f)|^2$$


$$\begin{aligned} \text{Power } [y(t)] &= \int_{-\infty}^{\infty} S_Y(f) df = \int_{-\infty}^{\infty} \frac{1}{2} |H(f)|^2 df \\ &= \frac{1}{2} \int_{-\infty}^{\infty} h^2(t) dt = \frac{1}{2} \int_0^{\infty} e^{-2t} dt \\ &= \frac{1}{2} \times \frac{1}{2} = \frac{1}{4} = 0.25 \text{ W} \end{aligned}$$


Question 22: Fourier Transforms (GATE EC 2023)

NAT

2 Marks



Let $x_1(t) = u(t + 1.5) - u(t - 1.5)$ and $x_2(t)$ is shown in the figure below. For $y(t) = x_1(t) * x_2(t)$, the $\int_{-\infty}^{\infty} y(t) dt$ is (rounded off to the nearest integer).





Detailed Solution – Question 22

$$x_1(t) = u(t + 1.5) - u(t - 1.5)$$



$$\Rightarrow x_1(t) = \text{rect}\left(\frac{t}{3}\right)$$

$$x_1(t) = \text{rect}\left(\frac{t}{3}\right) \xleftrightarrow{FT} 3\text{Sa}(1.5\omega)$$

$$\text{Now, } x_2(t) = \delta(t + 3) + \text{rect}\left(\frac{t}{2}\right) + 2\delta(t - 2)$$

Taking Fourier transform

$$X_2(\omega) = e^{3j\omega} + 2\text{Sa}(\omega) + 2e^{-2j\omega}$$

$$y(t) = x_1(t) * x_2(t)$$

$$Y(\omega) = X_1(\omega) \cdot X_2(\omega)$$

$$Y(\omega) = \int_{-\infty}^{\infty} y(t) \cdot e^{-j\omega t} \cdot dt$$

We know

$$\therefore \int_{-\infty}^{\infty} y(t) dt = Y(0)$$


$$\therefore Y(0) = X_1(0) \cdot X_2(0) = 3[1 + 2 + 2] = 15$$

Question 23: Sampling (GATE EC 2023)

MCQ

2 Marks

Let $x_1(t)$ and $x_2(t)$ be two band-limited signals having bandwidth $B = 4\pi \times 10^3 \text{ rad/sec}$. In the figure below, the Nyquist sampling frequency, in rad/s, required to sample $y(t)$, is





- (A) $20\pi \times 10^3$
- (B) $40\pi \times 10^3$
- (C) $8\pi \times 10^3$
- (D) **(Correct)** $32\pi \times 10^3$

Correct Answer: (D)



Detailed Solution – Question 23

Given that, $x_1(t)$ and $x_2(t)$ are two bandlimited signals having bandwidth $B = 4\pi \times 10^3 \text{ rad/sec}$.



and

$$y(t) = x_2(t) \cos(12\pi \times 10^3 t) + x_1(t) \cos(4\pi \times 10^3 t)$$



So,

$$\text{Nyquist Rate} = 2\omega_{\max} = 2[16\pi \times 10^3] = 32\pi \times 10^3 \text{ rad/sec}$$

Question 24: LTI Systems (GATE EC 2023)

MCQ

2 Marks

Let $x(t) = 10 \cos(10.5Wt)$ be passed through an LTI system having impulse response $h(t) = \pi \left(\frac{\sin Wt}{\pi t} \right)^2 \cos 10Wt$. The output of the system is

- (A) **(Correct)** $\left(\frac{15W}{4} \right) \cos(10.5Wt)$
- (B) $\left(\frac{15W}{2} \right) \cos(10.5Wt)$
- (C) $\left(\frac{15W}{8} \right) \cos(10.5Wt)$
- (D) $(15W) \cos(10.5Wt)$



Correct Answer: (A)

Detailed Solution – Question 24



Given $h(t)$ is Real and Even. When sinusoidal input applied to LTI system having even impulse response, then output will also be sinusoidal.

here, $y(t) = H(W)|_{W=10.5W} \cdot 10 \cos(10.5Wt)$

let, $h(t) = f(t) \cos 10Wt$ where, $f(t) = \pi \left(\frac{\sin Wt}{\pi t} \right)^2$



$$\text{Now; } H(W) = \frac{1}{2} [F(W + 10W) + F(W - 10W)]$$



$$\therefore H(W)|_{W=10.5W} = \frac{3}{8}W$$

Hence,

$$\begin{aligned} y(t) &= \left(\frac{3}{8}W \right) (10 \cos 10.5Wt) \\ &= \frac{15}{4}W \cos 10.5Wt \end{aligned}$$

Question 25: DTFS, DTFT & DFT (GATE EC 2023)

MCQ

2 Marks

Let an input $x[n]$ having discrete time Fourier transform.

$X(e^{j\Omega}) = 1 - e^{-j\Omega} + 2e^{-3j\Omega}$ be passed through an LTI system. The frequency response of the LTI system is $H(e^{j\Omega}) = 1 - \frac{1}{2}e^{-j2\Omega}$. The output $y[n]$ of the system is

(A)

$$\delta[n] + \delta[n-1] - \frac{1}{2}\delta[n-2] - \frac{5}{2}\delta[n-3] + \delta[n-5]$$

(B)

$$\delta[n] - \delta[n-1] - \frac{1}{2}\delta[n-2] - \frac{5}{2}\delta[n-3] + \delta[n-5]$$

(C) (Correct)

$$\delta[n] - \delta[n-1] - \frac{1}{2}\delta[n-2] + \frac{5}{2}\delta[n-3] - \delta[n-5]$$

(D)

$$\delta[n] + \delta[n-1] + \frac{1}{2}\delta[n-2] + \frac{5}{2}\delta[n-3] + \delta[n-5]$$

Correct Answer: (C)

Detailed Solution – Question 25

$$\begin{aligned}y[n] &= x[n] * h[n] \\Y(e^{j\Omega}) &= X(e^{j\Omega}) H(e^{j\Omega}) \\&= [1 - e^{-j\Omega} + 2e^{-3j\Omega}] \left[1 - \frac{1}{2}e^{-j2\Omega}\right] \\&= 1 - e^{-j\Omega} + 2.5e^{-3j\Omega} - 0.5e^{-j2\Omega} - e^{-j5\Omega}\end{aligned}$$

Taking IDTFT;

$$y[n] = \delta[n] - \delta[n-1] - 0.5\delta[n-2] + 2.5\delta[n-3] - \delta[n-5]$$

Question 26: DTFS, DTFT & DFT (GATE EC 2023)

MCQ

2 Marks

Consider a discrete-time periodic signal with period $N = 5$. Let the discrete-time Fourier series (DTFS) representation be $x[n] = \sum_{k=0}^4 a_k e^{\frac{jk2\pi n}{5}}$, where $a_0 = 1, a_1 = 3j, a_2 = 2j, a_3 = -2j$ and $a_4 = -3j$. The value of the sum $\sum_{n=0}^4 x[n] \sin \frac{4\pi n}{5}$ is

(A) (Correct) -10

(B) 10

(C) -2

(D) 2

Correct Answer: (A)

Detailed Solution – Question 26

Let, $I = \sum_{n=0}^4 x(n) \sin \frac{4\pi n}{5}$

$$\begin{aligned} &= \frac{1}{2j} \sum_{n=0}^4 x(n) \cdot \left[e^{j\frac{4\pi n}{5}} - e^{-j\frac{4\pi n}{5}} \right] \\ &= \frac{1}{2j} \left[\sum_{n=0}^4 x(n) e^{j\frac{4\pi n}{5}} - \sum_{n=0}^4 x(n) \cdot e^{-j\frac{4\pi n}{5}} \right] \quad (i) \end{aligned}$$

As we know,

$$a_k = \frac{1}{N} \sum_{n=0}^4 x(n) \cdot e^{-jk \cdot \frac{2\pi}{N} n}$$

$$= \frac{1}{5} \sum_{n=0}^4 x(n) \cdot e^{-j\frac{2\pi}{5} kn}$$

$$\text{Put } K = 2; \quad a_2 = \frac{1}{5} \sum_{n=0}^4 x(n) \cdot e^{-j\frac{4\pi n}{5}}$$

Put

$$K = -2; \quad a_{-2} = \frac{1}{5} \sum_{n=0}^4 x(n) \cdot e^{j\frac{4\pi n}{5}}$$

From equation (i),

$$I = \frac{1}{2j} [5a_{-2} - 5a_2] = \frac{5}{2j} [a_{-2} - a_2]$$

$$I = \frac{5}{2j} [-2j - 2j] = -10$$

$$\begin{aligned} a_{-2} &= a_{-2+N} \\ \therefore &= a_{-2+5} \\ &= a_3 \end{aligned}$$

Question 27: Basics of Signals & Systems (GATE EC 2023)

MCQ

1 Mark

In the table shown below, match the signal type with its spectral characteristics.

Signal type	Spectral Characteristics
(i) Continuous, aperiodic	(i) Continuous, aperiodic
(ii) Continuous, periodic	(ii) Continuous, periodic
(iii) Discrete, aperiodic	(iii) Discrete, aperiodic
(iv) Discrete, periodic	(iv) Discrete, periodic

- (A) (i) $\rightarrow$ (a), (ii) $\rightarrow$ (b), (iii) $\rightarrow$ (c), (iv) $\rightarrow$ (d)
- (B) **(Correct)** (i) $\rightarrow$ (a), (ii) $\rightarrow$ (c), (iii) $\rightarrow$, (iv) $\rightarrow$ (d)
- (C) (i) $\rightarrow$ (d), (ii) $\rightarrow$ (b), (iii) $\rightarrow$ (c), (iv) $\rightarrow$ (a)
- (D) (i) $\rightarrow$ (a), (ii) $\rightarrow$ (c), (iii) $\rightarrow$ (d), (iv) $\rightarrow$ (b)

Correct Answer: (B)

Question 28: Fourier Transforms (GATE EC 2023)

MCQ

1 Mark

The Fourier transform $X(\omega)$ of $x(t) = e^{-t^2}$ is

- (A) $\sqrt{\pi}e^{\frac{\omega^2}{2}}$
- (B) $\frac{e^{-\frac{\omega^2}{4}}}{2\sqrt{\pi}}$
- (C) **(Correct)** $\sqrt{\pi}e^{-\frac{\omega^2}{4}}$
- (D) $\sqrt{\pi}e^{-\frac{\omega^2}{2}}$

Correct Answer: (C)

Detailed Solution – Question 28

We know;

$$e^{-at^2}; a > 0 \xLeftrightarrow{FT} \sqrt{\frac{\pi}{a}} \cdot e^{-\omega^2/4a}$$

Here; $a = 1$

$$\therefore X(\omega) = \sqrt{\pi} \cdot e^{-\omega^2/4}$$

Question 29: Basics of Signals & Systems (GATE EC 2023)



MCQ

1 Mark

Let $m(t)$ be a strictly band-limited signal with bandwidth B and energy E . Assuming $\omega_0 = 10B$, the energy in the signal $m(t) \cos \omega_0 t$ is

- (A) $\frac{E}{4}$
- (B) **(Correct)** $\frac{E}{2}$
- (C) E
- (D) $2E$

Correct Answer: (B)





$$\text{Energy } (E) = \frac{1}{2\pi} \int_{-B}^B (1)^2 \cdot d\omega$$

$$E = \frac{B}{\pi}$$

Now, let $y(t) = m(t) \cos \omega_0 t$

$$Y(\omega) = \frac{1}{2} [M(\omega - \omega_0) + M(\omega + \omega_0)]$$

Here; $\omega_0 = 10B$



Now,

$$\begin{aligned} \text{Energy } (E') &= \frac{1}{2\pi} \int_{-\infty}^{\infty} |Y(\omega)|^2 \cdot d\omega \\ &= \frac{1}{2\pi} \left[\int_{-11B}^{-9B} \left(\frac{1}{2}\right)^2 \cdot d\omega + \int_{9B}^{11B} \left(\frac{1}{2}\right)^2 \cdot d\omega \right] \end{aligned}$$

$$= \frac{1}{2\pi} \left[\frac{1}{4} \times 2B + \frac{1}{4} \times 2B \right]$$

$$E' = \frac{B}{\pi} = E$$

Question 30: LTI Systems (GATE EC 2023)

MCQ

1 Mark

Consider a system with input $x(t)$ and output $y(t) = x(e^t)$. The system is

- (A) Causal and time invariant
- (B) **(Correct)** Non-causal and time varying
- (C) Causal and time varying
- (D) Non-causal and time invariant

Correct Answer: (B)

Detailed Solution – Question 30

We have, $y(t) = x(e^t)$

At $t = 0$

$$y(0) = x(1)$$

i.e. present value of output depends on future value of input, hence it is non-causal.

For Time Variant: Delay the input,

$$y(t) = x(e^t - t_0) \quad \dots(i)$$

Delay the output,

$$y(t - t_0) = x(e^{t-t_0}) \quad \dots(ii)$$

i.e. equations (i) $\neq$ (ii)

Hence, it is time variant system.

Question 31: DTFS, DTFT & DFT (GATE EC 2022)

NAT

2 Marks

For a vector $\bar{x} = [x[0], x[1], \dots, x[7]]$, the 8-point discrete Fourier transform (DFT) is denoted by $\bar{X} = DFT(\bar{x}) = [X[0], X[1], \dots, X[7]]$, where $X[k] = \sum_{n=0}^7 x[n] \exp(-j \frac{2\pi}{8} nk)$. Here, $j = \sqrt{-1}$. If $\bar{x} = [1, 0, 0, 0, 2, 0, 0, 0]$ and $\bar{y} = DFT(DFT(\bar{x}))$, then the value of $y[0]$ is _____ (rounded off to one decimal place).

Detailed Solution – Question 31

$$\begin{aligned}
 X[K] &= \sum_{n=0}^7 x[n] \exp\left(-j \frac{2\pi}{8} nk\right) \\
 \bar{y} &= DFT(DFT(\bar{x})) \text{ where} \\
 \bar{x} &= [x[0], x[1], \dots, x[7]] \\
 y(0) &=? \quad x[n] = [1, 0, 0, 0, 2, 0, 0, 0] \\
 x[n] &\xrightarrow{DFT} \xrightarrow{DFT} N \cdot x(-k) = \bar{y}(n) \\
 \bar{y}(n) &= N \cdot x(-k)|_{\text{mod } N} = N \cdot x(N-K), N = 8 \\
 \bar{y}(n) &= 8[1, 0, 0, 0, 2, 0, 0, 0] \\
 \bar{y}(n) &= [8, 0, 0, 0, 16, 0, 0, 0] \\
 y(0) &= 8
 \end{aligned}$$


Question 32: LTI Systems (GATE EC 2022)


MSQ

2 Marks

The outputs of four systems (S_1, S_2, S_3, S_4) corresponding to the input signal $\sin(t)$, for all time t , are shown in the figure.

Based on the given information, which of the four systems is/are definitely NOT LTI (linear and time-invariant)?






- (A) S_1
- (B) S_2
- (C) **(Correct)** S_3
- (D) **(Correct)** S_4

Correct Answer: (C, D)

Detailed Solution – Question 32



Since, LTI systems does not change the frequency of sinusoidal input. So S3 and S4 are definitely not LTI as input and output sinusoidal frequencies are different.

Question 33: LTI Systems (GATE EC 2022)

NAT

1 Mark

Let $x_1(t) = e^{-t}u(t)$ and $x_2(t) = u(t) - u(t-2)$, where $u(\cdot)$ denotes the unit step function. If $y(t)$ denotes the convolution of $x_1(t)$ and $x_2(t)$, then $\lim_{t \rightarrow \infty} y(t) = \dots\dots\dots$ (rounded off to one decimal place).

Detailed Solution – Question 33

$$\begin{aligned}
 x_1(t) &= e^{-t}U(t) \xleftrightarrow{L.T.} \frac{1}{(s+1)} \\
 x_2(t) &= U(t) - U(t-2) \xleftrightarrow{L.T.} \frac{1}{s} - \frac{e^{-2s}}{s} = \frac{1 - e^{-2s}}{s} \\
 y(t) &= x_1(t) \otimes x_2(t) \xleftrightarrow{L.T.} \frac{(1 - e^{-2s})}{s(s+1)} \\
 y(t) &\xleftrightarrow{L.T.} \frac{1 - e^{-2s}}{s(s+1)} \\
 \lim_{t \rightarrow \infty} y(t) &= \lim_{s \rightarrow 0} \frac{s(1 - e^{-2s})}{s(s+1)} = 0
 \end{aligned}$$

Question 34: DTFS, DTFT & DFT (GATE EC 2022)

MCQ

1 Mark

The Fourier transform $X(j\omega)$ of the signal $x(t) = \frac{t}{(1+t^2)^2}$ is -----.

(A) **(Correct)** $\frac{\pi}{2j}\omega e^{-|\omega|}$

(B) $\frac{\pi}{2}\omega e^{-|\omega|}$

(C) $\frac{\pi}{2j}e^{-|\omega|}$

(D) $\frac{\pi}{2}e^{-|\omega|}$

Correct Answer: (A)

Detailed Solution – Question 34

$$\begin{aligned} x(t) &= \frac{t}{(1+t^2)^2} \text{ As we know that FT of } te^{-|t|} \xleftrightarrow{FT} \frac{-j4\omega}{(1+\omega^2)^2} \text{ Duality } \frac{-j4\omega}{(1+t^2)^2} \leftrightarrow 2\pi(-\omega)e^{-|-\omega|} \\ &\Rightarrow \frac{t}{(1+t^2)^2} \xrightarrow{FT} \frac{-2\pi}{-j4}\omega e^{-|\omega|} \\ &\Rightarrow \rightarrow \frac{\pi}{j2}\omega e^{-|\omega|} \end{aligned}$$

Question 35: DTFS, DTFT & DFT (GATE EC 2021)

NAT

2 Marks

Consider the signals $x[n] = 2^{n-1}u[-n+2]$ and $y[n] = 2^{-n+2}u[n+1]$, where $u[n]$ is the unit step sequence. Let $X(e^{j\omega})$ and $Y(e^{j\omega})$ be the discrete-time Fourier transform of $x[n]$ and $y[n]$, respectively. The value of the integral

$$\frac{1}{2\pi} \int_0^{2\pi} X(e^{j\omega}) Y(e^{-j\omega}) d\omega$$

(rounded off to one decimal place) is -----

Detailed Solution – Question 35

$$x[n] = 2^{n-1}u[-n+2]$$

$$y[n] = 2^{-n+2}u[n+1]$$

$$y[-n] = 2^{n+2}u[-n+1]$$

$$V = \frac{1}{2\pi} \int_0^{2\pi} X(e^{j\omega}) Y(e^{-j\omega}) d\omega \quad \dots (i)$$

$$z[n] = x[n] * y[-n]$$

$$z[n] \rightarrow Z(e^{j\omega})$$

$$z[n] = \frac{1}{2\pi} \int_{-\pi}^{\pi} Z(e^{j\omega}) e^{j\omega n} d\omega$$

$$\text{Put } n = 0, \quad z[0] = \frac{1}{2\pi} \int_0^{2\pi} Z(e^{j\omega}) d\omega \quad \dots (ii)$$

Compare equations (i) and (ii)

$$z[0] = V$$

$$Z(e^{j\omega}) = X(e^{j\omega}) Y(e^{-j\omega})$$

$$\text{Apply IDTFT,} \quad Z[n] = x[n] * y[-n] = x[n] * p[n]$$

$$\therefore p[n] = y[-n] = 2^{n+2}u[-n+1]$$

$$z[n] = \sum_{k=-\infty}^{+\infty} 2^{k-1}u[-k+2]2^{n-k+2}u[-n+k+1]$$

$$= \sum_{k=-\infty}^2 2^{k-1}1 \cdot 2^{n-k+2}u[k+1-n]$$

$$= \sum_{k=-\infty}^2 2^{k-1+n-k+2}u[k+1-n]$$

$$z[n] = \sum_{k=-\infty}^2 2^{n+1}u[k-n+1]$$

$$\text{Put } n = 0, \quad V = z[0] = \sum_{k=-\infty}^2 2^1 \cdot u[k+1] = 2 \sum_{k=-1}^2 1 = 2[1+1+1+1]$$

$$V = 8$$

Question 36: LTI Systems (GATE EC 2021)

NAT


2 Marks

For a unit step input $u[n]$, a discrete-time LTI system produces an output signal

$$(2\delta[n+1] + \delta[n] + \delta[n-1])$$

. Let $y[n]$ be the output of the system for an input $\left(\left(\frac{1}{2}\right)^n u[n]\right)$. The value of $y[0]$ is _____

Detailed Solution – Question 36



The impulse response $h(n) = s(n) - s(n-1)$

$$\begin{aligned} h(n) &= 2\delta(n+1) + \delta(n) + \delta(n-1) - 2\delta(n) - \delta(n-1) - \delta(n-1-1) \\ &= 2\delta(n+1) + \delta(n) + \delta(n-1) - 2\delta(n) - \delta(n-1) - \delta(n-2) \\ h(n) &= 2\delta(n+1) - \delta(n) - \delta(n-2) \end{aligned}$$

For input $x_1(n) = (1/2)^n u(n)$ then output $y_1(n) = x_1(n) * h(n)$

$$y_1(n) = \left(\frac{1}{2}\right)^n u(n) * [2\delta(n+1) - \delta(n) - \delta(n-2)]$$

$$y_1(n) = \left(\frac{1}{2}\right)^n u(n) * 2\delta(n+1) - \left(\frac{1}{2}\right)^n u(n) * \delta(n) - \left(\frac{1}{2}\right)^n u(n) * \delta(n-2)$$

$$y_1(n) = 2 \left(\frac{1}{2}\right)^{n+1} u(n+1) - \left(\frac{1}{2}\right)^n u(n) - \left(\frac{1}{2}\right)^{n-2} u(n-2)$$

$$y_1(n)|_{n=0} = 2 \left(\frac{1}{2}\right)^1 u(1) - \left(\frac{1}{2}\right)^0 u(0) - \left(\frac{1}{2}\right)^{-2} u(-2)$$

$$= 1 - 1$$

$$y_1(0) = 0$$

Question 37: Fourier Transforms (GATE EC 2021)

NAT

2 Marks

The exponential Fourier series representation of a continuous-time periodic signal $x(t)$ is defined as

$$x(t) = \sum_{k=-\infty}^{\infty} a_k e^{jk\omega_0 t}$$

where ω_0 is the fundamental angular frequency of $x(t)$ and the coefficients of the series are a_k . The following information is given about $x(t)$ and a_k .

- I. $x(t)$ is real and even, having a fundamental period of 6
- II. The average value of $x(t)$ is 2
- III.

$$a_k = \begin{cases} k, & 1 \leq k \leq 3 \\ 0, & k > 3 \end{cases}$$

The average power of the signal $x(t)$ (rounded off to one decimal place) is _____

Detailed Solution – Question 37

1. $x(t)$ is real and even so a_k is also real and even $a_k = a_{-k}$ 2. Average of $x(t)$ is 2 i.e., $a_0 = 2$.

$$\begin{array}{rcll} 3. x(t) \rightarrow a_k = k & 1 \leq k \leq 3 & a_1 = 1 & a_{-1} = 1 \\ & 0 & a_2 = 2 & a_{-2} = 2 \\ & k > 3 & a_3 = 3 & a_{-3} = 3 \end{array}$$

4. $T_0 = 6$ Parseval's Power Theorem

$$\begin{aligned} \frac{1}{T} \int_0^T |x(t)|^2 dt &= \sum_{n=-\infty}^{+\infty} |a_k|^2 \\ P(t) &= \sum_{n=-\infty}^{+\infty} |a_k|^2 = |a_{-3}|^2 + |a_{-2}|^2 + |a_{-1}|^2 + |a_0|^2 + |a_1|^2 + |a_2|^2 + |a_3|^2 \\ &= 2|a_1|^2 + 2|a_2|^2 + 2|a_3|^2 + |a_0|^2 \\ &= 2 \times 1^2 + 2 \times (2)^2 + 2(3)^2 + (2)^2 \\ &= 2 + 8 + 18 + 4 \\ P_{x(t)} &= 32 \end{aligned}$$

Question 38: DTFS, DTFT & DFT (GATE EC 2021)

MCQ

1 Mark

Consider two 16-point sequences $x[n]$ and $h[n]$. Let the linear convolution of $x[n]$ and $h[n]$ be denoted by $y[n]$, while $z[n]$ denotes the 16-point inverse discrete Fourier transform (IDFT) of the product of the 16-point DFTs of $x[n]$ and $h[n]$. The value(s) of k for which $z[k]=y[k]$ is/are

- (A) $k=0,1,2,,15$
- (B) $k=0$
- (C) **(Correct)** $k=15$
- (D) $k=0$ and $k=15$

Correct Answer: (C)

Detailed Solution – Question 38

If two 'N' point signals $x(n)$ and $h(n)$ are convolving with each other linearly and circularly then $y(k) = z(k)$ at $k = N - 1$

where, $y(n)$ = Linear convolution of $x(n)$ and $h(n)$

$z(n)$ = Circular convolution of $x(n)$ and $h(n)$

Since, $N = 16$ (Given)

Therefore, $y(k) = z(k)$ at $k = N - 1 = 15$

Question 39: Sampling (GATE EC 2021)

MCQ







1 Mark

Consider a real-valued base-band signal $x(t)$, band limited to 10 kHz. The Nyquist rate for the signal

$$y(t) = x(t) x\left(1 + \frac{t}{2}\right) \text{ is}$$

- (A) 15 kHz
- (B) **(Correct)** 30 kHz
- (C) 60 kHz
- (D) 20 kHz

Correct Answer: (B)



$$NR = 2 \times f_{\max} = 2 \times 15 = 30 \text{ kHz}$$

Question 40: Z-Transform (GATE EC 2020)

NAT

2 Marks

The transfer function of a stable discrete-time LTI system is $H(z) = \frac{K(z-\alpha)}{z+0.5}$, where K and α are real numbers. The value of α (rounded off to one decimal place) with $|\alpha| > 1$, for which the magnitude response of the system is constant over all frequencies, is

Detailed Solution – Question 40

System is all-pass filter. For digital all-pass filter, condition is

zero = $\frac{1}{\text{pole}^*}$... (i) By given transfer function,



zero = α Pole = -0.5 using condition (i), $\alpha = \frac{1}{-0.5} = -2$

Question 41: Fourier Transforms (GATE EC 2020)

NAT

2 Marks

$X(\omega)$ is the Fourier transform of $x(t)$ shown below. The value of $\int_{-\infty}^{\infty} |X(\omega)|^2 d\omega$ (rounded off to two decimal places) is



Detailed Solution – Question 41

$$\begin{aligned}\int_{-\infty}^{\infty} |X(\omega)|^2 d\omega &= 2\pi \int_{-\infty}^{\infty} |x(t)|^2 dt \\&= 2\pi \int_{-\infty}^{\infty} |y(t)|^2 dt \\&= 2 \times 2\pi \int_{-2}^0 |y(t)|^2 dt \\&= 2 \times 2\pi \left[\int_{-2}^{-1} (t+2)^2 dt + \int_{-1}^0 (2t+3)^2 dt \right] \\&= 4\pi \left[\left\{ \frac{(t+2)^3}{3} \right\}_{-2}^{-1} + \left\{ \frac{(2t+3)^3}{3 \times 2} \right\}_{-1}^0 \right] \\&= 4\pi \left[\frac{1-0}{3} + \frac{3^3-1}{6} \right] \\&= 4\pi \left[\frac{1}{3} + \frac{26}{6} \right] \\&= 4\pi \times \left[\frac{1}{3} + \frac{26}{6} \right] \\&= 4\pi \times \left[\frac{1}{3} + \frac{13}{3} \right] \\&= 4\pi \times \frac{14}{3} \\&= \frac{56\pi}{3} = 58.61\end{aligned}$$

Question 42: DTFS, DTFT & DFT (GATE EC 2020)

MCQ

2 Marks

A finite duration discrete-time signal $x[n]$ is obtained by sampling the continuous-time signal $x(t) = \cos(200\pi t)$ at sampling instants $t = n/400$, $n = 0, 1, \dots, 7$. The 8-point discrete Fourier transform (DFT) of $x[n]$ is defined as

$$x[k] = \sum_{n=0}^7 x[n] e^{-j\frac{\pi kn}{4}}, \quad k=0, 1, \dots, 7.$$

Which one of the following statement is TRUE?

- (A) All $X[k]$ are non-zero
- (B) Only $X[4]$ is non-zero
- (C) **(Correct)** Only $X[2]$ and $X[6]$ are non-zero
- (D) Only $X[3]$ and $X[5]$ are non-zero

Correct Answer: (C)

Detailed Solution – Question 42

$$x(t) = \cos 200\pi t$$

$$t = \frac{n}{400}$$

$$x(n) = \cos \left(200\pi \frac{n}{400} \right)$$

$$= \cos \left(\frac{\pi}{2} n \right); \quad n = 0, 1, \dots, 7$$

$$= \left\{ \cos 0, \cos \frac{\pi}{2}, \cos \pi, \cos \frac{3\pi}{2}, \cos 2\pi, \cos \frac{5\pi}{2}, \cos 3\pi, \cos \frac{7\pi}{2} \right\}$$

$$= 1, 0, -1, 0, 1, 0, -1, 0 \iff \text{DFT } X(K)$$

$$\text{suppose, } y(n) = 1, -1, 1, -1 \iff \text{DFT } Y(k)$$

$$[Y(K)] = [W_N]_{N=4} [y(n)] = \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 1 \\ -1 \\ 1 \\ -1 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 4 & 0 \end{bmatrix}$$

Now, as we know, If for $\{a, b, c, d\} \iff \text{DFT } \{A, B, C, D\}$ Then for,

$$\{a, 0, b, 0, c, 0, d, 0\} \iff \text{DFT } \{A, B, C, D, A, B, C, D\}$$









Similarly for $y(n) = 1, -1, 1, -1 \iff \text{DFT } Y(k) = \{0, 0, 4, 0\}$ Here, for $x(n) = \{1, 0, -1, 0, 1, 0, -1, 0\}$ $X(k) = \left\{ \begin{matrix} \uparrow \\ 0 \end{matrix}, 0, 4, 0, 0, 0, 4, 0 \right\}$

Question 43: LTI Systems (GATE EC 2020)

MCQ

1 Mark

Which one of the following pole-zero corresponds to the transfer function of an LTI system characterized by the input-output difference equation given below? $y[n] = \sum_{k=0}^3 (-1)^k x[n-k]$



(A) (Correct) A

(B) B

(C) C



(D) D

Correct Answer: (A)

Detailed Solution – Question 43

$$\begin{aligned}y(n) &= \sum_{K=0}^3 (-1)^K x(n-K) \\&= x(n) - x(n-1) + x(n-2) - x(n-3) \\y(z) &= X(z) - z^{-1}X(z) + Z^{-2}X(z) - Z^{-3}X(z) \\H(z) &= \frac{Y(z)}{X(z)} = 1 - Z^{-1} + Z^{-2} - Z^{-3} \\&= \frac{z^3 - z^2 + z - 1}{z^3} = \frac{(z-1)(z^2+1)}{Z^3}\end{aligned}$$

Pole Zero plot:



Question 44: LTI Systems (GATE EC 2020)

MCQ

1 Mark

The output $y[n]$ of a discrete-time system for an input $x[n]$ is

$$y[n] = \max_{-\infty \leq k \leq n} |x[k]|$$

The unit impulse response of the system is

(A) 0 for all n

(B) 1 for all n

(C) **(Correct)** unit step signal $u[n]$.

(D) unit impulse signal $\delta[n]$.

Correct Answer: (C)

Question 45: Digital Filters (GATE EC 2019)

NAT

2 Marks

Let $h[n]$ be a length-7 discrete-time finite impulse response filter, given by

$h[0]=4, h[1]=3, h[2]=2, h[3]=1, h[-1]=-3, h[-2]=-2, h[-3]=-1,$

and $h[n]$ is zero for $|n| \geq 4$. A length-3 finite impulse response approximation $g[n]$ of $g[n]$ has to be obtained such that

$$E(h, g) = \int_{-\pi}^{\pi} |H(e^{j\omega}) - G(e^{j\omega})|^2 d\omega$$

is minimized, where $H(e^{j\omega})$ and $G(e^{j\omega})$ are the discrete-time Fourier transforms of $h[n]$ and $g[n]$, respectively. For the filter that minimizes $E(h, g)$, the value of $10g[-1] + g[1]$, rounded off to 2 decimal places, is _____

Detailed Solution – Question 45

From Parseval's theorem,

$$\sum_{n=-\infty}^{\infty} |x[n]|^2 = \frac{1}{2\pi} \int_{-\pi}^{\pi} |X(e^{j\omega})|^2 d\omega$$

So,

$$\int_{-\pi}^{\pi} |H(e^{j\omega}) - G(e^{j\omega})|^2 d\omega = 2\pi \sum_{n=-3}^3 |h(n) - g(n)|^2$$

The solution of $g(n)$ that minimizes $E(h, g)$ also minimizes $\sum_{n=-3}^3 |h(n) - g(n)|^2$. The solution of $g(n)$ that minimizes the above equation is $g(n) = (-3, 4, 3)$. So, $10g(-1) + g(1) = 10(-3) + 3 = -27$

Question 46: DTFS, DTFT & DFT (GATE EC 2019)

MCQ

2 Marks


It is desired to find a three-tap causal filter which gives zero signal as an output to an input of the form


$$x[n] = c_1 \exp\left(-\frac{j\pi n}{2}\right) + c_2 \exp\left(\frac{j\pi n}{2}\right)$$

where c_1 and c_2 are arbitrary real numbers. The desired three-tap filter is given by

$h[0] = 1, h[1] = a, h[2] = b$ and $h[n] = 0$ for $n < 0$ or $n > 2$

What are the values of the filter taps a and b if the output is $y[n]=0$ for all n , when $x[n]$ is as given above?





- (A) $a=1, b=1$
- (B) $a=0, b=-1$
- (C) $a=-1, b=1$
- (D) **(Correct)** $a=0, b=1$

Correct Answer: (D)

Detailed Solution – Question 46

$$x(n) = c_1 e^{-j\frac{\pi}{2}n} + c_2 e^{j\frac{\pi}{2}n}$$

$$\omega_0 = \frac{\pi}{2} \text{ rad/s}$$

$$H(e^{j\omega}) = 1 + ae^{-j\omega} + be^{-j2\omega}$$

To get $y(n) = 0$

$$H(e^{j\omega_0}) = H(e^{j\omega})|_{\omega=\frac{\pi}{2}} = 0$$

$$1 + ae^{-j\frac{\pi}{2}} + be^{-j2\frac{\pi}{2}} = 0$$

$$1 - ja - b = 0$$


From the given options, $a=0$ and $b=1$


Question 47: DTFS, DTFT & DFT (GATE EC 2019)

MCQ

2 Marks

Consider a six-point decimation-in-time Fast Fourier Transform (FFT) algorithm, for which the signal-flow graph corresponding to $X[1]$ is shown in the figure. Let $W_6 = \exp\left(-\frac{j2\pi}{6}\right)$. In the figure, what should be the values of the coefficients a_1, a_2, a_3 in terms of W_6 so that $X[1]$ is obtained correctly?





- (A) $a_1 = -1, a_2 = W_6, a_3 = W_6^2$
 (B) $a_1 = 1, a_2 = W_6^2, a_3 = W_6$
 (C) **(Correct)** $a_1 = 1, a_2 = W_6, a_3 = W_6^2$
 (D) $a_1 = -1, a_2 = W_6^2, a_3 = W_6$

Correct Answer: (C)

Detailed Solution – Question 47

$$X(k) = \sum_{n=0}^{N-1} x(n)e^{-j\frac{2\pi}{N}kn}$$

$$X(1) = \sum_{n=0}^5 x(n)W_6^n$$

$$= x(0) + x(1)W_6 + x(2)W_6^2 + x(3)W_6^3 + x(4)W_6^4 + x(5)W_6^5 \dots (i)$$

From the given flow graph, $X(k) = [x(0) - x(3)]a_1 + [x(1) - x(4)]a_2 + [x(2) - x(5)]a_3$ By comparing equations (i) and (ii), we get. $a_1 = 1, a_2 = W_6, a_3 = W_6^2$

Question 48: Basics of Signals & Systems (GATE EC 2019)

NAT

1 Mark

Consider the signal

$$f(t) = 1 + 2\cos(\pi t) + 3\sin\left(\frac{2\pi}{3}t\right) + 4\cos\left(\frac{\pi}{2}t + \frac{\pi}{4}\right)$$

, where t is in seconds. Its fundamental time period, in seconds, is _____

Detailed Solution – Question 48

$$f(t) = 1 + 2\cos(\pi t) + 3\sin\left(\frac{2\pi}{3}t\right) + 4\cos\left(\frac{\pi}{2}t + \frac{\pi}{4}\right)$$

$$\omega_1 = \pi$$

$$\omega_2 = \frac{2\pi}{3}$$

$$\omega_3 = \frac{\pi}{2}$$

$$\omega_0 = \text{GCD}\left(\pi, \frac{2\pi}{3}, \frac{\pi}{2}\right) = \frac{\pi}{6}$$

$$\text{Fundamental period, } N = \frac{2\pi}{\omega_0} = \frac{2\pi}{(\pi/6)} = 12$$

Question 49: Laplace Transform (GATE EC 2019)

MCQ

1 Mark

Let $Y(s)$ be the unit-step response of a causal system having a transfer function $G(s) = \frac{3-s}{(s+1)(s+3)}$ that is, $Y(s) = \frac{G(s)}{s}$. The forced response of the system is

- (A) $u(t) - 2e^{-t}u(t) + e^{-3t}u(t)$
- (B) $2u(t) - 2e^{-t}u(t) + e^{-3t}u(t)$
- (C) $2u(t)$
- (D) **(Correct)** $u(t)$

Correct Answer: (D)

Detailed Solution – Question 49

Given, $G(s) = \frac{3-s}{(s+1)(s+3)} \therefore Y(s) = \frac{G(s)}{s} = \frac{3-s}{s(s+1)(s+3)}$ Using partial fractions, we get,

$$Y(s) = \frac{A}{s} + \frac{B}{(s+1)} + \frac{C}{(s+3)}$$

$$A(s^2 + 4s + 3) + B(s^2 + 3s) + C(s^2 + s) = 3 - s$$

$$A + B + C = 0$$

$$4A + 3B + C = -1$$

$$\text{and } 3A = 3$$

Therefore, we get,

$$A = 1, B = -2 \text{ and } C = 1$$

$$\text{So, } Y(s) = \frac{1}{s} - \frac{2}{(s+1)} + \frac{1}{(s+3)}$$

$$\text{and } y(t) = u(t) - 2e^{-t}u(t) + e^{-3t}u(t)$$



Forced response, $y_t(t) = u(t) \Rightarrow$ option (D)

Question 50: Z-Transform (GATE EC 2019)

MCQ

1 Mark

Let $H(z)$ be the z-transform of a real-valued discrete-time signal $h[n]$. If $P(z) = H(z)H\left(\frac{1}{z}\right)$ has a zero at $z = \frac{1}{2} + \frac{1}{2}j$, and $P(z)$ has a total of four zeros, which one of the following plots represents all the zeros correctly?



- (A) A
- (B) B
- (C) C
- (D) (Correct) D

Correct Answer: (D)

Detailed Solution – Question 50

$P(Z) = H(Z)H\left(\frac{1}{Z}\right)$ (i) $h(n)$ is real. Som $p(n)$ will be also real (ii) $P(z) = P(z^{-1})$
From (i) : if z_1 is a zero of $P(z)$, then z_1^* will be also a zero of $P(z)$. From (ii): If z_1 is a zero of $P(z)$, then $\frac{1}{z_1}$ will be also a zero of $P(z)$. So, the 4 zeros are,

$$\begin{aligned}z_1 &= \frac{1}{2} + \frac{1}{2}j \\z_2 &= z_1^* = \frac{1}{2} - \frac{1}{2}j \\z_3 &= \frac{1}{z_1} = \frac{1}{\frac{1}{2} - \frac{1}{2}j} = 1 - j \\z_4 &= \left(\frac{1}{z_1}\right)^* = z_3^* = 1 + j\end{aligned}$$

Question 51: DTFS, DTFT & DFT (GATE EC 2018)

NAT

Let $X[k] = k + 1$, $0 \leq k \leq 7$ be 8-point DFT of a sequence $x[n]$, where $X[k] = \sum_{n=0}^{N-1} x[n]e^{-\frac{j2\pi kn}{N}}$. The value (correct to two decimal places) of $\sum_{n=0}^3 x[2n]$ is -----.

2 Marks

Detailed Solution – Question 51



$$\begin{aligned}x(k) &= \{1, 2, 3, 4, 5, 6, 7, 8\} \\x(k) &= \sum_{n=0}^7 x[n]e^{-j\frac{2\pi}{8}kn} \\&= \sum_{n=0}^7 x[n]e^{-i\frac{\pi}{4}kn} \\\sum_{n=0}^3 x[2n] &= \sum_{n=0,2,4,6}^7 x[n] \\&= \frac{1}{2} \sum_{n=0}^7 (x[n] + (-1)^n x[n]) \\\sum_{n=0}^7 x[n] &= x(0) = 1 \\\sum_{n=0}^7 (-1)^n x[n] &= \sum_{n=0}^7 x[n]e^{-i\frac{\pi}{4}4n} = x(4) = 5 \\\sum_{n=0}^3 x[2n] &= \frac{1}{2}[1 + 5] = 3\end{aligned}$$

Question 52: Sampling (GATE EC 2018)

NAT

2 Marks



A band limited low-pass signal $x(t)$ of bandwidth 5 kHz is sampled at a sampling rate f_s . The signal $x(t)$ is reconstructed using the reconstruction filter $H(f)$ whose magnitude response is shown below:





The minimum sampling rate f_s (in kHz) for perfect reconstruction of $x(t)$ is

Detailed Solution – Question 52

Let us assume an arbitrary spectrum for $x(t)$ as shown below:



The spectrum of the sampled signal can be given as,



For proper reconstruction of the signal,

$$f_s - 5 \geq 8$$

$$f_s \geq 8 + 5 = 13 \text{ kHz}$$


$$\text{So, } f_{s(\min)} = 13 \text{ kHz}$$

Question 53: Fourier Transforms (GATE EC 2018)

NAT

2 Marks

The input $4\text{sinc}(2t)$ is fed to a Hilbert transformer to obtain $y(t)$, as shown in the figure below:





Here $\text{sinc}(x) = \frac{\sin(\pi x)}{\pi x}$. The value (accurate to two decimal places) of $\int_{-\infty}^{\infty} |y(t)|^2 dt$ is

Detailed Solution – Question 53

Hilbert transform does not alter the amplitude spectrum of the signal.

$$\begin{aligned} \text{So, } \int_{-\infty}^{\infty} |y(t)|^2 dt &= \int_{-\infty}^{\infty} |x(t)|^2 dt = \int_{-\infty}^{\infty} |X(f)|^2 df \\ x(t) &= 4 \text{sinc}(2t) \\ \text{sinc}(t) &\xleftrightarrow{\text{CTFT}} \text{rect}(f) \\ 4\text{sinc}(2t) &\xleftrightarrow{\text{CTFT}} +\frac{4}{2}\text{rect}\left(\frac{f}{2}\right) = 2\text{rect}\left(\frac{f}{2}\right) \end{aligned} \quad \begin{aligned} \int_{-\infty}^{\infty} |X(f)|^2 df &= 2 \times (2)^2 = 8 \\ \text{So, } \int_{-\infty}^{\infty} |y(t)|^2 dt &= 8 \end{aligned}$$



Question 54: Fourier Series (GATE EC 2018)

MCQ

1 Mark

Let $x(t)$ be a periodic function with period $T = 10$. The Fourier series coefficients for this series are denoted by a_k , that is

$$x(t) = \sum_{k=-\infty}^{\infty} a_k e^{jk\frac{2\pi}{T}t}$$

The same function $x(t)$ can also be considered function with period $T = 40'$. Let b_k be the Fourier series coefficients when period is taken as T' . If $\sum_{k=-\infty}^{\infty} |a_k| = 16$, then $\sum_{k=-\infty}^{\infty} |b_k|$ is equal to

(A) 256

- (B) 64
(C) **(Correct)** 16
(D) 4

Correct Answer: (C)

Detailed Solution – Question 54

Change in only time period or frequency does not change in the value of Fourier series coefficients
So,

$$b_k = a_k$$
$$\sum_{k=-\infty}^{\infty} |b_k| = \sum_{k=-\infty}^{\infty} |a_k| = 16$$

Question 55: Z-Transform (GATE EC 2018)


MCQ

1 Mark

A discrete-time all-pass system has two of its poles at $0.25\angle 0^\circ$ and $2\angle 30^\circ$. Which one of the following statements about the system is TRUE?

- (A) It has two more poles at $0.5\angle 0^\circ$ and $4\angle 0^\circ$.
(B) **(Correct)** It is stable only when the impulse response is two-sided.
(C) It has constant phase response over all frequencies.
(D) It has constant phase response over the entire z-plane.

Correct Answer: (B)



The AOC should include unit circle to make the system stable. From the given pole pattern it is clear that, to make the system stable, the ROC should be finite circular strip or finite annular strip and hence the impulse response of the system should be also two-sided.

Question 56: Basics of Signals & Systems (GATE EC 2018)

MCQ

1 Mark

Let the input be u and the output be y of a system, and the other parameters are real constants. Identify which among the following systems is not a linear system:

(A)

$$\frac{d^3 y}{dt^3} + a_1 \frac{d^2 y}{dt^2} + a_2 \frac{dy}{dt} + a_3 y =$$

$$b_3 u + b_2 \frac{du}{dt} + b_1 \frac{d^2 u}{dt^2} \text{ (with initial rest conditions)}$$

(B) $y(t) = \int_0^t e^{a(t-\tau)} \beta u(\tau) d\tau$

(C) **(Correct)** $y = au + b, b \neq 0$

(D) $y = au$

Correct Answer: (C)

Detailed Solution – Question 56


$y = au + b, b \neq 0$ is a non-linear system.

Question 57: LTI Systems (GATE EC 2017-SET-2)

NAT

2 Marks

Consider the parallel combination of two LTI systems shown in the figure.



The impulse responses of the systems are $h_1(t) = 2\delta(t+2) - 3\delta(t+1)$ $h_2(t) = \delta(t-2)$ If the input $x(t)$ is a unit step signal, then the energy of $y(t)$ is

Detailed Solution – Question 57

Given that,

$$h_1(t) = 2\delta(t+2) - 3\delta(t+1)$$

$$h_2(t) = \delta(t-2)$$



Overall impulse response is,

$$\begin{aligned} h(t) &= h_1(t) + h_2(t) \\ &= 2\delta(t+2) - 3\delta(t+1) + \delta(t-2) \end{aligned}$$


If input, $x(t) = u(t)$, then the output will be,

$$\begin{aligned} y(t) &= x(t) * h(t) \\ &= u(t) * [2\delta(t+2) - 3\delta(t+1) + \delta(t-2)] \\ &= 2u(t+2) - 3u(t+1) + u(t-2) \end{aligned}$$

By plotting $y(t)$, we get,



The energy of $y(t)$ can be given as, $E_y = \int_{-\infty}^{\infty} y^2(t) dt$ By plotting $y^2(t)$, we get,



Question 58: Laplace Transform (GATE EC 2017-SET-2)

NAT

2 Marks

The transfer function of a causal LTI system is $H(s) = 1/s$. If the input to the system is $x(t) = [\sin(t)/\pi t]u(t)$, where $u(t)$ is a unit step function, the system output $y(t)$ as $t \rightarrow \infty$ is.....

Detailed Solution – Question 58

$$\begin{aligned}H(s) &= \frac{1}{s} \Rightarrow \text{integrator} \\x(t) &= \frac{\sin t}{\pi t} u(t) \\ \text{So. } y(t) &= \int_0^t \frac{\sin \tau}{\pi \tau} dt \\ y(t)_{t \rightarrow \infty} &= \frac{1}{\pi} \int_0^\infty \frac{\sin \tau}{\tau} dt \\ \int_0^\infty \frac{\sin \tau}{\tau} dt &= \frac{\pi}{2} \\ \text{So. } y(t)_{t \rightarrow \infty} &= \frac{1}{\pi} \times \frac{\pi}{2} = \frac{1}{2} = 0.5\end{aligned}$$

Question 59: Sampling (GATE EC 2017-SET-2)

MCQ

2 Marks

The signal $x(t) = \sin(14000\pi t)$, where t is in seconds is sampled at a rate of 9000 samples per second. The sampled signal is the input to an ideal low pass filter with frequency response $H(f)$ as follows :

$$H(f) = \begin{cases} 1, & |f| \leq 12 \text{ kHz} \\ 0, & |f| \geq 12 \text{ kHz} \end{cases}$$

What is the number of sinusoids in the output and their frequencies in kHz?

- (A) Number = 1, frequency = 7
- (B) **(Correct)** Number = 3, frequencies = 2, 7, 11
- (C) Number = 2, frequencies = 2, 7
- (D) Number = 2, frequencies = 2, 11

Correct Answer: (B)



Detailed Solution – Question 59

$$x(t) = \sin(14000\pi t); f_m = 7\text{kHz}$$

$$f_s = 9000 \text{ samples per second}$$

$$= 9\text{kHz}$$

The spectrum of the sampled signal can be given as shown below:



So, three sinusoids will be there at the output of the LPF and the frequencies of those sinusoids are 2 kHz, 7 kHz and 11 kHz.

Question 60: Fourier Transforms (GATE EC 2017-SET-2)

NAT

2 Marks

Consider an LTI system with magnitude response

$$|H(f)| = \begin{cases} 1 - \frac{|f|}{20} & |f| \leq 20 \\ 0 & |f| > 20 \end{cases}$$



And phase response $\text{Arg } H(f) = -2f$ If the input to the system is

$$x(t) = 8\cos(20\pi t + \frac{\pi}{4}) + 16\sin(40\pi t + \frac{\pi}{8}) + 24\cos(80\pi t + \frac{\pi}{16})$$

Then the average power of the output signal $y(t)$ is -----.

Detailed Solution – Question 60

Since,



$$\text{So, } y(t) = \frac{1}{2} \times 8 \cos(20\pi t + \phi)$$

$$\text{So, } = 4 \cos(20\pi t + \phi); \phi = \frac{\pi}{4} - 20^\circ$$

$$P_y = \frac{4^2}{2} = 8\text{W}$$

Question 61: Basics of Signals & Systems (GATE EC 2017-SET-2)

MCQ

1 Mark

The input $x(t)$ and the output $y(t)$ of a continuous-time system are related as $y(t) = \int_{t-T}^t x(u)du$. The system is

- (A) Linear and time-variant
- (B) **(Correct)** Linear and time-invariant
- (C) Non-linear and time-variant
- (D) Non-linear and time-invariant

Correct Answer: (B)

Detailed Solution – Question 61

Given that, $y(t) = \int_{t-T}^t x(u)du$

since the given system satisfies both homogeneity and additivity properties, the system is linear.

Check for time invariance: $y(t - t_0) = \int_{t-t_0-T}^{t-t_0} x(u)du$

When the applied input is $x(t - t_0)$

$$\begin{aligned} y_1(t) &= \int_{t-T}^t x(u - t_0) du = \int_{t-t_0-T}^{t-t_0} x(\tau) d\tau \\ &= y(t - t_0) \end{aligned}$$

$\Rightarrow$ System is time invariant

Question 62: DTFS, DTFT & DFT (GATE EC 2017-SET-2)

MCQ

1 Mark

An LTI system with unit sample response $h[n] = 5\delta[n] - 7\delta[n-1] + 7\delta[n-3] - 5\delta[n-4]$ is a

- (A) Low - pass filter
- (B) high - pass filter
- (C) **(Correct)** band - pass filter
- (D) band - stop filter

Correct Answer: (C)

Detailed Solution – Question 62

$$h[n] = 5\delta[n] - 7\delta[n-1] + 7\delta[n-3] - 5\delta[n-4]$$

$$\text{Now, } H(e^{j\omega}) = 5 - 7e^{-j\omega} + 7e^{-3j\omega} - 5e^{-4j\omega}$$

Now for $\omega = 0$,

$$H(e^{j0}) = 5 - 7 + 7 - 5 = 0$$

and for $\omega = \pi$,

$$\begin{aligned} H(e^{j\pi}) &= 5 - 7(-1) + 7(-1) - 5(1) \\ &= 5 + 7 - 7 - 5 = 0 \end{aligned}$$

System is attenuating low and high frequencies whereas passing the mid frequencies. So, its a BPF.

Question 63: Fourier Transforms (GATE EC 2017-SET-1)

NAT

2 Marks


A continuous time signal $x(t) = 4\cos(200\pi t) + 8\cos(400\pi t)$, where t is in seconds, is the input to a linear time invariant (LTI) filter with the impulse response

$$h(t) = \begin{cases} \frac{2\sin(300\pi t)}{\pi t} & t \neq 0 \\ 600 & t = 0 \end{cases}$$

Let $y(t)$ be the output of this filter. The maximum value of $|y(t)|$ is

Detailed Solution – Question 63

$$x(t) = 4 \cos 200\pi t + 8 \cos 400\pi t$$



$$\begin{aligned} \text{So, } y(t) &= 8 \cos 200\pi t \\ \therefore |y(t)|_{\max} &= 8 \end{aligned}$$

Question 64: DTFS, DTFT & DFT (GATE EC 2017-SET-1)

NAT

2 Marks

Let $h[n]$ be the impulse response of a discrete-time linear time invariant (LTI) filter. The impulse response is given by

$$h[0] = 1/3; h[1] = 1/3; h[2] = 1/3; \text{ and } h[n] = 0 \text{ for } n < 0 \text{ and } n > 2.$$

Let $H(\omega)$ be the discrete-time Fourier system transform (DTFT) of $h[n]$, where ω is the normalized angular frequency in radians. Given that $H(\omega_0) = 0$ and $0 < \omega_0 < \pi$, the value of ω_0 (in radians) is equal to

Detailed Solution – Question 64

$$\text{since } h[n] = \frac{1}{3}\delta[n] + \frac{1}{3}\delta[n-1] + \frac{1}{3}\delta[n-2]$$

$$\text{So, } H(e^{j\omega}) = \frac{1}{3}e^{-j\omega}[1 + 2\cos\omega]$$

$$H(e^{j\omega_0}) = 0, \quad \text{for } (1 + 2\cos\omega_0) = 0$$

$$\text{or } \cos\omega_0 = -\frac{1}{2}$$

$$\text{or } \omega_0 = \frac{2\pi}{3} = 2.10 \text{ radians}$$

Question 65: Fourier Series (GATE EC 2017-SET-1)

MCQ

2 Marks

Let $x(t)$ be a continuous time periodic signal with fundamental period $T = 1$ seconds. Let $\{a_k\}$ be the complex Fourier series coefficients of $x(t)$, where k is integer valued. Consider the following statements about $x(3t)$:

- I. The complex Fourier series coefficients of $x(3t)$ are $\{a_k\}$ where k is integer valued
 - II. The complex Fourier series coefficients of $x(3t)$ are $\{3a_k\}$ where k is integer valued
 - III. The fundamental angular frequency of $x(3t)$ is 6π rad/s
- For the three statements above, which one of the following is correct?

- (A) only II and III are true
- (B) **(Correct)** only I and III are true
- (C) only III is true
- (D) only I is true

Correct Answer: (B)

Detailed Solution – Question 65

Initially $T = 1\text{sec}$, so $\omega_0 = 2\pi\text{rad/sec}$. when is compressed by 3, frequency will expand by same factor but there is no change in values of a_k .
So, both statement I and III are correct

Question 66: LTI Systems (GATE EC 2017-SET-1)

NAT

2 Marks

Two discrete-time signals $x[n]$ and $h[n]$ are both non-zero for $n = 0, 1, 2$ and are zero otherwise. It is given that

$$x[0]=1, x[1]=2, x[2]=1, h[0]=1.$$

Let $y[n]$ be the linear convolution of $x[n]$ and $h[n]$. Given that $y[1] = 3$ and $y[2] = 4$, the value of the expression $(10y[3]+y[4])$ is -----.

Detailed Solution – Question 66

$$x[n] = \{1, 2, 1\}$$

$$h[n] = \{1, a, b\}$$

$$y[n] = \{A, 3, 4, B, C\}$$

$x \backslash h$	1	a	b
1	1	a	b
2	2	2a	2b
1	1	a	b

$x \backslash h$	1	a	b
1	1	a	b
2	2	2a	2b
1	1	a	b

$$y[0] = 1; y[1] = 2 + a; y[2] = 1 + 2a + b$$

$$y[3] = a + 2b; y[4] = b$$

$$\text{Given. } y[1] = 2 + a = 3 \Rightarrow a = 1$$

$$\text{Given, } y[2] = 1 + 2a + b = 4 \Rightarrow b = 1$$

$$\text{So, } y[3] = a + 2b = 3$$

$$\text{and } y[4] = b = 1$$

$$\text{So. } 10y[3] + y[4] = 10 \times 3 + 1 = 31$$

Question 67: Laplace Transform (GATE EC 2017-SET-1)

MCQ

1 Mark

Consider the following statements for continuous-time linear time invariant (LTI) systems.

I. There is no bounded input bounded output (BIBO) stable system with a pole in the righthalf of the complex plane.

II. There is non causal and BIBO stable system with a pole in the right half of the complex plane.

Which one among the following is correct?

- (A) Both I and II are true
- (B) Both I and II are not true
- (C) Only I is true
- (D) **(Correct)** Only II is true

Correct Answer: (D)

Detailed Solution – Question 67

A stable system can have poles in right half of complex plane, if it is a non-causal system. So, statement-I is wrong.

A causal and BIBO stable system should have all poles in the left half of complex plane. So, statement-II is correct.

Question 68: Fourier Series (GATE EC 2017-SET-1)

MCQ

1 Mark

A periodic signal $x(t)$ has a trigonometric Fourier series expansion $x(t) = a_0 + \sum_{n=1}^{\infty} (a_n \cos n\omega_0 t)$

If $x(t) = -x(t - \pi/\omega_0)$, we can conclude that

- (A) **(Correct)** a_n are zero for all n and b_n are zero for n even
- (B) a_n are zero for all n and b_n are zero for n odd
- (C) a_n are zero for n even and b_n are zero for n odd
- (D) a_n are zero for n odd and b_n are zero for n even

Correct Answer: (A)

Detailed Solution – Question 68

Signal has odd and half wave symmetries. So a_n are zero and b_n are zero for n even.

Question 69: Basics of Signals & Systems (GATE EC 2017-SET-1)

MCQ

1 Mark

Consider a single input single output discrete-time system with $x[n]$ as input and $y[n]$ as output, where the two are related as

$$y[n] = \begin{cases} n|x[n]| & \text{for } 0 \leq n \leq 10 \\ x[n] - x[n-1] & \text{otherwise} \end{cases}$$

Which one of the following statements is true about the system?

- (A) **(Correct)** It is causal and stable
- (B) It is causal but not stable
- (C) It is not causal but stable
- (D) It is neither causal nor stable

Correct Answer: (A)

Detailed Solution – Question 69


Since present output does not depend upon future values of input, the system is causal and also every bounded input produces bounded output, so it is stable.

Question 70: Digital Filters (GATE EC 2016-SET-3)

MCQ

2 Marks

The direct form structure of an FIR (finite impulse response) filter is shown in the figure.



The filter can be used to approximate a

- (A) low-pass filter
- (B) high-pass filter
- (C) **(Correct)** band-pass filter
- (D) band-stop filter

Correct Answer: (C)



Detailed Solution – Question 70

$$y[n] = 5[x[n] - x[n - 2]]$$

$$H(z) = \frac{Y(z)}{X(z)} = 5 [1 - z^{-2}]$$

$$\text{But, } z = e^{j\omega}$$

$$H(e^{j\omega}) = 5 [1 - e^{-j2\omega}]$$



$$\omega = 0 \quad |H(e^{j\omega})| = 0$$

$$\omega = \frac{\pi}{2} \quad |H(e^{j\omega})| = 10$$

$$\omega = \pi \quad |H(e^{j\omega})| = 0$$

$\therefore$ The given one is bandpass filter.

Question 71: DTFS, DTFT & DFT (GATE EC 2016-SET-3)

NAT

2 Marks

A continuous-time speech signal $x_a(t)$ is sampled at a rate of 8 kHz and the samples are subsequently grouped in blocks, each of size N . The DFT of each block is to be computed in real time using the radix-2 decimation-in-frequency FFT algorithm. If the processor performs all operations sequentially, and takes $20 \mu\text{s}$ for computing each complex multiplication (including multiplications by 1 and -1) and the time required for addition/subtraction is negligible, then the maximum value of N is _____

Detailed Solution – Question 71

$$f_s = 8000 \text{ samples/sec}$$

$$\Rightarrow T_s = \frac{1}{f_s} = \frac{1}{8000} \text{ sec}$$

Time for each multiplication = $T_m = 20 \mu\text{sec}$ $T_m = 20 \times 10^{-6} \text{sec}$ suppose block is of size N , then time taken to generate each block = $N \times T_s = N \times \frac{1}{8000}$. No. of multiplications that can be performed by processor in the time taken for each block = $\frac{N \times T_s}{T_m}$ No. of multiplications required to compute DFT by Radix - 2 FFT algorithm = $\frac{N}{2} \log_2 N$ No. of multiplication required by FFT $\leq$ No. of multiplications that can be performed by the processor in the time taken in each block [Reason: real time]

$$\frac{N}{2} \log_2 N \leq \frac{N \times T_s}{T_m}$$

$$\log_2 N \leq \frac{2 \times \frac{1}{8000}}{20 \times 10^{-6}} = 12.5$$

$$N \leq 2^{12.5}$$


$$\therefore N \leq 2^{12} = 4096$$


Question 72: Z-Transform (GATE EC 2016-SET-3)

MCQ

2 Marks

The ROC (region of convergence) of the z-transform of a discrete-time signal is represented by the shaded region in the z-plane. If the signal $x[n] = (2.0)^{|n|}$, $-\infty < n < +\infty$, then the ROC of its z-transform is represented by





- (A) A
(B) B
(C) C
(D) **(Correct)** D

Correct Answer: (D)

Detailed Solution – Question 72

$$\begin{aligned} \text{Given, } x[n] &= (2.0)^{\ln 1}, -\infty < n < +\infty \\ &= 2^n(n) + \left(\frac{1}{2}\right)^n u(-n-1) \\ \text{ROC : } |z| &> 2 \text{ and } |z| < \frac{1}{2} \\ \therefore \text{No Roc} \end{aligned}$$

Question 73: Laplace Transform (GATE EC 2016-SET-3)

MCQ

2 Marks

A signal $2\cos(\frac{2\pi t}{3}) - \cos(\pi t)$ is the input to an LTI system with the transfer function $H(s) = e^s + e^{-s}$.

If C_k denotes the k^{th} coefficient in the exponential Fourier series of the output signal, then C_3 is equal to

- (A) 0
(B) **(Correct)** 1



(C) 2

(D) 3

Correct Answer: (B)

Detailed Solution – Question 73

Given. $H(s) = e^s + e^{-s}$ $H(e^{j\omega}) = e^{j\omega} + e^{-j\omega} = 2 \cos \omega$



$$\text{if } x_1(t) = 2 \cos\left(\frac{2\pi}{3}t\right)$$

$$\omega_b = \frac{2\pi}{3}$$

$$H(j\omega_b) = 2 \cos\left(\frac{2\pi}{3}\right) = 2\left(-\frac{1}{2}\right) = -1$$

$$y_1(t) = 2 \cos\left(\frac{2\pi}{3}t + 180^\circ\right)$$

$$\text{if } x_2(t) = \cos \pi t$$

$$\omega_b = \pi$$

$$H(j\omega_b) = 2 \cos(\pi) = -2$$

$$y_2(t) = 2 \cos(\pi t + 180^\circ)$$

$$y(t) = 2 \cos\left(\frac{2\pi}{3}t + \pi\right) - 2 \cos(\pi t + \pi)$$

$$\omega_1 = \frac{2\pi}{3}, \omega_2 = \pi$$

$$\omega_1 = 3 \quad T_2 = 2$$

$$\therefore T_0 = 6$$

$$\Rightarrow \omega_0 = \frac{2\pi}{T_0} = \frac{\pi}{3}$$

$$\mathcal{V}(t) = 2 \cos(2\omega_0 t + \pi) - 2 \cos(3\omega_0 t + \pi)$$

$$\mathcal{N}(t) = e^{j(2 \cos t \pi)} + e^{-j(2\omega_0 t + \pi)} - e^{j(3\omega_0 t + \pi)} - e^{-j(3\omega_0 t + \pi)}$$

$$y(t) = -e^{j(2\omega_0 t)} - e^{-j(2\omega_0 t)} + e^{j(3\omega_0 t)} + e^{-j(3\omega_0 t)}$$

$$\therefore C_3 = 1$$

Question 74: Z-Transform (GATE EC 2016-SET-3)

MCQ

1 Mark

A discrete-time signal $x[n] = \delta[n-3] + 2\delta[n-5]$ has z-transform $X(z)$. If $X(z) = X(-z)$ is the z-transform of another signal $y[n]$, then

- (A) $y[n] = x[n]$
- (B) $y[n] = x[-n]$
- (C) **(Correct)** $y[n] = -x[n]$
- (D) $y[n] = -x[-n]$

Correct Answer: (C)

Detailed Solution – Question 74

Given,

$$\begin{aligned}x[n] &= \delta[n-3] + 2\delta[n-5] \\X(z) &= z^{-3} + 2z^{-5} \\X(-z) &= (-z)^{-3} + 2(-z)^{-5} \\Y(z) &= X(-z) = -z^{-3} - 2z^{-5} \\&= -[z^{-3} + 2z^{-5}] \\y[n] &= -x[n]\end{aligned}$$

Question 75: Fourier Transforms (GATE EC 2016-SET-3)





MCQ

1 Mark

If the signal $x(t) = \frac{\sin(t)}{\pi t} * \frac{\sin(t)}{\pi t}$ with $*$ denoting the convolution operation, then $x(t)$ is equal to



- (A) **(Correct)** $\frac{\sin(t)}{\pi t}$
- (B) $\frac{\sin(2t)}{2\pi t}$
- (C) $\frac{2\sin(t)}{\pi t}$
- (D) $(\frac{\sin(t)}{\pi t})^2$

Correct Answer: (A)



$$x(t) = x_1(t) * x_1(t)$$

$$X(\omega) = X_1(\omega) \cdot X_1(\omega)$$



Question 76: Sampling (GATE EC 2016-SET-3)

MCQ

1 Mark

Consider the signal $x(t) = \cos(6\pi t) + \sin(8\pi t)$, where t is in seconds. The Nyquist sampling rate (in samples/second) for the signal $y(t) = x(2t + 5)$ is

- (A) 8
- (B) 12
- (C) **(Correct)** 16
- (D) 32

Correct Answer: (C)

Detailed Solution – Question 76

$$\begin{aligned}X(t) &= \cos(6\pi t) + \sin(8\pi t) \\Y(t) &= x(2t + 5) \\Y(t) &= \cos[6\pi(2t + 5)] + \sin[8\pi(2t + 5)] \\&= \cos(12\pi t + 30\pi) + \sin(16\pi t + 40\pi) \\f_{m1} &= 6\text{Hz} \quad f_{m2} = 8\text{Hz} \\ \text{Nyquist sampling rate,} \\f_s &= 2f_{\max} \\&= 16 \text{ samples/second}\end{aligned}$$

Question 77: DTFS, DTFT & DFT (GATE EC 2016-SET-2)

NAT

2 Marks

The Discrete Fourier Transform (DFT) of the 4-point sequence

$$x[n] = x[0], x[1], x[2], x[3] = 3, 2, 3, 4 \text{ is } X[k] = X[0], X[1], X[2], X[3] = 12, 2j, 0, -2j.$$

If $X_1[k]$ is the DFT of the 12-point sequence $x_1[k] = 3, 0, 0, 2, 0, 0, 3, 0, 0, 4, 0, 0$, the value of $\left| \frac{x_1[8]}{x_1[11]} \right|$ is

Detailed Solution – Question 77

From the given question

$$\begin{aligned}x_1[n] &= x\left[\frac{n}{3}\right] \\x_1[k] &= \{12, 2j, 0, -2j, 12, 2j, 0, -2j, 12, 2j, 0, -2j\} \\x_1[8] &= 12; \quad x_1[11] = -2j \\ \therefore \frac{x_1[8]}{x_1[11]} &= \left| \frac{12}{-2j} \right| = 6\end{aligned}$$

Question 78: Digital Filters (GATE EC 2016-SET-2)

NAT

2 Marks

A continuous-time filter with transfer function $H(S) = \frac{2s+6}{s^2+6s+8}$ is converted to a discrete-time filter with transfer function $G(z) = \frac{2z^2-0.5032z}{z^2-0.5032z+k}$ so that the impulse response of the continuous-time filter, sampled at 2 Hz, is identical at the sampling instants to the impulse response of the discrete time filter. The value of k is -----

Detailed Solution – Question 78

$$\text{Given, } H(s) = \frac{2s+6}{s^2+6s+8} = \frac{1}{s+2} + \frac{1}{s+4}$$

$$h(t) = e^{-2t}u(t) + e^{-4t}u(t)$$

$$\text{Given, } f_s = 2\text{Hz}$$

$$\text{For discrete time, } t = nT_s = \frac{n}{2}$$

$$h[n] = (e^{-n} + e^{-2n}) \cup (n]$$





$$\begin{aligned} H(z) &= \frac{1}{1 - e^{-1}Z^{-1}} + \frac{1}{1 - e^{-2}Z^{-1}} \\ &= \frac{Z}{Z - e^{-1}} + \frac{Z}{Z - e^{-2}} \\ &= \frac{2Z^2 - 0.5032Z}{Z^2 - 0.5032Z + 0.049} \\ K &= 0.049 \end{aligned}$$

Question 79: Fourier Transforms (GATE EC 2016-SET-2)

NAT

1 Mark

The energy of the signal $x(t) = \frac{\sin(4\pi t)}{4\pi t}$ is -----



$$\begin{aligned} \text{Energy, } E_{x(i)} &= \frac{1}{2\pi} \int_{-\infty}^{\infty} |X(\omega)|^2 d\omega \\ &= \frac{1}{2\pi} \int_{-4\pi}^{4\pi} \left(\frac{1}{4}\right)^2 d\omega \\ &= \frac{1}{2\pi} \times \frac{1}{16} [8\pi] = \frac{1}{4} = 0.25\text{J} \end{aligned}$$

Question 80: DTFS, DTFT & DFT (GATE EC 2016-SET-1)

NAT

2 Marks

Consider the signal $x[n] = 6\delta[n+2] + 3\delta[n+1] + 8\delta[n] + 7\delta[n-1] + 4\delta[n-2]$. If $X(e^{j\omega})$ is the discrete-time Fourier transform of $x[n]$, then $\frac{1}{\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) \sin^2(2\omega) d\omega$ is equal to

Detailed Solution – Question 80

From the definition of DTFT

$$\begin{aligned}
 X(e^{j\omega}) &= \sum_{n=-\infty}^{\infty} x[n]e^{-j\omega n} \\
 x[n] &= \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) e^{j\omega n} d\omega \\
 x[0] &= \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) d\omega \\
 \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) Y(e^{j\omega}) d\omega &= [x(n) \otimes y(n)]_{n=0} \\
 Y(e^{j\omega}) &= \sin^2(2\omega) \\
 &= \frac{1 - \cos 4\omega}{2} \\
 &= \frac{1}{2} - \frac{1}{4}e^{4j\omega} - \frac{1}{4}e^{-4j\omega} \\
 y[n] &= \frac{1}{2}\delta[n] - \frac{1}{4}\delta[n+4] - \frac{1}{4}\delta[n-4] \\
 y[n] &= \left\{ -\frac{1}{4}, 0, 0, 0, \underset{\uparrow}{\frac{1}{2}}, 0, 0, 0, -\frac{1}{4} \right\} \\
 \Rightarrow y[0] &= \frac{1}{2} \\
 x[n] &= \{6, 3, \underset{\uparrow}{8}, 7, 4\}; \quad x[0] = 8 \\
 \frac{1}{\pi} \int_{-\pi}^{\pi} x(e^{j\omega}) Y(e^{j\omega}) d\omega &= 2 \sum_{n=-\infty}^{\infty} x[0]y[0] \\
 &= 2 \times 8 \times \frac{1}{2} = 8
 \end{aligned}$$

Question 81: Laplace Transform (GATE EC 2016-SET-1)

MCQ

2 Marks

A first-order low-pass filter of time constant T is excited with different input signals (with zero initial conditions up to $t = 0$). Match the excitation signals X, Y, Z with the corresponding time responses for $t \geq 0$:

X: Impulse

P: $1 - e^{-t/T}$

Y: Unit step

Q: $t - T(1 - e^{-t/T})$

Z: Ramp

R: $e^{-t/T}$

X: Impulse

Y: Unit step

Z: Ramp

P: $1 - e^{-t/T}$

Q: $t - T(1 - e^{-t/T})$

R: $e^{-t/T}$

- (A) $X \rightarrow R, Y \rightarrow Q, Z \rightarrow P$
(B) $X \rightarrow Q, Y \rightarrow P, Z \rightarrow R$
(C) **(Correct)** $X \rightarrow R, Y \rightarrow P, Z \rightarrow Q$
(D) $X \rightarrow P, Y \rightarrow R, Z \rightarrow Q$

Correct Answer: (C)

Detailed Solution – Question 81

For 1st order system $G(s) = \frac{1}{sT}; H(s) = 1$ Impulse response $A(s) = 1$

$$\begin{aligned}n(s) &= \left(\frac{G(s)}{1 + G(s)H(s)} R(s) \right) \\&= \left(\frac{1}{1 + sT} \right) = \frac{1}{T} e^{-t/T} \text{ for } t \geq 0\end{aligned}$$

Unit step response $A(s) = \frac{1}{s}$

$$\begin{aligned}\eta(s) &= \frac{1}{s(1 + sT)} = \frac{(1 + sT) - (sT)}{s(1 + sT)} \\&= \frac{1}{s} - \frac{T}{(1 + sT)} = \frac{1}{s} - \frac{T}{T(s + \frac{1}{T})}\end{aligned}$$

$$y(t) = 1 - e^{-t/T} \text{ for } t \geq 0$$

Ramp response $R(s) = \frac{1}{s^2}$

$$\eta(s) = \frac{1}{s^2(1 + sT)} = \frac{1}{s^2} - \frac{T}{s} + \frac{T}{s + \frac{1}{T}}$$

$$y(t) = t - T(1 - e^{-t/T}) \text{ for } t \geq 0$$

Question 82: Fourier Transforms (GATE EC 2016-SET-1)

MCQ

2 Marks

A network consisting of a finite number of linear resistor (R), inductor (L), and capacitor (C) elements, connected all in series or all in parallel, is excited with a source of the form

$$\sum_{k=1}^3 a_k \cos(k\omega_0 t), \text{ where } a_k \neq 0, \omega_0 \neq 0.$$

The source has nonzero impedance. Which one of the following is a possible form of the output measured across a resistor in the network?


- (A) **(Correct)** $\sum_{k=1}^3 b_k \cos(k\omega_0 t + \phi_k)$, where $b_k \neq a_k, \forall k$
(B) $\sum_{k=1}^4 b_k \cos(k\omega_0 t + \phi_k)$, where $b_k \neq 0, \forall k$

(C) $\sum_{k=1}^3 a_k \cos(k\omega_0 t + \phi_k)$

(D) $\sum_{k=1}^2 a_k \cos(k\omega_0 t + \phi_k)$

Correct Answer: (A)

Detailed Solution – Question 82




When a sinusoidal input is given to LTI system, the output is also a sinusoid with change in magnitude and the phase shift offered by LTI system.

Question 83: Laplace Transform (GATE EC 2016-SET-1)

MCQ

2 Marks

The Laplace transform of the causal periodic square wave of period T shown in the figure below is



(A) **(Correct)** $F(s) = \frac{1}{1+e^{-sT/2}}$

(B) $F(s) = \frac{1}{s(1+e^{-sT/2})}$

(C) $F(s) = \frac{1}{s(1-e^{-sT})}$

(D) $F(s) = \frac{1}{1-e^{-sT}}$

Correct Answer: (A)

Detailed Solution – Question 83

$$\begin{aligned}L(f(t)) &= \frac{1}{1 - e^{-sT} \int_0^{T/2} e^{-st} dt} \\&= \frac{1}{1 - e^{-sT}} \left(\frac{e^{-st}}{-s} \right) \Big|_0^{T/2} \\&= \frac{1}{s(1 - e^{-sT})} \cdot (1 - e^{-sT/2}) \\&= \frac{1}{s} \cdot \frac{1 - e^{-sT/2}}{(1 - e^{-sT/2})(1 + e^{-sT/2})} \\&= \frac{1}{s} \cdot \frac{1}{1 + e^{-sT/2}}\end{aligned}$$

As per GATE official answer Marks to ALL.

Question 84: Sampling (GATE EC 2016-SET-1)


NAT

1 Mark

A continuous-time sinusoid of frequency 33 Hz is multiplied with a periodic Dirac impulse train of frequency 46 Hz. The resulting signal is passed through an ideal analog low-pass filter with a cutoff frequency of 23 Hz. The fundamental frequency (in Hz) of the output is _____

Detailed Solution – Question 84

If $x(t)$ is a message signal and $y(t)$ is a sampled signal, then $y(t)$ is related to $x(t)$ as $y(t) = x(t) \sum_{n=-\infty}^{\infty} \delta(t - nT_s)$ $r(f) = f_s \sum_{n=-\infty}^{\infty} X(f - nf_s)$
Spectrum of $X(f)$ and $Y(f)$ are as shown



Cut off frequency of LPF = 23 Hz
Hence, frequency at the output is 13 Hz

Question 85: Z-Transform (GATE EC 2016-SET-1)

MCQ

1 Mark

Consider the sequence $x[n] = a^n u[n] + b^n u[n]$, where $u[n]$ denotes the unit-step sequence and $0 < -a < -b < 1$. The region of convergence (ROC) of the z-transform of $x[n]$ is

- (A) $-z \rightarrow -a-$
- (B) **(Correct)** $-z \rightarrow -b-$
- (C) $-z \leftarrow -a-$
- (D) $-a \leftarrow -z \leftarrow -b-$

Correct Answer: (B)

Detailed Solution – Question 85

$$\text{Given, } x[n] = a^n u[n] + b^n u[n]$$

$$0 < |a| < |b| < 1$$

$$\text{Also given, } AOC = (|z| > |a|) \text{ and } (|z| > |b|)$$

$$ROC = |z| > |b|$$

Question 86: Basics of Signals & Systems (GATE EC 2016-SET-1)

MCQ

1 Mark

A continuous-time function $x(t)$ is periodic with period T . The function is sampled uniformly with a sampling period T_s . In which one of the following cases is the sampled signal periodic?

- (A) $T = \sqrt{2}T_s$
- (B) **(Correct)** $T = 1.2T_s$
- (C) Always
- (D) Never

Correct Answer: (B)

Detailed Solution – Question 86

A signal is said to be periodic if $\frac{T}{T_s}$ is a rational number.
 Here, $T = 1.2T_s \Rightarrow \frac{T}{T_s} = \frac{6}{5}$ Which is a rational number

Question 87: LTI Systems (GATE EC 2016-SET-1)

MCQ

1 Mark

Which one of the following is an eigen function of the class of all continuous-time, linear, timeinvariant systems ($u(t)$ denotes the unit-step function)?

- (A) $e^{j\omega_0 t} u(t)$
- (B) $\cos(\omega_0 t)$
- (C) **(Correct)** $e^{j\omega_0 t}$
- (D) $\sin(\omega_0 t)$

Correct Answer: (C)

Detailed Solution – Question 87

If the input to the system is eigen signal output is also the same eigen signal.

Question 88: Laplace Transform (GATE EC 2016-SET-1)

MCQ

1 Mark

Which one of the following is a property of the solutions to the Laplace equation: $\nabla^2 f = 0$?

- (A) **(Correct)** The solutions have neither maxima nor minima anywhere except at the boundaries.
- (B) The solutions are not separable in the coordinates.
- (C) The solutions are not continuous
- (D) The solutions are not dependent on the boundary conditions

Correct Answer: (A)

Question 89: Basics of Signals & Systems (GATE EC 2015-SET-3)

NAT

2 Marks

Two sequences $x_1[n]$ and $x_2[n]$ have the same energy. Suppose $x_1[n] = \alpha 0.5^n u[n]$, where α is a positive real number and $u[n]$ is the unit step sequence. Assume

$$x_2[n] = \begin{cases} \sqrt{1.5} & \text{for } n = 0, 1 \\ 0 & \text{otherwise.} \end{cases}$$

Then the value of α is

Detailed Solution – Question 89

$$\begin{aligned} \text{Energy of } x_1[n] &= \sum_{n=-\infty}^{\infty} |x_1[n]|^2 \\ &= \sum_{n=0}^{\infty} \alpha^2 \left(\frac{1}{4}\right)^n = \alpha^2 \cdot \frac{1}{1 - \frac{1}{4}} = \alpha^2 \cdot \frac{4}{3} \end{aligned}$$

$$\text{Energy of } x_2[n] = 1.5 + 1.5 = 3$$

$$\Rightarrow \alpha^2 \frac{4}{3} = 3$$

$$\alpha^2 = \frac{9}{4}$$

$$\alpha = 1.5$$

Question 90: Sampling (GATE EC 2015-SET-3)

NAT

2 Marks



Consider a continuous-time signal defined as

$$x(t) = \left(\frac{\sin(\pi t/2)}{(\pi t/2)} \right) * \sum_{n=-\infty}^{\infty} \delta(t - 10n)$$

where '*' denotes the convolution operation and t is in seconds. The Nyquist sampling rate (in samples/sec) for x(t) is _____.

Detailed Solution – Question 90

$$x(t) = \frac{\sin\left(\frac{\pi t}{2}\right)}{\left(\frac{\pi t}{2}\right)} * \sum_{n=-\infty}^{\infty} \delta[t - 10n]$$



$$\begin{aligned} f_{\max} &= 0.2 \text{ Hz} \\ \Rightarrow f_s &= 2f_{\max} = 0.4 \text{ Hz} \end{aligned}$$

Question 91: DTFS, DTFT & DFT (GATE EC 2015-SET-3)

NAT

2 Marks

Let $\tilde{x}[n] = 1 + \cos\left(\frac{\pi n}{8}\right)$ be a periodic signal with period 16. Its DFS coefficients are defined by $a_k = \frac{1}{16} \sum_{n=0}^{15} \tilde{x}[n] \exp(-j\frac{\pi}{8}kn)$ for all k. The value of the coefficient a_{31} is _____.

Detailed Solution – Question 91


$$\begin{aligned} \tilde{x}[n] &= 1 + \cos\left(\frac{\pi n}{8}\right) \\ &= 1 + \frac{e^{j\left(\frac{2\pi}{16}\right)n}}{2} + \frac{e^{-j\left(\frac{2\pi}{16}\right)n}}{2} \quad (N = 16) \\ &= 1 + \frac{e^{j\left(\frac{2\pi}{16}\right)n}}{2} + \frac{e^{-j\left(\frac{2\pi}{16}\right)n}}{2} \\ \Rightarrow a_1 &= \frac{1}{2} \text{ and also } a_{31} = a_{15} = a_{-1} = \frac{1}{2} \end{aligned}$$

Question 92: Z-Transform (GATE EC 2015-SET-3)

MCQ

2 Marks

A realization of a stable discrete time system is shown in the figure. If the system is excited by a unit step sequence input $x[n]$, the response $y[n]$ is



- (A) $4(-\frac{1}{3})^n u[n] - 5(-\frac{2}{3})^n u[n]$
- (B) $5(-\frac{2}{3})^n u[n] - 3(-\frac{1}{3})^n u[n]$
- (C) **(Correct)** $5(\frac{1}{3})^n u[n] - 5(\frac{2}{3})^n u[n]$
- (D) $5(\frac{2}{3})^n u[n] - 5(\frac{1}{3})^n u[n]$

Correct Answer: (C)

Detailed Solution – Question 92

$$\begin{aligned}\frac{Y(z)}{X(z)} &= \frac{\frac{5}{3}[1-z]}{z^2 - z + \frac{2}{9}} \\ \Rightarrow \eta(z) &= \frac{5}{3} \frac{(1-z)}{\left(z - \frac{1}{3}\right)\left(z - \frac{2}{3}\right)} \\ \eta(z) &= \frac{5z}{z - \frac{1}{3}} - \frac{5z}{z - \frac{2}{3}} \\ y(n) &= 5 \left(\frac{1}{3}\right)^n u(n) - 5 \left(\frac{2}{3}\right)^n u(n)\end{aligned}$$

Question 93: Z-Transform (GATE EC 2015-SET-3)

MCQ

2 Marks

Suppose $x[n]$ is an absolutely summable discrete-time signal. Its z-transform is a rational function with two poles and two zeroes. The poles are at $z = \pm 2j$. Which one of the following statements is TRUE for the signal $x[n]$?

- (A) It is a finite duration signal.
- (B) It is a causal signal
- (C) **(Correct)** It is a non-causal signal
- (D) It is a periodic signal

Correct Answer: (C)

Detailed Solution – Question 93

Poles are at $z = \pm 2$

Since $x[n]$ is absolutely summable hence, DTFT exists which implies ROC must include unit circle.
 $\Rightarrow x(t)$ is a non-causal signal.

Question 94: Z-Transform (GATE EC 2015-SET-3)

MCQ

1 Mark

Consider a four-point moving average filter defined by the equation $y[n] = \sum_{i=0}^3 \alpha_i x[n-i]$, The condition on the filter coefficients that results in a null at zero frequency is

- (A) **(Correct)** $\alpha_1 = \alpha_2 = 0; \alpha_0 = -\alpha_3$
- (B) $\alpha_1 = \alpha_2 = 1; \alpha_0 = -\alpha_3$
- (C) $\alpha_0 = \alpha_3 = 0; \alpha_1 = \alpha_2$
- (D) $\alpha_1 = \alpha_2 = 0; \alpha_0 = \alpha_3$

Correct Answer: (A)

Detailed Solution – Question 94

$$\begin{aligned}y(n) &= \sum_{i=0}^3 \alpha_i x(n-i) \\&= \alpha_0 x[n] + \alpha_1 x[n-1] + \alpha_2 x[n-2] + \alpha_3 x[n-3] \\ \Rightarrow Y(z) &= \alpha_0 X(z) + \alpha_1 X(z)z^{-1} + \alpha_2 X(z)z^{-2} \\&\quad + \alpha_3 X(z)z^{-3} \\ H(z) &= \alpha_0 + \alpha_1 z^{-1} + \alpha_2 z^{-2} + \alpha_3 z^{-3} \\ \text{Null at zero frequency} \\ \Rightarrow z &= e^{j\omega} \Big|_{\omega=0} \\ 0 &= \alpha_0 + \alpha_1 + \alpha_2 + \alpha_3\end{aligned}$$

Option (A) satisfies the condition

Question 95: LTI Systems (GATE EC 2015-SET-3)

MCQ

1 Mark

The impulse response of an LTI system can be obtained by

- (A) differentiating the unit ramp response
- (B) **(Correct)** differentiating the unit step response
- (C) integrating the unit ramp response
- (D) integrating the unit step response

Correct Answer: (B)

Detailed Solution – Question 95

$$\begin{aligned}IR &= \frac{d}{dt}(SR) \\ \text{Step response,} \\ y(t) &= \int_{-\infty}^t h(\tau) \cdot d\tau \\ h(t) &= \frac{d}{dt}y(t)\end{aligned}$$

Question 96: DTFS, DTFT & DFT (GATE EC 2015-SET-3)

NAT

1 Mark

The value $\sum_{n=0}^{\infty} n(\frac{1}{2})^n$ is -----.

Detailed Solution – Question 96

$$\begin{aligned}
\sum_{n=0}^{\infty} \left(\frac{1}{2}\right)^n &= \sum_{n=-\infty}^{\infty} n \left(\frac{1}{2}\right)^n u(n) \\
&= Z \cdot T \left[n \left(\frac{1}{2}\right)^n u(n) \right]_{z=1} \\
&= \frac{\frac{1}{2}Z^{-1}}{\left(1 - \frac{1}{2}z^{-1}\right)^2} = \frac{\frac{Z}{2}}{\left(z - \frac{1}{2}\right)^2} \Big|_{z=1} \\
&= \frac{1/2}{1/4} = 2
\end{aligned}$$

Question 97: Fourier Transforms (GATE EC 2015-SET-3)**NAT****1 Mark**

Consider the function $g(t) = e^{-t} \sin(2\pi t) u(t)$ where $u(t)$ is the unit step function. The area under $g(t)$ is

Detailed Solution – Question 97

$$\begin{aligned}
g(t) &= e^{-t} \sin(2\pi t) u(t) \\
\text{Area} &= \int_{-\infty}^{\infty} g(t) dt \\
&= \int_{-\infty}^{\infty} \sin(2\pi t) u(t) e^{-t} dt = G(s) \Big|_{s=0} \\
G(s) &= \frac{2\pi}{(s+1)^2 + 4\pi^2} \\
\text{Area} &= \frac{2\pi}{(s+1)^2 + 4\pi^2} \Big|_{s=0} = 0.155
\end{aligned}$$

Question 98: Laplace Transform (GATE EC 2015-SET-2)**NAT****2 Marks**

Let $x(t) = \alpha s(t) + s(-t)$ with $s(t) = \beta e^{-4t} u(t)$, where $u(t)$ is unit step function. If the bilateral Laplace transform of $x(t)$ is $X(s) = \frac{16}{s^2 - 16}$ $-4 < \text{Re}\{s\} < 4$; then the value of β is

Detailed Solution – Question 98

$$\begin{aligned}
x(t) &= \alpha \beta e^{-4t} u(t) + \beta e^{4t} u(-t) \\
\text{Given, } x(s) &= \frac{16}{s^2} - 16 \quad -4 < \text{Re}[s] < 4 \\
&= \frac{16}{(s+4)(s-4)} = \frac{-2}{s+4} + \frac{2}{s-4} \\
x(t) &= -2e^{-4t} u(t) - 2e^{4t} u(-t)
\end{aligned}$$

On comparison $\beta = -2$

Question 99: DTFS, DTFT & DFT (GATE EC 2015-SET-2)

NAT

2 Marks

Consider two real sequences with time-origin marked by the bold value,

$$x_1[n] = \{1, 2, 3, 0\}, \quad x_2[n] = \{1, 3, 2, 1\}$$

Let $X_1(k)$ and $X_2(k)$ be 4-point DFTs of $x_1[n]$ and $x_2[n]$, respectively. Another sequence $x_3[n]$ is derived by taking 4-point inverse DFT of $X_3(k) = X_1(k)X_2(k)$. The value of $x_3[2]$ is

Detailed Solution – Question 99

$x_1[n] = \{1, 2, 3, 0\}$, $x_2[n] = \{1, 3, 2, 1\}$ $x(k)_3 = x(k), \lambda(k)_2 \Rightarrow x_3[n] =$ circular convolution of $x_1[n]$ and $x_2[n]$

$$\begin{aligned} &= x_1[n] \otimes x_2[n] \\ \begin{bmatrix} x_3(0) \\ x_3(1) \\ x_3(2) \\ x_3(3) \end{bmatrix} &= \begin{bmatrix} 1 & 0 & 3 & 2 \\ 2 & 1 & 0 & 3 \\ 3 & 2 & 1 & 0 \\ 0 & 3 & 2 & 1 \end{bmatrix} \begin{bmatrix} 1 \\ 3 \\ 2 \\ 1 \end{bmatrix} = \begin{bmatrix} 9 \\ 8 \\ 11 \\ 14 \end{bmatrix} \\ x_3[2] &= 11 \end{aligned}$$

Question 100: Laplace Transform (GATE EC 2015-SET-2)

MCQ

2 Marks

Input $x(t)$ and output $y(t)$ of an LTI system are related by the differential equation $y''(t) - y'(t) - 6y(t) = x(t)$. If the system is neither causal nor stable, the impulse response $h(t)$ of the system is

- (A) $\frac{1}{5}e^{3t}u(-t) + \frac{1}{5}e^{-2t}u(-t)$
(B) **(Correct)** $-\frac{1}{5}e^{3t}u(-t) + \frac{1}{5}e^{-2t}u(-t)$
(C) $\frac{1}{5}e^{3t}u(-t) - \frac{1}{5}e^{-2t}u(-t)$
(D) $-\frac{1}{5}e^{3t}u(-t) - \frac{1}{5}e^{-2t}u(-t)$

Correct Answer: (B)

Detailed Solution – Question 100

$y''(t) - y'(t) - 6y(t) = x(t)$ $H(s) = \frac{Y(s)}{X(s)} = \frac{1}{s^2 - s - 6} = \frac{1}{(s-3)(s+2)}$ $H(s) = \frac{(\frac{1}{5})}{s-3} + \frac{(-\frac{1}{5})}{s+2}$ If the system is neither causal nor stable, then

$$h(t) = -\frac{1}{5}e^{3t}u(-t) + \frac{1}{5}e^{-2t}u(-t) \quad \text{ROC: } \sigma < -2$$

Question 101: Laplace Transform (GATE EC 2015-SET-2)

MCQ

2 Marks

Consider the differential equation $\frac{dx}{dt} = 10 - 0.2x$ with initial condition $x(0) = 1$. The response $x(t)$ for $t \geq 0$ is

- (A) $2 - e^{-0.2t}$
- (B) $2 - e^{0.2t}$
- (C) **(Correct)** $50 - 49e^{-0.2t}$
- (D) $50 - 49e^{0.2t}$

Correct Answer: (C)

Detailed Solution – Question 101

Applying Laplace transform

$$sX(s) - x(0) = \frac{10}{s} - 0.2X(s)$$
$$X(s) = \frac{10}{s(s+0.2)} + \frac{1}{(s+0.2)}$$

Applying inverse Laplace transform, we get $x = 50 - 49e^{(-0.2)t}$

Question 102: Sampling (GATE EC 2015-SET-2)

MCQ

1 Mark

The signal $\cos(10\pi t + \frac{\pi}{4})$ is ideally sampled at a sampling frequency of 15 Hz. The sampled signal is passed through a filter with impulse response $(\frac{\sin(\pi t)}{\pi t})\cos(40\pi t - \frac{\pi}{2})$. The filter output is

- (A) **(Correct)** $\frac{15}{2}\cos(40\pi t - \frac{\pi}{4})$
- (B) $\frac{15}{2}(\frac{\sin(\pi t)}{\pi t})\cos(10\pi t + \frac{\pi}{4})$
- (C) $\frac{15}{2}\cos(10\pi t - \frac{\pi}{4})$
- (D) $\frac{15}{2}(\frac{\sin(\pi t)}{\pi t})\cos(40\pi t - \frac{\pi}{4})$

Correct Answer: (A)

Detailed Solution – Question 102

$$x(t) = \cos\left(10\pi t + \frac{\pi}{4}\right)$$
$$X(f) = \frac{1}{2}[\delta(f-5) + \delta(f+5)]e^{j\pi/4}$$

After sampling $x(t)$ by 15 Hz, we get $X_s(f) = 15 \sum_{n=-\infty}^{\infty} X(f-15n)$ Given,

$$h(t) = \left[\frac{\sin(\pi t)}{\pi t} \right] \cos\left(40\pi t - \frac{\pi}{2}\right)$$

$$H(f) = \frac{1}{2} \left[\text{rect}\frac{(f-20)}{2\pi} + \text{rect}\frac{(f+20)}{2\pi} \right] e^{-j\frac{\pi}{2}}$$

Output $Y(t) = X_s(f) \times H(f)$

$$y(t) = \frac{15}{2} \cos\left(40\pi t - \frac{\pi}{4}\right)$$

Question 103: Z-Transform (GATE EC 2015-SET-2)

NAT

1 Mark

Two causal discrete-time signals $x[n]$ and $y[n]$ are related as $y[n] = \sum_{m=0}^n x[m]$. If the z-transform of $y[n]$ is $\frac{2}{z(z-1)^2}$, the value of $x[2]$ is -----.

Detailed Solution – Question 103

$$f(n) = \sum_{m=0}^n x[m] = x[n] * u[n]$$

$$y(z) = X(z) \cdot \left(\frac{z}{z-1} \right)$$

Given $Y(z) = \frac{2}{z(z-1)^2} = X(z) \cdot \frac{z}{z-1}$

$$\Rightarrow A(z) = \frac{2 \cdot z^{-2}}{z-1} = 2z^{-3} \left(\frac{z}{z-1} \right)$$

$$\Rightarrow x[n] = 2u[n-3]$$

Therefore, $x[2] = 0$

Question 104: Laplace Transform (GATE EC 2015-SET-2)

MCQ

1 Mark

Let the signal $f(t) = 0$ outside the interval $[T_1, T_2]$, where T_1 and T_2 are finite. Furthermore, $|f(t)| < \infty$. The region of convergence (RoC) of the signal's bilateral Laplace transform $F(s)$ is

- (A) a parallel strip containing the $j\Omega$ axis
- (B) a parallel strip not containing the $j\Omega$ axis
- (C) **(Correct)** the entire s-plane

(D) a half plane containing the $j\Omega$ axis

Correct Answer: (C)

Detailed Solution – Question 104


ROC of a finite duration signal is entire s-plane.


Question 105: Fourier Series (GATE EC 2015-SET-2)

MCQ

1 Mark

The magnitude and phase of the complex Fourier series coefficients a_k of a periodic signal $x(t)$ are shown in the figure. Choose the correct statement from the four choices given. Notation: C is the set of complex numbers, R is the set of purely real numbers, and P is the set of purely imaginary numbers.





- (A) **(Correct)** $x(t) \in R$
- (B) $x(t) \in P$
- (C) $x(t) \in (C - R)$
- (D) the information given is not sufficient to draw any conclusion about $x(t)$

Correct Answer: (A)

Detailed Solution – Question 105

$|a_k|$ – even symmetry
 $\angle a_k$ – Odd symmetry (π can be $-\pi$)

$\Rightarrow x(t)$ is real.

Question 106: Laplace Transform (GATE EC 2015-SET-2)

MCQ

1 Mark

The bilateral Laplace transform of a function

$$f(t) = \begin{cases} 1 & \text{if } a \leq t \leq b \\ 0 & \text{otherwise} \end{cases}$$

is

- (A) $\frac{a-b}{s}$
- (B) $\frac{e^{x(a-b)}}{s}$
- (C) **(Correct)** $\frac{e^{-as} - e^{-bs}}{s}$
- (D) $\frac{e^{s(a-b)}}{s}$

Correct Answer: (C)

Detailed Solution – Question 106



$$\begin{aligned} f(t) &= \begin{cases} 1 & \text{if } a \leq t \leq b \\ 0 & \text{otherwise} \end{cases} \\ &= U(t-a) - U(t-b) \\ \Rightarrow F(s) &= \frac{e^{-as} - e^{-bs}}{s} \end{aligned}$$

Question 107: Z-Transform (GATE EC 2015-SET-1)

MCQ

2 Marks

The pole-zero diagram of a causal and stable discrete-time system is shown in the figure. The zero at the origin has multiplicity 4. The impulse response of the system is $h[n]$. If $h[0] = 1$, we can conclude



- (A) **(Correct)** $h[n]$ is real for all n
- (B) $h[n]$ is purely imaginary for all n
- (C) $h[n]$ is real for only even n
- (D) $h[n]$ is purely imaginary for only odd n

Correct Answer: (A)

Detailed Solution – Question 107


$$\begin{aligned}
 H(z) &= \frac{z^4}{\left[\left(z - \frac{1}{2} \right)^2 + \frac{1}{4} \right] \left[\left(z + \frac{1}{2} \right)^2 + \frac{1}{4} \right]} \\
 \text{Poles} &= \frac{1}{2} \pm j\frac{1}{2}, -\frac{1}{2} \pm j\frac{1}{2} \\
 &= \frac{z^4}{(z^2 - z + \frac{1}{2})(z^2 + z + \frac{1}{2})} \\
 &= \frac{z^4}{z^4 + z^2 + \frac{1}{4} - z^2} \\
 H(z) &= \frac{z^4}{z^4 + \frac{1}{4}} \\
 &= z^4 + \frac{1}{4} \Bigg) z^4 \left(1 - \frac{1}{4} z^{-4} \dots \right. \\
 &\quad \left. \frac{z + \frac{1}{4}}{-\frac{1}{4}} \right)
 \end{aligned}$$

Question 108: Z-Transform (GATE EC 2015-SET-1)

MCQ

2 Marks

For the discrete-time system shown in the figure, the poles of the system transfer function are located at



(A) 2, 3

(B) $1/2, 3$

(C) **(Correct)** $1/2, 1/3$

(D) $2, 1/3$

Correct Answer: (C)

Detailed Solution – Question 108

The difference equation of the system $x(n) - \frac{1}{6}y(n-2) + \frac{5}{6}y(n-1) = y(n)$

$$H(z) = \frac{Y(z)}{x(z)} = \frac{1}{1 + \frac{1}{6}z^{-2} - \frac{5}{6}z^{-1}}$$

Poles are $z = \frac{1}{2}, \frac{1}{3}$

Question 109: DTFS, DTFT & DFT (GATE EC 2015-SET-1)

MCQ

2 Marks

Two sequences $[a, b, c]$ and $[A, B, C]$ are related as

$$\begin{bmatrix} A \\ B \\ C \end{bmatrix} = \begin{bmatrix} 1 & 1 & 1 \\ 1 & W_3^{-1} & W_3^{-2} \\ 1 & W_3^{-2} & W_3^{-4} \end{bmatrix} \begin{bmatrix} a \\ b \\ c \end{bmatrix} \text{ where } W_3 = e^{j\frac{2\pi}{3}}$$

If another sequence $[p, q, r]$ is derived as,

$$\begin{bmatrix} p \\ q \\ r \end{bmatrix} = \begin{bmatrix} 1 & 1 & 1 \\ 1 & W_3^1 & W_3^2 \\ 1 & W_3^2 & W_3^4 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 \\ 0 & W_3^2 & 0 \\ 0 & 0 & W_3^4 \end{bmatrix} \begin{bmatrix} A/3 \\ B/3 \\ C/3 \end{bmatrix}$$

then the relationship between the sequences $[p, q, r]$ and $[a, b, c]$ is

$p, q, r = [b, a, c]$

$p, q, r = [b, c, a]$

(A) **(Correct)** $[p, q, r] = [c, a, b]$

$p, q, r = [c, b, a]$

Correct Answer: (C)

Detailed Solution – Question 109

$$\begin{bmatrix} A \\ B \\ C \end{bmatrix} = \begin{bmatrix} a + b + c \\ a + bW_3^{-1} + cW_3^{-2} \\ a + bW_3^{-2} + cW_3^{-1} \end{bmatrix}$$

$$\begin{bmatrix} p \\ q \\ r \end{bmatrix} = \begin{bmatrix} 1 & w_3^2 & w_3^1 \\ 1 & w_3^1 w_3^2 & w_3^2 w_3^1 \\ 1 & w_3^2 w_3^2 & W_3^1 W_3^1 \end{bmatrix} \begin{bmatrix} \frac{a+b+c}{3} \\ \frac{a+bW_3^{-1}+cW_3^{-2}}{3} \\ \frac{a+bW_3^{-2}+cW_3^{-1}}{3} \end{bmatrix}$$

where $W_3^4 = e^{j\frac{2\pi}{3}}$

$$W_3^2 = e^{j\frac{4\pi}{3}}$$

$$W_3^{-1} = e^{-j\frac{2\pi}{3}}$$

$$W_3^{-2} = e^{-j\frac{4\pi}{3}}$$

$$W_3^{-4} = W_3^{-1} = e^{-j\frac{2\pi}{3}}$$



$$\begin{bmatrix} p \\ q \\ r \end{bmatrix} = \begin{bmatrix} c \\ a \\ b \end{bmatrix}$$

Question 110: Basics of Signals & Systems (GATE EC 2015-SET-1)

MCQ

1 Mark

The waveform of a periodic signal $x(t)$ is shown in the figure.



A signal $g(t)$ is defined by $g(t) = x\left(\frac{t-1}{2}\right)$. The average power of $g(t)$ is

(A) 1

(B) **(Correct)** 2

(C) 3

(D) 4

Correct Answer: (B)

Detailed Solution – Question 110

$$\begin{aligned}x(t) &= -3t, \quad -1 < t < 1 \\x\left(\frac{t-1}{2}\right) &= -\frac{3}{2}(t-1) \quad -1 < t < 3 \\ \text{and } T &= 6 \\ \text{Average power} &= \frac{1}{6} \int_{-1}^3 \left(-\frac{3}{2}(t-1)\right)^2 dt = 2\end{aligned}$$

Question 111: LTI Systems (GATE EC 2015-SET-1)

MCQ

1 Mark

The result of the convolution $x(-t) * \delta(-t - t_o)$ is

(A) $x(t + t_o)$

(B) $x(t - t_o)$

(C) $x(-t + t_o)$

(D) **(Correct)** $x(-t - t_o)$

Correct Answer: (D)

Detailed Solution – Question 111

$$x(t) * \delta(-t - t_o) = x(-t) * \delta(t + t_o) = x(-t - t_o)$$

Question 112: DTFS, DTFT & DFT (GATE EC 2014-SET-4)

MCQ

2 Marks

The N -point DFT X of a sequence $x[n]$, $0 \leq n \leq N-1$ is given by,

$$X[k] = \frac{1}{\sqrt{N}} \sum_{n=0}^{N-1} x[n] e^{-j\frac{2\pi}{N}nk}, \quad 0 \leq k \leq N-1$$

Denote this relation as $X = DFT(x)$. For $N=4$, which one of the following sequences satisfies $DFT(DFT(x)) = x$?

(A)

$$x = [1 \quad 2 \quad 3 \quad 4]$$

(B) **(Correct)**

$$x = [1 \quad 2 \quad 3 \quad 2]$$

(C)

$$x = [1 \quad 3 \quad 2 \quad 2]$$

(D)

$$x = [1 \ 2 \ 2 \ 3]$$

Correct Answer: (B)

Detailed Solution – Question 112

$$\text{DFT} (\text{DFT}(x)) = x$$

$$\text{Let, } x = [123]$$

$$\text{DFT} (x) = \frac{1}{\sqrt{4}} \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 1 \\ 2 \\ 3 \\ 2 \end{bmatrix}$$

$$= \frac{1}{2} \begin{bmatrix} 8 \\ -2 \\ 0 \\ -2 \end{bmatrix} = \begin{bmatrix} 4 \\ -1 \\ 0 \\ -1 \end{bmatrix}$$

$$\text{DFT} (\text{DFT} (x)) = \frac{1}{\sqrt{4}} \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 4 \\ -1 \\ 0 \\ -1 \end{bmatrix}$$

$$= \frac{1}{2} \begin{bmatrix} 2 \\ 4 \\ 6 \\ 4 \end{bmatrix} = \begin{bmatrix} 1 \\ 2 \\ 3 \\ 2 \end{bmatrix}$$

Question 113: Laplace Transform (GATE EC 2014-SET-4)

NAT

2 Marks

A causal LTI system has zero initial conditions and impulse response $h(t)$. Its input $x(t)$ and output $y(t)$ are related through the linear constant-coefficient differential equation

$$\frac{d^2 y(t)}{dt^2} + \alpha \frac{dy(t)}{dt} + \alpha^2 y(t) = x(t)$$

Let another signal $g(t)$ be defined as

$$g(t) = \alpha^2 \int_0^t h(\tau) d\tau + \frac{dh(t)}{dt} + \alpha h(t)$$

If $G(s)$ is the Laplace transform of $g(t)$, then the number of poles of $G(s)$ is_____.

Detailed Solution – Question 113

$\frac{d^2y(t)}{dt^2} + \alpha \frac{dy}{dt} + \alpha^2 y(t) = x(t) \therefore (s^2 + \alpha s + \alpha^2) Y(s) = X(s)$ $H(s) = \frac{Y(s)}{X(s)} = \frac{1}{(s^2 + \alpha s + \alpha^2)}$ Let another signal $g(t)$ be defined as

$$\begin{aligned} G(s) &= \frac{\alpha^2}{s} H(s) + sH(s) + \alpha H(s) \\ G(s) &= \left(\frac{\alpha^2}{s} + s + \alpha \right) H(s) \\ &= \left(\frac{\alpha^2 + s^2 + s\alpha}{s} \right) \cdot (s^2 + \alpha s + \alpha^2) \\ &= \frac{(s^2 + s\alpha + \alpha^2)}{s(s^2 + \alpha s + \alpha^2)} = \frac{1}{s} \end{aligned}$$

So, number of poles of $G(s)$ is 1

Question 114: Laplace Transform (GATE EC 2014-SET-4)

MCQ

2 Marks

A stable linear time invariant (LTI) system has a transfer function $H(S) = \frac{1}{s^2 + s - 6}$. To make this system causal it needs to be cascaded with another LTI system having a transfer function $H_1(S)$. A correct choice for $H_1(S)$ among the following options is

- (A) $s+3$
- (B) **(Correct)** $s-2$
- (C) $s-6$
- (D) $s+1$

Correct Answer: (B)

Detailed Solution – Question 114

$H(s) = \frac{1}{(s^2 + s - 6)}$ The system is said to be causal if the output at any time depends only on present and/or past values of input or $h(t) = 0$ for $t > 0$ i.e. all poles must lie on LHS of S-plane. $H(s) = \frac{1}{(s+3)(s-2)}$ From the above expression it can be seen that $s=2$ is a pole which lies on RHS of s-plane. So, $H_1(s)$ system that needs to be cascaded should have one zero at $(s-2)$

$$\text{Thus, } H(s)H_1(s) = (s-2) \cdot \frac{1}{(s+3)(s-2)} = \frac{1}{(s+3)} \rightarrow \text{causal system}$$

Question 115: Laplace Transform (GATE EC 2014-SET-4)

MCQ

2 Marks

The unilateral Laplace transform of $f(t)$ is $\frac{1}{s^2 + s + 1}$. Which one of the following is the unilateral Laplace transform of $g(t) = t \cdot f(t)$?

- (A) $\frac{-s}{(s^2+s+1)^2}$
- (B) $\frac{-(2s+1)}{(s^2+s+1)^2}$
- (C) $\frac{s}{(s^2+s+1)^2}$
- (D) **(Correct)** $\frac{2s+1}{(s^2+s+1)^2}$

Correct Answer: (D)

Detailed Solution – Question 115

Given $F(s) = \frac{1}{s^2+s+1}$ Laplace transform of $g(t) = t \cdot f(t)$

$$\begin{aligned} &= -\frac{dF(s)}{ds} = \frac{-d}{ds} \left[\frac{1}{(s^2 + s + 1)} \right] \\ &= \frac{(2s + 1)}{(s^2 + s + 1)^2} \end{aligned}$$

Question 116: DTFS, DTFT & DFT (GATE EC 2014-SET-4)

NAT

1 Mark

The sequence $x[n] = 0.5^n u[n]$, where $u[n]$ is the unit step sequence, is convolved with itself to obtain $y[n]$. Then $\sum_{n=-\infty}^{+\infty} y[n]$ is -----.

Detailed Solution – Question 116

$$\begin{aligned}\text{Given } x[n] &= 0.5^n u[n] \\ y[n] &= x[n] * x[n] \\ &= \sum_{k=-\infty}^{\infty} x(k)h(n-k) \\ &= \sum_{K=-\infty}^{\infty} (0.5)^k u(k)(0.5)^{n-k} u(n-k) \\ &= (0.5)^n \left[\sum_{k=-\infty}^{\infty} u(k)u(n-k) \right]\end{aligned}$$

Also we know that $u[n] * u[n] = (n+1)u[n] \therefore$ Using the above formula, we get

$$\begin{aligned}y[n] &= (0.5)^n (n+1)u[n] \\ \text{Let } p &= \sum_{n=0}^{\infty} (0.5)^n (n+1) \\ \text{Also let } a &= 0.5 \\ \therefore p &= \sum_{n=0}^{\infty} a^n (n+1) \\ \rho &= a^0(1) + a^1(1+1) + a^2(2+1) + a^3(3+1) + \dots \\ ap &= a(1) + a^2(2) + a^3(3) + \dots \\ p - ap &= a^0 \cdot 1 + a^1 + a^2 + \dots \\ p(1-a) &= \frac{1}{1-a} \\ p &= \frac{1}{(1-a)^2} \\ a &= 0.5 \text{ or } \frac{1}{2} \\ p &= \frac{1}{(1-\frac{1}{2})^2} = \frac{1}{(\frac{1}{2})^2} = 4\end{aligned}$$

Question 117: Fourier Transforms (GATE EC 2014-SET-4)

MCQ

1 Mark

A real-valued signal $x(t)$ limited to the frequency band $|f| \leq \frac{W}{2}$ is passed through a linear time invariant system whose frequency response is

$$H(f) = \begin{cases} e^{-j4\pi f}, & |f| \leq \frac{W}{2} \\ 0, & |f| > \frac{W}{2} \end{cases}$$

The output of the system is

- (A) $x(t+4)$
- (B) $x(t-4)$
- (C) $x(t+2)$

(D) (Correct) $x(t-2)$

Correct Answer: (D)

Detailed Solution – Question 117

$$\text{Given: } H(f) = \begin{cases} e^{-j4\pi t}, & |f| \leq \frac{\omega}{2} \\ 0, & |f| > \frac{\omega}{2} \end{cases}$$

$$\text{So, } |H(f)| = 1$$

$$H(f) = e^{-j2.2\pi t}$$

$$H(\omega) = e^{j2\omega} \quad |f| \leq \frac{\omega}{2}$$

$$h(t) = \delta(t-2)$$

As we know that

$$y(t) = x(t) * h(t)$$

$$\text{or } y(t) = X(\omega) \cdot H(\omega)$$

$$y(t) = x(t) * \delta(t-2)$$

$$y(t) = x(t-2)$$

Question 118: DTFS, DTFT & DFT (GATE EC 2014-SET-4)

NAT

1 Mark

A Fourier transform pair is given by

$$\left(\frac{2}{3}\right)^n u[n+3] \xleftrightarrow{FT} \frac{Ae^{-j6\pi f}}{1 - \left(\frac{2}{3}\right)e^{-j2\pi f}}$$

where $u[n]$ denotes the unit step sequence. The values of A is _____.

Detailed Solution – Question 118

$$\left(\frac{2}{3}\right)^n u(n+3) \xleftrightarrow{F.T.} \frac{Ae^{j6\pi f}}{1 - \left(\frac{2}{3}\right)e^{-j2\pi f}}$$

Let, $x[n] = \left(\frac{2}{3}\right)^n u(n+3)$ Discrete Fourier transform is given as

$$\begin{aligned} X(e^{j\omega}) &= \sum_{n=-\infty}^{\infty} x[n]e^{-j\omega n} \\ &= \sum_{n=-3}^{\infty} \left(\frac{2}{3}\right)^n e^{-j\omega n} \end{aligned}$$

Put, $n+3 = m$

$$\begin{aligned} \text{So, } x(e^{j\omega}) &= \sum_{m=0}^{\infty} \left(\frac{2}{3}\right)^{m-3} e^{-j\omega(m-3)} \\ &= \left(\frac{2}{3}\right)^{-3} \sum_{m=0}^{\infty} \left(\frac{2}{3}\right)^m e^{-j\omega m} e^{j\omega 3} \\ &= \left(\frac{3}{2}\right)^3 \sum_{m=0}^{\infty} \left(\frac{2}{3}e^{-j\omega}\right)^m \cdot e^{j\omega 3} \\ &= \frac{3.375 \cdot e^{j2\pi/3}}{1 - \frac{2}{3}e^{-j2\pi t}} \\ &= \frac{3.375e^{j\pi\pi f}}{1 - \frac{2}{3}e^{-j2\pi t}} \end{aligned}$$

So, $A = 3.375$

Question 119: Sampling (GATE EC 2014-SET-4)

MCQ

1 Mark

For a given sample-and-hold circuit, if the value of the hold capacitor is increased, then

- (A) droop rate decreases and acquisition time decreases
- (B) **(Correct)** droop rate decreases and acquisition time increases
- (C) droop rate increases and acquisition time decreases
- (D) droop rate increases and acquisition time increases

Correct Answer: (B)

Detailed Solution – Question 119

We know that

$$Q = CV = i \cdot t \quad \dots (i)$$

$$t = \frac{CV}{i} \quad \dots (ii)$$

From equation (ii) $t \propto C$ and it is clear that if value of capacitor increases then the acquisition time increases. For capacitor the drop rate is given as $\frac{dv}{dt}$

$$i = C \frac{dv}{dt}$$
$$\frac{dv}{dt} = \frac{i}{C}$$
$$\frac{dv}{dt} \propto \frac{1}{C}$$

From above relation it is clear that if capacitor value increases drop rate decreases.

Question 120: Z-Transform (GATE EC 2014-SET-3)

NAT

2 Marks

The z-transform of the sequence $x[n]$ is given by $X(z) = \frac{1}{(1-2z^{-1})^2}$, with the region of convergence $|z| > 2$. Then, $x[2]$ is

Detailed Solution – Question 120

$$\text{Given, } X(z) = \frac{1}{(1-2z^{-1})^2}, \quad |z| > 2$$

$$X(z) = (1-2z^{-1})^{-2}$$

$$X(z) = 1 + 4z^{-1} + 12z^{-2} + \dots$$

(using binomial expansion)

Taking inverse z-transform, we get

$$\therefore x[n] = \{ 1, 4, 12, \dots \}$$

$$x[2] = 12$$

Question 121: Laplace Transform (GATE EC 2014-SET-3)

MCQ

2 Marks

Let $h(t)$ denote the impulse response of a causal system with transfer function $\frac{1}{s+1}$. Consider the following three statements.

S1 : The system is stable S2: $\frac{h(t+1)}{h(t)}$ is independent of $t > 0$ S3 : A non-causal system with the same transfer function is stable

For the above system

(A) (Correct) only S1 and S2 are true

- (B) only S2 and S3 are true
 (C) only S1 and S3 are true
 (D) S1,S2 and S3 are true

Correct Answer: (A)

Detailed Solution – Question 121

$$\begin{aligned}\text{Given } H(s) &= \frac{1}{(s+1)} \\ h(t) &= e^{-t}u(t) \\ \text{at } t = \infty, h(t) &= 0\end{aligned}$$



i.e. the system is stable as it converges to zero as $t \rightarrow \infty$. The system is causal as it can be seen from the graph that $h(t) = 0$ for $t < 0$. $\frac{h(t+1)}{h(t)} = \frac{e^{-(t+1)}}{e^{-t}} = \frac{e^{-t} \cdot e^{-1}}{e^{-t}} = e^{-1}$ i.e. independent of t . So, statements S_1 and S_2 are true.

Question 122: Z-Transform (GATE EC 2014-SET-3)

NAT

2 Marks

Let $H_1(z) = (1 - pz^{-1})^{-1}$, $H_2(z) = (1 - qz^{-1})^{-1}$, $H(z) = H_1(z) + rH_2(z)$. The quantities p, q, r are real numbers. Consider $p = \frac{1}{2}$, $q = -\frac{1}{4}$, $|r| < 1$. If the zero of $H(z)$ lies on the unit circle, then $r = \dots$.

Detailed Solution – Question 122

$$\begin{aligned}\text{Here } H_1(z) &= \frac{1}{1 - pz^{-1}} \\ H_2(z) &= \frac{1}{1 - qz^{-1}} \\ \text{also } p &= \frac{1}{2}, \quad q = -\frac{1}{4} \\ \therefore H(z) &= H_1(z) + rH_2(z) \\ &= \frac{1}{1 - pz^{-1}} + \frac{r}{1 - qz^{-1}} \\ &= \frac{1}{1 - \frac{1}{2}z^{-1}} + \frac{r}{1 + \frac{1}{4}z^{-1}} \\ H(z) &= \frac{(1 + \frac{1}{4}z^{-1}) + r(1 - \frac{1}{2}z^{-1})}{(1 - \frac{1}{2}z^{-1})(1 + \frac{1}{4}z^{-1})} \dots(i)\end{aligned}$$

zero of $H(z) \Rightarrow (1 + r) - (q + pr)z^{-1} = 0 \dots(ii)$ or $z = \frac{q+pr}{1+r}$ Since, the zero of $H(z)$ lies on the unit circle therefore $|z| = 1$ or $z = \pm 1$ Taking $z=1$, we get $z = \frac{q+pr}{1+r} = 1 \dots(iii)$ By solving above expression with $p = \frac{1}{2}$ and $q = -\frac{1}{4}$, we get $r = -2.5$ But $|r| < 1$ or $-1 < r < 1$ Taking $z=-1$ in equation (iii), we get $r = -0.5$

Question 123: Fourier Transforms (GATE EC 2014-SET-3)

MCQ

1 Mark

The phase response of a passband waveform at the receiver is given by $\varphi(f) = -2\pi\alpha(f - f_c) - 2\pi\beta f_c$ where f_c is the centre frequency, and α and β are positive constants. The actual signal propagation delay from the transmitter to receiver is

- (A) $\frac{\alpha - \beta}{\alpha + \beta}$
- (B) $\frac{\alpha\beta}{\alpha + \beta}$
- (C) (Correct) α
- (D) β

Correct Answer: (C)

Detailed Solution – Question 123

Group delay is given by $= \frac{-1}{2\pi} \frac{d\phi(f)}{df} = \frac{-1}{2\pi} [-2\pi\alpha]$ Group delay $= \alpha$

Question 124: Laplace Transform (GATE EC 2014-SET-3)

NAT

1 Mark

The input $-3e^{2t}u(t)$, where $u(t)$ is the unit step function, is applied to a system with transfer function $\frac{s-2}{s+3}$. If the initial value of the output is -2, then the value of the output at steady state is -----.

Detailed Solution – Question 124

Given, $x(t) = -3e^{-2t}$ Laplace transform of $x(t) \longleftrightarrow X(s)$ Where,

$$\begin{aligned}X(s) &= \frac{-3}{s+2} \\A \mid s0, H(s) &= \frac{s-2}{(s+3)} \\ \therefore Y(s) &= X(s)H(s) \\ \gamma(s) &= \frac{-3(s-2)}{(s+3)(s+2)}\end{aligned}$$

Using final value theorem, the steady state value of Y(s) is

$$\begin{aligned}y(\infty) &= \lim_{s \rightarrow 0} sY(s) \\ &= 0\end{aligned}$$

Question 125: Z-Transform (GATE EC 2014-SET-3)

MCQ

1 Mark

For an all-pass system $H(z) = \frac{(z^{-1}-b)}{(1-az^{-1})}$, where $|H(e^{-j\omega})| = 1$, for all ω . If $\text{Re}(a) \neq 0$, $\text{Im}(a) \neq 0$, then b equals

- (A) a
- (B) (Correct) a^*
- (C) $1/a^*$
- (D) $1/a$

Correct Answer: (B)

Detailed Solution – Question 125

For the given system $H(z) = \frac{(z^{-1}-b)}{(1-az^{-1})}$ The pole lie at $z=a$ and the zero lie at $z = \frac{1}{b}$ also 'a' is complex in nature. Thus, $a = |a|e^{i\angle a}$ For an all pass system where $|H(e^{-j\omega})| = 1$, for all ω , if the pole lies at 'a' then the zero must be present at $\frac{1}{a^*}$

$$\begin{aligned}\therefore \left(\frac{1}{b}\right) &= \frac{1}{|a|e^{-j\angle a}} = \frac{1}{a^*} \\ \text{or } b &= a^*\end{aligned}$$

Question 126: Sampling (GATE EC 2014-SET-3)

MCQ

1 Mark



Let $x(t) = \cos(10\pi t) + \cos(30\pi t)$ be sampled at 20 Hz and reconstructed using an ideal low-pass filter with cut-off frequency of 20 Hz. The frequency/ frequencies present in the reconstructed signal is/are

- (A) **(Correct)** 5 Hz and 15 Hz only
- (B) 10 Hz and 15 Hz only
- (C) 5 Hz, 10 Hz and 15 Hz only
- (D) 5 Hz only



Correct Answer: (A)

Detailed Solution – Question 126

$x(t) = \cos(10\pi t) + \cos(30\pi t)$ Given sampling frequency, $f_s = 20\text{Hz}$ $\omega_s = 40\pi\text{rad/sec}$



$Y(\omega) = \sum_{K=-\infty}^{\infty} X(\omega - K\omega_s)$ After sampling waveform will be



Applying an ideal low-pass filter of cut-off frequency of 20Hz or 40π rad/sec, we get the frequencies in reconstructed signal as 10π and 30π rad/sec. or 5Hz and 15Hz

Question 127: Fourier Transforms (GATE EC 2014-SET-2)

NAT

2 Marks

The value of the integral $\int_{-\infty}^{\infty} \text{sinc}^2(5t) dt$ is ____.

Detailed Solution – Question 127

$$\int_{-\infty}^{\infty} \sin^2(5t) dt$$

$$\text{Let, } f(t) = \sin c(5t) \\ = S_a(5\pi t) \quad [\because \sin c(t) = S_a(\pi t)]$$

$$TSa\left(t \cdot \frac{T}{2}\right) \longleftrightarrow 2\pi G_T(\omega)$$



$$\frac{T}{2} = 5\pi \Rightarrow [T = 10\pi]$$

$$10\pi Sa(5\pi t) \longleftrightarrow 2\pi G_{10\pi}(\omega)$$

$$\Rightarrow F(\omega) = \frac{1}{5} G_{10\pi}(\omega)$$

$$ESD_f = |F(\omega)|^2$$

$$E_f = \int_{-\infty}^{\infty} f^2(t) dt = \frac{1}{2\pi} \int_{-\infty}^{\infty} ESD_f d\omega$$



$$\begin{aligned} \int_{-\infty}^{\infty} \sin^2(5t) dt &= \frac{1}{2\pi} \int_{-5\pi}^{5\pi} \left(\frac{1}{5}\right)^2 d\omega \\ &= \frac{1}{2\pi} \times \frac{1}{25} \times 10\pi = \frac{1}{5} \end{aligned}$$

Question 128: Z-Transform (GATE EC 2014-SET-2)

MCQ

2 Marks

The input-output relationship of a causal stable LTI system is given as $y[n] = \alpha y[n-1] + \beta x[n]$. If the impulse response $h[n]$ of this system satisfies the condition $\sum_{n=0}^{\infty} h[n] = 2$, the relationship between α

and β is

(A) **(Correct)** $\alpha = 1 - \beta/2$

(B) $\alpha = 1 + \beta/2$

(C) $\alpha = 2\beta$

(D) $\alpha = -2\beta$

Correct Answer: (A)

Detailed Solution – Question 128

Input-output relation is given as

$$y[n] = \alpha y[n-1] + \beta x[n]$$

Taking Z-transform,

$$Y(z) = \alpha z^{-1} Y(z) + \beta X(z)$$

$$Y(z) [1 - \alpha z^{-1}] = \beta X(z)$$

$$\frac{Y(z)}{X(z)} = H(z) = \frac{\beta}{1 - \alpha z^{-1}}$$

$$h[n] = \beta \cdot \alpha^n u[n]$$

$$\text{Also } \sum_{n=0}^{\infty} h[n] = 2 \Rightarrow \sum_{n=0}^{\infty} \beta \cdot \alpha^n u[n] = 2$$

$$\frac{\beta}{1 - \alpha} = 2 \Rightarrow \beta = 2 - 2\alpha$$

$$\Rightarrow 2\alpha = 2 - \beta$$

$$\alpha = 1 - \frac{\beta}{2}$$

Question 129: LTI Systems (GATE EC 2014-SET-2)

NAT

2 Marks

Consider a discrete-time signal

$$x[n] = \begin{cases} n & \text{for } 0 \leq n \leq 10 \\ 0 & \text{otherwise} \end{cases}$$

If $y[n]$ is the convolution of $x[n]$ with itself, the value of $y[4]$ is

Detailed Solution – Question 129

$$x[n] = \begin{cases} n & \text{for } 0 \leq n \leq 10 \\ 0 & \text{otherwise} \end{cases}$$

$$y[n] = \sum_{k=-\infty}^{\infty} x(k)x(n-k)$$

$$y[4] = \sum_{k=0}^{10} x(k)x(4-k)$$

$$= x(0)x(4) + x(1)x(3) + x(2)x(2) + x(3)x(1) + 0$$

$$= 0 + (1 \times 3) + (2 \times 2) + (3 \times 1)$$


$$= 10$$

Question 130: Fourier Series (GATE EC 2014-SET-2)



NAT

1 Mark

Consider the periodic square wave in the figure shown.



The ratio of the power in the 7th harmonic to the power in the 5th harmonic for this waveform is closest in value to



$$\begin{aligned}
 X(\omega) &= \sum_{K=-\infty}^{\infty} 2\pi a_K \delta(\omega - K\omega_0) \\
 a_K &= \frac{1}{2\pi} \int_0^2 x(t) e^{-jK\omega_0 t} dt \\
 &= \frac{1}{2\pi} \left\{ \int_0^1 1 \cdot e^{-jK\omega_0 t} dt - \int_1^2 1 \cdot e^{-jK\omega_0 t} dt \right\} \\
 &= \frac{1}{2\pi} \left[\frac{1}{-jK\omega_0} [e^{-jK\omega_0} - 1] - \frac{1}{-jK\omega_0} [e^{-j2K\omega_0} - e^{-jK\omega_0}] \right] \\
 &= \frac{1}{2\pi} \left[\frac{e^{-jK\omega_0/2}}{jK\omega_0} 2j \sin \frac{K\omega_0}{2} - \frac{1}{jK\omega_0} e^{-j\frac{3K\omega_0}{2}} \left(2j \sin \frac{K\omega_0}{2} \right) \right] \\
 &= \frac{1}{\pi} \left[\frac{\sin \frac{K\omega_0}{2}}{K\omega_0} (e^{-jK\omega_0}) \left(e^{\frac{jK\omega_0}{2}} - e^{-\frac{jK\omega_0}{2}} \right) \right] \\
 &= \frac{1}{\pi} \left(\frac{\sin K\omega_0/2}{K\omega_0} \right) e^{-jK\omega_0} \times 2j \sin \left(\frac{K\omega_0}{2} \right) \\
 &= \frac{1}{\pi^2} \frac{(\sin K\frac{\pi}{2})^2}{K} 2j \times \cos K\pi
 \end{aligned}$$

$$7^{\text{th}} \text{ harmonic power} = (2\pi a_7)^2 \quad 5^{\text{th}} \text{ harmonic power} = (2\pi a_5)^2$$

$$Ratio = \left(\frac{a_7}{a_5} \right)^2 = \left(\frac{5}{7} \right)^2 = \frac{25}{49} = 0.51$$

Question 131: Z-Transform (GATE EC 2014-SET-2)

MCQ

1 Mark

Let $x[n] = x[-n]$. Let $X(z)$ be the z -transform of $x[n]$. If $0.5 + j0.25$ is a zero of $X(z)$, which one of the following must also be a zero of $X(z)$.

- (A) $0.5 - j0.25$
- (B) **(Correct)** $1/(0.5 + j0.25)$
- (C) $1/(0.5 - j0.25)$
- (D) $2 + j4$

Correct Answer: (B)

Detailed Solution – Question 131

Given $x[n] = x[-n]$ As we know that,

$$\begin{aligned}x[n] &\xleftrightarrow{Z} X[z] \\x[-n] &\xleftrightarrow{Z} X[z^{-1}]\end{aligned}$$

So, when $(0.5 + j0.25)$ is a zero of $X(z)$. Now $x[-n] \longleftrightarrow X(z^{-1})$ Zero of $X(z) = \frac{1}{(0.5 + j0.25)}$

Question 132: DTFS, DTFT & DFT (GATE EC 2014-SET-2)

MCQ

1 Mark

An FIR system is described by the system function $H(z) = 1 + \frac{7}{2}z^{-1} + \frac{3}{2}z^{-2}$ The system is

- (A) maximum phase
- (B) minimum phase
- (C) **(Correct)** mixed phase
- (D) zero phase

Correct Answer: (C)

Detailed Solution – Question 132

Minimum phase $\Rightarrow$ all zeroes are inside the unit circle.

For maximum phase, all the zeroes are outside the unit circle. $H(z) = 1 + \frac{7}{2}z^{-1} + \frac{3}{2}z^{-2} = 0$
 $2z^2 + 7z + 3 = 0$ $(2z + 1)(z + 3) = 0$ $z_1 = -\frac{1}{2}$ (inside the unit circle) $z_2 = -3$ (outside the unit circle) $\therefore$ Mixed phase.

Question 133: Laplace Transform (GATE EC 2014-SET-1)

MCQ

2 Marks

A system is described by the following differential equation, where $u(t)$ is the input to the system and $y(t)$ is the output of the system. $\dot{y}(t) + 5y(t) = u(t)$ when $y(0) = 1$ and $u(t)$ is a unit step function, $y(t)$ is

(A) $0.2 - 0.2e^{-5t}$

(B) $0.8 + 0.2e^{-5t}$

(C) $0.8 - 0.8e^{-5t}$

Correct Answer: ()

Detailed Solution – Question 133

$\dot{y}(t) + 5y(t) = u(t)$ Taking the Laplace transform of the above equation

$$sY(s) - y(0) + 5r(s) = \frac{1}{s}$$

$$(s + 5)r(s) - 1 = \frac{1}{s}$$

$$(s + 5)r(s) = \frac{s + 1}{s}$$

$$Y(s) = \frac{(s + 1)}{s(s + 5)}$$

$$\frac{A}{s} + \frac{B}{(s + 5)} = \frac{(s + 1)}{s(s + 5)}$$

$$A = 0.2$$

$$B = \frac{-4}{-5} = 0.8$$

$$r(s) = \frac{0.2}{s} + \frac{0.8}{(s + 5)}$$

$$y(t) = 0.2 + 0.8e^{-5t}$$

Question 134: DTFS, DTFT & DFT (GATE EC 2014-SET-1)

NAT

2 Marks

Consider a discrete time periodic signal $x[n] = \sin(\frac{\pi n}{5})$. Let a_k be the complex Fourier series coefficients of $x[n]$. The coefficients $\{a_k\}$ are non-zero when $k = Bm \pm 1$, where m is any integer. The value of B is ----.

Detailed Solution – Question 134

From discrete Fourier series definition

$$\begin{aligned} x[n] &= \sum_{K=0}^{N-1} a_K e^{jK(\frac{2\pi}{N})n} \\ &= a_{-1} e^{-j\frac{2\pi}{N}n} + a_0 + a_1 e^{j\frac{2\pi}{N}n} \quad \dots (i) \\ x[n] &= \frac{-1}{2j} e^{-i\frac{\pi}{5}n} + \frac{1}{2j} e^{i\frac{\pi}{5}n} \end{aligned}$$

Also given $x[n] = \sin\left(\frac{\pi n}{5}\right)$ where $N = 10 \left[\frac{2\pi}{N} = \frac{\pi}{5} \Rightarrow N = 10\right]$ By comparison $a_1 = \frac{1}{2j}$ and $a_9 = a_{-1} = \frac{-1}{2j}$ As the TFS coefficient a_K is also periodic with period $N=10$.

$$a_1 = a_{11} = a_{21} \dots$$

$$a_{-1} = a_9 = a_{19} \dots$$

Given that a_K is non-zero for $K = Bm \pm 1$

$$\begin{array}{ccc} Bm \pm 1 = 1 & & 9 \dots \\ -1 & & 11 \dots \\ \text{For } m = 0 & \text{for} & m = 1 \end{array}$$

To satisfy this condition B must be '10' where 'm' is any integer.

Question 135: Z-Transform (GATE EC 2014-SET-1)

MCQ

2 Marks

Let $x[n] = \left(-\frac{1}{9}\right)^n u(n) - \left(-\frac{1}{3}\right)^n u(-n-1)$. The Region of Convergence (ROC) of the z -transform of $x[n]$.

- (A) is $|z| > \frac{1}{9}$
- (B) is $|z| < \frac{1}{3}$
- (C) **(Correct)** is $\frac{1}{3} > |z| > \frac{1}{9}$
- (D) does not exist

Correct Answer: (C)

Detailed Solution – Question 135

$$x(n) = \frac{\left(-\frac{1}{9}\right)^n u(n) - \left(-\frac{1}{3}\right)^n u(-n-1)}{x_1(n)} \frac{1}{x_2(n)}$$

$$x_1(n) = \left(-\frac{1}{9}\right)^n u(n) \rightarrow \text{Right sided signal}$$

$$x_1(z) = \frac{1}{1 - \left(-\frac{1}{9}\right) z^{-1}}$$

$$\text{ROC } |z| \geq \left|\frac{1}{9}\right| \text{ or } |z| > \frac{1}{9}$$

$$x_2(n) = \left(-\frac{1}{3}\right)^n u(-n-1) \rightarrow \text{Left sided signal}$$

$$x_2(z) = \frac{1}{1 - \left(-\frac{1}{3}\right) z^{-1}}; \quad |z| \leq \frac{1}{3}$$

Now, when both the transforms are added using linearity property. ROC must be between $\frac{1}{3} > |z| > \frac{1}{9}$

Question 136: Fourier Transforms (GATE EC 2014-SET-1)

MCQ

2 Marks

For a function $g(t)$, it is given that $\int_{-\infty}^{+\infty} g(t)e^{-j\omega t} dt = \omega e^{-2\omega^2}$ for any real value ω . If $y(t) = \int_{-\infty}^t g(\tau) d\tau$, then $\int_{-\infty}^{+\infty} y(t) dt$ is

- (A) 0
- (B) **(Correct)** $-j$
- (C) $-\frac{j}{2}$
- (D) $\frac{j}{2}$

Correct Answer: (B)

Detailed Solution – Question 136

$$\begin{aligned} G(j\omega) &= \omega e^{-2\omega^2} \\ \int_{-\infty}^* g(t) dt &= G(j0) = 0 \\ y(t) &= g(t) * u(t) \\ \Rightarrow r(j\omega) &= G(j\omega)U(j\omega) \\ \Rightarrow \gamma(j\omega) &= G(j\omega) \left[\frac{1}{j\omega} + \pi\delta(\omega) \right] \\ &= \frac{\omega e^{-2\omega^2}}{j\omega} + \omega e^{-2\omega^2} \pi\delta(\omega) \\ \int_{-\infty}^* y(t) dt &= Y(j0) = \frac{1}{j} = -j \end{aligned}$$

Question 137: Fourier Transforms (GATE EC 2014-SET-1)

NAT

1 Mark

A continuous, linear time-invariant filter has an impulse response $h(t)$ described by

$$h(t) = \begin{cases} 3 & \text{for } 0 \leq t \leq 3 \\ 0 & \text{otherwise} \end{cases}$$

When a constant input of values 5 is applied to this filter, the steady state output is.....

Detailed Solution – Question 137

$$h(t) = \begin{cases} 3, & \text{for } 0 \leq t \leq 3 \\ 0, & \text{otherwise} \end{cases}$$

$$h(t) = 3[u(t) - u(t - 3)]$$

$$H(s) = 3 \left[\frac{1}{s} - \frac{e^{-3s}}{s} \right]$$

$$\therefore x(t) = 5$$

$$\text{Then } x(s) = \frac{5}{s}$$

We know that $Y(s) = H(s)X(s) = 3 \left[\frac{1}{s} - \frac{e^{-3s}}{s} \right] \cdot \frac{5}{s}$ Steady state output

$$\begin{aligned} &= \lim_{s \rightarrow 0} s \cdot Y(s) = \lim_{s \rightarrow 0} s \cdot \frac{15(1 - e^{-3s})}{s} \\ &= 15 \cdot \lim_{s \rightarrow 0} 3e^{-3s} \quad [\because \text{L-Hospital's rule}] \\ &= 45 \end{aligned}$$

Question 138: Sampling (GATE EC 2014-SET-1)

NAT

1 Mark

Consider two real valued signals, $x(t)$ band-limited to $[-500 \text{ Hz}, 500 \text{ Hz}]$ and $y(t)$ band-limited to $[-1 \text{ kHz}, 1 \text{ kHz}]$. For $z(t) = x(t) \cdot y(t)$, the Nyquist sampling frequency (in kHz) is

Detailed Solution – Question 138

Multiplication in time domain = convolution in frequency domain. $x_1(t) \cdot x_2(t) \leftrightarrow X_1(\omega) * X_2(\omega)$
So, highest frequency component contained by the convolved signal $z(t) = 1500 \text{ Hz} \therefore$ Nyquist rate
 $= 2 \times 1500 = 3000 \text{ Hz} = 3 \text{ kHz}$

Question 139: Basics of Signals & Systems (GATE EC 2014-SET-1)

MCQ

1 Mark

A discrete time signal $x[n] = \sin(\pi^2 n)$, n being an integer, is

- (A) periodic with period π
- (B) periodic with period π^2
- (C) periodic with period $\pi/2$

(D) **(Correct)** not periodic

Correct Answer: (D)

Detailed Solution – Question 139

$$\begin{aligned}x[n] &= \sin(\pi^2 n) \\ \omega_0 &= \pi^2 \\ \therefore N &= \frac{2\pi}{\omega_0} \cdot m\end{aligned}$$

where m is the smallest integer that converts $\frac{2\pi}{\omega_0}$ into a integer value. $\therefore N = \frac{2\pi}{\pi^2} \cdot m = \frac{2}{\pi} \cdot m$
So, there exists no such integer value of m which could make the N integer, so the system is not periodic.

Question 140: DTFS, DTFT & DFT (GATE EC 2013)

MCQ

1 Mark

The DFT of a vector $[a \ b \ c \ d]$ is the vector

$$[\alpha \ \beta \ \gamma \ \delta]$$

. Consider the product

$$[p \ q \ r \ s] = [a \ b \ c \ d] \begin{bmatrix} a & b & c & d \\ d & a & b & c \\ c & d & a & b \\ b & c & d & a \end{bmatrix}$$

The DFT of the vector

$$[p \ q \ r \ s]$$

is a scaled version of

(A) **(Correct)**

$$[\alpha^2 \ \beta^2 \ \gamma^2 \ \delta^2]$$

(B)

$$[\sqrt{\alpha} \ \sqrt{\beta} \ \sqrt{\gamma} \ \sqrt{\delta}]$$

(C)

$$[\alpha + \beta \ \beta + \delta \ \delta + \gamma \ \gamma + \alpha]$$

(D)

$$[\alpha \ \beta \ \gamma \ \delta]$$

Correct Answer: (A)

Detailed Solution – Question 140

$$\begin{aligned}\text{DFT}[pqrs] &= [abcd] * [abcd] \\ \text{So, DFT}[pqrs] &= [\alpha^2 \beta^2 \gamma^2 \delta^2]\end{aligned}$$

Question 141: Laplace Transform (GATE EC 2013)

MCQ

1 Mark

A system is described by the differential equation $\frac{d^2y}{dt^2} + 5\frac{dy}{dt} + 6y(t) = x(t)$. Let $x(t)$ be a rectangular pulse given by

$$x(t) = \begin{cases} 1 & 0 < t < 2 \\ 0 & \text{otherwise} \end{cases}$$

Assuming that $y(0) = 0$ and $\frac{dy}{dt} = 0$ at $t = 0$, the Laplace transform of $y(t)$ is

- (A) $\frac{e^{-2s}}{s(s+2)(s+3)}$
- (B) **(Correct)** $\frac{1-e^{-2s}}{s(s+2)(s+3)}$
- (C) $\frac{e^{-2s}}{(s+2)(s+3)}$
- (D) $\frac{1-e^{-2s}}{(s+2)(s+3)}$

Correct Answer: (B)

Detailed Solution – Question 141

$$x(t) = u(t) - u(t-2)$$
$$X(s) = \frac{1}{s} - \frac{e^{-2s}}{s} = \frac{1-e^{-2s}}{s}$$

Given that $\frac{d^2y}{dt^2} + 5\frac{dy}{dt} + 6y(t) = x(t)$ Taking Laplace transform on both the sides

$$\left(y(0) = 0 \text{ and } \frac{dy}{dt} = 0 \text{ at } t = 0 \right)$$
$$s^2Y(s) + 5sY(s) + 6Y(s) = X(s)$$
$$Y(s) [s^2 + 5s + 6] = \frac{1-e^{-2s}}{s}$$
$$Y(s) = \frac{1-e^{-2s}}{s(s^2+5s+6)} = \frac{1-e^{-2s}}{s(s+2)(s+3)}$$

Question 142: Basics of Signals & Systems (GATE EC 2013)

MCQ

1 Mark



The impulse response of a continuous time system is given by $h(t) = \delta(t-1) + \delta(t-3)$. The value of the step response at $t = 2$ is

- (A) 0
- (B) **(Correct)** 1
- (C) 2
- (D) 3

Correct Answer: (B)

Detailed Solution – Question 142

Step response = Integration of impulse response $\int_{-\infty}^t \delta(t-1)dt = u(t-1)$ $\int_{-\infty}^t \delta(t-3)dt = u(t-3)$



$$\text{at } t = 2$$



$$y(t) = 1$$

Question 143: Laplace Transform (GATE EC 2013)

MCQ

1 Mark

Assuming zero initial condition, the response $y(t)$ of the system given below to a unit step input $u(t)$ is



- (A) $u(t)$
- (B) **(Correct)** $tu(t)$
- (C) $\frac{t^2}{2}u(t)$
- (D) $e^{-t}u(t)$

Correct Answer: (B)

Detailed Solution – Question 143

$x(t) = u(t)$ Apply Laplace transform

$$\begin{aligned}X(s) &= \frac{1}{s} \\H(s) &= \frac{1}{s} \quad (\text{given}) \\Y(s) &= H(s)X(s) \\&= \frac{1}{s} \times \frac{1}{s} = \frac{1}{s^2}\end{aligned}$$

Taking inverse Laplace transform $y(t) = tu(t)$

Question 144: Laplace Transform (GATE EC 2013)

MCQ

1 Mark

Which one of the following statements is NOT TRUE for a continuous time causal and stable LTI system?

- (A) All the poles of the system must lie on the left side of the $j\omega$ axis.
- (B) Zeros of the system can lie anywhere in the s-plane.
- (C) **(Correct)** All the poles must lie within $|s| = 1$
- (D) All the roots of the characteristic equation must be located on the left side of the $j\omega$ axis.

Correct Answer: (C)

Detailed Solution – Question 144

For a causal and stable LTI system the ROC must be right sided and it must include the $s = j\omega$ line ($\sigma = 0$). For all the poles must lie within $|s| = 1$ then all poles will lie between -1 to +1. We know that ROC does not include any pole, so in this case ROC will not be able to include $s = j0$ line ($\sigma = 0$). Thus the system will not be stable. Hence, this statement is NOT TRUE.

Question 145: Sampling (GATE EC 2013)

MCQ

1 Mark

A band-limited signal with a maximum frequency of 5 kHz is to be sampled. According to the sampling theorem, the sampling frequency which is not valid is

- (A) **(Correct)** 5 kHz
- (B) 12 kHz
- (C) 15 kHz
- (D) 20 kHz

Correct Answer: (A)

Detailed Solution – Question 145

$$\begin{aligned}(f_s)_{\min} &= 2f_m \\ (f_s)_{\min} &= 2 \times 5 = 10\text{kHz} \\ \text{So, } f_s &\geq 10\text{kHz}\end{aligned}$$

Question 146: Basics of Signals & Systems (GATE EC 2013)

MCQ

1 Mark

For a periodic signal

$$v(t) = 30 \sin 100t + 10 \cos 300t + 6 \sin \left(500t + \frac{\pi}{4} \right)$$

, the fundamental frequency in rad/s is

- (A) **(Correct)** 100
- (B) 300
- (C) 500
- (D) 1500

Correct Answer: (A)

Detailed Solution – Question 146

$$\begin{aligned}\omega_1 &= 100 \\ \omega_2 &= 300 \\ \omega_3 &= 500\end{aligned}$$

$$\text{H.C.F. of } (\omega_1, \omega_2 \text{ and } \omega_3) = \text{H.C.F. } (100, 300, 500) \omega = 100\text{rad/sec}$$

Question 147: Laplace Transform (GATE EC 2013)

MCQ

1 Mark

The impulse response of a system is $h(t) = tu(t)$. For an input $u(t-1)$, the output is

- (A) $\frac{t^2}{2}u(t)$
- (B) $\frac{t(t-1)}{2}u(t-1)$
- (C) **(Correct)** $\frac{(t-1)^2}{2}u(t-1)$
- (D) $\frac{t^2-1}{2}u(t-1)$

Correct Answer: (C)

Detailed Solution – Question 147

$$h(t) = tu(t)$$

Taking Laplace transform

$$H(s) = \frac{1}{s^2}$$

$$x(t) = u(t - 1)$$

Taking Laplace transform

$$X(s) = \frac{e^{-s}}{s}$$

$$\frac{Y(s)}{X(s)} = H(s)$$

$$Y(s) = H(s)X(s)$$

$$Y(s) = \frac{1}{s^2} \cdot \frac{e^{-s}}{s} = \frac{e^{-s}}{s^3}$$

Taking the inverse Laplace transform

$$y(t) = \frac{(t-1)^2}{2} u(t-1)$$

Question 148: LTI Systems (GATE EC 2013)

MCQ

1 Mark

Two systems with impulse responses $h_1(t)$ and $h_2(t)$ are connected in cascade. Then the overall impulse response of the cascaded system is given by

- (A) product of $h_1(t)$ and $h_2(t)$
- (B) sum of $h_1(t)$ and $h_2(t)$
- (C) **(Correct)** convolution of $h_1(t)$ and $h_2(t)$
- (D) subtraction of $h_2(t)$ from $h_1(t)$

Correct Answer: (C)

Detailed Solution – Question 148

The overall impulse response $h(t)$ of the cascade system is given by: $h(t) = h_1(t) * h_2(t)$

Question 149: LTI Systems (GATE EC 2012)

MCQ

1 Mark

Let $y[n]$ denote the convolution of $h[n]$ and $g[n]$, where $h[n] = (1/2)^n u[n]$ and $g[n]$ is a causal sequence. If $y[0] = 1$ and $y[1] = 1/2$, then $g[1]$ equals

- (A) **(Correct)** 0

(B) $1/2$


(C) 1

(D) $3/2$



Correct Answer: (A)

$$h[n] = \left(\frac{1}{2}\right)^n u[n]$$

$$g[n] = ??$$



$$y[n] = \sum_{k=-\infty}^{\infty} h[n-k]g[k]$$



$$y[0] = \sum_{k=-\infty}^{\infty} h[-k]g[k]$$

$$y[0] = h[0]g[0]$$

$$1 = 1g[0]$$

$$g[0] = 1$$

$$y[1] = \sum_{k=-\infty}^{\infty} h[1-k]g[k]$$

$$y[1] = h[1]g[0] + h[0]g[1]$$

$h[1-k]$ will be zero for $k > 1$ and $g[k]$ will be zero for $k < 0$ as it is a causal sequence.

$$\frac{1}{2} = \frac{1}{2} \times 1 + 1g[1]$$

$$g[1] = 0$$

Question 150: Fourier Transforms (GATE EC 2012)

MCQ

1 Mark

The Fourier transform of a signal $h(t)$ is $H(j\omega) = (2\cos\omega)(\sin 2\omega) / \omega$. The value of $h(0)$ is

- (A) $1/4$
- (B) $1/2$
- (C) **(Correct)** 1
- (D) 2

Correct Answer: (C)



Detailed Solution – Question 150

$$\frac{2 \cos \omega \sin 2\omega}{\omega} = H(\omega)$$

$$H(\omega) = 2 \cos \omega \left(\frac{2 \sin 2\omega}{2\omega} - H_1(j\omega) \cdot H_2(j\omega) \right)$$

where, $H_1(j\omega) = 2 \cos \omega$

$$H_2(j\omega) = \frac{2 \sin 2\omega}{2\omega} = 2 \text{Sa}(2\omega)$$





$$H_1(j\omega) = 2 \cos \omega = (e^{j\omega} + e^{-j\omega}) = e^{j\omega t} + e^{j\omega(-1)}$$

So

$$H(j\omega) = 2 \cos \omega H_2(j\omega) = (e^{j\omega} + e^{-j\omega}) H_2(j\omega)$$

$$H(j\omega) = e^{j\omega} H_2(j\omega) + e^{-j\omega} H_2(j\omega) \Rightarrow h(t) = h_2(t+1) + h_2(t-1)$$



So, $h(0) = 1$

Question 151: Basics of Signals & Systems (GATE EC 2012)

MCQ

1 Mark

The input $x(t)$ and output $y(t)$ of a system are related as $y(t) = \int_{-\infty}^t x(\tau) \cos(3\tau) d\tau$. The system is

- (A) time-invariant and stable
- (B) stable and not time-invariant
- (C) time-invariant and not stable
- (D) **(Correct)** not time-invariant and not stable

Correct Answer: (D)

Detailed Solution – Question 151

$$y = \int_{-\infty}^t x(\tau) \cos(3\tau) d\tau$$
$$y(t - t_0) = \int_{-\infty}^{t-t_0} x(\tau) \cos(3\tau) d\tau$$

$y'(t)$ for input $x(t - t_0)$, is

$$y'(t) = \int_{-\infty}^t x(\tau - t_0) \cos 3\tau d\tau$$
$$y'(t) = \int_{-\infty}^{(t-t_0)} x(\tau) \cos 3(\tau + t_0) d\tau$$

$y'(t) \neq y(t - t_0)$ so system is not time invariant for input $x(\tau) = \cos(3\tau)$ (bounded input)

$$y(t) = \int_{-\infty}^t \cos^2(3\tau) d\tau \rightarrow \infty \text{ as } t \rightarrow \infty$$

So, for bounded i/p, o/p is not bounded therefore system is not stable.

Question 152: Z-Transform (GATE EC 2012)

MCQ

1 Mark

If $x[n] = (1/3)^{|n|} - (1/2)^n u[n]$, then the region of convergence (ROC) of its Z-transform in the Z-plane will be

- (A) $\frac{1}{3} < |z| < 3$
- (B) $\frac{1}{3} < |z| < \frac{1}{2}$
- (C) **(Correct)** $\frac{1}{2} < |z| < 3$
- (D) $\frac{1}{3} < |z|$

Correct Answer: (C)

Detailed Solution – Question 152

$$\begin{aligned}x[n] &= \left(\frac{1}{3}\right)^{|n|} - \left(\frac{1}{2}\right)^n \cup [n] \\x[n] &= \left(\frac{1}{3}\right)^n u[n] + \left(\frac{1}{3}\right)^{-n} u[-n-1] - \left(\frac{1}{2}\right)^n u[n] \\ \left(\frac{1}{3}\right)^n u[n] &\longleftrightarrow \frac{1}{1 - \frac{1}{3}z^{-1}} \quad \text{ROC } |z| > \frac{1}{3} \\ \left(\frac{1}{3}\right)^{-n} u[-n-1] &\longleftrightarrow \frac{-1}{1 - 3z^{-1}} \text{ROC } |z| < 3 \\ \left(\frac{1}{2}\right)^n u[n] &\longleftrightarrow \frac{1}{1 - \frac{1}{2}z^{-1}} \quad \text{ROC } |z| > \frac{1}{2}\end{aligned}$$

So, overall ROC will be intersection of there ROC i.e. $\frac{1}{2} < |z| < 3$

Question 153: Laplace Transform (GATE EC 2012)

MCQ

1 Mark

The unilateral Laplace transform of $f(t)$ is $\frac{1}{s^2+s+1}$. The unilateral Laplace transform of $tf(t)$ is

- (A) $-\frac{s}{(s^2+s+1)^2}$
- (B) $-\frac{2s+1}{(s^2+s+1)^2}$
- (C) $\frac{s}{(s^2+s+1)^2}$
- (D) **(Correct)** $\frac{2s+1}{(s^2+s+1)^2}$

Correct Answer: (D)

Detailed Solution – Question 153

If $L[f(t)] = \bar{f}(s)$ then

$$L[t^n f(t)] = (-1)^n \frac{d^n}{ds^n} \bar{f}(s)$$

In this problem, Given,

$$L[f(t)] = \frac{1}{s^2 + s + 1} = \bar{f}(s)$$

$$\text{We need } L[tf(t)] = (-1)^1 \frac{d^1}{ds^1} \bar{f}(s)$$

$$= -\frac{d}{ds} \bar{f}(s)$$

$$= -\frac{d}{ds} \left[\frac{1}{s^2 + s + 1} \right]$$

$$= -\left[\frac{-1}{(s^2 + s + 1)^2} \right] \times (2s + 1)$$

$$= \left[\frac{2s + 1}{(s^2 + s + 1)^2} \right]$$

Question 154: DTFS, DTFT & DFT (GATE EC 2011)

MCQ

1 Mark

The first six points of the 8-point DFT of a real valued sequence are 5, 1-j3, 0, 3-j4, 0 and 3+j4. The last two points of the DFT are respectively

- (A) 0, 1-j3
- (B) **(Correct)** 0, 1+j3
- (C) 1+j3, 5
- (D) 1-j3, 5

Correct Answer: (B)

Detailed Solution – Question 154

$$x[n] \rightarrow \text{real}$$

$$X[k] \rightarrow \text{Conjugate symmetric}$$

$$\Rightarrow X[k] = X^*[N - k]$$

$$N = 8$$

$$X[k] = X^*[8 - k]$$

$$\therefore X[6] = X^*[8 - 6] = X^*[2] = 0$$


$$X[7] = X^*[8 - 7] = X^*[1] = 1 + j3$$

Question 155: Z-Transform (GATE EC 2011)

MCQ

1 Mark

Two systems $H_1(z)$ and $H_2(z)$ are connected in cascade as shown below. The overall output $y(n)$ is the same as the input $x(n)$ with a one unit delay. The transfer function of the second system $H_2(z)$ is



- (A) $\frac{1-0.6z^{-1}}{z^{-1}(1-0.4z^{-1})}$
- (B) **(Correct)** $\frac{z^{-1}(1-0.6z^{-1})}{(1-0.4z^{-1})}$
- (C) $\frac{z^{-1}(1-0.4z^{-1})}{(1-0.6z^{-1})}$
- (D) $\frac{1-0.4z^{-1}}{z^{-1}(1-0.6z^{-1})}$

Correct Answer: (B)

Detailed Solution – Question 155

$y[n] = x[n - 1]$ Taking z-transform of both sides

$$r(z) = z^{-1}X(z)$$

$$\frac{r(z)}{X(z)} = z^{-1}$$

For cascaded system

$$H(z) = H_1(z) \cdot H_2(z)$$

$$z^{-1} = \frac{(1 - 0.4z^{-1})}{(1 - 0.6z^{-1})^{-1}(z)}$$

$$\therefore H_2(z) = \frac{z^{-1}(1 - 0.6z^{-1})}{(1 - 0.4z^{-1})}$$

Question 156: Laplace Transform (GATE EC 2011)

MCQ

1 Mark

If $F(s) = L[f(t)] = \frac{2(s+1)}{s^2+4s+7}$ then the initial and final values of $f(t)$ are respectively

- (A) 0 , 2
- (B) **(Correct)** 2 , 0
- (C) 0 , 2/7

(D) $2/7, 0$

Correct Answer: (B)

Detailed Solution – Question 156

$$F(s) = L[f(t)] = \frac{2(s+1)}{s^2 + 4s + 7}$$

Initial value,

$$\begin{aligned}\lim_{t \rightarrow 0} f(t) &= \lim_{s \rightarrow \infty} sF(s) = \lim_{s \rightarrow \infty} s \cdot \frac{2(s+1)}{s^2 + 4s + 7} \\ &= \lim_{s \rightarrow \infty} \frac{2s^2 \left(1 + \frac{1}{s}\right)}{s^2 \left(1 + \frac{4}{s} + \frac{7}{s^2}\right)} \\ &= \frac{2(1+0)}{(1+0+0)} = 2\end{aligned}$$

Final value,

$$\begin{aligned}\lim_{t \rightarrow \infty} f(t) &= \lim_{s \rightarrow 0} sF(s) = \lim_{s \rightarrow 0} s \cdot \frac{2(s+1)}{s^2 + 4s + 7} \\ &= 0\end{aligned}$$

Question 157: Laplace Transform (GATE EC 2011)

MCQ

1 Mark

An input $x(t) = \exp(-2t)u(t) + \delta(t-6)$ is applied to an LTI system with impulse response $h(t) = u(t)$. The output is

$1 - \exp(-2t) \quad u(t) + u(t+6)$

$1 - \exp(-2t) \quad u(t) + u(t-6)$

(A) $0.5[1 - \exp(-2t)]u(t) + u(t+6)$

(B) **(Correct)** $0.5[1 - \exp(-2t)]u(t) + u(t-6)$

Correct Answer: (D)

Detailed Solution – Question 157

$$x(t) = e^{-2t}u(t) + \delta(t-6)$$

$$x(s) = \frac{1}{s+2} + e^{-6s}$$

$$H(s) = \frac{1}{s}$$

$$\therefore Y(s) = X(s) \cdot H(s)$$

$$\Rightarrow Y(s) = \frac{1}{s(s+2)} + \frac{1}{s}e^{-6s}$$

$$\Rightarrow Y(s) = \frac{1}{2} \left(\frac{1}{s} - \frac{1}{s+2} \right) + \frac{1}{s}e^{-6s}$$

Taking inverse Laplace transform, we have

$$y(t) = 0.5(1 - e^{-2t})u(t) + u(t-6)$$

Question 158: Fourier Series (GATE EC 2011)

MCQ

1 Mark

The trigonometric Fourier series of an even function does not have the

- (A) dc term
- (B) cosine terms
- (C) **(Correct)** sine terms
- (D) odd harmonic terms

Correct Answer: (C)

Detailed Solution – Question 158

Trigonometric Fourier series of an even function has de and cosine terms only.

Question 159: Laplace Transform (GATE EC 2011)

MCQ

1 Mark

If the unit step response of a network is $(1 - e^{-at})$, then its unit impulse response is

- (A) **(Correct)** αe^{-at}
- (B) $\alpha^{-1} e^{-at}$
- (C) $(1 - \alpha^{-1}) e^{at}$
- (D) $(1 - \alpha) e^{-at}$

Correct Answer: (A)

Detailed Solution – Question 159

Unit step response $s(t) = (1 - e^{-at})$ So, unit impulse response is

$$\begin{aligned} h(t) &= \frac{ds(t)}{dt} = \frac{d}{dt} (1 - e^{-at}) \\ &= \alpha e^{-at} \end{aligned}$$

Question 160: LTI Systems (GATE EC 2011)

MCQ

1 Mark

A system is defined by its impulse response $h(n) = 2^n u(n - 2)$. The system is

- (A) stable and causal

- (B) **(Correct)** causal but not stable
- (C) stable but not causal
- (D) unstable and non-causal

Correct Answer: (B)

Detailed Solution – Question 160

$h(n) = 2^n u(n-2)$ For causal system $h(n) = 0$ for $n < 0$ Hence given system is causal. For stability: $\sum_{n=2}^{\infty} 2^n = \infty$, so given system is not stable.

Question 161: Z-Transform (GATE EC 2010)

MCQ

1 Mark

The transfer function of a discrete time LTI system is given by $H(z) = \frac{2 - \frac{3}{4}z^{-1}}{1 - \frac{3}{4}z^{-1} + \frac{1}{8}z^{-2}}$ Consider the following statements:

- S1: The system is stable and causal for ROC: $|z| > 1/2$
 S2: The system is stable but not causal for ROC: $|z| < 1/4$
 S3: The system is neither stable nor causal for ROC: $1/4 < |z| < 1/2$

Which one of the following statements is valid ?

- (A) Both S1 and S2 are true
- (B) Both S2 and S3 are true
- (C) **(Correct)** Both S1 and S3 are true
- (D) S1, S2 and S3 are all

Correct Answer: (C)

Detailed Solution – Question 161

A discrete-time LTI system is causal if and only if the ROC of its system function is the exterior of a circle, including infinity.

A discrete-time LTI system is stable if and only if the ROC of its system function includes the unit circle, $|z| = 1$

$$H(z) = \frac{(1 - \frac{1}{4}z^{-1}) + (1 - \frac{1}{2}z^{-1})}{(1 - \frac{1}{4}z^{-1})(1 - \frac{1}{2}z^{-1})}$$

$$\text{or } H(z) = \frac{1}{1 - \frac{1}{4}z^{-1}} + \frac{1}{1 - \frac{1}{2}z^{-1}}$$

For ROC : $|z| > \frac{1}{2}$, the system is stable and causal.

For ROC : $|z| < \frac{1}{4}$, ROC does not include unit circle. So, system is not stable.

For ROC : $\frac{1}{4} < |z| < \frac{1}{2}$, ROC does not include unit circle. So, system is not stable. Also ROC is not the exterior of $|z| = \frac{1}{2}$. So, it is not causal.

Question 162: Laplace Transform (GATE EC 2010)

MCQ

1 Mark

A continuous time LTI system is described by $\frac{d^2y(t)}{dt^2} + 4\frac{dy(t)}{dt} + 3y(t) = 2\frac{dx(t)}{dt} + 4x(t)$. Assuming zero initial conditions, the response $y(t)$ of the above system for the input $x(t) = e^{-2t}u(t)$ is given by

- (A) $(e^t - e^{3t})u(t)$
- (B) **(Correct)** $(e^{-t} - e^{-3t})u(t)$
- (C) $(e^{-t} + e^{-3t})u(t)$
- (D) $(e^t + e^{3t})u(t)$

Correct Answer: (B)

Detailed Solution – Question 162

$$\frac{d^2y(t)}{dt^2} + \frac{4dy(t)}{dt} + 3y(t) = \frac{2dx(t)}{dt} + 4x(t)$$

Taking Laplace transform on both sides (assuming zero initial conditions).

$$s^2Y(s) + 4sY(s) + 3Y(s) = 2sX(s) + 4X(s)$$

$$\text{or } \frac{Y(s)}{X(s)} = \frac{2s + 4}{s^2 + 4s + 3} \\ = \frac{2(s + 2)}{(s + 1)(s + 3)}$$

Given that

$$x(t) = e^{-2t}u(t)$$

$$x(s) = \frac{1}{s + 2}$$

$$Y(s) = \frac{2(s + 2)}{(s + 1)(s + 3)(s + 2)} \\ = \frac{2}{(s + 1)(s + 3)} \\ = \frac{1}{s + 1} - \frac{1}{s + 3}$$

Taking inverse Laplace transform on both sides. $y(t) = (e^{-t} - e^{-3t})u(t)$

Question 163: Laplace Transform (GATE EC 2010)

MCQ

1 Mark

Given $f(t) = l^{-1}\left[\frac{3s+1}{s^3+4s^2+(K-3)s}\right]$. If $\lim_{t \rightarrow \infty} f(t) = 1$, then the value of K is

- (A) 1
- (B) 2
- (C) 3
- (D) **(Correct)** 4

Correct Answer: (D)

Detailed Solution – Question 163

$\lim_{t \rightarrow \infty} f(t) = \lim_{s \rightarrow 0} sF(s)$ Given that,

$$\begin{aligned} F(s) &= \left[\frac{3s+1}{s^3+4s^2+(K-3)s} \right] \\ \lim_{t \rightarrow \infty} f(t) &= 1 \\ \Rightarrow \lim_{s \rightarrow 0} s \left[\frac{3s+1}{s^3+4s^2+(K-3)s} \right] &= 1 \\ \Rightarrow \lim_{s \rightarrow 0} \left[\frac{3s+1}{s^2+4s+(K-3)} \right] &= 1 \\ \Rightarrow \frac{1}{K-3} &= 1 \\ \Rightarrow K-3 &= 1 \\ \Rightarrow K &= 4 \end{aligned}$$

Question 164: DTFS, DTFT & DFT (GATE EC 2010)

MCQ

1 Mark

For a N -point FET algorithm $N = 2^m$, which one of the following statements is TRUE ?

- (A) It is not possible to construct a signal flow graph with both input and output in normal order
- (B) The number of butterflies in the m^{th} stage in N/m
- (C) In-place computation requires storage of only 2N data
- (D) **(Correct)** Computation of a butterfly requires only one complex multiplication.

Correct Answer: (D)

Detailed Solution – Question 164

For an N-point FFT algorithm with $N = 2^m$,
computation of a butterfly requires only one complex multiplication and two complex additions

Question 165: Z-Transform (GATE EC 2010)

MCQ

1 Mark

Two discrete time system with impulse response $h_1[n] = \delta[n-1]$ and $h_2[n] = \delta[n-2]$ are connected in cascade. The overall impulse response of the cascaded system is

- (A) $\delta[n-1] + \delta[n-2]$
- (B) $\delta[n-4]$
- (C) **(Correct)** $\delta[n-3]$
- (D) $\delta[n-1]\delta[n-2]$

Correct Answer: (C)

Detailed Solution – Question 165

$$h_1[n] = \delta[n - 1] \xleftrightarrow{Z} H_1(z) = z^{-1}$$

$$h_2[n] = \delta[n - 2] \xleftrightarrow{Z} H_2(z) = z^{-2}$$

Overall impulse response in z-domain,

$$\begin{aligned} H(z) &= H_1(z)H_2(z) \\ &= z^{-1}z^{-2} \\ &= z^{-3} \end{aligned}$$

Overall impulse response in discrete-time domain. $h[n] = \delta[n - 3]$

Question 166: Z-Transform (GATE EC 2010)

MCQ

1 Mark

Consider the z-transform $X(z) = 5z^2 + 4z^{-1} + 3; 0 < |z| < \infty$. The inverse z-transform $x[n]$ is

- (A) **(Correct)** $5\delta[n + 2] + 3\delta[n] + 4\delta[n - 1]$
- (B) $5\delta[n - 2] + 3\delta[n] + 4\delta[n + 1]$
- (C) $5u[n + 2] + 3u[n] + 4u[n - 1]$
- (D) $5u[n - 2] + 3u[n] + 4u[n + 1]$

Correct Answer: (A)

Detailed Solution – Question 166


$$\begin{aligned} \delta[n + n_0] &\xleftrightarrow{Z} z^{n_0} \\ X(z) &= 5z^2 + 4z^{-1} + 3; 0 < |z| < \infty \\ x(n) &= 5\delta(n + 2) + 4\delta(n - 1) + 3\delta(n) \end{aligned}$$

Question 167: Fourier Series (GATE EC 2010)

MCQ

1 Mark

The trigonometric Fourier series for the waveform $f(t)$ shown below contains



- (A) only cosine terms and zero values for the dc components
- (B) only cosine terms and a positive value for the dc components
- (C) **(Correct)** only cosine terms and a negative value for the dc components
- (D) only sine terms and a negative value for the dc components

Correct Answer: (C)

Detailed Solution – Question 167

since $f(t)$ is an even function, its trigonometric Fourier series contains only cosine terms. D.C. component,

$$\begin{aligned}
 A_0 &= \frac{1}{T} \int_{-T/2}^{T/2} f(t) dt = \frac{2}{T} \int_0^{T/2} f(t) dt \\
 &= \frac{2}{T} \left[\int_0^{T/4} A dt + \int_{T/4}^{T/2} (-2A) dt \right] \\
 &= \frac{2}{T} \left[\frac{AT}{4} - 2A \left(\frac{T}{2} - \frac{T}{4} \right) \right] \\
 &= \frac{2}{T} \left[-\frac{AT}{4} \right] = -\frac{A}{2}
 \end{aligned}$$

Therefore, the trigonometric Fourier series for the waveform $f(t)$ contains only cosine terms and a negative value for the dc component.

Question 168: Sampling (GATE EC 2009)

MCQ



1 Mark

An LTI system having transfer function $\frac{s^2+1}{s^2+2s+1}$ and input $x(t) = \sin(t+1)$ is in steady state. The output is sampled at a rate ω_s rad/s to obtain the final output $y(k)$. Which of the following is true ?

- (A) **(Correct)** $y(\cdot)$ is zero for all sampling frequencies ω_s
- (B) $y(\cdot)$ is nonzero for all sampling frequencies ω_s
- (C) $y(\cdot)$ is nonzero for $\omega_s > 2$, but zero for $\omega_s < 2$
- (D) $y(\cdot)$ is zero for $\omega_s > 2$, but nonzero for $\omega_s < 2$

Correct Answer: (A)

Detailed Solution – Question 168



$$x(t) = \sin(t+1)$$

$$\omega = 1 \text{ rad/sec}$$

$$X(s) = \frac{\omega}{(\omega)^2 + s^2} \cdot e^s = \frac{1}{1^2 + s^2} \theta^s = \frac{e^s}{s^2 + 1}$$

$$H(s) = \frac{Y(s)}{X(s)}$$

$$Y(s) = H(s)X(s)$$

$$Y(s) = \frac{s^2 + 1}{s^2 + 2s + 1} \times \frac{e^s}{s^2 + 1} = \frac{e^s}{s^2 + 2s + 1}$$

$$Y(s) = \frac{e^s}{(s+1)^2}$$

$$y(t) = (t+1)e^{(t+1)}$$

$$y(\infty) = \lim_{s \rightarrow 0} sY(s) = \lim_{s \rightarrow 0} \frac{se^s}{(s+1)^2} = 0$$

So, at steady state y remains zero for all sampling frequencies ω_s

Question 169: DTFS, DTFT & DFT (GATE EC 2009)

MCQ

1 Mark

The 4-point Discrete Fourier Transform (DFT) of a discrete time sequence 1,0,2,3 is

0, -2+2j, 2, -2-2j

2, 2+2j, 6, 2-2j

6, 1-3j, 2, 1+3j

(A) (Correct) [6, -1+3j, 0, -1-3j]

Correct Answer: (D)

Detailed Solution – Question 169

4-point DFT of sequence 1, 0, 2, 3 is given as

$$\begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 1 \\ 0 \\ 2 \\ 3 \end{bmatrix} = \begin{bmatrix} 1+2+3 \\ 1-2+3j \\ 1+2-3 \\ 1-2-3j \end{bmatrix} \\ = \begin{bmatrix} 6 \\ -1+3j \\ 0 \\ -1-3j \end{bmatrix}$$

Question 170: Fourier Transforms (GATE EC 2009)

MCQ

1 Mark

Consider a system whose input x and output y are related by the equation $y(t) = \int_{-\infty}^{\infty} x(t-\tau)g(2\tau)d\tau$ where $h(t)$ is shown in the graph.



Which of the following four properties are possessed by the system ?

BIBO : Bounded input gives a bounded output.

Causal : The system is causal,

LP : The system is low pass.

LTI : The system is linear and time-invariant.




(A) Causal, LP

- (B) **(Correct)** BIBO, LTI
- (C) BIBO, Causal, LTI
- (D) LP, LTI

Correct Answer: (B)

Detailed Solution – Question 170

$$y(t) = \int_{-\infty}^{\infty} x(t - \tau)h(2\tau)d\tau$$



It is not low pass filter.
But the system is LTI and BIBO.

Question 171: DTFS, DTFT & DFT (GATE EC 2009)

MCQ

1 Mark

A system with transfer function $H(z)$ has impulse response $h(\cdot)$ defined as $h(2)=1$, $h(3)=-1$ and $h(k)=0$ otherwise. Consider the following statements.

S1 : $H(z)$ is a low-pass filter.

S2 : $H(z)$ is an FIR filter.

Which of the following is correct?

- (A) **(Correct)** Only S2 is true
- (B) Both S1 and S2 are false
- (C) Both S1 and S2 are true, and S2 is a reason for S1
- (D) Both S1 and S2 are true, but S2 is not a reason for S1



Correct Answer: (A)

Detailed Solution – Question 171

$$h(2) = 1$$

$$h(3) = -1$$

$$h(k) = 0 \text{ otherwise}$$



It is finite impulse response. It is not low pass filter

Question 172: Laplace Transform (GATE EC 2009)

MCQ

1 Mark

Given that $F(s)$ is the one-side Laplace transform of $f(t)$, the Laplace transform of $\int_0^t f(\tau) d\tau$ is

- (A) $sF(s) - f(0)$
- (B) $\frac{1}{s}F(s)$
- (C) $\int_0^s F(\tau) d\tau$
- (D) **(Correct)** $\frac{1}{s}[F(s) - f(0)]$

Correct Answer: (D)

Detailed Solution – Question 172

$$\mathcal{L} \left[\int_0^t f(\tau) d\tau \right] = \frac{1}{s} [F(s) - f(0)]$$

Question 173: Z-Transform (GATE EC 2009)

MCQ

1 Mark

The ROC of z -transform of the discrete time sequence $x(n) = (\frac{1}{3})^n u(n) - (\frac{1}{2})^n u(-n - 1)$ is

- (A) **(Correct)** $\frac{1}{3} < |z| < \frac{1}{2}$
- (B) $|z| > \frac{1}{2}$
- (C) $|z| < \frac{1}{3}$
- (D) $2 < |z| < 3$

Correct Answer: (A)

Detailed Solution – Question 173

$x(n) = (\frac{1}{3})^n u(n) - (\frac{1}{2})^n u(-n - 1)$ $(\frac{1}{3})^n u(n)$ is right sided signal, so ROC will be $|z| > 1/3$
... (i) $-(\frac{1}{2})^n u(-n - 1)$ is left sided signal so ROC will be $|z| < 1/2$... (ii) from (i) and (ii) we see that ROC of the function will be $1/3 < |z| < 1/2$

Question 174: Fourier Transforms (GATE EC 2009)

MCQ

1 Mark

A function is given by $f(t) = \sin^2 t + \cos 2t$. Which of the following is true ?

- (A) f has frequency components at 0 and $\frac{1}{2\pi} Hz$
- (B) **(Correct)** f has frequency components at 0 and $\frac{1}{\pi} Hz$
- (C) f has frequency components at $\frac{1}{2\pi}$ and $\frac{1}{\pi} Hz$
- (D) f has frequency components at 0, $\frac{1}{2\pi}$ and $\frac{1}{\pi} Hz$

Correct Answer: (B)

Detailed Solution – Question 174

$f(t) = \frac{1}{2}(1 - \cos 2t) + \cos 2t$ frequency components are

$$f_1 = 0$$
$$f_2 = \frac{\omega_2}{2\pi} = \frac{2}{2\pi} = \frac{1}{\pi} \text{Hz}$$

Question 175: Fourier Series (GATE EC 2009)

MCQ

1 Mark

The Fourier series of a real periodic function has only (P) cosine terms if it is even

- (Q) sine terms if it is even
- (R) cosine terms if it is odd
- (S) sine terms if it is odd

Which of the above statements are correct ?

- (A) **(Correct)** P and S
- (B) P and R
- (C) Q and S
- (D) Q and R

Correct Answer: (A)

Detailed Solution – Question 175

The Fourier series of a real periodic function has only cosine terms if it is even and only sine terms if it is odd.

Question 176: Fourier Transforms (GATE EC 2008)

MCQ

1 Mark

The impulse response $h(t)$ of a linear time invariant continuous time system is given by $h(t) = \exp(-2t)u(t)$, where $u(t)$ denotes the unit step function

The output of this system, to the sinusoidal input $x(t) = 2\cos(2t)$ for all time t , is

- (A) 0
- (B) $2^{-0.25}\cos(2t - 0.125\pi)$
- (C) $2^{-0.5}\cos(2t - 0.125\pi)$
- (D) **(Correct)** $2^{-0.5}\cos(2t - 0.25\pi)$

Correct Answer: (D)

Detailed Solution – Question 176

Input $x(t) = 2\cos(2t)$ Frequency response

$$X(\omega) = 2\pi[\delta(\omega - 2) + \delta(\omega + 2)]$$

$$H(\omega) = \frac{1}{2 + j\omega}$$

$$\text{output } Y(\omega) = H(\omega)X(\omega)$$

$$\begin{aligned} &= \frac{1}{2 + j\omega} \cdot 2\pi[\delta(\omega - 2) + \delta(\omega + 2)] \\ &= \frac{2\pi}{2 + j2}\delta(\omega - 2) + \frac{2\pi}{2 - j2}\delta(\omega + 2) \\ &= \frac{2\pi}{8}[(2 - j2)\delta(\omega - 2) + (2 + j2)\delta(\omega + 2)] \\ &= \frac{\pi}{4}[2\{\delta(\omega - 2) + \delta(\omega + 2)\} + j2\{\delta(\omega + 2) - \delta(\omega - 2)\}] \\ &= \frac{\pi}{2}[\delta(\omega - 2) + \delta(\omega + 2)] - j\frac{\pi}{2}[\delta(\omega - 2) - \delta(\omega + 2)] \\ \therefore y(t) &= \frac{\cos 2t}{2} + \frac{\sin 2t}{2} \\ &= \frac{\sqrt{2}}{2} \left[\frac{1}{\sqrt{2}} \cos 2t + \frac{1}{\sqrt{2}} \sin 2t \right] \\ &= \frac{1}{\sqrt{2}} \cos(2t - 0.25\pi) \\ &= 2^{-0.5} \cos(2t - 0.25\pi) \end{aligned}$$

Question 177: Fourier Transforms (GATE EC 2008)

MCQ

1 Mark

The impulse response $h(t)$ of a linear time invariant continuous time system is given by $h(t) = \exp(-2t)u(t)$, where $u(t)$ denotes the unit step function

The frequency response $H(\omega)$ of this system in terms of angular frequency ω , is given by $H(\omega) =$

- (A) $\frac{1}{1+j2\omega}$
- (B) $\frac{\sin\omega}{\omega}$
- (C) **(Correct)** $\frac{1}{2+j\omega}$
- (D) $\frac{j\omega}{2+j\omega}$

Correct Answer: (C)

Detailed Solution – Question 177


$$\begin{aligned}h(t) &= \exp(-2t)u(t) \\H(\omega) &= \int_{-\infty}^{\infty} h(t)e^{-j\omega t} dt \\&= \int_0^{\infty} e^{-2t} e^{-j\omega t} dt = \int_0^{\infty} e^{-(2+j\omega)t} dt \\&= -\frac{1}{2+j\omega} \cdot e^{-(2+j\omega)t} \Big|_0^{\infty} \\&= \frac{1}{2+j\omega}\end{aligned}$$


Question 178: Z-Transform (GATE EC 2008)

MCQ

1 Mark

In the following network, the switch is closed at $t=0^-$ and the sampling starts from $t=0$. The sampling frequency is 10Hz.





The expression and the region of convergence of the z-transform of the sampled signal are

- (A) $\frac{5z}{z-e^{-5}}, |z| < e^{-5}$
- (B) $\frac{5z}{z-e^{-0.05}}, |z| < e^{-0.05}$
- (C) **(Correct)** $\frac{5z}{z-e^{-0.05}}, |z| > e^{-0.05}$
- (D) $\frac{5z}{z-e^{-5}}, |z| > e^{-5}$

Correct Answer: (C)

Detailed Solution – Question 178


$$\begin{aligned}
 x(z) &= \sum_{n=0}^{\infty} 5e^{-0.05n} z^{-n} \\
 &= 5 \sum_{n=0}^{\infty} (e^{-0.05} z^{-1})^n \\
 \text{For } |e^{-0.05} z^{-1}| < 1 \text{ or } |z| > e^{-0.05} \\
 x(z) &= \frac{5z}{z - e^{-0.05}}
 \end{aligned}$$


Question 179: Z-Transform (GATE EC 2008)

MCQ

1 Mark

In the following network, the switch is closed at $t=0^-$ and the sampling starts from $t=0$. The sampling frequency is 10Hz.





The samples $x(n)$, $n = (0, 1, 2, \dots)$ are given by

- (A) $5(1 - e^{-0.05n})$
- (B) **(Correct)** $5e^{-0.05n}$
- (C) $5(1 - e^{-5n})$
- (D) $5e^{-5n}$

Correct Answer: (B)

Detailed Solution – Question 179

$$\begin{aligned}
 V_R(s) &= \left(\frac{200 \times 10^3}{200 \times 10^3 + \frac{1}{10 \times 10^{-6}s}} \right) \frac{5}{s} \\
 &= \frac{5 \times 2 \times 10^5 \times 10 \times 10^{-6}}{2 \times 10^5 \times 10^{-5}s + 1} \\
 &= \frac{10}{2s + 1} = \frac{5}{s + 0.5} \\
 v_A(t) &= 5e^{-0.5t}
 \end{aligned}$$

Therefore, samples $x(n) = 5e^{-0.5n/10} = 5e^{-0.05n}$

Question 180: DTFS, DTFT & DFT (GATE EC 2008)

MCQ

1 Mark

$x(n)$ is a real-valued periodic sequence with a period N . $x(n)$ and $X(k)$ form N -point Discrete Fourier Transform (DFT) pairs. The DFT $Y(k)$ of the sequence $y(n) = \frac{1}{N} \sum_{r=0}^{N-1} x(r)x(n+r)$ is

- (A) **(Correct)** $|X(k)|^2$
- (B) $\frac{1}{N} \sum_{r=0}^{N-1} X(r)X^*(k+r)$
- (C) $\frac{1}{N} \sum_{r=0}^{N-1} X(r)X(k+r)$
- (D) 0

Correct Answer: (A)

Question 181: Basics of Signals & Systems (GATE EC 2008)

MCQ

1 Mark

Let $x(t)$ be the input and $y(t)$ be the output of a continuous time system. Match the system properties P1, P2 and P3 with system relations R1, R2, R3, R4

Properties	Relations
P1 : Linear but NOT time - invariant	R1 : $y(t) = t^2 x(t)$
P2 : Time - invariant but NOT linear	R2 : $y(t) = t x(t) $
P3 : Linear and time - invariant	R3 : $y(t) = x(t) $
	R4 : $y(t) = x(t - 5)$

Properties	Relations
P1 : Linear but NOT time - invariant	R1 : $y(t) = t^2 x(t)$
P2 : Time - invariant but NOT linear	R2 : $y(t) = t x(t) $
P3 : Linear and time - invariant	R3 : $y(t) = x(t) $
	R4 : $y(t) = x(t - 5)$

- (A) (P1, R1), (P2, R3), (P3, R4)
(B) **(Correct)** (P1, R2), (P2, R3), (P3, R4)
(C) (P1, R3), (P2, R1), (P3, R2)
(D) (P1, R1), (P2, R2), (P3, R3)

Correct Answer: (B)

Question 182: LTI Systems (GATE EC 2008)

MCQ

1 Mark

A discrete time linear shift-invariant system has an impulse response $h[n]$ with $h[0]=1$, $h[1]=-1$, $h[2]=2$, and zero otherwise. The system is given an input sequence $x[n]$ with $x[0]=x[2]=1$, and zero otherwise. The number of nonzero samples in the output sequence $y[n]$, and the value of $y[2]$ are respectively

- (A) 5, 2
(B) 6, 2
(C) 6, 1
(D) **(Correct)** 5, 3


Correct Answer: (D)

Detailed Solution – Question 182

$L_1 = 3, L_2 = 3 \Rightarrow$ Number of samples in output $= L_1 + L_2 - 1 = 5$

$$y[n] = \sum_{k=-\infty}^{\infty} x[k]h[n-k]$$

$$y[2] = \sum_{k=-\infty}^{\infty} x[k]h[2-k]$$



$\Rightarrow y(2) = 3$

Question 183: Fourier Transforms (GATE EC 2008)

MCQ

1 Mark

The signal $x(t)$ is described by

$$x(t) = \begin{cases} 1 & \text{for } -1 \leq t \leq +1 \\ 0 & \text{otherwise} \end{cases}$$

Two of the angular frequencies at which its Fourier transform becomes zero are

- (A) **(Correct)** $\pi, 2\pi$
- (B) $0.5\pi, 1.5\pi$
- (C) $0, \pi$
- (D) $2\pi, 2.5\pi$

Correct Answer: (A)

Detailed Solution – Question 183

$$\begin{aligned} X(\omega) &= \int_{-\infty}^{\infty} x(t)e^{-j\omega t} dt \\ &= \int_{-1}^1 e^{-j\omega t} dt = \left. \frac{e^{-j\omega t}}{-j\omega} \right|_{-1}^1 \\ &= \frac{e^{-j\omega}}{-j\omega} - \frac{e^{j\omega}}{-j\omega} \\ &= \frac{1}{j\omega} (e^{j\omega} - e^{-j\omega}) \\ X(\omega) &= 0 \\ \Rightarrow e^{j\omega} - e^{-j\omega} &= 0 \\ \Rightarrow e^{j\omega} - \frac{1}{e^{j\omega}} &= 0 \\ \Rightarrow e^{2j\omega} - 1 &= 0 \\ \Rightarrow e^{2j\omega} &= 1 \\ \Rightarrow e^{j\omega} &= \pm 1 \\ \Rightarrow \omega &= \pi, 2\pi \end{aligned}$$

Question 184: LTI Systems (GATE EC 2008)

MCQ

1 Mark



The impulse response $h(t)$ of a linear time invariant continuous time system is described by $h(t) = \exp(\alpha t)u(t) + \exp(\beta t)u(-t)$, where $u(t)$ denotes the unit step function, and α and β are real constants. This system is stable if

- (A) α is positive and β is positive
- (B) α is negative and β is negative
- (C) α is positive and β is negative
- (D) **(Correct)** α is negative and β is positive

Correct Answer: (D)

Detailed Solution – Question 184

$h(t) = e^{\alpha t}u(t) + e^{\beta t}u(-t)$ For the system to be stable, $\int_{-\infty}^{\infty} h(t)dt < \infty$ For the above condition, $h(t)$ should be as shown below.



Question 185: Basics of Signals & Systems (GATE EC 2008)

MCQ

1 Mark

The input and output of a continuous time system are respectively denoted by $x(t)$ and $y(t)$. Which of the following descriptions corresponds to a causal system ?

- (A) $y(t) = x(t - 2) + x(t + 4)$
- (B) $y(t) = (t - 4)x(t + 1)$
- (C) **(Correct)** $y(t) = (t + 4)x(t - 1)$
- (D) $y(t) = (t + 5)x(t + 5)$

Correct Answer: (C)

Detailed Solution – Question 185

A system is casual if the output at any time depends only on values of the input at the present time and in the past.

Question 186: Z-Transform (GATE EC 2007)

MCQ

1 Mark

The z-transform $X[z]$ of a sequence $x[n]$ is given by $X(z) = \frac{0.5}{1-2z^{-1}}$. It is given that the region of convergence of $X[z]$ includes the unit circle. The value of $x[0]$ is

- (A) -0.5
 (B) **(Correct)** 0
 (C) 0.25
 (D) 5

Correct Answer: (B)

Detailed Solution – Question 186

$$X(z) = \frac{0.5}{1-2z^{-1}} \because \text{ROC includes unit circle} \Rightarrow \text{Left handed system} \Rightarrow x(n) = -(0.5)(2)^n u(-n-1) \\ \Rightarrow x(0) = 0$$

Question 187: DTFS, DTFT & DFT (GATE EC 2007)

MCQ

1 Mark

A 5-point sequence $x[n]$ is given as $x[-3]=1$, $x[-2]=1$, $x[-1]=0$, $x[0]=5$ and $x[1]=1$. Let $X(e^{j\omega})$ denoted the discrete-time Fourier transform of $x[n]$. The value of $\int_{-\pi}^{\pi} X(e^{j\omega}) d\omega$ is

- (A) 5
 (B) **(Correct)** 10π
 (C) 16π
 (D) $5 + j10\pi$

Correct Answer: (B)

Detailed Solution – Question 187

$$X(e^{j\omega}) = e^{3j\omega} + e^{2j\omega} + 0 + 5 + e^{-j\omega} \\ \because \int_{-\pi}^{\pi} e^{zi\omega} d\omega = 0 \text{ if } a \neq 0 \\ \int_{-\pi}^{\pi} X(e^{j\omega}) d\omega = \left[\frac{e^{3j\omega}}{3j} + \frac{e^{2j\omega}}{2j} + 5\omega + \frac{e^{-j\omega}}{-j} \right]_{-\pi}^{\pi} \\ = 5\pi + 5\pi = 10\pi$$

Question 188: Basics of Signals & Systems (GATE EC 2007)

MCQ

1 Mark

A Hilbert transformer is a

- (A) **(Correct)** non-linear system
 (B) non-causal system
 (C) time-varying system

(D) low-pass system

Correct Answer: (A)

Detailed Solution – Question 188

The Hilbert transformer is characterised by the impulse response

$$h(t) = \frac{1}{\pi t} \quad t \in (-\infty, \infty)$$
$$h(t) \neq 0 \text{ for } t < 0$$

Thus, the Hilbert transformer is a non-causal system.

Question 189: Fourier Transforms (GATE EC 2007)

MCQ

1 Mark

The 3-dB bandwidth of the low-pass signal $e^{-t}u(t)$, where $u(t)$ is the unit step function, is given by

(A) **(Correct)** $\frac{1}{2\pi} \text{ Hz}$

(B) $\frac{1}{2\pi} \sqrt{\sqrt{2} - 1} \text{ Hz}$

(C) ∞

(D) 1 Hz

Correct Answer: (A)

Detailed Solution – Question 189

Laplace transform of $e^{-t}u(t) = \frac{1}{s+1} \therefore$ magnitude at 3 dB frequency $= \frac{1}{\sqrt{2}}$

$$\Rightarrow \frac{1}{\sqrt{2}} = \frac{1}{\sqrt{1 + \omega^2}}$$
$$\omega = 1 \text{ rad}$$
$$f = \frac{1}{2\pi} \text{ Hz}$$

Question 190: Laplace Transform (GATE EC 2007)

MCQ

1 Mark

If the Laplace transform of a signal $y(t)$ is $Y(s) = \frac{1}{s(s-1)}$, then its final value is

(A) -1

(B) 0

(C) 1

(D) **(Correct)** Unbounded

Correct Answer: (D)

Detailed Solution – Question 190

Final value theorem is applicable only when all the poles of system lies in left half of s-plane.
 $\therefore s = 1$ is right S-plane pole. Therefore, final value theorem cannot be applied.

$$Y(s) = \frac{1}{s-1} - \frac{1}{s}$$
$$y(t) = (e^t - 1) u(t)$$

$\therefore$ Unbounded.

Question 191: Basics of Signals & Systems (GATE EC 2006)

MCQ

1 Mark

A system with input $x[n]$ and output $y[n]$ is given as $y[n] = (\sin \frac{5}{6}\pi n) x[n]$. The system is

- (A) linear, stable and invertible
- (B) non-linear, stable and non-invertible
- (C) **(Correct)** linear, stable and non-invertible
- (D) linear, unstable and invertible

Correct Answer: (C)

Detailed Solution – Question 191

$$y(n) = \left(\sin \frac{5}{6}\pi n \right) x(n)$$

Let $x(n) = 8(n)$
 $\therefore y(n) = \sin 0 = 0$ (bounded)
BIBO stable

Question 192: Sampling (GATE EC 2006)



MCQ

1 Mark





A signal $m(t)$ with bandwidth 500 Hz is first multiplied by a signal $g(t)$ where $g(t) = \int_{R=-\infty}^{\infty} (-1)^k \delta(t - 0.5 \times 10^{-4}k)$. The resulting signal is then passed through an ideal lowpass filter with bandwidth 1 kHz. The output of the lowpass filter would be

- (A) $\delta(t)$
- (B) **(Correct)** $m(t)$
- (C) 0
- (D) $m(t)\delta(t)$

Correct Answer: (B)



$$m(t)g(t) \leftrightarrow M(f) * G(f)$$



Question 193: Laplace Transform (GATE EC 2006)

MCQ



1 Mark

Consider the function $f(t)$ having Laplace transform $F(s) = \frac{\omega_0}{s^2 + \omega_0^2}$ $\text{Re}[s] > 0$ The final value of $f(t)$ would be

- (A) 0
- (B) 1
- (C) **(Correct)** $-1 \leq f(\infty) \leq 1$
- (D) ∞

Correct Answer: (C)

Detailed Solution – Question 193



$$\begin{aligned} L^{-1}[F(s)] &= \sin \omega_0 t \\ f(t) &= \sin \omega_0 t \\ -1 &\leq f(\infty) \leq 1 \end{aligned}$$

Question 194: Z-Transform (GATE EC 2006)

MCQ

1 Mark

If the region of convergence of $x_1[n] + x_2[n]$ is $\frac{1}{3} < |z| < \frac{2}{3}$ then the region of convergence of $x_1[n] - x_2[n]$ includes

- (A) $\frac{1}{3} < |z| < 3$
- (B) $\frac{2}{3} < |z| < 3$
- (C) $\frac{3}{2} < |z| < 3$

(D) (Correct) $\frac{1}{3} < |z| < \frac{2}{3}$

Correct Answer: (D)

Detailed Solution – Question 194

ROC remains the same for addition and subtraction in z-domain

Question 195: Basics of Signals & Systems (GATE EC 2006)

MCQ

1 Mark

The Dirac delta function $\delta(t)$ is defined as

(A)

$$\delta(t) = \begin{cases} 1 & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

(B)

$$\delta(t) = \begin{cases} \infty & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

(C)

$$\delta(t) = \begin{cases} 1 & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

$$\text{and } \int_{-\infty}^{\infty} \delta(t) dt = 1$$



(D) (Correct)

$$\delta(t) = \begin{cases} \infty & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

$$\text{and } \int_{-\infty}^{\infty} \delta(t) dt = 1$$

Correct Answer: (D)

Detailed Solution – Question 195



Question 196: Fourier Transforms (GATE EC 2006)

MCQ

1 Mark

Let $x(t) \leftrightarrow X(j\omega)$ be Fourier Transform pair. The Fourier Transform of the signal $x(5t - 3)$ in terms of $X(j\omega)$ is given as

- (A) **(Correct)** $\frac{1}{5}e^{-\frac{j3\omega}{5}}X\left(\frac{j\omega}{5}\right)$
- (B) $\frac{1}{5}e^{\frac{j3\omega}{5}}X\left(\frac{j\omega}{5}\right)$
- (C) $\frac{1}{5}e^{-j3\omega}X\left(\frac{j\omega}{5}\right)$
- (D) $\frac{1}{5}e^{j3\omega}X\left(\frac{j\omega}{5}\right)$

Correct Answer: (A)

Detailed Solution – Question 196

$$x(t) \leftrightarrow x(j\omega)$$

$$x\left[5\left(t - \frac{3}{5}\right)\right] = \frac{1}{5}e^{-\frac{j3\omega}{5}}X\left(\frac{j\omega}{5}\right)$$

Using scaling and shifting property.

Question 197: Z-Transform (GATE EC 2006)

MCQ

1 Mark

A low-pass filter having a frequency response $H(j\omega) = A(\omega)e^{j\phi(\omega)}$ does not produce any phase distortions if

- (A) $A(\omega) = C\omega^2, \phi(\omega) = k\omega^3$
- (B) **(Correct)** $A(\omega) = C\omega^2, \phi(\omega) = k\omega$
- (C) $A(\omega) = C\omega, \phi(\omega) = k\omega^2$
- (D) $A(\omega) = C, \phi(\omega) = k\omega^{-1}$

Correct Answer: (B)

Detailed Solution – Question 197


For distortionless transmission. $\frac{d\phi(\omega)}{d\omega} = \text{constant}$ Phase response should be linear $\phi(\omega) = k\omega$

Question 198: DTFS, DTFT & DFT (GATE EC 2005)

MCQ

1 Mark

A sequence $x(n)$ has non-zero values as shown in figure.



The Fourier transform of $y(2n)$ will be

- (A) $e^{-j2\omega}[\cos 4\omega + 2\cos 2\omega + 2]$
- (B) $\cos 2\omega + 2\cos \omega + 2$
- (C) **(Correct)** $e^{-j\omega}[\cos 2\omega + 2\cos \omega + 2]$
- (D) $e^{j2\omega}[\cos 2\omega + 2\cos \omega + 2]$

Correct Answer: (C)

Detailed Solution – Question 198

$$y(2n) = x(n-1), \text{ seeing in graph}$$

$$f(n) = y(2n)$$

$$= \frac{1}{2}\delta(n+1) + \delta(n) + 2\delta(n-1) + \delta(n-2) + \frac{1}{2}\delta(n-3)$$

Taking z-transform

$$F(z) = \frac{1}{2}z + 1 + 2z^{-1} + z^{-2} + \frac{1}{2}z^{-3}$$

$$Z = e^{j\omega}$$

$$F(e^{j\omega}) = \frac{1}{2}e^{j\omega} + 1 + 2e^{-j\omega} + e^{-2j\omega} + \frac{1}{2}e^{-3j\omega}$$

$$= e^{-j\omega} \left(\frac{1}{2}e^{2j\omega} + e^{j\omega} + 2 + e^{-j\omega} + \frac{1}{2}e^{-2j\omega} \right)$$

$$= e^{-j\omega} \left[\frac{e^{2j\omega} + e^{-2j\omega}}{2} + e^{j\omega} + e^{-j\omega} + 2 \right]$$



$$f(n) = e^{-j\omega}[\cos 2\omega + 2\cos \omega + 2]$$

Question 199: DTFS, DTFT & DFT (GATE EC 2005)

MCQ

1 Mark








A sequence $x(n)$ has non-zero values as shown in figure.



The sequence

$$y(n) = \begin{cases} X\left(\frac{n}{2} - 1\right), & \text{For } n \text{ is even} \\ 0, & \text{For } n \text{ is odd} \end{cases}$$

will be



(A) (Correct) A

(B) B

- (C) C
(D) D

Correct Answer: (A)

Detailed Solution – Question 199

$$\begin{aligned} y(n) &= x\left(\frac{n}{2} - 1\right), n \text{ even} \\ &= 0 \text{ for } n \text{ odd} \\ n = 0, y(n) &= x(-1) = 1 \\ n = 2, y(n) &= x(0) = 2 \\ n = 4, y(n) &= x(1) = 1 \\ n = 6, y(n) &= x(2) = 1/2 \end{aligned}$$

Question 200: Fourier Transforms (GATE EC 2005)

MCQ

1 Mark

For a signal $x(t)$ the Fourier transform is $X(f)$. Then the inverse Fourier transform of $X(3f + 2)$ is given by

- (A) $\frac{1}{2}x\left(\frac{1}{2}\right)e^{j3\pi t}$
 (B) **(Correct)** $\frac{1}{3}x\left(\frac{1}{3}\right)e^{j3\pi t}$
 (C) $3x(3t)e^{-4j\pi t}$
 (D) $x(3t+2)$

Correct Answer: (B)

Detailed Solution – Question 200

$$x\left[3\left(t + \frac{2}{3}\right)\right] = \frac{1}{3}x\left(\frac{t}{3}\right)e^{-j4\pi t/3}$$

Applying scaling & shifting property.

Question 201: DTFS, DTFT & DFT (GATE EC 2005)

MCQ

1 Mark

A signal $x(n) = \sin(\omega_0 n + \phi)$ is the input to a linear time-invariant system having a frequency response $H(e^{j\omega})$. If the output of the system is $Ax(n - n_0)$ then the most general form of $\angle H(e^{j\omega})$ will be

- (A) $-n_0\omega_0 + \beta$ for any arbitrary real β
 (B) **(Correct)** $-n_0\omega_0 + 2\pi k$ for any arbitrary integer k
 (C) $n_0\omega_0 + 2\pi k$ for any arbitrary integer k

(D) $-n_0\omega_0 + \phi$

Correct Answer: (B)

Detailed Solution – Question 201

$$\begin{aligned}\sin(\omega_0 n + \phi) &= x(n) \leftrightarrow X(e^{j\omega}) \\ y(n) &= Ax(n - n_o) \\ (e^{j\omega}) &= Ae^{-j\omega} X(e^{j\omega}) \\ H(e^{j\omega}) &= \frac{Y(e^{j\omega})}{X(e^{j\omega})} = Ae^{-jn_o\omega} \\ \angle H(e^{j\omega}) &= -n_o\omega_o + 2\pi k \quad (\text{at } \omega = \omega_o)\end{aligned}$$

Question 202: DTFS, DTFT & DFT (GATE EC 2005)

MCQ

1 Mark

Match the following and choose the correct combination.

Group 1

E. Continuous and aperiodic signal

F. Continuous and periodic signal

G. Discrete and aperiodic signal

H. Discrete and periodic signal Group 2

1. Fourier representation is continuous and aperiodic

2. Fourier representation is discrete and aperiodic

3. Fourier representation is continuous and periodic

4. Fourier representation is discrete and periodic

(A) E - 3, F - 2, G - 4, H - 1

(B) E - 1, F - 3, G - 2, H - 4

(C) **(Correct)** E - 1, F - 2, G - 3, H - 4

(D) E - 2, F - 1, G - 4, H - 3

Correct Answer: (C)

Question 203: Fourier Transforms (GATE EC 2005)

MCQ

1 Mark

The output $y(t)$ of a linear time invariant system is related to its input $x(t)$ by the following equations:
 $y(t) = 0.5x(t - t_d + T) + x(t - t_d) + 0.5x(t - t_d + T)$ The filter transfer function $H(\omega)$ of such a system is given by

(A) **(Correct)** $(1 + \cos\omega T)e^{-j\omega t_d}$

(B) $(1 + 0.5\cos\omega T)e^{-j\omega t_d}$

(C) $(1 + \cos\omega T)e^{j\omega t_d}$

(D) $(1 - 0.5\cos\omega T)e^{-j\omega t_d}$

Correct Answer: (A)

Detailed Solution – Question 203

$$y(t) = 0.5x(t - t_d + T) + 0.5x(t - t_d - T) + x(t - t_d)$$

Taking Fourier transform

$$Y(\omega) = [0.5e^{j\omega(-t_d+T)} + 0.5e^{j\omega(-t_d-T)} + e^{-j\omega t_d}] X(\omega)$$

$$\frac{Y(\omega)}{X(\omega)} = e^{-j\omega t_d} [0.5e^{j\omega T} + 0.5e^{-j\omega T} + 1]$$

$$\frac{Y(\omega)}{X(\omega)} = e^{-j\omega t_d} [\cos\omega T + 1]$$

$$H(\omega) = (1 + \cos\omega T)e^{-j\omega t_d}$$

Question 204: Laplace Transform (GATE EC 2005)

MCQ

1 Mark

In what range should $\text{Re}(s)$ remain so that the Laplace transform of the function $e^{(a+2)t+5}$ exists.

- (A) **(Correct)** $\text{Re}(s) > a + 2$
- (B) $\text{Re}(s) > a + 7$
- (C) $\text{Re}(s) < 2$
- (D) $\text{Re}(s) > a + 5$

Correct Answer: (A)

Detailed Solution – Question 204

$$f(t)Y = e^{(a+2)t+5} = e^5 \cdot e^{(a+2)t}$$

$$F(s) = \left[\frac{1}{s - (a+2)} \right] e^5$$

$\therefore$ For LT to exist, $\text{Re}(s) > a + 2$

Question 205: Basics of Signals & Systems (GATE EC 2005)

MCQ

1 Mark

The power in the signal $s(t) = 8\cos(20\pi t - \frac{\pi}{2}) + 4\sin(15\pi t)$ is

- (A) **(Correct)** 40
- (B) 41
- (C) 42

(D) 82

Correct Answer: (A)

Detailed Solution – Question 205

$$\begin{aligned}s(t) &= 8 \cos \left(\frac{\pi}{2} - 20\pi t \right) + 4 \sin 15\pi t \\&= 8 \sin 20\pi t + 4 \sin 15\pi t \\P &= \frac{8^2}{2} + \frac{4^2}{2} = 32 + 8 = 40\end{aligned}$$

Question 206: DTFS, DTFT & DFT (GATE EC 2005)

MCQ

1 Mark

Let $x(n) = \left(\frac{1}{2}\right)^n u(n)$, $y(n) = x^2(n)$ and $Y(e^{j\omega})$ be the Fourier transform of $y(n)$ then $Y(e^{j0})$

- (A) $\frac{1}{4}$
- (B) 2
- (C) 4
- (D) **(Correct)** $\frac{4}{3}$

Correct Answer: (D)

Detailed Solution – Question 206









$$\begin{aligned}x(n) &= \left(\frac{1}{2}\right)^n \cdot u(n) \\y(n) &= x^2(n) = \left(\frac{1}{2}\right)^{2n} u^2(n) \\y(n) &= \left(\frac{1}{4}\right)^n u(n) \\Y(z) &= \frac{1}{1 - \frac{1}{4}z^{-1}} \\ \text{Put, } z &= e^{j\omega} \\Y(e^{j\omega}) &= \frac{1}{1 - \frac{1}{4}e^{-j\omega}}; \\Y(e^{j0}) &= \frac{1}{1 - \frac{1}{4}} = \frac{4}{3}\end{aligned}$$

Question 207: LTI Systems (GATE EC 2005)

MCQ

1 Mark

Which of the following can be impulse response of a causal system ?



- (A) A
(B) B
(C) C
(D) **(Correct)** D

Correct Answer: (D)

Detailed Solution – Question 207

For a causal system $h(t) = 0$ for $t < 0$

Question 208: Z-Transform (GATE EC 2005)

MCQ

1 Mark

The region of convergence of z-transform of the sequence $(\frac{5}{6})^n u(n) - (\frac{6}{5})^n u(-n-1)$ must be

- (A) $|z| < \frac{5}{6}$
(B) $|z| > \frac{5}{6}$
(C) **(Correct)** $\frac{5}{6} < |z| < \frac{6}{5}$
(D) $\frac{5}{6} < |z| < \infty$

Correct Answer: (C)

Detailed Solution – Question 208



$$\begin{aligned} & z\text{-transform of } \left(\frac{5}{6}\right)^n u(n) - \left(\frac{6}{5}\right)^n u(-n-1) \\ &= \frac{1}{1-\frac{5}{6}z^{-1}} + \left[1 - \frac{1}{1-\left(\frac{6}{5}\right)^{-1}z}\right] \\ &\quad \text{(ROC)} \quad \quad \quad \text{(ROC)} \\ &= |z| > \frac{5}{6} \quad |z| < \frac{6}{5} \\ &\frac{5}{6} < |z| < \frac{6}{5} \end{aligned}$$

Question 209: Basics of Signals & Systems (GATE EC 2005)

MCQ

1 Mark

The function $x(t)$ is shown in the figure. Even and odd parts of a unit step function $u(t)$ are respectively,



(A) **(Correct)** $\frac{1}{2}, \frac{1}{2}x(t)$

(B) $-\frac{1}{2}, \frac{1}{2}x(t)$

(C) $\frac{1}{2}, -\frac{1}{2}x(t)$




(D) $-\frac{1}{2}, -\frac{1}{2}x(t)$

Correct Answer: (A)

Detailed Solution – Question 209

$$\text{Even part} = \frac{u(t) + u(-t)}{2}$$

$$\text{Odd part} = \frac{u(t) - u(-t)}{2}$$



180

$u_o(t)$

Question 210: Fourier Series (GATE EC 2005)

MCQ

1 Mark

Choose the function $f(t)$; $-\infty < t < \infty$ for which a Fourier series cannot be defined.

- (A) $3\sin(25t)$
- (B) $4\cos(20t+3)+2\sin(10t)$
- (C) **(Correct)** $\exp(-t)\sin(25t)$
- (D) 1

Correct Answer: (C)

Detailed Solution – Question 210


All other functions are either periodic or constant function.

Question 211: Fourier Transforms (GATE EC 2004)

MCQ

1 Mark

Let $x(t)$ and $y(t)$ with Fourier transforms $X(f)$ and $Y(f)$ respectively be related as shown in Fig.



Then $Y(f)$ is

- (A) $-\frac{1}{2}X(f/2)e^{-j\pi f}$
- (B) **(Correct)** $-\frac{1}{2}X(f/2)e^{j2\pi f}$
- (C) $-X(f/2)e^{j2\pi f}$
- (D) $-X(f/2)e^{-j2\pi f}$

Correct Answer: (B)

Detailed Solution – Question 211

$$\begin{aligned}y(t) &= -x[2(t+1)] \\x(t-t_0) &\leftrightarrow x(f)e^{-j2\pi ft_0} \\t_0 &= -1 \\x(at) &= \frac{1}{|a|}X\left(\frac{t}{a}\right) \\a &= -2 \\\therefore Y(f) &= -\frac{1}{2}X\left(\frac{f}{2}\right)e^{j2\pi f}\end{aligned}$$

Question 212: DTFS, DTFT & DFT (GATE EC 2004)

MCQ

1 Mark

The impulse response $h[n]$ of a linear time invariant system is given as

$$\begin{cases} -2\sqrt{2} & n = 1, -1 \\ 4\sqrt{2} & n = 2, -2 \\ 0 & \text{otherwise} \end{cases}$$

If the input to the above system is the sequence $e^{j\pi n/4}$, then the output is

- (A) $4\sqrt{2}e^{j\pi n/4}$
- (B) $4\sqrt{2}e^{-j\pi n/4}$
- (C) $4e^{j\pi n/4}$
- (D) **(Correct)** $-4e^{j\pi n/4}$

Correct Answer: (D)

Detailed Solution – Question 212

$$\begin{aligned}
 h(n) &= 4\sqrt{2}\delta(n+2) - 2\sqrt{2}\delta(n+1) \\
 &\quad - 2\sqrt{2}\delta(n-1) + 4\sqrt{2}\delta(n-2) \\
 x(n) &= e^{jn\pi/4} \\
 y(n) &= x(n) * h(n) \\
 &= 4\sqrt{2}\delta(n+2) * e^{jn\pi/4} + 4\sqrt{2}\delta(n-2) * e^{jn\pi/4} \\
 &\quad - 2\sqrt{2} \left[\delta(n+1) * e^{jn\pi/4} + \delta(n-1) * e^{jn\pi/4} \right] \\
 x(n) * \delta(n-a) &\rightarrow x(n-a) \\
 y(n) &= 4\sqrt{2} \left[e^{j\pi/4(n+2)} + e^{j\pi/4(n-2)} \right] \\
 &\quad - 2\sqrt{2} \left[e^{j\pi/4(n+1)} + e^{j\pi/4(n-1)} \right] \\
 &= e^{jn\pi/4} \left[4\sqrt{2} \left(e^{j\pi/2} + e^{-j\pi/2} \right) \right] \\
 &\quad - 2\sqrt{2} \left(e^{j\pi/4} + e^{-j\pi/4} \right) \\
 &= e^{jn\pi/4} [0 - 2\sqrt{2} \times 2 \cos \pi/4] \\
 y(n) &= -4e^{jn\pi/4}
 \end{aligned}$$

Question 213: Z-Transform (GATE EC 2004)

MCQ

1 Mark

A causal LTI system is described by the difference equation

$$2y[n] = \alpha y[n-2] - 2x[n] + \beta x[n-1]$$

The system is stable only if

- (A) $|\alpha| = 2, |\beta| < 2$
- (B) $|\alpha| > 2, |\beta| > 2$
- (C) **(Correct)** $|\alpha| < 2$, any value of β
- (D) $|\beta| < 2$, any value of α

Correct Answer: (C)

Detailed Solution – Question 213

$2y[n] = \alpha y[n-2] - 2x[n] + \beta x[n-1]$ Taking z-transform

$$\begin{aligned} 2Y(z) &= \alpha Y(z)z^2 - 2X(z) + \beta X(z)z^{-1} \\ Y(z) [2 - \alpha z^2] &= X(z) [\beta z^{-1} - 2] \\ \frac{Y(z)}{X(z)} &= \left(\frac{\beta z^{-1} - 2}{2 - \alpha z^{-2}} \right) \end{aligned}$$

For system to be stable, β can be of any value.

$$\begin{aligned} 2 - \alpha z^{-2} &= 0 \\ 2z^2 - \alpha &= 0 \\ z &= \sqrt{\frac{\alpha}{2}} < 1 \\ |\alpha| &< 2 \end{aligned}$$

For system to be stable all poles should be inside unity circle.

Question 214: Basics of Signals & Systems (GATE EC 2004)

MCQ

1 Mark

Consider the sequence $x[n] = [-4 - j5, 1 + j2.5]$. The conjugate anti-symmetric part of the sequence is

(A) (Correct) $[-4 - j2.5, j2, 4 - j2.5]$

$-j2.5, 1, j2.5$

$-j5, j2, 0$

$-4, 1, 4$

Correct Answer: (A)

Detailed Solution – Question 214



$$\begin{aligned} x(n) &= [-4 - j5, 1 + j2, 4] \\ x^*(-n) &= [4, 1 - j2, -4 + j5] \\ x_{\text{CAS}}(n) &= \frac{x(n) - x^*(-n)}{2} \\ &= [-4 - j2.5, j2, 4 - j2.5] \end{aligned}$$

Question 215: Fourier Transforms (GATE EC 2004)

MCQ

1 Mark

A rectangular pulse train $s(t)$ as shown in the figure is convolved with the signal $\cos^2(4\pi \times 10^3 t)$. The convolved signal will be a



- (A) DC
- (B) 12 kHz sinusoid
- (C) 8 kHz sinusoid
- (D) **(Correct)** 14 kHz sinusoid


Correct Answer: (D)

Detailed Solution – Question 215


$$T_0 = 0.1 \times 10^{-3} = 10^{-4}$$

$$f_0 = \frac{1}{T_0} = 10^4 = 10\text{kHz}$$

$\cos^2(4\pi \times 10^3 t)$ has frequency = 4kHz



So only at '0', we get output after convolution. (Only odd harmonics are present.)



Question 216: Sampling (GATE EC 2004)

MCQ

1 Mark

A 1 kHz sinusoidal signal is ideally sampled at 1500 samples/sec and the sampled signal is passed through an ideal low-pass filter with cut-off frequency 800 Hz. The output signal has the frequency.

- (A) zero Hz
- (B) 0.75 kHz
- (C) **(Correct)** 0.5 kHz
- (D) 0.25 kHz

Correct Answer: (C)

Detailed Solution – Question 216

$$f_s = 1.5\text{kHz}$$

$$f_m = 1\text{kHz}$$

Available frequency components are $nf_s \pm f_m$. So, 1kHz, 2.5kHz, 0.5kHz LPF has $f_c = 0.8\text{k}$ only 0.5 k will appear at output.

Question 217: Fourier Transforms (GATE EC 2004)

MCQ

1 Mark

The Fourier transform of a conjugate symmetric function is always

- (A) imaginary
- (B) conjugate anti-symmetric
- (C) **(Correct)** real
- (D) conjugate symmetric

Correct Answer: (C)

Question 218: Z-Transform (GATE EC 2004)

MCQ

1 Mark

The z-transform of a system is $H(z) = \frac{z}{z-0.2}$. If the ROC is $|z| < 0.2$, then the impulse response of the system is

- (A) $(0.2)^n u[n]$
- (B) $(0.2)^n u[-n-1]$
- (C) $-(0.2)^n u[n]$
- (D) **(Correct)** $-(0.2)^n u[-n-1]$

Correct Answer: (D)

Detailed Solution – Question 218

$$H(z) = \frac{z}{z-0.2} = \frac{z}{z(1-0.2z^{-1})}$$

$$H(z) = \frac{1}{1-0.2z^{-1}}$$

ROC is $|z| < 0.2$ Comparing with, $-a^n u(-n-1) \rightarrow \frac{1}{1-az^{-1}}, |z| < a$ We get, $h(n) = -(0.2)^n u(-n-1)$

Question 219: LTI Systems (GATE EC 2004)

MCQ

1 Mark

The impulse response $h[n]$ of a linear time-invariant system is given by $h[n] = u[n+3] + u[n-2] - 2u[n-7]$ where $u[n]$ is the unit step sequence. The above system is

- (A) **(Correct)** stable but not causal
- (B) stable and causal
- (C) causal but unstable
- (D) unstable and not causal

Correct Answer: (A)

Detailed Solution – Question 219

$$\begin{aligned}\sum_{k=-\infty}^{\infty} h(k) &= \sum_{k=-3}^{\infty} u(k+3) + \sum_{k=2}^{\infty} u(k-2) \\ &\quad - 2 \sum_{k=7}^{\infty} u(k-7) \\ &= \sum_{k=-3}^6 1 + \sum_{k=2}^6 1 \\ &= 10 + 5 = 15 < \infty\end{aligned}$$



For bounded input, bounded output. So system is stable. Response depends on future value of input signal i.e. $u(n+3)$. So, system is not causal

Question 220: Sampling (GATE EC 2003)

MCQ

1 Mark

Let $x(t) = 2 \cos(800\pi t) + \cos(1400\pi t)$. $x(t)$ is sampled with the rectangular pulse train shown in the figure. The only spectral components (in kHz) present in the sampled signal in the frequency range 2.5 kHz to 3.5 kHz are



- (A) 2.7, 3.4
 (B) 3.3, 3.6
 (C) 2.6, 2.7
 (D) **(Correct)** 2.7, 3.3

Correct Answer: (D)

Detailed Solution – Question 220

From Fourier series expansion,

$$C_n = \frac{1}{T_0} \int_{-T_0/6}^{T_0/6} A \cdot e^{-j\pi\omega_0 t} dt = \frac{A}{\pi n} \sin\left(\frac{n\pi}{3}\right)$$

$\therefore$ From C_n it is clear that 1, 2, 4, 5, 7... harmonics are present. Freq of $p(t)$ corr. to 1, 2, 4, 5, 7... are $10^3, 2 \times 10^3, 4 \times 10^3 \dots$ frequency components $0.7k$ and $0.4k$ ($t^{(t)}$ has $s'(t)$ gives $(1 \pm 0.7)k, (2 \pm 0.7)k$ $(4 \pm 0.7)k(1 \pm 0.4)k, (2 \pm 0.4)k \dots$ Frequency present in range of 2.5k to 3.5k are 2.7, 3.3

Question 221: Fourier Transforms (GATE EC 2003)

MCQ

1 Mark

The system under consideration is an RC low-pass filter (RC-LPF) with $R = 1 \text{ k}\Omega$ and $C = 1.0 \text{ }\mu\text{F}$. Let $t_g(f)$ be the group delay function of the given RC-LPF and $f_2 = 100 \text{ Hz}$. Then $t_g(f_2)$ in ms, is

- (A) **(Correct)** 0.717
- (B) 7.17
- (C) 71.7
- (D) 4.505

Correct Answer: (A)

Detailed Solution – Question 221

$$\begin{aligned}H(\omega) &= \frac{1}{1 + j\omega RC} \\ \theta(\omega) &= -\tan^{-1} RC\omega \\ t_g &= \frac{10^{-3}}{1 + 10^{-6} \times 4\pi^2 \times 10^4} \\ t_g &= 0.717\text{ms}\end{aligned}$$

Question 222: Fourier Transforms (GATE EC 2003)

MCQ

1 Mark

The system under consideration is an RC low-pass filter (RC-LPF) with $R = 1 \text{ k}\Omega$ and $C = 1.0 \text{ }\mu\text{F}$.



Let $H(f)$ denote the frequency response of the RC-LPF. Let f_1 be the highest frequency such that

$$0 \leq |f| \leq f_1, \frac{|H(f_1)|}{H(0)} \geq 0.95$$

. Then f_1 (in Hz) is

- (A) 324.8
- (B) 163.9
- (C) **(Correct)** 52.2
- (D) 104.4

Correct Answer: (C)



$$\begin{aligned}
 H(f) &= \frac{1}{1 + j2\pi fRC} \\
 H(0) &= 1 \\
 \frac{|H(f_1)|}{H(0)} &= \frac{1}{\sqrt{1 + 4\pi^2 f_1^2 R^2 C^2}} \geq 0.95 \\
 \Rightarrow \frac{1}{1 + 4\pi^2 f_1^2 (RC)^2} &\leq 0.9025 \\
 \Rightarrow 1.108 &\leq 1 + 4\pi^2 f_1^2 (RC)^2 \\
 \Rightarrow 0.108 &\geq 4\pi^2 f_1^2 (RC)^2 \\
 f_1^2 &\leq \frac{0.108}{4\pi^2 (RC)^2} \\
 f_1 &\leq \frac{0.329}{2\pi \times 10^{-3}} \\
 \Rightarrow f_{1\max} &= 52.2\text{Hz}
 \end{aligned}$$

Question 223: Basics of Signals & Systems (GATE EC 2003)

MCQ

1 Mark

Let P be linearity, Q be time-invariance, R be causality and S be stability. A discrete time system has the input-output relationship,

$$y(n) = \begin{cases} x(n) & n \geq 1 \\ 0, & n = 0 \\ x(n+1) & n \leq -1 \end{cases}$$

where $x(n)$ is the input and $y(n)$ is the output. The above system has the properties

- (A) **(Correct)** P, S but not Q, R
- (B) P, Q, S but not R

(C) P, Q, R, S

(D) Q, R, S but not P

Correct Answer: (A)

Detailed Solution – Question 223

$$y(n - n_0) = x(n - n_0 + 1) \text{ (time varying)}$$

$$y(n) = x(n + 1) \text{ (depends on future)}$$

$$\text{i.e. } y(1) = x(2) \text{ (non causal)}$$

For bounded input, system has bounded output. So it is stable.

$$y(n) = x(n), n \geq 1$$

$$= 0, n = 0$$

$$= x(n + 1), n \leq -1$$

So, system is linear.

Question 224: Z-Transform (GATE EC 2003)

MCQ

1 Mark

A sequence $x(n)$ with the z-transform $X(z) = z^4 + z^2 - 2z + 2 - 3z^{-4}$ is applied as an input to a linear, time-invariant system with the impulse response $h(n) = 2\delta(n - 3)$ where

$$\delta(n) = \begin{cases} 1, & n = 0 \\ 0, & \text{otherwise} \end{cases}$$

The output at $n = 4$ is

(A) -6

(B) **(Correct)** zero

(C) 2

(D) -4

Correct Answer: (B)

Detailed Solution – Question 224

$$Y(z) = H(z)X(z)$$

$$H(z) = 2z^{-3}$$

$$\begin{aligned} \therefore Y(z) &= 2z^3 (z^4 + z^2 - 2z + 2 - 3z^{-4}) \\ &= 2(z + z^{-1} - 2z^2 + 2z^3 - 3z^7) \end{aligned}$$

Taking inverse of z -transform

$$\begin{aligned} y(n) &= 2[\delta(n + 1) + \delta(n - 1) - 2\delta(n - 2) \\ &\quad + 2\delta(n - 3) - 3\delta(n - 7)] \end{aligned}$$

$$\text{At } n = 4, y(4) = 0$$

Question 225: Fourier Transforms (GATE EC 2003)

MCQ

1 Mark

Let $x(t)$ be the input to a linear, time-invariant system. The required output is $4x(t-2)$. The transfer function of the system should be

- (A) $4e^{j4\pi f}$
- (B) $2e^{-j8\pi f}$
- (C) **(Correct)** $4e^{-j4\pi f}$
- (D) $2e^{j8\pi f}$

Correct Answer: (C)

Detailed Solution – Question 225

$$\begin{aligned}y(t) &= 4x(t-2) \\Y(s) &= 4e^{-2s}X(s) \\ \frac{Y(s)}{X(s)} &= 4e^{-2s} \\ H(f) &= 4e^{-2xj.2\pi t} = 4e^{-j4\pi t}\end{aligned}$$

Question 226: Fourier Series (GATE EC 2003)

MCQ

1 Mark

The Fourier series expansion of a real periodic signal with fundamental frequency f_0 is given by $g_p(t) = \sum_{n=-\infty}^{\infty} c_n e^{j2\pi n f_0 t}$. It is given that $c_3 = 3 + j5$. Then c_{-3} is

- (A) $5 + j3$
- (B) $-3 - j5$
- (C) $-5 + j3$
- (D) **(Correct)** $3 - j5$

Correct Answer: (D)

Detailed Solution – Question 226

$$\begin{aligned}c_{-k} &= c_k^* \\ c_3 &= 3 + j5 \\ c_{-3} &= c_3^* = 3 - j5\end{aligned}$$

Question 227: Laplace Transform (GATE EC 2003)

MCQ

1 Mark

The Laplace transform of $i(t)$ is given by $I(s) = \frac{2}{s(1+s)}$. At $t \rightarrow \infty$ The value of $i(t)$ tends to

- (A) 0
- (B) 1
- (C) **(Correct)** 2
- (D) ∞

Correct Answer: (C)

Detailed Solution – Question 227

$$\begin{aligned}\lim_{t \rightarrow \infty} i(t) &= \lim_{s \rightarrow 0} sI(s) \\ &= \lim_{s \rightarrow 0} \frac{2}{s(1+s)} = 2\end{aligned}$$

Question 228: Z-Transform (GATE EC 2002)

MCQ

1 Mark

If the impulse response of a discrete-time system is $h[n] = -5^n u[-n-1]$, then the system function $H(z)$ is equal to

- (A) $\frac{-z}{z-5}$ and the system is stable
- (B) **(Correct)** $\frac{z}{z-5}$ and the system is stable
- (C) $\frac{-z}{z-5}$ and the system is unstable
- (D) $\frac{z}{z-5}$ and the system is unstable

Correct Answer: (B)

Detailed Solution – Question 228

$$\begin{aligned}h(n) &= -5^n u[-n-1] \\H(z) &= \sum_{n=-\infty}^{\infty} h(n) z^{-n} \\H(z) &= \sum_{n=-\infty}^{-1} -5^n z^{-n}, \text{ Let } n = -k \\&= - \sum_{k=\infty}^1 (5z^{-1})^{-k} \\&= 1 - \sum_{k=0}^{\infty} (5^{-1}z)^k \\&= 1 - \frac{1}{1 - 5^{-1}z}, \quad |5^{-1}z| < 1, \quad |z| < 5 \\&= 1 - \frac{5}{5-z} \\&= -\frac{z}{5-z} = \frac{z}{z-5}\end{aligned}$$

The system is stable because ROC includes unit circle.

Question 229: Laplace Transform (GATE EC 2002)

MCQ

1 Mark

The Laplace transform of a continuous-time signal $x(t)$ is $X(s) = \frac{5-s}{s^2-s-2}$. If the Fourier transform of this signal exists, then $x(t)$ is

- (A) $e^{2t}u(t) - 2e^{-t}u(t)$
- (B) $-e^{2t}u(-t) + 2e^{-t}u(t)$
- (C) **(Correct)** $-e^{2t}u(-t) - 2e^{-t}u(t)$
- (D) $e^{2t}u(-t) - 2e^{-t}u(t)$

Correct Answer: (C)

Detailed Solution – Question 229

$$\begin{aligned}x(s) &= \frac{5-s}{s^2-s-2} = \frac{5-s}{(s+1)(s-2)} \\ \frac{5-s}{(s+1)(s-2)} &= \frac{A}{s+1} + \frac{B}{s-2} \\ 5-s &= A(s-2) + B(s+1) \\ s=2, 3 &= 3B \\ \Rightarrow B &= 1 \\ s=-1, 6 &= -3A \\ \Rightarrow A &= -2 \\ x(t) &= -2e^{-1}u(t) - e^{2t}u(-t) \\ \therefore -1 < \sigma < 2\end{aligned}$$

Note: ROC of Laplace transform should include $\sigma = 0$ line.

Question 230: Fourier Transforms (GATE EC 2002)

MCQ

1 Mark

A linear phase channel with phase delay T_P and group delay T_g must have

- (A) (Correct) $T_P = T_g = \text{constant}$
- (B) $T_P \propto f$ and $T_g \propto f$
- (C) $T_P = \text{constant}$ and $T_g \propto f$
- (D) $T_P \propto f$ and $T_g = \text{constant}$

Correct Answer: (A)

Detailed Solution – Question 230

$$\begin{aligned}\theta(\omega) &= -\omega\zeta_0 \\ T_P &= \frac{-\theta(\omega)}{\omega} = T_0 \\ T_g &= - \cdot \frac{d\theta(\omega)}{d\omega} = T_0 \\ T_P &= T_g = T_0 = \text{constant}\end{aligned}$$

,

Question 231: Fourier Transforms (GATE EC 2002)

MCQ

1 Mark

The Fourier transform $F\{e^{-1}u(t)\}$ is equal to $\frac{1}{1+j2\pi f}$. therefore, $F\{\frac{1}{1+j2\pi t}\}$ is

- (A) $e^f u(f)$

- (B) $e^{-f}u(f)$
 (C) **(Correct)** $e^f u(-f)$
 (D) $e^{-f}u(-f)$

Correct Answer: (C)

Detailed Solution – Question 231

$$f(t) = e^{-t}u(t)$$

$$F(t) = \frac{1}{1 + j2\pi f}$$

From duality, $F(t) \xleftrightarrow{FT} f(-f)$

$$\Rightarrow F(t) = \frac{1}{1 + j2\pi t}$$

$$f(-f) = e^f u(-f)$$

$$F(t) \xleftrightarrow{FT} e^f u(-f)$$

Question 232: Fourier Series (GATE EC 2002)

MCQ

1 Mark

Which of the following cannot be the Fourier series expansion of a periodic signal?

- (A) $x(t) = 2\cos t + 3 \cos 3t$
 (B) **(Correct)** $x(t) = 2\cos \pi t + 7 \cos t$
 (C) $x(t) = \cos t + 0.5$
 (D) $x(t) = 2\cos 1.5\pi t + \sin 3.5 \pi t$

Correct Answer: (B)

Detailed Solution – Question 232

$$x(t) = 2 \cos \pi t + 7 \cos t$$

$$T_1 = \frac{2\pi}{(0)} = 2$$

$$T_2 = \frac{2\pi}{1} = 2\pi$$

$$\frac{T_1}{T_2} = \frac{1}{\pi} = \text{irrational}$$

$\therefore x(t)$ is not periodic and does not satisfy Dirichlet condition.

Question 233: LTI Systems (GATE EC 2002)

MCQ

1 Mark

Convolution of $x(t+5)$ with impulse function $\delta(t-7)$ is equal to

- (A) $x(t - 12)$
- (B) $x(t + 12)$
- (C) **(Correct)** $x(t - 2)$
- (D) $x(t + 2)$

Correct Answer: (C)

Detailed Solution – Question 233

$$\begin{aligned}x(t+5) * \delta(t-7) &= x(t+5-7) \\ &= x(t-2)\end{aligned}$$

Question 234: LTI Systems (GATE EC 2001)

MCQ

1 Mark

The impulse response functions of four linear systems S1, S2, S3, S4 are given respectively by $h_1(t) = 1$, $h_2(t) = U(t)$, $h_3(t) = \frac{U(t)}{t+1}$, $h_4(t) = e^{-3t}U(t)$ where $U(t)$ is the step function. Which of these systems is time invariant, causal and stable?

- (A) S1
- (B) S2
- (C) S3
- (D) **(Correct)** S4

Correct Answer: (D)

Detailed Solution – Question 234

$h_1(t) \neq 0$ for $t < 0$ Therefore, is non causal

$$\begin{aligned}h_2(t) &= u(t) = 0 \text{ for } t < 0 \\ \int_{-\infty}^{\infty} h_2(t) dt &= \int_{-\infty}^{\infty} u(t) dt = \int_0^{\infty} dt = \infty\end{aligned}$$

Therefore s_2 is unstable and causal

$$h_3(t) = \frac{u(t)}{t+1}$$

at $t = -1$

$$h_f(t) = \infty, h_3(t) = 0 \text{ for } t < 0$$

Therefore s_3 is unstable and causal $h_4(t) = e^{-3t}u(t)$ s_4 is time invariant, causal and stable

Question 235: Basics of Signals & Systems (GATE EC 2001)

MCQ

1 Mark

If a signal $f(t)$ has energy E , the energy of the signal $f(2t)$ is equal to

- (A) E
- (B) **(Correct)** $\frac{E}{2}$
- (C) $2E$
- (D) $4E$

Correct Answer: (B)

Detailed Solution – Question 235

$$\begin{aligned} E &= \int_{-\infty}^{\infty} f(t)^2 dt \\ E' &= \int_{-\infty}^{\infty} f(2t)^2 dt \\ &= \int_{-\infty}^{\infty} f(p)^2 \cdot \frac{dp}{2} \left(2t = p; dt = \frac{dp}{2} \right) \\ E' &= \frac{E}{2} \end{aligned}$$

Question 236: Basics of Signals & Systems (GATE EC 2001)

MCQ

1 Mark

Let $\delta(t)$ denote the delta function. The value of the integral $\int_{-\infty}^{\infty} \delta(t) \cos\left(\frac{3t}{2}\right) dt$ is

- (A) **(Correct)** 1
- (B) -1
- (C) 0
- (D) $\frac{\pi}{2}$

Correct Answer: (A)

Detailed Solution – Question 236

$$\int_{-\infty}^{\infty} \delta(t) \cos\left(\frac{3t}{2}\right) dt = f(0) = \cos\left(\frac{3 \times 0}{2}\right) = \cos 0 = 1$$

Question 237: Z-Transform (GATE EC 2001)

MCQ

1 Mark

The region of convergence of the z-transform of a unit step function is

- (A) **(Correct)** $|z| > 1$
- (B) $|z| < 1$
- (C) (real part of Z) > 0

Correct Answer: (A)

Detailed Solution – Question 237

$$h(n) = u(n)$$

$$H(z) = \sum_{n=0}^{\infty} 1 \cdot z^{-n}$$

For the convergence of $H(z)$ $\sum_{n=0}^{\infty} (z^{-1})^n < \infty \therefore$ ROC is the range of values of z for which $|z^{-1}| < 1$ or $|z| > 1$

Question 238: Laplace Transform (GATE EC 2001)

MCQ

1 Mark

The transfer function of a system is given by $H(s) = \frac{1}{s^2(s-2)}$. The impulse response of the system is: (* denotes convolution, and $U(t)$ is unit step function)

- (A) $(t^2 * e^{-2t})U(t)$
- (B) **(Correct)** $(t * e^{2t})U(t)$
- (C) $(te^{-2t})U(t)$
- (D) $(te^{-2t})U(t)$

Correct Answer: (B)

Detailed Solution – Question 238

Impulse response of system is $L^{-1}[H(s)]$

$$\frac{1}{s^2(s-2)} = \frac{1}{s^2} \times \frac{1}{s-2} = (t * e^{+2t}) u(t)$$