

GATE EC: Signals and Systems

Previous Year Solved Questions

PracticePaper.in Archive

July 27, 2026

Contents

Question 1 – GATE EC 2026, Basics of Signals and Systems	2
Question 2 – GATE EC 2026, LTI Systems Continuous and Discrete	3
Question 3 – GATE EC 2026, Fourier Transforms, Frequency Response and Correlation	4
Question 4 – GATE EC 2026, Basics of Signals and Systems	5
Question 5 – GATE EC 2026, Fourier Series	6
Question 6 – GATE EC 2026, LTI Systems Continuous and Discrete	7
Question 7 – GATE EC 2026, LTI Systems Continuous and Discrete	8
Question 8 – GATE EC 2026, Sampling	9
Question 9 – GATE EC 2026, Laplace Transform	10
Question 10 – GATE EC 2025, Fourier Series	11
Question 11 – GATE EC 2025, Sampling	12
Question 12 – GATE EC 2025, DTFS, DTFT and DFT	13
Question 13 – GATE EC 2025, Fourier Transforms, Frequency Response and Correlation	14
Question 14 – GATE EC 2025, LTI Systems Continuous and Discrete	15
Question 15 – GATE EC 2024, DTFS, DTFT and DFT	16
Question 16 – GATE EC 2024, Basics of Signals and Systems	16
Question 17 – GATE EC 2024, Fourier Transforms, Frequency Response and Correlation	17
Question 18 – GATE EC 2024, Fourier Transforms, Frequency Response and Correlation	19
Question 19 – GATE EC 2024, LTI Systems Continuous and Discrete	21
Question 20 – GATE EC 2024, LTI Systems Continuous and Discrete	21

Question 21 – GATE EC 2023, LTI Systems Continuous and Discrete	22
Question 22 – GATE EC 2023, Fourier Transforms, Frequency Response and Correlation	23
Question 23 – GATE EC 2023, Sampling	24
Question 24 – GATE EC 2023, LTI Systems Continuous and Discrete	27
Question 25 – GATE EC 2023, DTFS, DTFT and DFT	29
Question 26 – GATE EC 2023, DTFS, DTFT and DFT	29
Question 27 – GATE EC 2023, Basics of Signals and Systems	30
Question 28 – GATE EC 2023, Fourier Transforms, Frequency Response and Correlation	31
Question 29 – GATE EC 2023, Basics of Signals and Systems	31
Question 30 – GATE EC 2023, LTI Systems Continuous and Discrete	33
Question 31 – GATE EC 2022, DTFS, DTFT and DFT	33
Question 32 – GATE EC 2022, LTI Systems Continuous and Discrete	34
Question 33 – GATE EC 2022, LTI Systems Continuous and Discrete	35
Question 34 – GATE EC 2022, DTFS, DTFT and DFT	36
Question 35 – GATE EC 2021, DTFS, DTFT and DFT	36
Question 36 – GATE EC 2021, LTI Systems Continuous and Discrete	37
Question 37 – GATE EC 2021, Fourier Transforms, Frequency Response and Correlation	38
Question 38 – GATE EC 2021, DTFS, DTFT and DFT	39
Question 39 – GATE EC 2021, Sampling	40
Question 40 – GATE EC 2020, Z-Transform	42
Question 41 – GATE EC 2020, Fourier Transforms, Frequency Response and Correlation	42
Question 42 – GATE EC 2020, DTFS, DTFT and DFT	43
Question 43 – GATE EC 2020, LTI Systems Continuous and Discrete	44
Question 44 – GATE EC 2020, LTI Systems Continuous and Discrete	46
Question 45 – GATE EC 2019, Digital Filters	47
Question 46 – GATE EC 2019, DTFS, DTFT and DFT	47
Question 47 – GATE EC 2019, DTFS, DTFT and DFT	48
Question 48 – GATE EC 2019, Basics of Signals and Systems	49

Question 49 – GATE EC 2019, Laplace Transform	50
Question 50 – GATE EC 2019, Z-Transform	50
Question 51 – GATE EC 2018, DTFS, DTFT and DFT	52
Question 52 – GATE EC 2018, Sampling	52
Question 53 – GATE EC 2018, Fourier Transforms, Frequency Response and Correlation	54
Question 54 – GATE EC 2018, Fourier Series	55
Question 55 – GATE EC 2018, Z-Transform	56
Question 56 – GATE EC 2018, Basics of signals and Systems	57
Question 57 – GATE EC 2017-SET-2, LTI Systems Continuous and Discrete	58
Question 58 – GATE EC 2017-SET-2, Laplace Transform	60
Question 59 – GATE EC 2017-SET-2, Sampling	60
Question 60 – GATE EC 2017-SET-2, Fourier Transforms, Frequency Response and Correlation	61
Question 61 – GATE EC 2017-SET-2, Basics of signals and Systems	62
Question 62 – GATE EC 2017-SET-2, DTFS, DTFT and DFT	63
Question 63 – GATE EC 2017-SET-1, Fourier Transforms, Frequency Response and Correlation	63
Question 64 – GATE EC 2017-SET-1, DTFS, DTFT and DFT	64
Question 65 – GATE EC 2017-SET-1, Fourier Series	65
Question 66 – GATE EC 2017-SET-1, LTI Systems Continuous and Discrete	65
Question 67 – GATE EC 2017-SET-1, Laplace Transform	66
Question 68 – GATE EC 2017-SET-1, Fourier Series	67
Question 69 – GATE EC 2017-SET-1, Basics of signals and Systems	67
Question 70 – GATE EC 2016-SET-3, Digital Filters	68
Question 71 – GATE EC 2016-SET-3, DTFS, DTFT and DFT	69
Question 72 – GATE EC 2016-SET-3, Z-Transform	70
Question 73 – GATE EC 2016-SET-3, Laplace Transform	71
Question 74 – GATE EC 2016-SET-3, Z-Transform	73
Question 75 – GATE EC 2016-SET-3, Fourier Transforms, Frequency Response and Correlation	73
Question 76 – GATE EC 2016-SET-3, Sampling	75

Question 77 – GATE EC 2016-SET-2, DTFS, DTFT and DFT	75
Question 78 – GATE EC 2016-SET-2, Digital Filters	76
Question 79 – GATE EC 2016-SET-2, Fourier Transforms, Frequency Response and Correlation	76
Question 80 – GATE EC 2016-SET-1, DTFS, DTFT and DFT	77
Question 81 – GATE EC 2016-SET-1, Laplace Transform	78
Question 82 – GATE EC 2016-SET-1, Fourier Transforms, Frequency Response and Correlation	79
Question 83 – GATE EC 2016-SET-1, Laplace Transform	80
Question 84 – GATE EC 2016-SET-1, Sampling	81
Question 85 – GATE EC 2016-SET-1, Z-Transform	82
Question 86 – GATE EC 2016-SET-1, Basics of signals and Systems	83
Question 87 – GATE EC 2016-SET-1, LTI Systems Continuous and Discrete	83
Question 88 – GATE EC 2016-SET-1, Laplace Transform	84
Question 89 – GATE EC 2015-SET-3, Basics of Signals and Systems	84
Question 90 – GATE EC 2015-SET-3, Sampling	85
Question 91 – GATE EC 2015-SET-3, DTFS, DTFT and DFT	85
Question 92 – GATE EC 2015-SET-3, Z-Transform	86
Question 93 – GATE EC 2015-SET-3, Z-Transform	87
Question 94 – GATE EC 2015-SET-3, Z-Transform	87
Question 95 – GATE EC 2015-SET-3, LTI Systems Continuous and Discrete	88
Question 96 – GATE EC 2015-SET-3, DTFS, DTFT and DFT	88
Question 97 – GATE EC 2015-SET-3, Fourier Transforms, Frequency Response and Correlation	89
Question 98 – GATE EC 2015-SET-2, Laplace Transform	89
Question 99 – GATE EC 2015-SET-2, DTFS, DTFT and DFT	90
Question 100 – GATE EC 2015-SET-2, Laplace Transform	90
Question 101 – GATE EC 2015-SET-1, Signals and Systems	91
Question 102 – GATE EC 2014-SET-1, Signals and Systems	92
Question 103 – GATE EC 2013, Signals and Systems	92
Question 104 – GATE EC 2013, Signals and Systems	93

Question 105 – GATE EC 2012, Signals and Systems	94
Question 106 – GATE EC 2008, Signals and Systems	94
Question 107 – GATE EC 2008, Signals and Systems	95
Question 108 – GATE EC 2007, Signals and Systems	95
Question 109 – GATE EC 2006, Signals and Systems	96
Question 110 – GATE EC 2006, Signals and Systems	96
Question 111 – GATE EC 2005, Signals and Systems	97
Question 112 – GATE EC 2005, Signals and Systems	98
Question 113 – GATE EC 2004, Signals and Systems	100
Question 114 – GATE EC 2003, Signals and Systems	100
Question 115 – GATE EC 2001, Signals and Systems	101
Question 116 – GATE EC 2001, Signals and Systems	101
Question 117 – GATE EC 2015-SET-1, Signals and Systems	102
Question 118 – GATE EC 2014-SET-4, Signals and Systems	103
Question 119 – GATE EC 2014-SET-4, Signals and Systems	104
Question 120 – GATE EC 2014-SET-4, Signals and Systems	104
Question 121 – GATE EC 2014-SET-2, Signals and Systems	105
Question 122 – GATE EC 2014-SET-1, Signals and Systems	106
Question 123 – GATE EC 2013, Signals and Systems	106
Question 124 – GATE EC 2011, Signals and Systems	107
Question 125 – GATE EC 2010, Signals and Systems	107
Question 126 – GATE EC 2009, Signals and Systems	108
Question 127 – GATE EC 2009, Signals and Systems	108
Question 128 – GATE EC 2008, Signals and Systems	109
Question 129 – GATE EC 2007, Signals and Systems	109
Question 130 – GATE EC 2005, Signals and Systems	110
Question 131 – GATE EC 2005, Signals and Systems	111
Question 132 – GATE EC 2005, Signals and Systems	113
Question 133 – GATE EC 2005, Signals and Systems	114
Question 134 – GATE EC 2005, Signals and Systems	114

Question 135 – GATE EC 2004, Signals and Systems	115
Question 136 – GATE EC 2014-SET-4, Signals and Systems	116
Question 137 – GATE EC 2014-SET-3, Signals and Systems	117
Question 138 – GATE EC 2014-SET-2, Signals and Systems	117
Question 139 – GATE EC 2014-SET-1, Signals and Systems	118
Question 140 – GATE EC 2014-SET-1, Signals and Systems	119
Question 141 – GATE EC 2012, Signals and Systems	120
Question 142 – GATE EC 2009, Signals and Systems	122
Question 143 – GATE EC 2009, Signals and Systems	123
Question 144 – GATE EC 2008, Signals and Systems	123
Question 145 – GATE EC 2008, Signals and Systems	124
Question 146 – GATE EC 2007, Signals and Systems	125
Question 147 – GATE EC 2006, Signals and Systems	126
Question 148 – GATE EC 2005, Signals and Systems	126
Question 149 – GATE EC 2005, Signals and Systems	127
Question 150 – GATE EC 2004, Signals and Systems	127
Question 151 – GATE EC 2004, Signals and Systems	128
Question 152 – GATE EC 2004, Signals and Systems	130
Question 153 – GATE EC 2003, Signals and Systems	131
Question 154 – GATE EC 2003, Signals and Systems	131
Question 155 – GATE EC 2002, Signals and Systems	132
Question 156 – GATE EC 2002, Signals and Systems	132
Question 157 – GATE EC 2015-SET-1, Signals and Systems	133
Question 158 – GATE EC 2014-SET-2, Signals and Systems	133
Question 159 – GATE EC 2013, Signals and Systems	133
Question 160 – GATE EC 2012, Signals and Systems	134
Question 161 – GATE EC 2011, Signals and Systems	136
Question 162 – GATE EC 2008, Signals and Systems	136
Question 163 – GATE EC 2008, Signals and Systems	137
Question 164 – GATE EC 2005, Signals and Systems	138

Question 165 – GATE EC 2004, Signals and Systems	139
Question 166 – GATE EC 2002, Signals and Systems	140
Question 167 – GATE EC 2001, Signals and Systems	140
Question 168 – GATE EC 2015-SET-2, Signals and Systems	141
Question 169 – GATE EC 2014-SET-4, Signals and Systems	142
Question 170 – GATE EC 2014-SET-3, Signals and Systems	142
Question 171 – GATE EC 2014-SET-1, Signals and Systems	143
Question 172 – GATE EC 2013, Signals and Systems	144
Question 173 – GATE EC 2009, Signals and Systems	144
Question 174 – GATE EC 2006, Signals and Systems	145
Question 175 – GATE EC 2004, Signals and Systems	147
Question 176 – GATE EC 2003, Signals and Systems	147
Question 177 – GATE EC 2015-SET-2, Signals and Systems	148
Question 178 – GATE EC 2015-SET-2, Signals and Systems	149
Question 179 – GATE EC 2015-SET-2, Signals and Systems	149
Question 180 – GATE EC 2014-SET-4, Signals and Systems	150
Question 181 – GATE EC 2014-SET-4, Signals and Systems	150
Question 182 – GATE EC 2014-SET-4, Signals and Systems	151
Question 183 – GATE EC 2014-SET-3, Signals and Systems	151
Question 184 – GATE EC 2014-SET-3, Signals and Systems	152
Question 185 – GATE EC 2014-SET-1, Signals and Systems	153
Question 186 – GATE EC 2013, Signals and Systems	154
Question 187 – GATE EC 2013, Signals and Systems	154
Question 188 – GATE EC 2013, Signals and Systems	155
Question 189 – GATE EC 2013, Signals and Systems	155
Question 190 – GATE EC 2012, Signals and Systems	156
Question 191 – GATE EC 2011, Signals and Systems	157
Question 192 – GATE EC 2011, Signals and Systems	158
Question 193 – GATE EC 2011, Signals and Systems	158
Question 194 – GATE EC 2010, Signals and Systems	159

Question 195 – GATE EC 2010, Signals and Systems	160
Question 196 – GATE EC 2009, Signals and Systems	160
Question 197 – GATE EC 2007, Signals and Systems	161
Question 198 – GATE EC 2006, Signals and Systems	161
Question 199 – GATE EC 2005, Signals and Systems	162
Question 200 – GATE EC 2003, Signals and Systems	162
Question 201 – GATE EC 2002, Signals and Systems	163
Question 202 – GATE EC 2001, Signals and Systems	164
Question 203 – GATE EC 2015-SET-2, Signals and Systems	164
Question 204 – GATE EC 2015-SET-1, Signals and Systems	164
Question 205 – GATE EC 2015-SET-1, Signals and Systems	166
Question 206 – GATE EC 2014-SET-3, Signals and Systems	166
Question 207 – GATE EC 2014-SET-3, Signals and Systems	167
Question 208 – GATE EC 2014-SET-3, Signals and Systems	167
Question 209 – GATE EC 2014-SET-2, Signals and Systems	168
Question 210 – GATE EC 2014-SET-2, Signals and Systems	169
Question 211 – GATE EC 2014-SET-1, Signals and Systems	169
Question 212 – GATE EC 2012, Signals and Systems	170
Question 213 – GATE EC 2011, Signals and Systems	171
Question 214 – GATE EC 2010, Signals and Systems	172
Question 215 – GATE EC 2010, Signals and Systems	173
Question 216 – GATE EC 2010, Signals and Systems	173
Question 217 – GATE EC 2009, Signals and Systems	174
Question 218 – GATE EC 2008, Signals and Systems	174
Question 219 – GATE EC 2007, Signals and Systems	175
Question 220 – GATE EC 2006, Signals and Systems	175
Question 221 – GATE EC 2006, Signals and Systems	176
Question 222 – GATE EC 2005, Signals and Systems	176
Question 223 – GATE EC 2004, Signals and Systems	177
Question 224 – GATE EC 2004, Signals and Systems	177

Question 225 – GATE EC 2003, Signals and Systems	178
Question 226 – GATE EC 2002, Signals and Systems	178
Question 227 – GATE EC 2001, Signals and Systems	179
Question 228 – GATE EC 2015-SET-2, Signals and Systems	180
Question 229 – GATE EC 2014-SET-2, Signals and Systems	181
Question 230 – GATE EC 2011, Signals and Systems	183
Question 231 – GATE EC 2010, Signals and Systems	183
Question 232 – GATE EC 2009, Signals and Systems	184
Question 233 – GATE EC 2005, Signals and Systems	185
Question 234 – GATE EC 2003, Signals and Systems	185
Question 235 – GATE EC 2002, Signals and Systems	185
Question 236 – Control Systems, Frequency Response Analysis	186
Question 237 – Analog Circuits, Frequency Response of Amplifier	188
Question 238 – Control Systems, Frequency Response Analysis	189
Question 239 – Analog Circuits, Frequency Response of Amplifier	189
Question 240 – Control Systems, Frequency Response Analysis	190
Question 241 – Control Systems, Frequency Response Analysis	191
Question 242 – Control Systems, Frequency Response Analysis	193
Question 243 – Control Systems, Frequency Response Analysis	195
Question 244 – Control Systems, Frequency Response Analysis	196
Question 245 – Control Systems, Frequency Response Analysis	197
Question 246 – Control Systems, Frequency Response Analysis	198
Question 247 – Control Systems, Frequency Response Analysis	198
Question 248 – Analog Circuits, Frequency Response of Amplifier	199
Question 249 – Control Systems, Frequency Response Analysis	200
Question 250 – Control Systems, Frequency Response Analysis	200
Question 251 – Control Systems, Frequency Response Analysis	201
Question 252 – Control Systems, Frequency Response Analysis	202
Question 253 – Analog Circuits, Frequency Response of Amplifier	203
Question 254 – Control Systems, Frequency Response Analysis	203

Question 255 – Control Systems, Frequency Response Analysis	204
Question 256 – Control Systems, Frequency Response Analysis	205
Question 257 – Control Systems, Frequency Response Analysis	206
Question 258 – Control Systems, Frequency Response Analysis	207
Question 259 – Control Systems, Frequency Response Analysis	208
Question 260 – Control Systems, Frequency Response Analysis	209
Question 261 – Control Systems, Frequency Response Analysis	210
Question 262 – Control Systems, Frequency Response Analysis	211
Question 263 – Control Systems, Frequency Response Analysis	213
Question 264 – Control Systems, Frequency Response Analysis	214
Question 265 – Control Systems, Frequency Response Analysis	215
Question 266 – Analog Circuits, Frequency Response of Amplifier	216
Question 267 – Control Systems, Frequency Response Analysis	217
Question 268 – Control Systems, Frequency Response Analysis	218
Question 269 – Control Systems, Frequency Response Analysis	219
Question 270 – Control Systems, Frequency Response Analysis	220
Question 271 – Control Systems, Frequency Response Analysis	221
Question 272 – Control Systems, Frequency Response Analysis	222
Question 273 – Control Systems, Frequency Response Analysis	223
Question 274 – Control Systems, Frequency Response Analysis	223
Question 275 – Control Systems, Frequency Response Analysis	224
Question 276 – Control Systems, Frequency Response Analysis	225
Question 277 – Control Systems, Frequency Response Analysis	226
Question 278 – Control Systems, Frequency Response Analysis	226
Question 279 – Control Systems, Frequency Response Analysis	227
Question 280 – Control Systems, Frequency Response Analysis	228
Question 281 – Control Systems, Frequency Response Analysis	230
Question 282 – Control Systems, Frequency Response Analysis	230
Question 283 – Analog Circuits, Frequency Response of Amplifier	231
Question 284 – Control Systems, Frequency Response Analysis	232

Question 285 – Control Systems, Frequency Response Analysis	232
Question 286 – Control Systems, Frequency Response Analysis	233
Question 287 – Control Systems, Frequency Response Analysis	234
Question 288 – Control Systems, Frequency Response Analysis	235
Question 289 – Control Systems, Frequency Response Analysis	235
Question 290 – Control Systems, Frequency Response Analysis	236
Question 291 – Analog Circuits, Frequency Response of Amplifier	237

Question 1: GATE EC 2026, Basics of Signals and Systems

MSQ

2 Marks

Let $x_1(t) = \cos(2\pi nt)$ and $x_2(t) = 2\sin(4\pi nt)$ represent two sinusoids for a positive integer n and $-\infty < t < \infty$.

Which of the following statements about $x_1(t)$ and $x_2(t)$ is/are valid?

- (A) **(Correct)** $x_1(t)$ and $x_2(t)$ are orthogonal to each other over $0 \leq t < 1/n$.
- (B) $x_1(t)$ and $x_2(t)$ are orthonormal to each other over $0 \leq t < 1/n$.
- (C) **(Correct)** $x_2(t)$ is a harmonic of $x_1(t)$.
- (D) **(Correct)** $x_1(t)$ and $x_2(t)$ are non-orthogonal to each other over $0 \leq t < 1/(2n)$.

Correct Answer: (A, C, D)

Detailed Solution – Question 1

Given, $x_1(t) = \cos(2\pi nt)$ and $x_2(t) = 2\sin(4\pi nt)$
where n is a positive integer.

For $x_1(t)$, the frequency is: $f_1 = n$

For $x_2(t)$, the frequency is: $f_2 = 2n$

Thus, $f_2 = 2f_1$

Hence, $x_2(t)$ is the second harmonic of $x_1(t)$.

Therefore, **option (C) is correct**.

Now check orthogonality over $0 \leq t < \frac{1}{n}$.

Two signals are orthogonal if:

$$\int_0^{1/n} x_1(t)x_2(t), dt = 0$$

Substituting,

$$\int_0^{1/n} \cos(2\pi nt) \cdot 2\sin(4\pi nt), dt$$

Using identity,

$$2\sin A \cos B = \sin(A+B) + \sin(A-B)$$

we get,

$$2\cos(2\pi nt)\sin(4\pi nt) = \sin(6\pi nt) + \sin(2\pi nt)$$

$$\text{Hence, } \int_0^{1/n} [\sin(6\pi nt) + \sin(2\pi nt)] dt$$

Both sine terms integrate to zero over the interval $0 \leq t < \frac{1}{n}$. Therefore,

$$\int_0^{1/n} x_1(t)x_2(t), dt = 0$$

Hence, the signals are orthogonal over $0 \leq t < \frac{1}{n}$.

Therefore, **option (A) is correct**.

Now check orthonormality.

For orthonormal signals, each signal must have unit energy over the interval.

Energy of $x_1(t)$:

$$\int_0^{1/n} \cos^2(2\pi nt), dt \neq 1$$

Hence, the signals are not normalized. Therefore, **option (B) is incorrect**.

Now check option (D).

Over $0 \leq t < \frac{1}{2n}$,

$$\int_0^{1/(2n)} x_1(t)x_2(t), dt \neq 0$$

Thus, the signals are non-orthogonal over this interval.

Therefore, **option (D) is correct**.

Correct Options: (A), (C), and (D).


Question 2: GATE EC 2026, LTI Systems Continuous and Discrete

MCQ

2 Marks

Consider the discrete time system (S) with input $x[n]$ and output $y[n]$ as shown in the Figure. The two sub-systems represented by their impulse responses $h_1[n]$ and $h_2[n]$ are linear and time invariant.

Which of the following statements is necessarily TRUE?



- (A) S is causal.
- (B) **(Correct)** S is linear and time invariant.
- (C) S is linear and time varying.
- (D) S is non-linear.

Correct Answer: (B)

Detailed Solution – Question 2

From the figure: $x[n]$ is the input. The system has two paths:

Upper path: $x[n] \rightarrow h_1[n] \rightarrow \Sigma$

Lower path: $x[n] \rightarrow z^{-1} \rightarrow (-)\Sigma \rightarrow h_2[n] \rightarrow z^{-1} \rightarrow \Sigma$

The right summing junction combines the upper (positive) and lower (negative, delayed) signals to produce $y[n]$.

Step 1: Analyse the lower branch

The lower sub-system receives $x[n] - x[n-1]$ (difference, which is a linear time-invariant operation) and passes it through $h_2[n]$, then delays by z^{-1} . All operations (delay, difference, convolution with $h_2[n]$) are LTI.

Step 2: Output equation

$$y[n] = (x[n] * h_1[n]) - (x[n-1] * h_2[n-1])$$

Both terms are linear functions of $x[n]$, and all shifts are fixed. The overall system S is a linear combination of LTI subsystems, S is also **Linear and Time Invariant**.

Question 3: GATE EC 2026, Fourier Transforms, Frequency Response and Correlation

MCQ

2 Marks

Consider a real baseband signal $x(t) = e^{-2t}$, for t (in seconds) ≥ 0 .

If 99% of energy of $x(t)$ lies within B Hz, then which of the following options is TRUE for the value of B ?

- (A) $B > 1$ kHz
- (B) **(Correct)** $63/\pi$ Hz $< B < 64/\pi$ Hz
- (C) $126/\pi$ Hz $< B < 128/\pi$ Hz
- (D) $B < 1$ Hz

Correct Answer: (B)

Detailed Solution – Question 3

Step 1: Fourier Transform of the signal

The Fourier Transform of $e^{-at}u(t)$ is

Here, $a = 2$. Therefore,

$$X(f) = \frac{1}{2+j2\pi f}$$

Magnitude squared is

$$|X(f)|^2 = \frac{1}{4 + 4\pi^2 f^2}$$

Step 2: Total energy of the signal

Total energy is $E = \int_{-\infty}^{\infty} |X(f)|^2 df$

Substituting, $E = \int_{-\infty}^{\infty} \frac{df}{4+4\pi^2 f^2}$

Simplifying, $E = \frac{1}{4} \int_{-\infty}^{\infty} \frac{df}{1+\pi^2 f^2}$

Using the standard result, we get $E = \frac{1}{4}$

Step 3: Energy within bandwidth B

Required condition:

$$\int_{-B}^B |X(f)|^2 df = 0.99E$$

Substituting values,

$$\int_{-B}^B \frac{df}{4 + 4\pi^2 f^2} = 0.99 \times \frac{1}{4}$$

Simplifying,

$$\int_{-B}^B \frac{df}{1 + \pi^2 f^2} = 0.99$$

Using symmetry,

$$2 \int_0^B \frac{df}{1 + \pi^2 f^2} = 0.99$$

Integrating, $\frac{2}{\pi} \tan^{-1}(\pi B) = 0.99$

Hence, $\tan^{-1}(\pi B) = 0.495\pi$

Now,

$$0.495\pi \approx 1.555$$

Since $\tan(1.555) \approx 63.7$,

$$\pi B \approx 63.7$$

Therefore,

$$B \approx \frac{63.7}{\pi}$$

Question 4: GATE EC 2026, Basics of Signals and Systems

MCQ

2 Marks

Consider a real signal $x(t)$, $-\infty < t < \infty$, such that

$x(t) = 0$ for $t < 0$, $x(t) = 2$ for $0 \leq t < 1$ and $x(t) = 0$ for $t \geq 1$.

Let $E[x(t)] = \int_{-\infty}^{\infty} [x(t)]^2 dt$.

Which of the following options correctly represents the ratio,

$$E[x(t)]/E[3x(-3t+5)]?$$

(A) 3

(B) 1

(C) (Correct) $1/3$

(D) $1/9$

Correct Answer: (C)

Detailed Solution – Question 4

Given:

$x(t) = 0$ for $t < 0$; $x(t) = 2$ for $0 \leq t < 1$; $x(t) = 0$ for $t \geq 1$

$$E[x(t)] = \int_{-\infty}^{\infty} [x(t)]^2, dt$$

Step 1: Compute $E[x(t)]$

$$E[x(t)] = \int_0^1 (2)^2, dt = 4 \times 1 = 4$$

Step 2: Analyze $g(t) = 3x(-3t + 5)$

$$E[g(t)] = \int_{-\infty}^{\infty} [3x(-3t + 5)]^2, dt = 9 \int_{-\infty}^{\infty} [x(-3t + 5)]^2, dt$$

Let $u = -3t + 5 \Rightarrow du = -3, dt \Rightarrow dt = \frac{du}{3}$ (with $\frac{1}{3}$ scaling):

$$= 9 \cdot \frac{1}{3} \int_{-\infty}^{\infty} [x(u)]^2, du = 3 \cdot E[x(t)] = 3 \times 4 = 12$$

Step 3: Compute ratio

$$\frac{E[x(t)]}{E[3x(-3t+5)]} = \frac{4}{12} = \frac{1}{3}$$

Question 5: GATE EC 2026, Fourier Series

MCQ

2 Marks

The continuous time signal $x(t)$ is real, periodic with period T and satisfies the Dirichlet conditions.

The Fourier series representation of $x(t) = \sum_{n=-\infty}^{\infty} a_n e^{j(2\pi nt/T)}$ and $x(t)$ satisfies the following:
 $x(t - T/2) = -x(t)$.

For any integer m , which of the following options is correct?

(A) (Correct) $a_{2m} = 0$

(B) $a_{2m} = 1$

(C) $a_{2m} = a_{2m+1}$

(D) $a_{2m} = -1$

Correct Answer: (A)

Detailed Solution – Question 5

Given:

$x(t)$ is real, periodic with period T , satisfying:

$$x\left(t - \frac{T}{2}\right) = -x(t) \quad (\text{half-wave symmetry})$$

Fourier series: $x(t) = \sum_{n=-\infty}^{\infty} a_n e^{j2\pi n t/T}$

Step 1: Effect of half-wave symmetry on Fourier coefficients

Compute the Fourier coefficient a_n :

$$a_n = \frac{1}{T} \int_0^T x(t) e^{-j2\pi n t/T} dt$$

Under the substitution $t \rightarrow t + T/2$:

$$a_n = \frac{1}{T} \int_0^T x\left(t + \frac{T}{2}\right) e^{-j2\pi n(t+T/2)/T} dt$$

$$= e^{-j\pi n} \cdot \frac{1}{T} \int_0^T x\left(t + \frac{T}{2}\right) e^{-j2\pi n t/T} dt$$

Using $x\left(t + \frac{T}{2}\right) = -x(t)$ (from given symmetry, replacing $t \rightarrow t + T/2$):

$$a_n = e^{-j\pi n} \cdot (-a_n) = (-1)^n \cdot (-a_n)$$

Step 2: Determine which coefficients survive

$$a_n = -(-1)^n a_n$$

For **even** n : $a_n = -a_n \Rightarrow a_n = 0$

For **odd** n : $a_n = +a_n$ (no constraint, coefficients can be nonzero)

Conclusion:

For any integer m , $a_{2m} = 0$ (all even-indexed Fourier coefficients are zero). Only odd harmonics exist in the spectrum.

Question 6: GATE EC 2026, LTI Systems Continuous and Discrete

MCQ

1 Mark

The relation between the input current (I) and the output voltage (V) of a circuit is governed by the equation: $C \frac{dV}{dt} = I(t) - m(t)$. The circuit is excited by $I(t) = q\delta(t)$, where q is a real valued constant. V at $t = 0^-$ is V_0 .

Which of the following is an equivalent representation of the above case?

- (A) **(Correct)** $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = V_0 + q/C$
- (B) $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = V_0 + q/C + m(t = 0^-)$
- (C) $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = V_0 - q/C + m(t = 0^-)$
- (D) $C \frac{dV}{dt} = -m(t)$, with $V(t = 0^+) = q/C$

Correct Answer: (A)

Detailed Solution – Question 6

Given:

$$C \frac{dV}{dt} = I(t) - m(t), \quad I(t) = q\delta(t), \quad V(0^-) = V_0$$

Step 1: Effect of impulse current

$I(t) = q\delta(t)$ acts instantaneously at $t = 0$. Integrating both sides from 0^- to 0^+ :

$$C[V(0^+) - V(0^-)] = q - 0 \Rightarrow V(0^+) = V_0 + \frac{q}{C}$$

Step 2: For $t > 0$

The impulse is gone, so:

$$C \frac{dV}{dt} = -m(t), \quad V(0^-) \rightarrow V(0^+) = V_0 + \frac{q}{C}$$

The equivalent representation treats the initial condition as updated by the impulse:

$$C \frac{dV}{dt} = -m(t), \quad \text{with } V(t = 0^-) = V_0 + \frac{q}{C}$$

Question 7: GATE EC 2026, LTI Systems Continuous and Discrete

MCQ

1 Mark

The response of a discrete time system $y[n]$ obeys the following relation:

$$y[n] = \frac{5}{6}y[n-1] - \frac{1}{6}y[n-2] + x[n]$$

The input to the system is $x[n] = \delta[n] - \frac{1}{3}\delta[n-1]$.

Which of the following options is TRUE for $y[n]$?

- (A) **(Correct)** Stable and causal response
- (B) Stable and non-causal response
- (C) Unstable and causal response
- (D) Unstable and non-causal response

Correct Answer: (A)

Detailed Solution – Question 7

Given Difference Equation:

$$y[n] = \frac{5}{6}y[n-1] - \frac{1}{6}y[n-2] + x[n]$$

Input signal:

$$x[n] = \delta[n] - \frac{1}{3}\delta[n-1]$$

To determine the nature of the response, we analyze the system poles.

Taking Z-transform of the system equation under zero initial conditions,

$$Y(z) = \frac{5}{6}z^{-1}Y(z) - \frac{1}{6}z^{-2}Y(z) + X(z)$$

Rearranging terms,

$$Y(z) \left(1 - \frac{5}{6}z^{-1} + \frac{1}{6}z^{-2}\right) = X(z)$$

Hence, the transfer function is

$$H(z) = \frac{Y(z)}{X(z)} = \frac{1}{1 - \frac{5}{6}z^{-1} + \frac{1}{6}z^{-2}}$$

Multiplying numerator and denominator by z^2 ,

$$H(z) = \frac{z^2}{z^2 - \frac{5}{6}z + \frac{1}{6}}$$

The characteristic equation is

$$z^2 - \frac{5}{6}z + \frac{1}{6} = 0$$

Factorizing,

$$\left(z - \frac{1}{2}\right) \left(z - \frac{1}{3}\right) = 0$$

Therefore, the poles are

$$z = \frac{1}{2}, \quad z = \frac{1}{3}$$

Since both poles lie inside the unit circle, the system is **stable**.

Also, the output depends only on present and past values:

$$x[n], \quad y[n-1], \quad y[n-2]$$

Hence, the system is **causal**

Question 8: GATE EC 2026, Sampling

MCQ

1 Mark

Two analog signals $x_1(t)$ and $x_2(t)$ (t in second) are sampled at a rate $F_s = 40$ Hz, where

$$x_1(t) = \cos(20\pi t), t \geq 0, \text{ and } x_2(t) = \cos(100\pi t), t \geq 0.$$

The first ten samples (starting from $t = 0$) are considered for the analysis.

Which of the following statements is TRUE?

- (A) All of the first three samples of $x_1(t)$ are greater than the corresponding samples of $x_2(t)$.
- (B) All of the last three samples of $x_1(t)$ are greater than the corresponding samples of $x_2(t)$.
- (C) All of the samples of $x_2(t)$ are greater than the corresponding samples of $x_1(t)$.
- (D) **(Correct)** All of the fourth to seventh samples of $x_1(t)$ are equal to the corresponding samples of $x_2(t)$.

Correct Answer: (D)

Detailed Solution – Question 8

Given:

Sampling frequency:

$$f_s = 40 \text{ Hz}$$

Signal 1:

$$x_1(t) = \cos(20\pi t)$$

Signal 2:

$$x_2(t) = \cos(100\pi t)$$

The sampling interval is

Therefore,

$$T_s = \frac{1}{40} \text{ sec}$$

The sampled signals are obtained at

$$t = nT_s = \frac{n}{40}, \quad n = 0, 1, 2, \dots$$

Step 1: Samples of $x_1(t)$

$$\begin{aligned} x_1[n] &= \cos\left(20\pi \frac{n}{40}\right) \\ &= \cos\left(\frac{n\pi}{2}\right) \end{aligned}$$

Thus, the sequence becomes

$$1, 0, -1, 0, 1, 0, -1, 0, 1, 0, \dots$$

Step 2: Samples of $x_2(t)$

$$\begin{aligned} x_2[n] &= \cos\left(100\pi \frac{n}{40}\right) \\ &= \cos\left(\frac{5n\pi}{2}\right) \end{aligned}$$

Using periodicity of cosine,

$$\cos\left(\frac{5n\pi}{2}\right) = \cos\left(\frac{n\pi}{2}\right)$$

Hence,

$$x_2[n] = x_1[n]$$

Therefore, all corresponding samples of the two sequences are equal.

In particular, the fourth to seventh samples are equal.

Question 9: GATE EC 2026, Laplace Transform

MCQ

1 Mark

The Laplace Transform of the signal $x(t) = u(t-2) * (t \cdot u(t))$ is given by which of the following expressions?

[Note: "*" represents convolution operator]

- (A) $\frac{e^{-2s}}{s^2(s-2)}$
- (B) $\frac{e^{-2(s-2)}}{s^3}$
- (C) $\frac{se^{-2s}}{(s-2)^2}$
- (D) **(Correct)** $\frac{e^{-2s}}{s^3}$

Correct Answer: (D)

Detailed Solution – Question 9

Given:

$$x(t) = u(t - 2) * (tu(t))$$

where $*$ denotes convolution.

Using the convolution property of Laplace Transform,

$$\mathcal{L}\{f(t) * g(t)\} = F(s)G(s)$$

So,

$$X(s) = \mathcal{L}\{u(t - 2)\} \times \mathcal{L}\{tu(t)\}$$

Step 1: Laplace Transform of $u(t - 2)$

Using the standard formula,

For $a = 2$,

$$\mathcal{L}\{u(t - 2)\} = \frac{e^{-2s}}{s}$$

Step 2: Laplace Transform of $tu(t)$

Using the standard result,

Therefore,

$$\mathcal{L}\{tu(t)\} = \frac{1}{s^2}$$

Step 3: Apply convolution property

$$X(s) = \frac{e^{-2s}}{s} \times \frac{1}{s^2}$$

Hence,

$$X(s) = \frac{e^{-2s}}{s^3}$$

Question 10: GATE EC 2025, Fourier Series

MSQ

2 Marks

Let $f(t)$ be a periodic signal with fundamental period $T_0 > 0$. Consider the signal $y(t) = f(\alpha t)$, where $\alpha > 1$.

The Fourier series expansions of $f(t)$ and $y(t)$ are given by

$$f(t) = \sum_{k=-\infty}^{\infty} c_k e^{j\frac{2\pi}{T_0}kt} \text{ \& } y(t) = \sum_{k=-\infty}^{\infty} d_k e^{j\frac{2\pi}{T_0}\alpha kt}$$

Which of following statement is/are TRUE?

- (A) **(Correct)** $c_k = d_k$ for all k
- (B) $y(t)$ is periodic with a fundamental period αT_0
- (C) $c_k = d_k/\alpha$ for all k
- (D) **(Correct)** $y(t)$ is periodic with a fundamental period T_0/α

Correct Answer: (A, D)

Detailed Solution – Question 10

Let the original signal $f(t)$ have period T_0 . Then:

$$f(t + T_0) = f(t)$$

Now consider the time-scaled signal:

$$y(t) = f(\alpha t) \text{ To find its period, assume } y(t + T) = y(t):$$

$$f(\alpha(t + T)) = f(\alpha t) \Rightarrow f(\alpha t + \alpha T) = f(\alpha t)$$

Since $f(t)$ is periodic with period T_0 , this implies:

$$\alpha T = T_0 \Rightarrow T = \frac{T_0}{\alpha} \text{ Therefore, } y(t) \text{ is periodic with fundamental period } \frac{T_0}{\alpha}$$

So, (D) is TRUE, and (B) is FALSE

Fourier Series Comparison: The Fourier series of $f(t)$ is:

$$f(t) = \sum_{k=-\infty}^{\infty} c_k e^{j \frac{2\pi}{T_0} k t} \text{ Now } y(t) = f(\alpha t) ?$$

$$y(t) = \sum_{k=-\infty}^{\infty} c_k e^{j \frac{2\pi}{T_0} k \alpha t} = \sum_{k=-\infty}^{\infty} d_k e^{j \frac{2\pi}{T_0/\alpha} k t}$$

Hence, $d_k = c_k$ for all k

So (A) is TRUE

(C) is FALSE

Question 11: GATE EC 2025, Sampling

MCQ

2 Marks

Consider a continuous-time finite-energy signal $f(t)$ whose Fourier transform vanishes outside the frequency interval $[-\omega_c, \omega_c]$, where ω_c is in rad/sec.

The signal $f(t)$ is uniformly sampled to obtain $y(t) = f(t)p(t)$. Here,

$$p(t) = \sum_{n=-\infty}^{\infty} \delta(t - \tau - nT_s),$$

with $\delta(t)$ being the Dirac impulse, $T_s > 0$, and $\tau > 0$. The sampled signal $y(t)$ is passed through an ideal lowpass filter $h(t) = \omega_c T_s \frac{\sin(\omega_c t)}{\pi \omega_c t}$ with cutoff frequency ω_c and passband gain T_s .

The output of the filter is given by _____ .

(A) **(Correct)** $f(t)$ if $T_s < \pi/\omega_c$

(B) $f(t - \tau)$ if $T_s < \pi/\omega_c$

(C) $f(t - \tau)$ if $T_s < 2\pi/\omega_c$

(D) $T_s f(t)$ if $T_s < 2\pi/\omega_c$

Correct Answer: (A)

Detailed Solution – Question 11

We are given that $f(t)$ is bandlimited to $[-\omega_c, \omega_c]$, meaning its Fourier transform $F(j\omega)$ is zero outside this interval.

Step 1: Sampling process Sampling is done using the impulse train:

$$p(t) = \sum_{n=-\infty}^{\infty} \delta(t - \tau - nT_s)$$

Multiplying this with $f(t)$ gives:

$$y(t) = f(t) \cdot p(t) = \sum_{n=-\infty}^{\infty} f(\tau + nT_s) \cdot \delta(t - \tau - nT_s)$$

This means we are taking samples of $f(t)$ at times $t = \tau + nT_s$.

Step 2: Filtering with ideal LPF

The sampled signal $y(t)$ is passed through an ideal lowpass filter with impulse response:

$$h(t) = T_s \cdot \text{sinc}\left(\frac{\omega_c t}{\pi}\right)$$

The output of the system is:

$$z(t) = y(t) * h(t) = \sum_{n=-\infty}^{\infty} f(\tau + nT_s) \cdot h(t - \tau - nT_s)$$

Substitute $h(t)$:

$$z(t) = T_s \sum_{n=-\infty}^{\infty} f(\tau + nT_s) \cdot \text{sinc}\left(\frac{\omega_c(t - \tau - nT_s)}{\pi}\right)$$

This is the reconstruction formula for $f(t)$, but it appears to reconstruct $f(t - \tau)$ at first glance.

Step 3: Time-invariance and interpretation

Here's the key point: Even though the samples are taken at $t = \tau + nT_s$, the reconstruction system is linear and time-invariant. A shift in sampling time does not affect the shape of the reconstructed signal, because the sinc interpolation is symmetric and consistent.

Hence, the filter effectively undoes the delay, and we recover the original signal $f(t)$.

Step 4: Condition for perfect reconstruction

Perfect reconstruction using sinc interpolation is possible only if there is no aliasing, which happens when:

$$T_s < \frac{\pi}{\omega_c}$$

This is the Nyquist condition for bandlimited signals.

Question 12: GATE EC 2025, DTFS, DTFT and DFT

MSQ

1 Mark

Let $x[n]$ be a discrete-time signal whose z -transform is $X(z)$.

Which of the following statements is/are TRUE?

- (A) The discrete-time Fourier transform (DTFT) of $x[n]$ always exists
- (B) The region of convergence (ROC) of $X(z)$ contains neither poles nor zeros
- (C) **(Correct)** The discrete-time Fourier transform (DTFT) exists if the region of convergence (ROC) contains the unit circle
- (D) **(Correct)** If $x[n] = \alpha\delta[n]$, where $\delta[n]$ is the unit impulse and α is a scalar, then the region of convergence (RoC) is the entire z -plane

Correct Answer: (C, D)

Detailed Solution – Question 12

- (A) The DTFT does not always exist. It exists only if the signal is absolutely summable: $\sum_{n=-\infty}^{\infty} |x[n]| < \infty$. So this statement is False.
- (B) The region of convergence (RoC) contains no poles, but it can include zeros (since zeros do not affect convergence). So this statement is False.
- (C) This is True. The DTFT of $x[n]$ exists iff the RoC of $X(z)$ includes the unit circle $|z| = 1$.
- (D) For $x[n] = \alpha\delta[n]$, the z -transform is $X(z) = \alpha$ (a constant), which is defined for all $z \in \mathbb{C}$. Hence, the RoC is the entire z -plane, so this is True.

Question 13: GATE EC 2025, Fourier Transforms, Frequency Response and Correlation

MCQ

1 Mark

Consider a continuous-time, real-valued signal $f(t)$ whose Fourier transform $F(\omega) = \int_{-\infty}^{\infty} f(t) \exp(-j\omega t) dt$ exists.

Which one of the following statements is always TRUE?

- (A) **(Correct)** $|F(\omega)| \leq \int_{-\infty}^{\infty} |f(t)| dt$
- (B) $|F(\omega)| > \int_{-\infty}^{\infty} |f(t)| dt$
- (C) $|F(\omega)| \leq \int_{-\infty}^{\infty} f(t) dt$
- (D) $|F(\omega)| \geq \int_{-\infty}^{\infty} f(t) dt$

Correct Answer: (A)

Detailed Solution – Question 13

We are given that $F(\omega) = \int_{-\infty}^{\infty} f(t) e^{-j\omega t} dt$ exists.

This means that $f(t)$ is absolutely integrable, i.e., $\int_{-\infty}^{\infty} |f(t)| dt < \infty$.

To find a general bound on $|F(\omega)|$, we apply the triangle inequality for integrals:

$$|F(\omega)| = \left| \int_{-\infty}^{\infty} f(t) e^{-j\omega t} dt \right| \leq \int_{-\infty}^{\infty} |f(t) e^{-j\omega t}| dt = \int_{-\infty}^{\infty} |f(t)| dt$$

This inequality is always true.

Now check the options:

- (A) $|F(\omega)| \leq \int_{-\infty}^{\infty} |f(t)| dt$ – Correct
- (B) Strict inequality – not always true
- (C) Inequality involving $\int f(t) dt$ – this can be 0 for symmetric signals (e.g., odd functions), but $|F(\omega)|$ may be nonzero
- (D) Similar issue – not always true


Question 14: GATE EC 2025, LTI Systems Continuous and Discrete

MCQ

1 Mark

Consider the discrete-time system below with input $x[n]$ and output $y[n]$. In the figure, $h_1[n]$ and $h_2[n]$ denote the impulse responses of LTI Subsystems 1 and 2, respectively. Also, $\delta[n]$ is the unit impulse, and $b > 0$.

Assuming $h_2[n] \neq \delta[n]$, the overall system (denoted by the dashed box) is



- (A) linear and time invariant
- (B) linear and time variant
- (C) nonlinear and time invariant
- (D) **(Correct)** nonlinear and time variant

Correct Answer: (D)

Detailed Solution – Question 14

$$y_2[n] = \{y_1[n] + b\delta[n]\} * h_2[n]$$

$$\text{Output } y[n] = \{x[n] * h_1[n] + b\delta[n]\} * h_2[n] - b\delta[n]$$

$$y(n) = \underbrace{x[n] * h_1[n] * h_2[n]}_{\text{This is LTI}} + \underbrace{b h_2[n] - b\delta[n]}_{\text{N.L. terms}}$$

$$h_2[n] \neq \delta[n]$$

If we consider $h_2[n] = \text{nu}[n]$

$y[n]$ is variable function of time $\Rightarrow$ Time variant So, Non Linear & Time variant.

Question 15: GATE EC 2024, DTFS, DTFT and DFT

NAT

2 Marks

The relationship between any N-length sequence $x[n]$ and its corresponding N-point discrete Fourier transform $X[k]$ is defined as

$$X[k] = F\{x[n]\}.$$

Another sequence $y[n]$ is formed as below

$$y[n] = F\{F\{F\{F\{x[n]\}\}\}\}$$

For the sequence $x[n] = \{1, 2, 1, 3\}$, the value of $Y[0]$ is _____

Detailed Solution – Question 15

$$y[n] = N^2 x[n]$$

$$y[n] = N^2 x[n]$$

$$\begin{aligned} Y[k]|_{K=0} &= \sum_{n=0}^3 y[n] = \sum_{n=0}^3 N^2 x[n] \\ &= N^2 [x[0] + x[1] + x[2] + x[3]] \\ &= (4)^2 [1 + 2 + 1 + 3] = 16 \times 7 = 112 \end{aligned}$$

$$y[n] = N^2 x[n] \quad \because N = 4$$

Question 16: GATE EC 2024, Basics of Signals and Systems

MSQ

2 Marks

The radian frequency value(s) for which the discrete time sinusoidal signal $x[n] = A \cos(\Omega n + \pi/3)$ has a period of 40 is/are _____

(A) **(Correct)** 0.15π

(B) 0.225π

(C) **(Correct)** 0.3π

(D) **(Correct)** 0.45π

Correct Answer: (A, C, D)

Detailed Solution – Question 16

$$x[n] = A \cos \left[\Omega n + \frac{\pi}{3} \right]$$

$$N = 40$$

$$\Omega = ?$$

$$\frac{\Omega}{2\pi} = \frac{m}{N}$$

$$\frac{\Omega}{2\pi} = \frac{m}{40}$$

$$\Omega = m \cdot \frac{2\pi}{40} = \pi \cdot m(0.05)$$

$$\Omega = 0.05\pi$$

$$m = 1 \quad \Omega = 0.05\pi$$

$$m = 2 \quad \Omega = 0.10\pi$$

$$m = 3 \quad \Omega = 0.15\pi$$

$$m = 4 \quad \Omega = 0.20\pi$$

$$m = 5 \quad \Omega = 0.25\pi$$

$$m = 6 \quad \Omega = 0.30\pi$$

$$m = 7 \quad \Omega = 0.35\pi$$

$$m = 8 \quad \Omega = 0.40\pi$$

$$m = 9 \quad \Omega = 0.45\pi$$

Question 17: GATE EC 2024, Fourier Transforms, Frequency Response and Correlation

MCQ

2 Marks

A continuous time signal $x(t) = 2 \cos(8\pi t + \pi/3)$ is sampled at a rate of 15 Hz. The sampled signal $x_s(t)$ when passed through an LTI system with impulse response

$$h(t) = \left(\frac{\sin 2\pi t}{\pi t} \right) \cos(38\pi t - \pi/2)$$

produces an output $x_0(t)$. The expression for $x_0(t)$ is -----

- (A) $15 \sin(38\pi t + \pi/3)$
- (B) $15 \sin(38\pi t - \pi/3)$
- (C) **(Correct)** $15 \cos(38\pi t - \pi/6)$
- (D) $15 \cos(38\pi t + \pi/6)$

Correct Answer: (C)

Detailed Solution – Question 17



$$x(t) = 2 \cos \left(8\pi t + \frac{\pi}{3} \right), \quad \omega_o = 8\pi$$

$$f_s = 15 \text{ Hz}$$

$$x(t) \rightarrow \text{sample } x_s(t) \rightarrow h(t)x_o(t)$$

$$\Rightarrow h(t) = \frac{\sin 2\pi t}{\pi t} \cos \left(38\pi t - \frac{\pi}{2} \right)$$

$$\text{Let } p(t) = \frac{\sin 2\pi t}{\pi t}$$



After sampling:

$$X_s(\omega) = f_s \sum_{n=-\infty}^{\infty} X(\omega - n\omega_s)$$

Frequency components present in sampler output $n\omega_s \pm \omega_o$

$$\omega_o, \omega_s + \pm\omega_o, 2\omega_s \pm \omega_o, \dots$$

$$8\pi, 30\pi \pm 8\pi, 60\pi \pm 8\pi, \dots$$

$$8\pi, 22\pi, 38\pi, 52\pi, 68\pi, \dots \text{ (rad/sec)}$$

System will pass '38π' component of input.

$$x_o(t) = 2 \times \frac{f_s}{2} \cos \left[38\pi t + \frac{\pi}{3} - \frac{\pi}{2} \right] = 15 \cos \left(38\pi t - \frac{\pi}{6} \right)$$





As per GATE official Answer Key-MTA

Question 18: GATE EC 2024, Fourier Transforms, Frequency Response and Correlation

MCQ

2 Marks

Consider two continuous time signals $x(t)$ and $y(t)$ as shown below





If $X(f)$ denotes the Fourier transform of $x(t)$, then the Fourier transform of $y(t)$ is ----

- (A) $-4X(4f)e^{-j\pi f}$
- (B) **(Correct)** $-4X(4f)e^{-j4\pi f}$
- (C) $-\frac{1}{4}X(f/4)e^{-j\pi f}$
- (D) $-\frac{1}{4}X(f/4)e^{-j4\pi f}$



Correct Answer: (B)

Detailed Solution – Question 18

Given



Length of $x(t)$ is 1 and length of $y(t)$ is 4.



$$\therefore y(t) = -x\left(\frac{t-2}{4}\right)$$

$$y(t) = -x\left(\frac{t}{4} - \frac{2}{4}\right) = -x\left(\frac{t}{4} - \frac{1}{2}\right)$$

On taking Fourier transform, we get

$$x(t) \leftrightarrow X(f)$$

Question 19: GATE EC 2024, LTI Systems Continuous and Discrete

MSQ

1 Mark

For a causal discrete-time LTI system with transfer function

$$H(z) = \frac{2z^2+3}{(z+\frac{1}{3})(z-\frac{1}{3})}$$

which of the following statements is/are true?

- (A) **(Correct)** The system is stable.
- (B) The system is a minimum phase system.
- (C) **(Correct)** The initial value of the impulse response is 2.
- (D) **(Correct)** The final value of the impulse response is 0.

Correct Answer: (A, C, D)

Detailed Solution – Question 19

Given: $H(z) = \frac{2z^2+3}{(z+\frac{1}{3})(z-\frac{1}{3})}$

System is non-minimum phase system. Since zero are lying outside the unit circle.

Final value:

$$h(\infty) = \lim_{z \rightarrow 1} (z-1) \frac{2z^2+3}{(z+\frac{1}{3})(z-\frac{1}{3})} = 0$$

Initial value:

$$\begin{aligned} h(0) &= \lim_{z \rightarrow \infty} \frac{(2z^2+3)}{(z+\frac{1}{3})(z-\frac{1}{3})} = \lim_{z \rightarrow \infty} \frac{z^2 [2 + \frac{3}{z^2}]}{z^2 [1 + \frac{1}{3z}] [1 - \frac{1}{3z}]} \\ &= \lim_{z \rightarrow \infty} \frac{[2 + \frac{3}{z^2}]}{[1 + \frac{1}{3z}] [1 - \frac{1}{3z}]} = \frac{2}{1 \times 1} = 2 \\ |z| &= \frac{1}{3} = 0.33 \end{aligned}$$

$$z = -\frac{1}{3}, z = \frac{1}{3}$$

System is stable. Since | pole | < 1 i.e. pole are lying inside the unit circle.

Question 20: GATE EC 2024, LTI Systems Continuous and Discrete

MCQ

1 Mark

A causal and stable LTI system with impulse response $h(t)$ produces an output $y(t)$ for an input signal $x(t)$. A signal $x(0.5t)$ is applied to another causal and stable LTI system with impulse response $h(0.5t)$. The resulting output is _____

- (A) **(Correct)** $2y(0.5t)$
- (B) $4y(0.5t)$
- (C) $0.25y(2t)$

(D) $0.25y(0.25t)$

Correct Answer: (A)

Detailed Solution – Question 20

$$y(t) = x(t) * h(t)$$

$$x(t) \leftrightarrow X(\omega)$$

$$x(0.5t) \leftrightarrow 2X(2\omega)$$

$$h(0.5t) \leftrightarrow 2H(2\omega)$$

$$y(t) \leftrightarrow Y(\omega)$$

$$Y(\omega) \leftrightarrow X(\omega) \times H(\omega)$$

After scaling,

$$Y_1(\omega) = 2X(2\omega) \times 2H(2\omega)$$

$$= 4X(2\omega) \times H(2\omega) \text{ After taking inverser Fourier transform } y_1(t) = 2y(0.5t)$$


Question 21: GATE EC 2023, LTI Systems Continuous and Discrete

NAT

2 Marks

Let $X(t)$ be a white Gaussian noise with power spectral density $\frac{1}{2}$ W/Hz. If $X(t)$ is input to an LTI system with impulse response $e^{-t}u(t)$. The average power of the system output is ___ W. (Rounded off to two decimal place).

Detailed Solution – Question 21



$$h(t) = e^{-t}u(t)$$

Given: Input PSD

$$\Rightarrow S_x(f) = \frac{1}{2} \text{ W/Hz}$$

We know output PSD,

$$S_Y(f) = S_X(f)|H(f)|^2$$

$$S_Y(f) = \frac{1}{2}|H(f)|^2$$


$$\begin{aligned} \text{Power } [y(t)] &= \int_{-\infty}^{\infty} S_Y(f) df = \int_{-\infty}^{\infty} \frac{1}{2} |H(f)|^2 df \\ &= \frac{1}{2} \int_{-\infty}^{\infty} h^2(t) dt = \frac{1}{2} \int_0^{\infty} e^{-2t} dt \\ &= \frac{1}{2} \times \frac{1}{2} = \frac{1}{4} = 0.25 \text{ W} \end{aligned}$$


Question 22: GATE EC 2023, Fourier Transforms, Frequency Response and Correlation

NAT

2 Marks



Let $x_1(t) = u(t + 1.5) - u(t - 1.5)$ and $x_2(t)$ is shown in the figure below. For $y(t) = x_1(t) * x_2(t)$, the $\int_{-\infty}^{\infty} y(t) dt$ is (rounded off to the nearest integer).





Detailed Solution – Question 22

$$x_1(t) = u(t + 1.5) - u(t - 1.5)$$



$$\Rightarrow x_1(t) = \text{rect}\left(\frac{t}{3}\right)$$

$$]x_1(t) = \text{rect}\left(\frac{t}{3}\right) \xleftrightarrow{FT} 3\text{Sa}(1.5\omega)$$

$$\text{Now, } x_2(t) = \delta(t + 3) + \text{rect}\left(\frac{t}{2}\right) + 2\delta(t - 2)$$

Taking Fourier transform

$$X_2(\omega) = e^{3j\omega} + 2\text{Sa}(\omega) + 2e^{-2j\omega}$$

$$y(t) = x_1(t) * x_2(t)$$

$$Y(\omega) = X_1(\omega) \cdot X_2(\omega)$$

$$Y(\omega) = \int_{-\infty}^{\infty} y(t) \cdot e^{-j\omega t} \cdot dt$$

We know

$$\therefore \int_{-\infty}^{\infty} y(t) = Y(0)$$


$$\therefore Y(0) = X_1(0) \cdot X_2(0) = 3[1 + 2 + 2] = 15$$

Question 23: GATE EC 2023, Sampling

MCQ

2 Marks

Let $x_1(t)$ and $x_2(t)$ be two band-limited signals having bandwidth $B = 4\pi \times 10^3 \text{ rad/sec}$. In the figure below, the Nyquist sampling frequency, in rad/s, required to sample $y(t)$, is





- (A) $20\pi \times 10^3$
- (B) $40\pi \times 10^3$
- (C) $8\pi \times 10^3$
- (D) **(Correct)** $32\pi \times 10^3$

Correct Answer: (D)



Detailed Solution – Question 23

Given that, $x_1(t)$ and $x_2(t)$ are two bandlimited signals having bandwidth $B = 4\pi \times 10^3 \text{ rad/sec}$.



and

$$y(t) = x_2(t) \cos(12\pi \times 10^3 t) + x_1(t) \cos(4\pi \times 10^3 t)$$



So,

$$\text{Nyquist Rate} = 2\omega_{\max} = 2[16\pi \times 10^3] = 32\pi \times 10^3 \text{ rad/sec}$$

Question 24: GATE EC 2023, LTI Systems Continuous and Discrete

MCQ

2 Marks

Let $x(t) = 10 \cos(10.5Wt)$ be passed through an LTI system having impulse response $h(t) = \pi \left(\frac{\sin Wt}{\pi t} \right)^2 \cos 10Wt$. The output of the system is

- (A) **(Correct)** $\left(\frac{15W}{4} \right) \cos(10.5Wt)$
- (B) $\left(\frac{15W}{2} \right) \cos(10.5Wt)$
- (C) $\left(\frac{15W}{8} \right) \cos(10.5Wt)$
- (D) $(15W) \cos(10.5Wt)$



Correct Answer: (A)

Detailed Solution – Question 24



Given $h(t)$ is Real and Even. When sinusoidal input applied to LTI system having even impulse response, then output will also be sinusoidal.

here, $y(t) = H(W)|_{W=10.5W} \cdot 10 \cos(10.5Wt)$

let, $h(t) = f(t) \cos 10Wt$ where, $f(t) = \pi \left(\frac{\sin Wt}{\pi t} \right)^2$



$$\text{Now; } H(W) = \frac{1}{2} [F(W + 10W) + F(W - 10W)]$$



$$\therefore H(W)|_{W=10.5W} = \frac{3}{8}W$$

Hence,

$$\begin{aligned} y(t) &= \left(\frac{3}{8}W \right) (10 \cos 10.5Wt) \\ &= \frac{15}{4}W \cos 10.5Wt \end{aligned}$$

Question 25: GATE EC 2023, DTFS, DTFT and DFT

MCQ

2 Marks

Let an input $x[n]$ having discrete time Fourier transform.

$X(e^{j\Omega}) = 1 - e^{-j\Omega} + 2e^{-3j\Omega}$ be passed through an LTI system. The frequency response of the LTI system is $H(e^{j\Omega}) = 1 - \frac{1}{2}e^{-j2\Omega}$. The output $y[n]$ of the system is

(A)

$$\delta[n] + \delta[n-1] - \frac{1}{2}\delta[n-2] - \frac{5}{2}\delta[n-3] + \delta[n-5]$$

(B)

$$\delta[n] - \delta[n-1] - \frac{1}{2}\delta[n-2] - \frac{5}{2}\delta[n-3] + \delta[n-5]$$

(C) (Correct)

$$\delta[n] - \delta[n-1] - \frac{1}{2}\delta[n-2] + \frac{5}{2}\delta[n-3] - \delta[n-5]$$

(D)

$$\delta[n] + \delta[n-1] + \frac{1}{2}\delta[n-2] + \frac{5}{2}\delta[n-3] + \delta[n-5]$$

Correct Answer: (C)

Detailed Solution – Question 25

$$\begin{aligned} y[n] &= x[n] * h[n] \\ Y(e^{j\Omega}) &= X(e^{j\Omega}) H(e^{j\Omega}) \\ &= [1 - e^{-j\Omega} + 2e^{-3j\Omega}] \left[1 - \frac{1}{2}e^{-j2\Omega} \right] \\ &= 1 - e^{-j\Omega} + 2.5e^{-3j\Omega} - 0.5e^{-j2\Omega} - e^{-j5\Omega} \end{aligned}$$

Taking IDTFT;

$$y[n] = \delta[n] - \delta[n-1] - 0.5\delta[n-2] + 2.5\delta[n-3] - \delta[n-5]$$

Question 26: GATE EC 2023, DTFS, DTFT and DFT

MCQ

2 Marks

Consider a discrete-time periodic signal with period $N = 5$. Let the discrete-time Fourier series (DTFS) representation be $x[n] = \sum_{k=0}^4 a_k e^{\frac{jk2\pi n}{5}}$, where $a_0 = 1$, $a_1 = 3j$, $a_2 = 2j$, $a_3 = -2j$ and $a_4 = -3j$. The value of the sum $\sum_{n=0}^4 x[n] \sin \frac{4\pi n}{5}$ is

(A) (Correct) -10

(B) 10

(C) -2

(D) 2

Correct Answer: (A)

Detailed Solution – Question 26

Let, $I = \sum_{n=0}^4 x(n) \sin \frac{4\pi n}{5}$

$$\begin{aligned} &= \frac{1}{2j} \sum_{n=0}^4 x(n) \cdot \left[e^{j\frac{4\pi n}{5}} - e^{-j\frac{4\pi n}{5}} \right] \\ &= \frac{1}{2j} \left[\sum_{n=0}^4 x(n) e^{j\frac{4\pi n}{5}} - \sum_{n=0}^4 x(n) \cdot e^{-j\frac{4\pi n}{5}} \right] \quad (i) \end{aligned}$$

As we know,

$$a_k = \frac{1}{N} \sum_{n=0}^4 x(n) \cdot e^{-jk \cdot \frac{2\pi}{N} n}$$

$$= \frac{1}{5} \sum_{n=0}^4 x(n) \cdot e^{-j\frac{2\pi}{N} kn}$$

$$\text{Put } K = 2; \quad a_2 = \frac{1}{5} \sum_{n=0}^4 x(n) \cdot e^{-j\frac{4\pi n}{5}}$$

Put

$$K = -2; \quad a_{-2} = \frac{1}{5} \sum_{n=0}^4 x(n) \cdot e^{j\frac{4\pi n}{5}}$$

From equation (i),

$$I = \frac{1}{2j} [5a_{-2} - 5a_2] = \frac{5}{2j} [a_3 - a_2]$$

$$I = \frac{5}{2j} [-2j - 2j] = -10$$

$$\begin{aligned} a_{-2} &= a_{-2+N} \\ \therefore &= a_{-2+5} \\ &= a_3 \end{aligned}$$

Question 27: GATE EC 2023, Basics of Signals and Systems

MCQ

1 Mark

In the table shown below, match the signal type with its spectral characteristics.

Signal type	Spectral Characteristics
(i) Continuous, aperiodic	(i) Continuous, aperiodic
(ii) Continuous, periodic	(ii) Continuous, periodic
(iii) Discrete, aperiodic	(iii) Discrete, aperiodic
(iv) Discrete, periodic	(iv) Discrete, periodic

- (A) (i) $\rightarrow$ (a), (ii) $\rightarrow$ (b), (iii) $\rightarrow$ (c), (iv) $\rightarrow$ (d)
- (B) **(Correct)** (i) $\rightarrow$ (a), (ii) $\rightarrow$ (c), (iii) $\rightarrow$, (iv) $\rightarrow$ (d)
- (C) (i) $\rightarrow$ (d), (ii) $\rightarrow$ (b), (iii) $\rightarrow$ (c), (iv) $\rightarrow$ (a)
- (D) (i) $\rightarrow$ (a), (ii) $\rightarrow$ (c), (iii) $\rightarrow$ (d), (iv) $\rightarrow$ (b)

Correct Answer: (B)

Question 28: GATE EC 2023, Fourier Transforms, Frequency Response and Correlation

MCQ

1 Mark

The Fourier transform $X(\omega)$ of $x(t) = e^{-t^2}$ is

- (A) $\sqrt{\pi}e^{\frac{\omega^2}{2}}$
- (B) $\frac{e^{-\frac{\omega^2}{4}}}{2\sqrt{\pi}}$
- (C) **(Correct)** $\sqrt{\pi}e^{-\frac{\omega^2}{4}}$
- (D) $\sqrt{\pi}e^{-\frac{\omega^2}{2}}$

Correct Answer: (C)

Detailed Solution – Question 28

We know;

$$e^{-at^2}; a > 0 \xrightarrow{FT} \sqrt{\frac{\pi}{a}} \cdot e^{-\omega^2/4a}$$

Here; $a = 1$

$$\therefore X(\omega) = \sqrt{\pi} \cdot e^{-\omega^2/4}$$

Question 29: GATE EC 2023, Basics of Signals and Systems



MCQ

1 Mark

Let $m(t)$ be a strictly band-limited signal with bandwidth B and energy E . Assuming $\omega_0 = 10B$, the energy in the signal $m(t) \cos \omega_0 t$ is

- (A) $\frac{E}{4}$
- (B) **(Correct)** $\frac{E}{2}$
- (C) E
- (D) $2E$

Correct Answer: (B)





$$\text{Energy } (E) = \frac{1}{2\pi} \int_{-B}^B (1)^2 \cdot d\omega$$

$$E = \frac{B}{\pi}$$

Now, let $y(t) = m(t) \cos \omega_0 t$

$$Y(\omega) = \frac{1}{2} [M(\omega - \omega_0) + M(\omega + \omega_0)]$$

Here; $\omega_0 = 10B$



Now,

$$\begin{aligned} \text{Energy } (E') &= \frac{1}{2\pi} \int_{-\infty}^{\infty} |Y(\omega)|^2 \cdot d\omega \\ &= \frac{1}{2\pi} \left[\int_{-11B}^{-9B} \left(\frac{1}{2}\right)^2 \cdot d\omega + \int_{9B}^{11B} \left(\frac{1}{2}\right)^2 \cdot d\omega \right] \end{aligned}$$

$$= \frac{1}{2\pi} \left[\frac{1}{4} \times 2B + \frac{1}{4} \times 2B \right]$$

$$E' = \frac{B}{\pi} = E$$

Question 30: GATE EC 2023, LTI Systems Continuous and Discrete

MCQ

1 Mark

Consider a system with input $x(t)$ and output $y(t) = x(e^t)$. The system is

- (A) Causal and time invariant
- (B) **(Correct)** Non-causal and time varying
- (C) Causal and time varying
- (D) Non-causal and time invariant

Correct Answer: (B)

Detailed Solution – Question 30

We have, $y(t) = x(e^t)$

At $t = 0$

$$y(0) = x(1)$$

i.e. present value of output depends on future value of input, hence it is non-causal.

For Time Variant: Delay the input,

$$y(t) = x(e^t - t_0) \quad \dots(i)$$

Delay the output,

$$y(t - t_0) = x(e^{t-t_0}) \quad \dots(ii)$$

i.e. equations (i) $\neq$ (ii)

Hence, it is time variant system.

Question 31: GATE EC 2022, DTFS, DTFT and DFT

NAT

2 Marks

For a vector $\bar{x} = [x[0], x[1], \dots, x[7]]$, the 8-point discrete Fourier transform (DFT) is denoted by $\bar{X} = DFT(\bar{x}) = [X[0], X[1], \dots, X[7]]$, where $X[k] = \sum_{n=0}^7 x[n] \exp(-j \frac{2\pi}{8} nk)$. Here, $j = \sqrt{-1}$. If $\bar{x} = [1, 0, 0, 0, 2, 0, 0, 0]$ and $\bar{y} = DFT(DFT(\bar{x}))$, then the value of $y[0]$ is _____ (rounded off to one decimal place).

Detailed Solution – Question 31

$$X[K] = \sum_{n=0}^7 x[n] \exp\left(-j \frac{2\pi}{8} nk\right)$$

$$\bar{y} = DFT(DFT(\bar{x})) \text{ where}$$

$$\bar{x} = [x[0], x[1], \dots, x[7]]$$

$$y(0) = ? \quad x[n] = [1, 0, 0, 0, 2, 0, 0, 0]$$

$$x[n] \xrightarrow{DFT} \xrightarrow{DFT} N \cdot x(-k) = \bar{y}(n)$$

$$\bar{y}(n) = N \cdot x(-k)|_{mod.N} = N \cdot x(N.K), N = 8$$

$$\bar{y}(n) = 8[1, 0, 0, 0, 2, 0, 0, 0]$$

$$\bar{y}(n) = [8, 0, 0, 0, 16, 0, 0, 0]$$

$$y(0) = 8$$


Question 32: GATE EC 2022, LTI Systems Continuous and Discrete

MSQ

2 Marks

The outputs of four systems (S_1, S_2, S_3, S_4) corresponding to the input signal $\sin(t)$, for all time t , are shown in the figure.


Based on the given information, which of the four systems is/are definitely NOT LTI (linear and time-invariant)?



- (A) S_1
- (B) S_2
- (C) **(Correct)** S_3
- (D) **(Correct)** S_4

Correct Answer: (C, D)

Detailed Solution – Question 32



Since, LTI systems does not change the frequency of sinusoidal input. So S_3 and S_4 are definitely not LTI as input and output sinusoidal frequencies are different.

Question 33: GATE EC 2022, LTI Systems Continuous and Discrete

NAT

1 Mark

Let $x_1(t) = e^{-t}u(t)$ and $x_2(t) = u(t) - u(t-2)$, where $u(\cdot)$ denotes the unit step function. If $y(t)$ denotes the convolution of $x_1(t)$ and $x_2(t)$, then $\lim_{t \rightarrow \infty} y(t) = \text{-----}$ (rounded off to one decimal place).

Detailed Solution – Question 33

$$\begin{aligned}
 x_1(t) &= e^{-1}U(t) \xleftrightarrow{L.T.} \frac{1}{(s+1)} \\
 x_2(t) &= U(t) - U(t-2) \xleftrightarrow{L.T.} \frac{1}{s} - \frac{e^{-2s}}{s} = \frac{1 - e^{-2s}}{s} \\
 y(t) &= x_1(t) \otimes x_2(t) \xleftrightarrow{L.T.} \frac{(1 - e^{-2s})}{s(s+1)} \\
 y(t) &\xleftrightarrow{L.T.} \frac{1 - e^{-2s}}{s(s+1)} \\
 \lim_{t \rightarrow \infty} y(t) &= \lim_{s \rightarrow 0} \frac{s(1 - e^{-2s})}{s(s+1)} = 0
 \end{aligned}$$

Question 34: GATE EC 2022, DTFS, DTFT and DFT

MCQ

1 Mark

The Fourier transform $X(j\omega)$ of the signal $x(t) = \frac{t}{(1+t^2)^2}$ is -----.

- (A) **(Correct)** $\frac{\pi}{2j}\omega e^{-|\omega|}$
- (B) $\frac{\pi}{2}\omega e^{-|\omega|}$
- (C) $\frac{\pi}{2j}e^{-|\omega|}$
- (D) $\frac{\pi}{2}e^{-|\omega|}$

Correct Answer: (A)

Detailed Solution – Question 34

$$\begin{aligned}
 x(t) &= \frac{t}{(1+t^2)^2} \text{ As we know that FT of } te^{-|t|} \xleftrightarrow{FT} \frac{-j4\omega}{(1+\omega^2)^2} \text{ Duality } \frac{-j4\omega}{(1+t^2)^2} \leftrightarrow 2\pi(-\omega)e^{-|\omega|} \\
 &\Rightarrow \frac{t}{(1+t^2)^2} \xrightarrow{FT} \frac{-2\pi}{-j4}\omega e^{-|\omega|} \\
 &\Rightarrow \rightarrow \frac{\pi}{j2}\omega e^{-|\omega|}
 \end{aligned}$$

Question 35: GATE EC 2021, DTFS, DTFT and DFT

NAT

2 Marks

Consider the signals $x[n] = 2^{n-1}u[-n+2]$ and $y[n] = 2^{-n+2}u[n+1]$, where $u[n]$ is the unit step sequence. Let $X(e^{j\omega})$ and $Y(e^{j\omega})$ be the discrete-time Fourier transform of $x[n]$ and $y[n]$, respectively. The value of the integral

$$\frac{1}{2\pi} \int_0^{2\pi} X(e^{j\omega}) Y(e^{-j\omega}) d\omega$$

(rounded off to one decimal place) is -----

Detailed Solution – Question 35

$$x[n] = 2^{n-1}u[-n+2]$$

$$y[n] = 2^{-n+2}u[n+1]$$

$$y[-n] = 2^{n+2}u[-n+1]$$

$$V = \frac{1}{2\pi} \int_0^{2\pi} X(e^{j\omega}) Y(e^{-j\omega}) d\omega \quad \dots (i)$$

$$z[n] = x[n] * y[-n]$$

$$z[n] \rightarrow Z(e^{j\omega})$$

$$z[n] = \frac{1}{2\pi} \int_{-\pi}^{\pi} Z(e^{j\omega}) e^{j\omega n} d\omega$$

$$\text{Put } n = 0, \quad z[0] = \frac{1}{2\pi} \int_0^{2\pi} Z(e^{j\omega}) d\omega \quad \dots (ii)$$

Compare equations (i) and (ii)

$$z[0] = V$$

$$Z(e^{j\omega}) = X(e^{j\omega}) Y(e^{-j\omega})$$

$$\text{Apply IDTFT,} \quad Z[n] = x[n] * y[-n] = x[n] * p[n]$$

$$\therefore p[n] = y[-n] = 2^{n+2}u[-n+1]$$

$$z[n] = \sum_{k=-\infty}^{+\infty} 2^{k-1}u[-k+2]2^{n-k+2}u[-n+k+1]$$

$$= \sum_{k=-\infty}^2 2^{k-1}1 \cdot 2^{n-k+2}u[k+1-n]$$

$$= \sum_{k=-\infty}^2 2^{k-1+n-k+2}u[k+1-n]$$

$$z[n] = \sum_{k=-\infty}^2 2^{n+1}u[k-n+1]$$

$$\text{Put } n = 0, \quad V = z[0] = \sum_{k=-\infty}^2 2^1 \cdot u[k+1] = 2 \sum_{k=-1}^2 1 = 2[1+1+1+1]$$

$$V = 8$$

Question 36: GATE EC 2021, LTI Systems Continuous and Discrete

NAT


2 Marks

For a unit step input $u[n]$, a discrete-time LTI system produces an output signal

$$(2\delta[n+1] + \delta[n] + \delta[n-1])$$

. Let $y[n]$ be the output of the system for an input $\left(\left(\frac{1}{2}\right)^n u[n]\right)$. The value of $y[0]$ is -----

Detailed Solution – Question 36



The impulse response $h(n) = s(n) - s(n-1)$

$$\begin{aligned} h(n) &= 2\delta(n+1) + \delta(n) + \delta(n-1) - 2\delta(n) - \delta(n-1) - \delta(n-1-1) \\ &= 2\delta(n+1) + \delta(n) + \delta(n-1) - 2\delta(n) - \delta(n-1) - \delta(n-2) \\ h(n) &= 2\delta(n+1) - \delta(n) - \delta(n-2) \end{aligned}$$

For input $x_1(n) = (1/2)^n u(n)$ then output $y_1(n) = x_1(n) * h(n)$

$$\begin{aligned} y_1(n) &= \left(\frac{1}{2}\right)^n u(n) * [2\delta(n+1) - \delta(n) - \delta(n-2)] \\ y_1(n) &= \left(\frac{1}{2}\right)^n u(n) * 2\delta(n+1) - \left(\frac{1}{2}\right)^n u(n) * \delta(n) - \left(\frac{1}{2}\right)^n u(n) * \delta(n-2) \\ y_1(n) &= 2 \left(\frac{1}{2}\right)^{n+1} u(n+1) - \left(\frac{1}{2}\right)^n u(n) - \left(\frac{1}{2}\right)^{n-2} u(n-2) \\ y_1(n)|_{n=0} &= 2 \left(\frac{1}{2}\right)^1 u(1) - \left(\frac{1}{2}\right)^0 u(0) - \left(\frac{1}{2}\right)^{-2} u(-2) \\ &= 1 - 1 \\ y_1(0) &= 0 \end{aligned}$$

Question 37: GATE EC 2021, Fourier Transforms, Frequency Response and Correlation

NAT

2 Marks

The exponential Fourier series representation of a continuous-time periodic signal $x(t)$ is defined as

$$x(t) = \sum_{k=-\infty}^{\infty} a_k e^{jk\omega_0 t}$$

where ω_0 is the fundamental angular frequency of $x(t)$ and the coefficients of the series are a_k . The following information is given about $x(t)$ and a_k .

- I. $x(t)$ is real and even, having a fundamental period of 6
- II. The average value of $x(t)$ is 2
- III.

$$a_k = \begin{cases} k, & 1 \leq k \leq 3 \\ 0, & k > 3 \end{cases}$$

The average power of the signal $x(t)$ (rounded off to one decimal place) is _____

Detailed Solution – Question 37

1. $x(t)$ is real and even so a_k is also real and even $a_k = a_{-k}$ 2. Average of $x(t)$ is 2 i.e., $a_0 = 2$.

$$\begin{array}{rcll} 3. x(t) \rightarrow a_k = k & 1 \leq k \leq 3 & a_1 = 1 & a_{-1} = 1 \\ & 0 & a_2 = 2 & a_{-2} = 2 \\ & k > 3 & a_3 = 3 & a_{-3} = 3 \end{array}$$

4. $T_0 = 6$ Parseval's Power Theorem

$$\begin{aligned} \frac{1}{T} \int_0^T |x(t)|^2 dt &= \sum_{n=-\infty}^{+\infty} |a_k|^2 \\ P(t) &= \sum_{n=-\infty}^{+\infty} |a_k|^2 = |a_{-3}|^2 + |a_{-2}|^2 + |a_{-1}|^2 + |a_0|^2 + |a_1|^2 + |a_2|^2 + |a_3|^2 \\ &= 2|a_1|^2 + 2|a_2|^2 + 2|a_3|^2 + |a_0|^2 \\ &= 2 \times 1^2 + 2 \times (2)^2 + 2(3)^2 + (2)^2 \\ &= 2 + 8 + 18 + 4 \\ P_{x(t)} &= 32 \end{aligned}$$

Question 38: GATE EC 2021, DTFS, DTFT and DFT

MCQ

1 Mark

Consider two 16-point sequences $x[n]$ and $h[n]$. Let the linear convolution of $x[n]$ and $h[n]$ be denoted by $y[n]$, while $z[n]$ denotes the 16-point inverse discrete Fourier transform (IDFT) of the product of the 16-point DFTs of $x[n]$ and $h[n]$. The value(s) of k for which $z[k]=y[k]$ is/are

- (A) $k=0,1,2,,15$
- (B) $k=0$
- (C) **(Correct)** $k=15$
- (D) $k=0$ and $k=15$

Correct Answer: (C)

Detailed Solution – Question 38

If two 'N' point signals $x(n)$ and $h(n)$ are convolving with each other linearly and circularly then $y(k) = z(k)$ at $k = N - 1$

where, $y(n)$ = Linear convolution of $x(n)$ and $h(n)$

$z(n)$ = Circular convolution of $x(n)$ and $h(n)$

Since, $N = 16$ (Given)

Therefore, $y(k) = z(k)$ at $k = N - 1 = 15$

Question 39: GATE EC 2021, Sampling

MCQ







1 Mark

Consider a real-valued base-band signal $x(t)$, band limited to 10 kHz. The Nyquist rate for the signal

$$y(t) = x(t) x\left(1 + \frac{t}{2}\right) \text{ is}$$

- (A) 15 kHz
- (B) **(Correct)** 30 kHz
- (C) 60 kHz
- (D) 20 kHz

Correct Answer: (B)



Question 40: GATE EC 2020, Z-Transform

NAT

2 Marks

The transfer function of a stable discrete-time LTI system is $H(z) = \frac{K(z-\alpha)}{z+0.5}$, where K and α are real numbers. The value of α (rounded off to one decimal place) with $|\alpha| > 1$, for which the magnitude response of the system is constant over all frequencies, is

Detailed Solution – Question 40

System is all-pass filter. For digital all-pass filter, condition is

zero = $\frac{1}{\text{pole}^*}$... (i) By given transfer function,



zero = α Pole = -0.5 using condition (i), $\alpha = \frac{1}{-0.5} = -2$

Question 41: GATE EC 2020, Fourier Transforms, Frequency Response and Correlation

NAT

2 Marks

$X(\omega)$ is the Fourier transform of $x(t)$ shown below. The value of $\int_{-\infty}^{\infty} |X(\omega)|^2 d\omega$ (rounded off to two decimal places) is



Detailed Solution – Question 41

$$\begin{aligned}\int_{-\infty}^{\infty} |X(\omega)|^2 d\omega &= 2\pi \int_{-\infty}^{\infty} |x(t)|^2 dt \\&= 2\pi \int_{-\infty}^{\infty} |y(t)|^2 dt \\&= 2 \times 2\pi \int_{-2}^0 |y(t)|^2 dt \\&= 2 \times 2\pi \left[\int_{-2}^{-1} (t+2)^2 dt + \int_{-1}^0 (2t+3)^2 dt \right] \\&= 4\pi \left[\left\{ \frac{(t+2)^3}{3} \right\}_{-2}^{-1} + \left\{ \frac{(2t+3)^3}{3 \times 2} \right\}_{-1}^0 \right] \\&= 4\pi \left[\frac{1-0}{3} + \frac{3^3-1}{6} \right] \\&= 4\pi \left[\frac{1}{3} + \frac{26}{6} \right] \\&= 4\pi \times \left[\frac{1}{3} + \frac{26}{6} \right] \\&= 4\pi \times \left[\frac{1}{3} + \frac{13}{3} \right] \\&= 4\pi \times \frac{14}{3} \\&= \frac{56\pi}{3} = 58.61\end{aligned}$$

Question 42: GATE EC 2020, DTFS, DTFT and DFT

MCQ

2 Marks

A finite duration discrete-time signal $x[n]$ is obtained by sampling the continuous-time signal $x(t) = \cos(200\pi t)$ at sampling instants $t = n/400$, $n = 0, 1, \dots, 7$. The 8-point discrete Fourier transform (DFT) of $x[n]$ is defined as

$$x[k] = \sum_{n=0}^7 x[n] e^{-j\frac{\pi kn}{4}}, \quad k=0, 1, \dots, 7.$$

Which one of the following statement is TRUE?

- (A) All $X[k]$ are non-zero
- (B) Only $X[4]$ is non-zero
- (C) **(Correct)** Only $X[2]$ and $X[6]$ are non-zero
- (D) Only $X[3]$ and $X[5]$ are non-zero

Correct Answer: (C)

Detailed Solution – Question 42

$$x(t) = \cos 200\pi t$$

$$t = \frac{n}{400}$$

$$x(n) = \cos \left(200\pi \frac{n}{400} \right)$$

$$= \cos \left(\frac{\pi}{2} n \right); \quad n = 0, 1, \dots, 7$$

$$= \left\{ \cos 0, \cos \frac{\pi}{2}, \cos \pi, \cos \frac{3\pi}{2}, \cos 2\pi, \cos \frac{5\pi}{2}, \cos 3\pi, \cos \frac{7\pi}{2} \right\}$$

$$= 1, 0, -1, 0, 1, 0, -1, 0 \iff \text{DFT } X(K)$$

$$\text{suppose, } y(n) = 1, -1, 1, -1 \iff \text{DFT } Y(k)$$

$$[Y(K)] = [W_N]_{N=4} [y(n)] = \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 1 \\ -1 \\ 1 \\ -1 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 4 & 0 \end{bmatrix}$$

Now, as we know, If for $\{a, b, c, d\} \iff \text{DFT } \{A, B, C, D\}$ Then for,

$$\{a, 0, b, 0, c, 0, d, 0\} \iff \text{DFT } \{A, B, C, D, A, B, C, D\}$$









Similarly for $y(n) = 1, -1, 1, -1 \iff \text{DFT } Y(k) = \{0, 0, 4, 0\}$ Here, for $x(n) = \{1, 0, -1, 0, 1, 0, -1, 0\}$ $X(k) = \left\{ \begin{matrix} 1 \\ 0 \end{matrix}, 0, 4, 0, 0, 0, 4, 0 \right\}$

Question 43: GATE EC 2020, LTI Systems Continuous and Discrete

MCQ

1 Mark

Which one of the following pole-zero corresponds to the transfer function of an LTI system characterized by the input-output difference equation given below? $y[n] = \sum_{k=0}^3 (-1)^k x[n-k]$



(A) (Correct) A

(B) B

(C) C



(D) D

Correct Answer: (A)

Detailed Solution – Question 43

$$\begin{aligned}y(n) &= \sum_{K=0}^3 (-1)^K x(n-K) \\&= x(n) - x(n-1) + x(n-2) - x(n-3) \\y(z) &= X(z) - z^{-1}X(z) + Z^{-2}X(z) - Z^{-3}X(z) \\H(z) &= \frac{Y(z)}{X(z)} = 1 - Z^{-1} + Z^{-2} - Z^{-3} \\&= \frac{z^3 - z^2 + z - 1}{z^3} = \frac{(z-1)(z^2+1)}{Z^3}\end{aligned}$$

Pole Zero plot:



Question 44: GATE EC 2020, LTI Systems Continuous and Discrete

MCQ

1 Mark

The output $y[n]$ of a discrete-time system for an input $x[n]$ is

$$y[n] = \max_{-\infty \leq k \leq n} |x[k]|$$

The unit impulse response of the system is

- (A) 0 for all n
- (B) 1 for all n
- (C) **(Correct)** unit step signal $u[n]$.

(D) unit impulse signal $\delta[n]$.

Correct Answer: (C)

Question 45: GATE EC 2019, Digital Filters

NAT

2 Marks

Let $h[n]$ be a length-7 discrete-time finite impulse response filter, given by

$$h[0]=4, h[1]=3, h[2]=2, h[3]=1, h[-1]=-3, h[-2]=-2, h[-3]=-1,$$

and $h[n]$ is zero for $|n| \geq 4$. A length-3 finite impulse response approximation $g[n]$ of $g[n]$ has to be obtained such that

$$E(h, g) = \int_{-\pi}^{\pi} |H(e^{j\omega}) - G(e^{j\omega})|^2 d\omega$$

is minimized, where $H(e^{j\omega})$ and $G(e^{j\omega})$ are the discrete-time Fourier transforms of $h[n]$ and $g[n]$, respectively. For the filter that minimizes $E(h, g)$, the value of $10g[-1] + g[1]$, rounded off to 2 decimal places, is -----

Detailed Solution – Question 45

From Parseval's theorem,

$$\sum_{n=-\infty}^{\infty} |x[n]|^2 = \frac{1}{2\pi} \int_{-\pi}^{\pi} |X(e^{j\omega})|^2 d\omega$$

So,

$$\int_{-\pi}^{\pi} |H(e^{j\omega}) - G(e^{j\omega})|^2 d\omega = 2\pi \sum_{n=-3}^3 |h(n) - g(n)|^2$$

The solution of $g(n)$ that minimizes $E(h, g)$ also minimizes $\sum_{n=-3}^3 |h(n) - g(n)|^2$. The solution of $g(n)$ that minimizes the above equation is $g(n) = (-3, 4, 3)$. So, $10g(-1) + g(1) = 10(-3) + 3 = -27$

Question 46: GATE EC 2019, DTFS, DTFT and DFT

MCQ

2 Marks


It is desired to find a three-tap causal filter which gives zero signal as an output to an input of the form


$$x[n] = c_1 \exp\left(-\frac{j\pi n}{2}\right) + c_2 \exp\left(\frac{j\pi n}{2}\right)$$

where c_1 and c_2 are arbitrary real numbers. The desired three-tap filter is given by

$$h[0] = 1, h[1] = a, h[2] = b \text{ and } h[n] = 0 \text{ for } n < 0 \text{ or } n > 2$$

What are the values of the filter taps a and b if the output is $y[n]=0$ for all n , when $x[n]$ is as given above?





- (A) $a=1, b=1$
- (B) $a=0, b=-1$
- (C) $a=-1, b=1$
- (D) **(Correct)** $a=0, b=1$

Correct Answer: (D)

Detailed Solution – Question 46

$$x(n) = c_1 e^{-j\frac{\pi}{2}n} + c_2 e^{j\frac{\pi}{2}n}$$

$$\omega_0 = \frac{\pi}{2} \text{ rad/s}$$

$$H(e^{j\omega}) = 1 + ae^{-j\omega} + be^{-j2\omega}$$

To get $y(n) = 0$

$$H(e^{j\omega_0}) = H(e^{j\omega})|_{\omega=\frac{\pi}{2}} = 0$$

$$1 + ae^{-j\frac{\pi}{2}} + be^{-j2\frac{\pi}{2}} = 0$$

$$1 - ja - b = 0$$


From the given options, $a=0$ and $b=1$


Question 47: GATE EC 2019, DTFS, DTFT and DFT

MCQ

2 Marks

Consider a six-point decimation-in-time Fast Fourier Transform (FFT) algorithm, for which the signal-flow graph corresponding to $X[1]$ is shown in the figure. Let $W_6 = \exp\left(-\frac{j2\pi}{6}\right)$. In the figure, what should be the values of the coefficients a_1, a_2, a_3 in terms of W_6 so that $X[1]$ is obtained correctly?





- (A) $a_1 = -1, a_2 = W_6, a_3 = W_6^2$
- (B) $a_1 = 1, a_2 = W_6^2, a_3 = W_6$
- (C) **(Correct)** $a_1 = 1, a_2 = W_6, a_3 = W_6^2$
- (D) $a_1 = -1, a_2 = W_6^2, a_3 = W_6$

Correct Answer: (C)

Detailed Solution – Question 47

$$X(k) = \sum_{n=0}^{N-1} x(n)e^{-j\frac{2\pi}{N}kn}$$

$$X(1) = \sum_{n=0}^5 x(n)W_6^n$$

$$= x(0) + x(1)W_6 + x(2)W_6^2 + x(3)W_6^3 + x(4)W_6^4 + x(5)W_6^5 \dots (i)$$

From the given flow graph, $X(k) = [x(0) - x(3)]a_1 + [x(1) - x(4)]a_2 + [x(2) - x(5)]a_3$ By comparing equations (i) and (ii), we get. $a_1 = 1, a_2 = W_6, a_3 = W_6^2$

Question 48: GATE EC 2019, Basics of Signals and Systems

NAT

1 Mark

Consider the signal

$$f(t) = 1 + 2\cos(\pi t) + 3\sin\left(\frac{2\pi}{3}t\right) + 4\cos\left(\frac{\pi}{2}t + \frac{\pi}{4}\right)$$

, where t is in seconds. Its fundamental time period, in seconds, is _____

Detailed Solution – Question 48

$$f(t) = 1 + 2\cos(\pi t) + 3\sin\left(\frac{2\pi}{3}t\right) + 4\cos\left(\frac{\pi}{2}t + \frac{\pi}{4}\right)$$

$$\omega_1 = \pi$$

$$\omega_2 = \frac{2\pi}{3}$$

$$\omega_3 = \frac{\pi}{2}$$

$$\omega_0 = \text{GCD}\left(\pi, \frac{2\pi}{3}, \frac{\pi}{2}\right) = \frac{\pi}{6}$$

$$\text{Fundamental period, } N = \frac{2\pi}{\omega_0} = \frac{2\pi}{(\pi/6)} = 12$$

Question 49: GATE EC 2019, Laplace Transform

MCQ

1 Mark

Let $Y(s)$ be the unit-step response of a causal system having a transfer function $G(s) = \frac{3-s}{(s+1)(s+3)}$

that is, $Y(s) = \frac{G(s)}{s}$. The forced response of the system is

- (A) $u(t) - 2e^{-t}u(t) + e^{-3t}u(t)$
- (B) $2u(t) - 2e^{-t}u(t) + e^{-3t}u(t)$
- (C) $2u(t)$
- (D) **(Correct)** $u(t)$

Correct Answer: (D)

Detailed Solution – Question 49

Given, $G(s) = \frac{3-s}{(s+1)(s+3)} \therefore Y(s) = \frac{G(s)}{s} = \frac{3-s}{s(s+1)(s+3)}$ Using partial fractions, we get,

$$Y(s) = \frac{A}{s} + \frac{B}{(s+1)} + \frac{C}{(s+3)}$$

$$A(s^2 + 4s + 3) + B(s^2 + 3s) + C(s^2 + s) = 3 - s$$

$$A + B + C = 0$$

$$4A + 3B + C = -1$$

$$\text{and } 3A = 3$$

Therefore, we get,

$$A = 1, B = -2 \text{ and } C = 1$$

$$\text{So, } Y(s) = \frac{1}{s} - \frac{2}{(s+1)} + \frac{1}{(s+3)}$$

$$\text{and } y(t) = u(t) - 2e^{-t}u(t) + e^{-3t}u(t)$$



Forced response, $y_t(t) = u(t) \Rightarrow$ option (D)

Question 50: GATE EC 2019, Z-Transform

MCQ

1 Mark

Let $H(z)$ be the z-transform of a real-valued discrete-time signal $h[n]$. If $P(z) = H(z)H\left(\frac{1}{z}\right)$ has a zero at $z = \frac{1}{2} + \frac{1}{2}j$, and $P(z)$ has a total of four zeros, which one of the following plots represents all the zeros correctly?



- (A) A
- (B) B
- (C) C
- (D) (Correct) D

Correct Answer: (D)

Detailed Solution – Question 50

$P(Z) = H(Z)H\left(\frac{1}{Z}\right)$ (i) $h(n)$ is real. Som $p(n)$ will be also real (ii) $P(z) = P(z^{-1})$
From (i) : if z_1 is a zero of $P(z)$, then z_1^* will be also a zero of $P(z)$. From (ii): If z_1 is a zero of $P(z)$, then $\frac{1}{z_1}$ will be also a zero of $P(z)$. So, the 4 zeros are,

$$\begin{aligned}z_1 &= \frac{1}{2} + \frac{1}{2}j \\z_2 &= z_1^* = \frac{1}{2} - \frac{1}{2}j \\z_3 &= \frac{1}{z_1} = \frac{1}{\frac{1}{2} - \frac{1}{2}j} = 1 - j \\z_4 &= \left(\frac{1}{z_1}\right)^* = z_3^* = 1 + j\end{aligned}$$

Question 51: GATE EC 2018, DTFS, DTFT and DFT

NAT

Let $X[k] = k + 1$, $0 \leq k \leq 7$ be 8-point DFT of a sequence $x[n]$, where $X[k] = \sum_{n=0}^{N-1} x[n]e^{-j\frac{2\pi}{N}kn}$. The value (correct to two decimal places) of $\sum_{n=0}^3 x[2n]$ is -----.

2 Marks

Detailed Solution – Question 51



$$\begin{aligned}x(k) &= \{1, 2, 3, 4, 5, 6, 7, 8\} \\x(k) &= \sum_{n=0}^7 x[n]e^{-j\frac{2\pi}{8}kn} \\&= \sum_{n=0}^7 x[n]e^{-i\frac{\pi}{4}kn} \\\sum_{n=0}^3 x[2n] &= \sum_{n=0,2,4,6}^7 x[n] \\&= \frac{1}{2} \sum_{n=0}^7 (x[n] + (-1)^n x[n]) \\\sum_{n=0}^7 x[n] &= x(0) = 1 \\\sum_{n=0}^7 (-1)^n x[n] &= \sum_{n=0}^7 x[n]e^{-i\frac{\pi}{4}4n} = x(4) = 5 \\\sum_{n=0}^3 x[2n] &= \frac{1}{2}[1 + 5] = 3\end{aligned}$$

Question 52: GATE EC 2018, Sampling

NAT

2 Marks



A band limited low-pass signal $x(t)$ of bandwidth 5 kHz is sampled at a sampling rate f_s . The signal $x(t)$ is reconstructed using the reconstruction filter $H(f)$ whose magnitude response is shown below:





The minimum sampling rate f_s (in kHz) for perfect reconstruction of $x(t)$ is

Detailed Solution – Question 52

Let us assume an arbitrary spectrum for $x(t)$ as shown below:



The spectrum of the sampled signal can be given as,



For proper reconstruction of the signal,

$$f_s - 5 \geq 8$$

$$f_s \geq 8 + 5 = 13 \text{ kHz}$$


$$\text{So, } f_{s(\min)} = 13 \text{ kHz}$$

Question 53: GATE EC 2018, Fourier Transforms, Frequency Response and Correlation

NAT

2 Marks

The input $4\text{sinc}(2t)$ is fed to a Hilbert transformer to obtain $y(t)$, as shown in the figure below:





Here $\text{sinc}(x) = \frac{\sin(\pi x)}{\pi x}$. The value (accurate to two decimal places) of $\int_{-\infty}^{\infty} |y(t)|^2 dt$ is

Detailed Solution – Question 53

Hilbert transform does not alter the amplitude spectrum of the signal.

$$\begin{aligned} \text{So, } \int_{-\infty}^{\infty} |y(t)|^2 dt &= \int_{-\infty}^{\infty} |x(t)|^2 dt = \int_{-\infty}^{\infty} |X(f)|^2 df \\ x(t) &= 4 \text{sinc}(2t) \\ \text{sinc}(t) &\xleftrightarrow{CTFT} \text{rect}(f) \\ 4\text{sinc}(2t) &\xleftrightarrow{CTFT} 2 \text{rect}\left(\frac{f}{2}\right) = 2 \text{rect}\left(\frac{f}{2}\right) \end{aligned}$$

$$\begin{aligned} \int_{-\infty}^{\infty} |X(f)|^2 df &= 2 \times (2)^2 = 8 \\ \text{So, } \int_{-\infty}^{\infty} |y(t)|^2 dt &= 8 \end{aligned}$$



Question 54: GATE EC 2018, Fourier Series

MCQ

1 Mark

Let $x(t)$ be a periodic function with period $T = 10$. The Fourier series coefficients for this series are denoted by a_k , that is

$$x(t) = \sum_{k=-\infty}^{\infty} a_k e^{jk \frac{2\pi}{T} t}$$

The same function $x(t)$ can also be considered function with period $T = 40'$. Let b_k be the Fourier series coefficients when period is taken as T' . If $\sum_{k=-\infty}^{\infty} |a_k| = 16$, then $\sum_{k=-\infty}^{\infty} |b_k|$ is equal to

- (A) 256
- (B) 64
- (C) **(Correct)** 16
- (D) 4

Correct Answer: (C)

Detailed Solution – Question 54

Change in only time period or frequency does not change in the value of Fourier series coefficients
So,

$$b_k = a_k$$
$$\sum_{k=-\infty}^{\infty} |b_k| = \sum_{k=-\infty}^{\infty} |a_k| = 16$$

Question 55: GATE EC 2018, Z-Transform


MCQ

1 Mark

A discrete-time all-pass system has two of its poles at $0.25\angle 0^\circ$ and $2\angle 30^\circ$. Which one of the following statements about the system is TRUE?

- (A) It has two more poles at $0.5\angle 0^\circ$ and $4\angle 0^\circ$.
- (B) **(Correct)** It is stable only when the impulse response is two-sided.
- (C) It has constant phase response over all frequencies.
- (D) It has constant phase response over the entire z-plane.

Correct Answer: (B)



The AOC should include unit circle to make the system stable. From the given pole pattern it is clear that, to make the system stable, the ROC should be finite circular strip or finite annular strip and hence the impulse response of the system should be also two-sided.

Question 56: GATE EC 2018, Basics of signals and Systems

MCQ

1 Mark

Let the input be u and the output be y of a system, and the other parameters are real constants. Identify which among the following systems is not a linear system:

(A)

$$\frac{d^3 y}{dt^3} + a_1 \frac{d^2 y}{dt^2} + a_2 \frac{dy}{dt} + a_3 y =$$

$$b_3 u + b_2 \frac{du}{dt} + b_1 \frac{d^2 u}{dt^2} \text{ (with initial rest conditions)}$$

(B) $y(t) = \int_0^t e^{a(t-\tau)} \beta u(\tau) d\tau$

(C) **(Correct)** $y = au + b, b \neq 0$

(D) $y = au$

Correct Answer: (C)

Detailed Solution – Question 56


$y = au + b, b \neq 0$ is a non-linear system.

Question 57: GATE EC 2017-SET-2, LTI Systems Continuous and Discrete

NAT

2 Marks

Consider the parallel combination of two LTI systems shown in the figure.



The impulse responses of the systems are $h_1(t) = 2\delta(t+2) - 3\delta(t+1)$ $h_2(t) = \delta(t-2)$ If the input $x(t)$ is a unit step signal, then the energy of $y(t)$ is

Detailed Solution – Question 57

Given that,

$$h_1(t) = 2\delta(t+2) - 3\delta(t+1)$$

$$h_2(t) = \delta(t-2)$$



Overall impulse response is,

$$\begin{aligned} h(t) &= h_1(t) + h_2(t) \\ &= 2\delta(t+2) - 3\delta(t+1) + \delta(t-2) \end{aligned}$$


If input, $x(t) = u(t)$, then the output will be,

$$\begin{aligned} y(t) &= x(t) * h(t) \\ &= u(t) * [2\delta(t+2) - 3\delta(t+1) + \delta(t-2)] \\ &= 2u(t+2) - 3u(t+1) + u(t-2) \end{aligned}$$

By plotting $y(t)$, we get,



The energy of $y(t)$ can be given as, $E_y = \int_{-\infty}^{\infty} y^2(t) dt$ By plotting $y^2(t)$, we get,



Question 58: GATE EC 2017-SET-2, Laplace Transform

NAT

2 Marks

The transfer function of a causal LTI system is $H(s) = 1/s$. If the input to the system is $x(t) = [\sin(t)/\pi t]u(t)$, where $u(t)$ is a unit step function, the system output $y(t)$ as $t \rightarrow \infty$ is_____.

Detailed Solution – Question 58

$$\begin{aligned}H(s) &= \frac{1}{s} \Rightarrow \text{integrator} \\x(t) &= \frac{\sin t}{\pi t} u(t) \\ \text{So, } y(t) &= \int_0^t \frac{\sin \tau}{\pi \tau} dt \\ y(t)_{t \rightarrow \infty} &= \frac{1}{\pi} \int_0^\infty \frac{\sin \tau}{\tau} dt \\ \int_0^\infty \frac{\sin \tau}{\tau} dt &= \frac{\pi}{2} \\ \text{So, } y(t)_{t \rightarrow \infty} &= \frac{1}{\pi} \times \frac{\pi}{2} = \frac{1}{2} = 0.5\end{aligned}$$

Question 59: GATE EC 2017-SET-2, Sampling

MCQ

2 Marks

The signal $x(t) = \sin(14000\pi t)$, where t is in seconds is sampled at a rate of 9000 samples per second. The sampled signal is the input to an ideal low pass filter with frequency response $H(f)$ as follows :

$$H(f) = \begin{cases} 1, & |f| \leq 12\text{kHz} \\ 0, & |f| \geq 12\text{kHz} \end{cases}$$

What is the number of sinusoids in the output and their frequencies in kHz?

- (A) Number = 1, frequency = 7
- (B) **(Correct)** Number = 3, frequencies = 2, 7, 11
- (C) Number = 2, frequencies = 2, 7
- (D) Number = 2, frequencies = 2, 11

Correct Answer: (B)


Detailed Solution – Question 59

$$x(t) = \sin(14000\pi t); f_m = 7\text{kHz}$$

$$f_s = 9000 \text{ samples per second}$$

$$= 9\text{kHz}$$

The spectrum of the sampled signal can be given as shown below:



So, three sinusoids will be there at the output of the LPF and the frequencies of those sinusoids are 2 kHz, 7 kHz and 11 kHz.

Question 60: GATE EC 2017-SET-2, Fourier Transforms, Frequency Response and Correlation

NAT

2 Marks

Consider an LTI system with magnitude response

$$|H(f)| = \begin{cases} 1 - \frac{|f|}{20} & |f| \leq 20 \\ 0 & |f| > 20 \end{cases}$$



And phase response $\text{Arg } H(f) = -2f$ If the input to the system is

$$x(t) = 8\cos(20\pi t + \frac{\pi}{4}) + 16\sin(40\pi t + \frac{\pi}{8}) + 24\cos(80\pi t + \frac{\pi}{16})$$

Then the average power of the output signal $y(t)$ is -----.

Detailed Solution – Question 60

Since,



$$\text{So, } y(t) = \frac{1}{2} \times 8 \cos(20\pi t + \phi)$$

$$\text{So, } = 4 \cos(20\pi t + \phi); \phi = \frac{\pi}{4} - 20^\circ$$

$$P_y = \frac{4^2}{2} = 8\text{W}$$

Question 61: GATE EC 2017-SET-2, Basics of signals and Systems

MCQ

1 Mark

The input $x(t)$ and the output $y(t)$ of a continuous-time system are related as $y(t) = \int_{t-T}^t x(u)du$. The system is

- (A) Linear and time-variant
- (B) **(Correct)** Linear and time-invariant
- (C) Non-linear and time-variant
- (D) Non-linear and time-invariant

Correct Answer: (B)

Detailed Solution – Question 61

Given that, $y(t) = \int_{t-T}^t x(u)du$

since the given system satisfies both homogeneity and additivity properties, the system is linear.

Check for time invariance: $y(t - t_0) = \int_{t-t_0-T}^{t-t_0} x(u)du$

When the applied input is $x(t - t_0)$

$$\begin{aligned} y_1(t) &= \int_{t-T}^t x(u - t_0) du = \int_{t-t_0-T}^{t-t_0} x(\tau) d\tau \\ &= y(t - t_0) \end{aligned}$$

$\Rightarrow$ System is time invariant

Question 62: GATE EC 2017-SET-2, DTFS, DTFT and DFT

MCQ

1 Mark

An LTI system with unit sample response $h[n] = 5\delta[n] - 7\delta[n-1] + 7\delta[n-3] - 5\delta[n-4]$ is a

- (A) Low - pass filter
- (B) high - pass filter
- (C) **(Correct)** band - pass filter
- (D) band - stop filter

Correct Answer: (C)

Detailed Solution – Question 62

$$h[n] = 5\delta[n] - 7\delta[n-1] + 7\delta[n-3] - 5\delta[n-4]$$

$$\text{Now, } H(e^{j\omega}) = 5 - 7e^{-j\omega} + 7e^{-3j\omega} - 5e^{-4j\omega}$$

Now for $\omega = 0$,

$$H(e^{j0}) = 5 - 7 + 7 - 5 = 0$$

and for $\omega = \pi$,

$$\begin{aligned} H(e^{j\pi}) &= 5 - 7(-1) + 7(-1) - 5(1) \\ &= 5 + 7 - 7 - 5 = 0 \end{aligned}$$

System is attenuating low and high frequencies whereas passing the mid frequencies. So, its a BPF.

Question 63: GATE EC 2017-SET-1, Fourier Transforms, Frequency Response and Correlation

NAT

2 Marks



A continuous time signal $x(t) = 4\cos(200\pi t) + 8\cos(400\pi t)$, where t is in seconds, is the input to a linear time invariant (LTI) filter with the impulse response

$$h(t) = \begin{cases} \frac{2\sin(300\pi t)}{\pi t} & t \neq 0 \\ 600 & t = 0 \end{cases}$$

Let $y(t)$ be the output of this filter. The maximum value of $|y(t)|$ is

Detailed Solution – Question 63

$$x(t) = 4 \cos 200\pi t + 8 \cos 400\pi t$$



$$\text{So, } y(t) = 8 \cos 200\pi t$$

$$\therefore |y(t)|_{\max} = 8$$

Question 64: GATE EC 2017-SET-1, DTFS, DTFT and DFT

NAT

2 Marks

Let $h[n]$ be the impulse response of a discrete-time linear time invariant (LTI) filter. The impulse response is given by

$$h[0] = 1/3; h[1] = 1/3; h[2] = 1/3; \text{ and } h[n] = 0 \text{ for } n < 0 \text{ and } n > 2.$$

Let $H(\omega)$ be the discrete-time Fourier system transform (DTFT) of $h[n]$, where ω is the normalized angular frequency in radians. Given that $H(\omega_0) = 0$ and $0 < \omega_0 < \pi$, the value of ω_0 (in radians) is equal to

Detailed Solution – Question 64

$$\text{since } h[n] = \frac{1}{3}\delta[n] + \frac{1}{3}\delta[n-1] + \frac{1}{3}\delta[n-2]$$

$$\text{So, } H(e^{j\omega}) = \frac{1}{3}e^{-j\omega}[1 + 2\cos\omega]$$

$$H(e^{j\omega_0}) = 0, \quad \text{for } (1 + 2\cos\omega_0) = 0$$

$$\text{or } \cos\omega_0 = -\frac{1}{2}$$

$$\text{or } \omega_0 = \frac{2\pi}{3} = 2.10 \text{ radians}$$

Question 65: GATE EC 2017-SET-1, Fourier Series

MCQ

2 Marks

Let $x(t)$ be a continuous time periodic signal with fundamental period $T = 1$ seconds. Let $\{a_k\}$ be the complex Fourier series coefficients of $x(t)$, where k is integer valued. Consider the following statements about $x(3t)$:

- I. The complex Fourier series coefficients of $x(3t)$ are $\{a_k\}$ where k is integer valued
 - II. The complex Fourier series coefficients of $x(3t)$ are $\{3a_k\}$ where k is integer valued
 - III. The fundamental angular frequency of $x(3t)$ is 6π rad/s
- For the three statements above, which one of the following is correct?

- (A) only II and III are true
- (B) **(Correct)** only I and III are true
- (C) only III is true
- (D) only I is true

Correct Answer: (B)

Detailed Solution – Question 65

Initially $T = 1\text{sec}$, so $\omega_0 = 2\pi\text{rad/sec}$. when is compressed by 3, frequency will expand by same factor but there is no change in values of a_k .
So, both statement I and III are correct

Question 66: GATE EC 2017-SET-1, LTI Systems Continuous and Discrete

NAT

2 Marks

Two discrete-time signals $x[n]$ and $h[n]$ are both non-zero for $n = 0, 1, 2$ and are zero otherwise. It is given that

$$x[0]=1, x[1]=2, x[2]=1, h[0]=1.$$

Let $y[n]$ be the linear convolution of $x[n]$ and $h[n]$. Given that $y[1] = 3$ and $y[2] = 4$, the value of the expression $(10y[3]+y[4])$ is -----.

Detailed Solution – Question 66

$$x[n] = \{1, 2, 1\}$$

$$h[n] = \{1, a, b\}$$

$$y[n] = \{A, 3, 4, B, C\}$$

$x \backslash h$	1	a	b
1	1	a	b
2	2	2a	2b
1	1	a	b

$x \backslash h$	1	a	b
1	1	a	b
2	2	2a	2b
1	1	a	b

$$y[0] = 1; y[1] = 2 + a; y[2] = 1 + 2a + b$$

$$y[3] = a + 2b; y[4] = b$$

$$\text{Given, } y[1] = 2 + a = 3 \Rightarrow a = 1$$

$$\text{Given, } y[2] = 1 + 2a + b = 4 \Rightarrow b = 1$$

$$\text{So, } y[3] = a + 2b = 3$$

$$\text{and } y[4] = b = 1$$

$$\text{So, } 10y[3] + y[4] = 10 \times 3 + 1 = 31$$

Question 67: GATE EC 2017-SET-1, Laplace Transform

MCQ

1 Mark

Consider the following statements for continuous-time linear time invariant (LTI) systems.

I. There is no bounded input bounded output (BIBO) stable system with a pole in the righthalf of the complex plane.

II. There is non causal and BIBO stable system with a pole in the right half of the complex plane.

Which one among the following is correct?

- (A) Both I and II are true
- (B) Both I and II are not true
- (C) Only I is true
- (D) **(Correct)** Only II is true

Correct Answer: (D)

Detailed Solution – Question 67

A stable system can have poles in right half of complex plane, if it is a non-causal system. So, statement-I is wrong.

A causal and BIBO stable system should have all poles in the left half of complex plane. So, statement-II is correct.

Question 68: GATE EC 2017-SET-1, Fourier Series

MCQ

1 Mark

A periodic signal $x(t)$ has a trigonometric Fourier series expansion $x(t) = a_0 + \sum_{n=1}^{\infty} (a_n \cos n\omega_0 t)$

If $x(t) = -x(t - \pi/\omega_0)$, we can conclude that

- (A) **(Correct)** a_n are zero for all n and b_n are zero for n even
- (B) a_n are zero for all n and b_n are zero for n odd
- (C) a_n are zero for n even and b_n are zero for n odd
- (D) a_n are zero for n odd and b_n are zero for n even

Correct Answer: (A)

Detailed Solution – Question 68

Signal has odd and half wave symmetries. So a_n are zero and b_n are zero for n even.

Question 69: GATE EC 2017-SET-1, Basics of signals and Systems

MCQ

1 Mark

Consider a single input single output discrete-time system with $x[n]$ as input and $y[n]$ as output, where the two are related as

$$y[n] = \begin{cases} n|x[n]| & \text{for } 0 \leq n \leq 10 \\ x[n] - x[n-1] & \text{otherwise} \end{cases}$$

Which one of the following statements is true about the system?

- (A) **(Correct)** It is causal and stable
- (B) It is causal but not stable
- (C) It is not causal but stable
- (D) It is neither causal nor stable

Correct Answer: (A)

Detailed Solution – Question 69


Since present output does not depend upon future values of input, the system is causal and also every bounded input produces bounded output, so it is stable.

Question 70: GATE EC 2016-SET-3, Digital Filters

MCQ

2 Marks

The direct form structure of an FIR (finite impulse response) filter is shown in the figure.



The filter can be used to approximate a

- (A) low-pass filter
- (B) high-pass filter
- (C) **(Correct)** band-pass filter
- (D) band-stop filter

Correct Answer: (C)



Detailed Solution – Question 70

$$y[n] = 5[x[n] - x[n - 2]]$$

$$H(z) = \frac{Y(z)}{X(z)} = 5 [1 - z^{-2}]$$

$$\text{But, } z = e^{j\omega}$$

$$H(e^{j\omega}) = 5 [1 - e^{-j2\omega}]$$



$$\omega = 0 \quad |H(e^{j\omega})| = 0$$

$$\omega = \frac{\pi}{2} \quad |H(e^{j\omega})| = 10$$

$$\omega = \pi \quad |H(e^{j\omega})| = 0$$

$\therefore$ The given one is bandpass filter.

Question 71: GATE EC 2016-SET-3, DTFS, DTFT and DFT

NAT

2 Marks

A continuous-time speech signal $x_a(t)$ is sampled at a rate of 8 kHz and the samples are subsequently grouped in blocks, each of size N . The DFT of each block is to be computed in real time using the radix-2 decimation-in-frequency FFT algorithm. If the processor performs all operations sequentially, and takes $20 \mu\text{s}$ for computing each complex multiplication (including multiplications by 1 and -1) and the time required for addition/subtraction is negligible, then the maximum value of N is _____

Detailed Solution – Question 71

$$f_s = 8000 \text{ samples/sec}$$

$$\Rightarrow T_s = \frac{1}{f_s} = \frac{1}{8000} \text{ sec}$$

Time for each multiplication = $T_m = 20 \mu\text{sec}$ $T_m = 20 \times 10^{-6} \text{sec}$ suppose block is of size N , then time taken to generate each block = $N \times T_s = N \times \frac{1}{8000}$. No. of multiplications that can be performed by processor in the time taken for each block = $\frac{N \times T_s}{T_m}$ No. of multiplications required to compute DFT by Radix - 2 FFT algorithm = $\frac{N}{2} \log_2 N$ No. of multiplication required by FFT $\leq$ No. of multiplications that can be performed by the processor in the time taken in each block [Reason: real time]

$$\frac{N}{2} \log_2 N \leq \frac{N \times T_s}{T_m}$$

$$\log_2 N \leq \frac{2 \times \frac{1}{8000}}{20 \times 10^{-6}} = 12.5$$

$$N \leq 2^{12.5}$$


$$\therefore N \leq 2^{12} = 4096$$


Question 72: GATE EC 2016-SET-3, Z-Transform

MCQ

2 Marks

The ROC (region of convergence) of the z-transform of a discrete-time signal is represented by the shaded region in the z-plane. If the signal $x[n] = (2.0)^{|n|}$, $-\infty < n < +\infty$, then the ROC of its z-transform is represented by





- (A) A
(B) B
(C) C
(D) (Correct) D

Correct Answer: (D)

Detailed Solution – Question 72

$$\begin{aligned} \text{Given, } x[n] &= (2.0)^{\ln 1}, -\infty < n < +\infty \\ &= 2^n(n) + \left(\frac{1}{2}\right)^n u(-n-1) \\ \text{ROC : } |z| > 2 \text{ and } |z| < \frac{1}{2} \\ \therefore \text{No Roc} \end{aligned}$$

Question 73: GATE EC 2016-SET-3, Laplace Transform

MCQ

2 Marks

A signal $2\cos(\frac{2\pi t}{3}) - \cos(\pi t)$ is the input to an LTI system with the transfer function $H(s) = e^s + e^{-s}$.

If C_k denotes the k^{th} coefficient in the exponential Fourier series of the output signal, then C_3 is equal to

- (A) 0
(B) (Correct) 1



(C) 2

(D) 3

Correct Answer: (B)

Detailed Solution – Question 73

Given. $H(s) = e^s + e^{-s}$ $H(e^{j\omega}) = e^{j\omega} + e^{-j\omega} = 2 \cos \omega$



$$\text{if } x_1(t) = 2 \cos\left(\frac{2\pi}{3}t\right)$$

$$\omega_b = \frac{2\pi}{3}$$

$$H(j\omega_b) = 2 \cos\left(\frac{2\pi}{3}\right) = 2\left(-\frac{1}{2}\right) = -1$$

$$y_1(t) = 2 \cos\left(\frac{2\pi}{3}t + 180^\circ\right)$$

$$\text{if } x_2(t) = \cos \pi t$$

$$\omega_b = \pi$$

$$H(j\omega_b) = 2 \cos(\pi) = -2$$

$$y_2(t) = 2 \cos(\pi t + 180^\circ)$$

$$y(t) = 2 \cos\left(\frac{2\pi}{3}t + \pi\right) - 2 \cos(\pi t + \pi)$$

$$\omega_1 = \frac{2\pi}{3}, \omega_2 = \pi$$

$$\omega_1 = 3 \quad T_2 = 2$$

$$\therefore T_0 = 6$$

$$\Rightarrow T_0 = \frac{2\pi}{T_0} = \frac{\pi}{3}$$

$$\mathcal{V}(t) = 2 \cos(2\omega_0 t + \pi) - 2 \cos(3\omega_0 t + \pi)$$

$$\mathcal{N}(t) = e^{j(2 \cos t \pi)} + e^{-j(2\omega_0 t' + \pi)} - e^{j(3\omega_0 t + \pi)} - e^{-j(3\omega_0 t + \pi)}$$

$$y(t) = -e^{j(2\omega_0 t)} - e^{-j(2\omega_0 t)} + e^{j(3\omega_0 t)} + e^{-j(3\omega_0 t)}$$

$$\therefore C_3 = 1$$

Question 74: GATE EC 2016-SET-3, Z-Transform

MCQ

1 Mark

A discrete-time signal $x[n] = \delta[n-3] + 2\delta[n-5]$ has z-transform $X(z)$. If $X(z) = X(-z)$ is the z-transform of another signal $y[n]$, then

- (A) $y[n] = x[n]$
- (B) $y[n] = x[-n]$
- (C) **(Correct)** $y[n] = -x[n]$
- (D) $y[n] = -x[-n]$

Correct Answer: (C)

Detailed Solution – Question 74

Given,

$$\begin{aligned}x[n] &= \delta[n-3] + 2\delta[n-5] \\X(z) &= z^3 + 2z^5 \\X(-z) &= (-z)^{-3} + 2(-z)^{-5} \\Y(z) &= X(-z) = -z^{-3} - 2z^{-5} \\&= -[z^{-3} + 2z^{-5}] \\y[n] &= -x[n]\end{aligned}$$

Question 75: GATE EC 2016-SET-3, Fourier Transforms, Frequency Response and Correlation





MCQ

1 Mark

If the signal $x(t) = \frac{\sin(t)}{\pi t} * \frac{\sin(t)}{\pi t}$ with $*$ denoting the convolution operation, then $x(t)$ is equal to



- (A) **(Correct)** $\frac{\sin(t)}{\pi t}$
- (B) $\frac{\sin(2t)}{2\pi t}$
- (C) $\frac{2\sin(t)}{\pi t}$
- (D) $(\frac{\sin(t)}{\pi t})^2$

Correct Answer: (A)



$$x(t) = x_1(t) * x_1(t)$$

$$X(\omega) = X_1(\omega) \cdot X_1(\omega)$$



Question 76: GATE EC 2016-SET-3, Sampling

MCQ

1 Mark

Consider the signal $x(t) = \cos(6\pi t) + \sin(8\pi t)$, where t is in seconds. The Nyquist sampling rate (in samples/second) for the signal $y(t) = x(2t + 5)$ is

- (A) 8
- (B) 12
- (C) (Correct) 16
- (D) 32

Correct Answer: (C)

Detailed Solution – Question 76

$$\begin{aligned}X(t) &= \cos(6\pi t) + \sin(8\pi t) \\Y(t) &= x(2t + 5) \\Y(t) &= \cos[6\pi(2t + 5)] + \sin[8\pi(2t + 5)] \\&= \cos(12\pi t + 30\pi) + \sin(16\pi t + 40\pi) \\f_{m1} &= 6\text{Hz} \quad f_{m2} = 8\text{Hz} \\ \text{Nyquist sampling rate,} \\f_s &= 2f_{\max} \\&= 16 \text{ samples/second}\end{aligned}$$

Question 77: GATE EC 2016-SET-2, DTFS, DTFT and DFT

NAT

2 Marks

The Discrete Fourier Transform (DFT) of the 4-point sequence

$$x[n] = x[0], x[1], x[2], x[3] = 3, 2, 3, 4 \text{ is } X[k] = X[0], X[1], X[2], X[3] = 12, 2j, 0, -2j.$$

If $X_1[k]$ is the DFT of the 12-point sequence $x_1[k] = 3, 0, 0, 2, 0, 0, 3, 0, 0, 4, 0, 0$, the value of $\left| \frac{x_1[8]}{x_1[11]} \right|$ is

Detailed Solution – Question 77

From the given question

$$\begin{aligned}x_1[n] &= x\left[\frac{n}{3}\right] \\x_1[k] &= \{12, 2j, 0, -2j, 12, 2j, 0, -2j, 12, 2j, 0, -2j\} \\x_1[8] &= 12; \quad x_1[11] = -2j \\ \therefore \frac{x_1[8]}{x_1[11]} &= \left| \frac{12}{-2j} \right| = 6\end{aligned}$$

Question 78: GATE EC 2016-SET-2, Digital Filters

NAT

2 Marks

A continuous-time filter with transfer function $H(S) = \frac{2s+6}{s^2+6s+8}$ is converted to a discrete-time filter with transfer function $G(z) = \frac{2z^2-0.5032z}{z^2-0.5032z+K}$ so that the impulse response of the continuous-time filter, sampled at 2 Hz, is identical at the sampling instants to the impulse response of the discrete time filter. The value of K is _____

Detailed Solution – Question 78

$$\text{Given, } H(s) = \frac{2s+6}{s^2+6s+8} = \frac{1}{s+2} + \frac{1}{s+4}$$

$$h(t) = e^{-2t}u(t) + e^{-4t}u(t)$$

$$\text{Given, } f_s = 2\text{Hz}$$

$$\text{For discrete time, } t = nT_s = \frac{n}{2}$$

$$h[n] = (e^{-n} + e^{-2n}) \cup (n)$$

$$H(z) = \frac{1}{1 - e^{-1}Z^{-1}} + \frac{1}{1 - e^{-2}Z^{-1}}$$

$$= \frac{Z}{Z - e^{-1}} + \frac{Z}{Z - e^{-2}}$$

$$= \frac{2Z^2 - 0.5032Z}{Z^2 - 0.5032Z + 0.049}$$





$$K = 0.049$$

Question 79: GATE EC 2016-SET-2, Fourier Transforms, Frequency Response and Correlation

NAT

1 Mark

The energy of the signal $x(t) = \frac{\sin(4\pi t)}{4\pi t}$ is _____



$$\begin{aligned} \text{Energy, } E_{x(i)} &= \frac{1}{2\pi} \int_{-\infty}^{\infty} |X(\omega)|^2 d\omega \\ &= \frac{1}{2\pi} \int_{-4\pi}^{4\pi} \left(\frac{1}{4}\right)^2 d\omega \\ &= \frac{1}{2\pi} \times \frac{1}{16} [8\pi] = \frac{1}{4} = 0.25\text{J} \end{aligned}$$

Question 80: GATE EC 2016-SET-1, DTFS, DTFT and DFT

NAT

2 Marks

Consider the signal $x[n] = 6\delta[n+2] + 3\delta[n+1] + 8\delta[n] + 7\delta[n-1] + 4\delta[n-2]$. If $X(e^{j\omega})$ is the discrete-time Fourier transform of $x[n]$, then $\frac{1}{\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) \sin^2(2\omega) d\omega$ is equal to

Detailed Solution – Question 80

From the definition of DTFT

$$\begin{aligned}
 X(e^{j\omega}) &= \sum_{n=-\infty}^{\infty} x[n]e^{-j\omega n} \\
 x[n] &= \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) e^{j\omega n} d\omega \\
 x[0] &= \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) d\omega \\
 \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega}) Y(e^{j\omega}) d\omega &= [x(n) \otimes y(n)]_{n=0} \\
 Y(e^{j\omega}) &= \sin^2(2\omega) \\
 &= \frac{1 - \cos 4\omega}{2} \\
 &= \frac{1}{2} - \frac{1}{4}e^{4j\omega} - \frac{1}{4}e^{-4j\omega} \\
 y[n] &= \frac{1}{2}\delta[n] - \frac{1}{4}\delta[n+4] - \frac{1}{4}\delta[n-4] \\
 y[n] &= \left\{ -\frac{1}{4}, 0, 0, 0, \underset{\uparrow}{\frac{1}{2}}, 0, 0, 0, -\frac{1}{4} \right\} \\
 \Rightarrow y[0] &= \frac{1}{2} \\
 x[n] &= \{6, 3, \underset{\uparrow}{8}, 7, 4\}; \quad x[0] = 8 \\
 \frac{1}{\pi} \int_{-\pi}^{\pi} x(e^{j\omega}) Y(e^{j\omega}) d\omega &= 2 \sum_{n=-\infty}^{\infty} x[0]y[0] \\
 &= 2 \times 8 \times \frac{1}{2} = 8
 \end{aligned}$$

Question 81: GATE EC 2016-SET-1, Laplace Transform

MCQ

2 Marks

A first-order low-pass filter of time constant T is excited with different input signals (with zero initial conditions up to $t = 0$). Match the excitation signals X, Y, Z with the corresponding time responses for $t \geq 0$:

X: Impulse

Y: Unit step

Z: Ramp

P: $1 - e^{-t/T}$

Q: $t - T(1 - e^{-t/T})$

R: $e^{-t/T}$

X: Impulse

Y: Unit step

Z: Ramp

P: $1 - e^{-t/T}$

Q: $t - T(1 - e^{-t/T})$

R: $e^{-t/T}$

- (A) $X \rightarrow R, Y \rightarrow Q, Z \rightarrow P$
(B) $X \rightarrow Q, Y \rightarrow P, Z \rightarrow R$
(C) **(Correct)** $X \rightarrow R, Y \rightarrow P, Z \rightarrow Q$
(D) $X \rightarrow P, Y \rightarrow R, Z \rightarrow Q$

Correct Answer: (C)

Detailed Solution – Question 81

For 1st order system $G(s) = \frac{1}{sT}; H(s) = 1$ Impulse response $A(s) = 1$

$$\begin{aligned}n(s) &= \left(\frac{G(s)}{1 + G(s)H(s)} R(s) \right) \\&= \left(\frac{1}{1 + sT} \right) = \frac{1}{T} e^{-t/T} \text{ for } t \geq 0\end{aligned}$$

Unit step response $A(s) = \frac{1}{s}$

$$\begin{aligned}\eta(s) &= \frac{1}{s(1 + sT)} = \frac{(1 + sT) - (sT)}{s(1 + sT)} \\&= \frac{1}{s} - \frac{T}{(1 + sT)} = \frac{1}{s} - \frac{T}{T(s + \frac{1}{T})}\end{aligned}$$

$$y(t) = 1 - e^{-t/T} \text{ for } t \geq 0$$

Ramp response $R(s) = \frac{1}{s^2}$

$$\eta(s) = \frac{1}{s^2(1 + sT)} = \frac{1}{s^2} - \frac{T}{s} + \frac{T}{s + \frac{1}{T}}$$

$$y(t) = t - T(1 - e^{-t/T}) \text{ for } t \geq 0$$

Question 82: GATE EC 2016-SET-1, Fourier Transforms, Frequency Response and Correlation

MCQ

2 Marks

A network consisting of a finite number of linear resistor (R), inductor (L), and capacitor (C) elements, connected all in series or all in parallel, is excited with a source of the form

$$\sum_{k=1}^3 a_k \cos(k\omega_0 t), \text{ where } a_k \neq 0, \omega_0 \neq 0.$$


The source has nonzero impedance. Which one of the following is a possible form of the output measured across a resistor in the network?

- (A) **(Correct)** $\sum_{k=1}^3 b_k \cos(k\omega_0 t + \phi_k)$, where $b_k \neq a_k, \forall k$

- (B) $\sum_{k=1}^4 b_k \cos(k\omega_0 t + \phi_k)$, where $b_k \neq 0, \forall k$
- (C) $\sum_{k=1}^3 a_k \cos(k\omega_0 t + \phi_k)$
- (D) $\sum_{k=1}^2 a_k \cos(k\omega_0 t + \phi_k)$

Correct Answer: (A)

Detailed Solution – Question 82




When a sinusoidal input is given to LTI system, the output is also a sinusoid with change in magnitude and the phase shift offered by LTI system.

Question 83: GATE EC 2016-SET-1, Laplace Transform

MCQ

2 Marks

The Laplace transform of the causal periodic square wave of period T shown in the figure below is



- (A) **(Correct)** $F(s) = \frac{1}{1+e^{-sT/2}}$
- (B) $F(s) = \frac{1}{s(1+e^{-sT/2})}$
- (C) $F(s) = \frac{1}{s(1-e^{-sT})}$
- (D) $F(s) = \frac{1}{1-e^{-sT}}$

Correct Answer: (A)

Detailed Solution – Question 83

$$\begin{aligned}L(f(t)) &= \frac{1}{1 - e^{-sT} \int_0^{T/2} e^{-st} dt} \\&= \frac{1}{1 - e^{-sT}} \left(\frac{e^{-st}}{-s} \right) \Big|_0^{T/2} \\&= \frac{1}{s(1 - e^{-sT})} \cdot (1 - e^{-sT/2}) \\&= \frac{1}{s} \cdot \frac{1 - e^{-sT/2}}{(1 - e^{-sT/2})(1 + e^{-sT/2})} \\&= \frac{1}{s} \cdot \frac{1}{1 + e^{-sT/2}}\end{aligned}$$

As per GATE official answer Marks to ALL.

Question 84: GATE EC 2016-SET-1, Sampling


NAT

1 Mark

A continuous-time sinusoid of frequency 33 Hz is multiplied with a periodic Dirac impulse train of frequency 46 Hz. The resulting signal is passed through an ideal analog low-pass filter with a cutoff frequency of 23 Hz. The fundamental frequency (in Hz) of the output is _____

Detailed Solution – Question 84

If $x(t)$ is a message signal and $y(t)$ is a sampled signal, then $y(t)$ is related to $x(t)$ as $y(t) = x(t) \sum_{n=-\infty}^{\infty} \delta(t - nT_s)$ $r(f) = f_s \sum_{n=-\infty}^{\infty} X(f - nf_s)$
Spectrum of $X(f)$ and $Y(f)$ are as shown



Cut off frequency of LPF = 23 Hz
Hence, frequency at the output is 13 Hz

Question 85: GATE EC 2016-SET-1, Z-Transform

MCQ

1 Mark

Consider the sequence $x[n] = a^n u[n] + b^n u[n]$, where $u[n]$ denotes the unit-step sequence and $0 < -a < -b < 1$. The region of convergence (ROC) of the z-transform of $x[n]$ is

- (A) $-z- > -a-$
 (B) **(Correct)** $-z- > -b-$
 (C) $-z- < -a-$
 (D) $-a- < -z- < -b-$

Correct Answer: (B)

Detailed Solution – Question 85

$$\text{Given, } x[n] = a^n u[n] + b^n u[n]$$

$$0 < |a| < |b| < 1$$

$$\text{Also given, } AOC = (|z| > |a|) \text{ and } (|z| > |b|)$$

$$ROC = |z| > |b|$$

Question 86: GATE EC 2016-SET-1, Basics of signals and Systems

MCQ

1 Mark

A continuous-time function $x(t)$ is periodic with period T . The function is sampled uniformly with a sampling period T_s . In which one of the following cases is the sampled signal periodic?

- (A) $T = \sqrt{2}T_s$
 (B) **(Correct)** $T = 1.2T_s$
 (C) Always
 (D) Never

Correct Answer: (B)

Detailed Solution – Question 86

A signal is said to be periodic if $\frac{T}{T_s}$ is a rational number.
 Here, $T = 1.2T_s \Rightarrow \frac{T}{T_s} = \frac{6}{5}$ Which is a rational number

Question 87: GATE EC 2016-SET-1, LTI Systems Continuous and Discrete

MCQ

1 Mark

Which one of the following is an eigen function of the class of all continuous-time, linear, timeinvariant systems ($u(t)$ denotes the unit-step function)?

- (A) $e^{j\omega_0 t} u(t)$
 (B) $\cos(\omega_0 t)$
 (C) **(Correct)** $e^{j\omega_0 t}$

(D) $\sin(\omega_0 t)$

Correct Answer: (C)

Detailed Solution – Question 87

If the input to the system is eigen signal output is also the same eigen signal.

Question 88: GATE EC 2016-SET-1, Laplace Transform

MCQ

1 Mark

Which one of the following is a property of the solutions to the Laplace equation: $\nabla^2 f = 0$?

- (A) **(Correct)** The solutions have neither maxima nor minima anywhere except at the boundaries.
- (B) The solutions are not separable in the coordinates.
- (C) The solutions are not continuous
- (D) The solutions are not dependent on the boundary conditions

Correct Answer: (A)

Question 89: GATE EC 2015-SET-3, Basics of Signals and Systems

NAT

2 Marks

Two sequences $x_1[n]$ and $x_2[n]$ have the same energy. Suppose $x_1[n] = \alpha 0.5^n u[n]$, where α is a positive real number and $u[n]$ is the unit step sequence. Assume

$$x_2[n] = \begin{cases} \sqrt{1.5} & \text{for } n = 0, 1 \\ 0 & \text{otherwise.} \end{cases}$$

Then the value of α is _____.

Detailed Solution – Question 89

$$\begin{aligned} \text{Energy of } x_1[n] &= \sum_{n=-\infty}^{\infty} |x_1[n]|^2 \\ &= \sum_{n=0}^{\infty} \alpha^2 \left(\frac{1}{4}\right)^n = \alpha^2 \cdot \frac{1}{1 - \frac{1}{4}} = \alpha^2 \cdot \frac{4}{3} \end{aligned}$$

$$\text{Energy of } x_2[n] = 1.5 + 1.5 = 3$$

$$\Rightarrow \alpha^2 \frac{4}{3} = 3$$

$$\alpha^2 = \frac{9}{4}$$

$$\alpha = 1.5$$

Question 90: GATE EC 2015-SET-3, Sampling

NAT

2 Marks



Consider a continuous-time signal defined as

$$x(t) = \left(\frac{\sin(\pi t/2)}{(\pi t/2)} \right) * \sum_{n=-\infty}^{\infty} \delta(t - 10n)$$

where '*' denotes the convolution operation and t is in seconds. The Nyquist sampling rate (in samples/sec) for x(t) is _____.

Detailed Solution – Question 90

$$x(t) = \frac{\sin\left(\frac{\pi t}{2}\right)}{\left(\frac{\pi t}{2}\right)} * \sum_{n=-\infty}^{\infty} \delta[t - 10n]$$



$$\begin{aligned} f_{\max} &= 0.2\text{Hz} \\ \Rightarrow f_s &= 2f_{\max} = 0.4\text{Hz} \end{aligned}$$

Question 91: GATE EC 2015-SET-3, DTFS, DTFT and DFT

NAT

2 Marks

Let $\tilde{x}[n] = 1 + \cos\left(\frac{\pi n}{8}\right)$ be a periodic signal with period 16. Its DFS coefficients are defined by $a_k = \frac{1}{16} \sum_{n=0}^{15} \tilde{x}[n] \exp(-j\frac{\pi}{8}kn)$ for all k. The value of the coefficient a_{31} is _____.

Detailed Solution – Question 91


$$\begin{aligned} \tilde{x}[n] &= 1 + \cos\left(\frac{\pi n}{8}\right) \\ &= 1 + \frac{e^{j\left(\frac{2\pi}{16}\right)n}}{2} + \frac{e^{-j\left(\frac{2\pi}{16}\right)n}}{2} \quad (N = 16) \\ &= 1 + \frac{e^{j\left(\frac{2\pi}{16}\right)n}}{2} + \frac{e^{-j\left(\frac{2\pi}{16}\right)n}}{2} \\ \Rightarrow a_1 &= \frac{1}{2} \text{ and also } a_{31} = a_{15} = a_{-1} = \frac{1}{2} \end{aligned}$$

Question 92: GATE EC 2015-SET-3, Z-Transform

MCQ

2 Marks

A realization of a stable discrete time system is shown in the figure. If the system is excited by a unit step sequence input $x[n]$, the response $y[n]$ is



- (A) $4(-\frac{1}{3})^n u[n] - 5(-\frac{2}{3})^n u[n]$
- (B) $5(-\frac{2}{3})^n u[n] - 3(-\frac{1}{3})^n u[n]$
- (C) **(Correct)** $5(\frac{1}{3})^n u[n] - 5(\frac{2}{3})^n u[n]$
- (D) $5(\frac{2}{3})^n u[n] - 5(\frac{1}{3})^n u[n]$

Correct Answer: (C)

Detailed Solution – Question 92

$$\begin{aligned}\frac{Y(z)}{X(z)} &= \frac{\frac{5}{3}[1-z]}{z^2 - z + \frac{2}{9}} \\ \Rightarrow \eta(z) &= \frac{5}{3} \frac{(1-z)}{\left(z - \frac{1}{3}\right)\left(z - \frac{2}{3}\right)} \\ \eta(z) &= \frac{5z}{z - \frac{1}{3}} - \frac{5z}{z - \frac{2}{3}} \\ y(n) &= 5 \left(\frac{1}{3}\right)^n u(n) - 5 \left(\frac{2}{3}\right)^n u(n)\end{aligned}$$

Question 93: GATE EC 2015-SET-3, Z-Transform

MCQ

2 Marks

Suppose $x[n]$ is an absolutely summable discrete-time signal. Its z-transform is a rational function with two poles and two zeroes. The poles are at $z = \pm 2j$. Which one of the following statements is TRUE for the signal $x[n]$?

- (A) It is a finite duration signal.
- (B) It is a causal signal
- (C) **(Correct)** It is a non-causal signal
- (D) It is a periodic signal

Correct Answer: (C)

Detailed Solution – Question 93

Poles are at $z = \pm 2$

Since $x[n]$ is absolutely summable hence, DTFT exists which implies ROC must include unit circle.
 $\Rightarrow x(t)$ is a non-causal signal.

Question 94: GATE EC 2015-SET-3, Z-Transform

MCQ

1 Mark

Consider a four-point moving average filter defined by the equation $y[n] = \sum_{i=0}^3 \alpha_i x[n-i]$, The condition on the filter coefficients that results in a null at zero frequency is

- (A) **(Correct)** $\alpha_1 = \alpha_2 = 0; \alpha_0 = -\alpha_3$
- (B) $\alpha_1 = \alpha_2 = 1; \alpha_0 = -\alpha_3$
- (C) $\alpha_0 = \alpha_3 = 0; \alpha_1 = \alpha_2$
- (D) $\alpha_1 = \alpha_2 = 0; \alpha_0 = \alpha_3$

Correct Answer: (A)

Detailed Solution – Question 94

$$\begin{aligned}y(n) &= \sum_{i=0}^3 \alpha_i x(n-i) \\&= \alpha_0 x[n] + \alpha_1 x[n-1] + \alpha_2 x[n-2] + \alpha_3 x[n-3] \\ \Rightarrow Y(z) &= \alpha_0 X(z) + \alpha_1 X(z)z^{-1} + \alpha_2 X(z)z^{-2} \\&\quad + \alpha_3 X(z)z^{-3} \\ H(z) &= \alpha_0 + \alpha_1 z^{-1} + \alpha_2 z^{-2} + \alpha_3 z^{-3} \\ \text{Null at zero frequency} \\ \Rightarrow z &= e^{j\omega} \Big|_{\omega=0} \\ 0 &= \alpha_0 + \alpha_1 + \alpha_2 + \alpha_3\end{aligned}$$

Option (A) satisfies the condition

Question 95: GATE EC 2015-SET-3, LTI Systems Continuous and Discrete

MCQ

1 Mark

The impulse response of an LTI system can be obtained by

- (A) differentiating the unit ramp response
- (B) **(Correct)** differentiating the unit step response
- (C) integrating the unit ramp response
- (D) integrating the unit step response

Correct Answer: (B)

Detailed Solution – Question 95

$$\begin{aligned}IR &= \frac{d}{dt}(SR) \\ \text{Step response,} \\ y(t) &= \int_{-\infty}^t h(\tau) \cdot d\tau \\ h(t) &= \frac{d}{dt}y(t)\end{aligned}$$

Question 96: GATE EC 2015-SET-3, DTFS, DTFT and DFT

NAT

1 Mark

The value $\sum_{n=0}^{\infty} n(\frac{1}{2})^n$ is -----.

Detailed Solution – Question 96

$$\begin{aligned}
\sum_{n=0}^{\infty} \left(\frac{1}{2}\right)^n &= \sum_{n=-\infty}^{\infty} n \left(\frac{1}{2}\right)^n u(n) \\
&= Z \cdot T \left[n \left(\frac{1}{2}\right)^n u(n) \right]_{z=1} \\
&= \frac{\frac{1}{2}Z^{-1}}{\left(1 - \frac{1}{2}z^{-1}\right)^2} = \frac{\frac{Z}{2}}{\left(z - \frac{1}{2}\right)^2} \Bigg|_{z=1} \\
&= \frac{1/2}{1/4} = 2
\end{aligned}$$

Question 97: GATE EC 2015-SET-3, Fourier Transforms, Frequency Response and Correlation**NAT****1 Mark**

Consider the function $g(t) = e^{-t} \sin(2\pi t) u(t)$ where $u(t)$ is the unit step function. The area under $g(t)$ is _____.

Detailed Solution – Question 97

$$\begin{aligned}
g(t) &= e^{-t} \sin(2\pi t) u(t) \\
\text{Area} &= \int_{-\infty}^{\infty} g(t) dt \\
&= \int_{-\infty}^{\infty} \sin(2\pi t) u(t) e^{-t} dt = G(s) \Big|_{s=0} \\
G(s) &= \frac{2\pi}{(s+1)^2 + 4\pi^2} \\
\text{Area} &= \frac{2\pi}{(s+1)^2 + 4\pi^2} \Bigg|_{s=0} = 0.155
\end{aligned}$$

Question 98: GATE EC 2015-SET-2, Laplace Transform**NAT****2 Marks**

Let $x(t) = \alpha s(t) + s(-t)$ with $s(t) = \beta e^{-4t} u(t)$, where $u(t)$ is unit step function. If the bilateral Laplace transform of $x(t)$ is $X(s) = \frac{16}{s^2 - 16}$ $-4 < \text{Re}\{s\} < 4$; then the value of β is _____.

Detailed Solution – Question 98

$$x(t) = \alpha\beta e^{-4t}u(t) + \beta e^{4t}u(-t)$$

$$\text{Given, } x(s) = \frac{16}{s^2} - 16 \quad -4 < \text{Re}[s] < 4$$

$$= \frac{16}{(s+4)(s-4)} = \frac{-2}{s+4} + \frac{2}{s-4}$$

$$x(t) = -2e^{-4t}u(t) - 2e^{4t}u(-t)$$

On comparison $\beta = -2$

Question 99: GATE EC 2015-SET-2, DTFS, DTFT and DFT**NAT****2 Marks**

Consider two real sequences with time-origin marked by the bold value,

$$x_1[n] = \{1, 2, 3, 0\}, \quad x_2[n] = \{1, 3, 2, 1\}$$

Let $X_1(k)$ and $X_2(k)$ be 4-point DFTs of $x_1[n]$ and $x_2[n]$, respectively. Another sequence $x_3[n]$ is derived by taking 4-point inverse DFT of $X_3(k) = X_1(k)X_2(k)$. The value of $x_3[2]$ is _____.

Detailed Solution – Question 99

$x_1[n] = \{1, 2, 3, 0\}$, $x_2[n] = \{1, 3, 2, 1\}$ $x(k)_3 = x(k), \lambda(k)_2 \Rightarrow x_3[n] =$ circular convolution of $x_1[n]$ and $x_2[n]$

$$= x_1[n] \otimes x_2[n]$$

$$\begin{bmatrix} x_3(0) \\ x_3(1) \\ x_3(2) \\ x_3(3) \end{bmatrix} = \begin{bmatrix} 1 & 0 & 3 & 2 \\ 2 & 1 & 0 & 3 \\ 3 & 2 & 1 & 0 \\ 0 & 3 & 2 & 1 \end{bmatrix} \begin{bmatrix} 1 \\ 3 \\ 2 \\ 1 \end{bmatrix} = \begin{bmatrix} 9 \\ 8 \\ 11 \\ 14 \end{bmatrix}$$

$$x_3[2] = 11$$

Question 100: GATE EC 2015-SET-2, Laplace Transform**MCQ****2 Marks**

Input $x(t)$ and output $y(t)$ of an LTI system are related by the differential equation $y''(t) - y'(t) - 6y(t) = x(t)$. If the system is neither causal nor stable, the impulse response $h(t)$ of the system is

- (A) $\frac{1}{5}e^{3t}u(-t) + \frac{1}{5}e^{-2t}u(-t)$
- (B) **(Correct)** $-\frac{1}{5}e^{3t}u(-t) + \frac{1}{5}e^{-2t}u(-t)$
- (C) $\frac{1}{5}e^{3t}u(-t) - \frac{1}{5}e^{-2t}u(-t)$
- (D) $-\frac{1}{5}e^{3t}u(-t) - \frac{1}{5}e^{-2t}u(-t)$

Correct Answer: (B)

Detailed Solution – Question 100

$y''(t) - y'(t) - 6y(t) = x(t)$ $H(s) = \frac{Y(s)}{X(s)} = \frac{1}{s^2 - s - 6} = \frac{1}{(s-3)(s+2)}$ $H(s) = \frac{(\frac{1}{5})}{s-3} + \frac{(-\frac{1}{5})}{s+2}$ If the system is neither causal nor stable, then


$$h(t) = -\frac{1}{5}e^{3t}u(-t) + \frac{1}{5}e^{-2t}u(-t) \quad \text{ROC} : \sigma < -2$$

Question 101: GATE EC 2015-SET-1, Signals and Systems

MCQ

1 Mark

The waveform of a periodic signal $x(t)$ is shown in the figure.



A signal $g(t)$ is defined by $g(t) = x\left(\frac{t-1}{2}\right)$. The average power of $g(t)$ is

- (A) 1
- (B) (Correct) 2
- (C) 3
- (D) 4

Correct Answer: (B)

Detailed Solution – Question 101

$$\begin{aligned}
 x(t) &= -3t, \quad -1 < t < 1 \\
 x\left(\frac{t-1}{2}\right) &= -\frac{3}{2}(t-1) \quad -1 < t < 3 \\
 \text{and } T &= 6 \\
 \text{Average power} &= \frac{1}{6} \int_{-1}^3 \left(-\frac{3}{2}(t-1)\right)^2 dt = 2
 \end{aligned}$$

Question 102: GATE EC 2014-SET-1, Signals and Systems

MCQ

1 Mark

A discrete time signal $x[n] = \sin(\pi^2 n)$, n being an integer, is

- (A) periodic with period π
- (B) periodic with period π^2
- (C) periodic with period $\pi/2$
- (D) **(Correct)** not periodic

Correct Answer: (D)

Detailed Solution – Question 102

$$\begin{aligned}x[n] &= \sin(\pi^2 n) \\ \omega_0 &= \pi^2 \\ \therefore N &= \frac{2\pi}{\omega_0} \cdot m\end{aligned}$$

where m is the smallest integer that converts $\frac{2\pi}{\omega_0}$ into an integer value. $\therefore N = \frac{2\pi}{\pi^2} \cdot m = \frac{2}{\pi} \cdot m$
So, there exists no such integer value of m which could make the N integer, so the system is not periodic.

Question 103: GATE EC 2013, Signals and Systems

MCQ

1 Mark



The impulse response of a continuous time system is given by $h(t) = \delta(t - 1) + \delta(t - 3)$. The value of the step response at $t = 2$ is

- (A) 0
- (B) **(Correct)** 1
- (C) 2
- (D) 3

Correct Answer: (B)

Detailed Solution – Question 103

Step response = Integration of impulse response $\int_{-\infty}^t \delta(t-1)dt = u(t-1)$ $\int_{-\infty}^t \delta(t-3)dt = u(t-3)$



$$\text{at } t = 2$$
$$y(t) = 1$$

Question 104: GATE EC 2013, Signals and Systems

MCQ

1 Mark

For a periodic signal

$$v(t) = 30 \sin 100t + 10 \cos 300t + 6 \sin \left(500t + \frac{\pi}{4} \right)$$

, the fundamental frequency in rad/s is

- (A) **(Correct)** 100
- (B) 300
- (C) 500
- (D) 1500

Correct Answer: (A)

Detailed Solution – Question 104

$$\omega_1 = 100$$

$$\omega_2 = 300$$

$$\omega_3 = 500$$

H.C.F. of $(\omega_1, \omega_2 \text{ and } \omega_3) = \text{H.C.F. } (100, 300, 500) = 100 \text{ rad/sec}$

Question 105: GATE EC 2012, Signals and Systems

MCQ

1 Mark

The input $x(t)$ and output $y(t)$ of a system are related as $y(t) = \int_{-\infty}^t x(\tau) \cos(3\tau) d\tau$. The system is

- (A) time-invariant and stable
- (B) stable and not time-invariant
- (C) time-invariant and not stable
- (D) **(Correct)** not time-invariant and not stable

Correct Answer: (D)

Detailed Solution – Question 105

$$y = \int_{-\infty}^t x(\tau) \cos(3\tau) d\tau$$
$$y(t - t_0) = \int_{-\infty}^{t-t_0} x(\tau) \cos(3\tau) d\tau$$

$y'(t)$ for input $x(t - t_0)$, is

$$y'(t) = \int_{-\infty}^t x(\tau - t_0) \cos 3\tau d\tau$$
$$y'(t) = \int_{-\infty}^{(t-t_0)} x(\tau) \cos 3(\tau + t_0) d\tau$$

$y'(t) \neq y(t - t_0)$ so system is not time invariant for input $x(\tau) = \cos(3\tau)$ (bounded input)

$$y(t) = \int_{-\infty}^t \cos^2(3\tau) d\tau \rightarrow \infty \text{ as } t \rightarrow \infty$$

So, for bounded i/p, o/p is not bounded therefore system is not stable.

Question 106: GATE EC 2008, Signals and Systems

MCQ

1 Mark

Let $x(t)$ be the input and $y(t)$ be the output of a continuous time system. Match the system properties P1, P2 and P3 with system relations R1, R2, R3, R4

Properties

- P1 : Linear but NOT time - invariant
- P2 : Time - invariant but NOT linear
- P3 : Linear and time - invariant

Relations

- R1 : $y(t) = t^2 x(t)$
- R2 : $y(t) = t |x(t)|$
- R3 : $y(t) = |x(t)|$
- R4 : $y(t) = x(t - 5)$

Properties

- P1 : Linear but NOT time - invariant
- P2 : Time - invariant but NOT linear
- P3 : Linear and time - invariant

Relations

- R1 : $y(t) = t^2 x(t)$
- R2 : $y(t) = t|x(t)|$
- R3 : $y(t) = |x(t)|$
- R4 : $y(t) = x(t - 5)$

- (A) (P1, R1), (P2, R3), (P3, R4)
- (B) **(Correct)** (P1, R2), (P2, R3), (P3, R4)
- (C) (P1, R3), (P2, R1), (P3, R2)
- (D) (P1, R1), (P2, R2), (P3, R3)

Correct Answer: (B)

Question 107: GATE EC 2008, Signals and Systems

MCQ

1 Mark

The input and output of a continuous time system are respectively denoted by $x(t)$ and $y(t)$. Which of the following descriptions corresponds to a causal system ?

- (A) $y(t) = x(t - 2) + x(t + 4)$
- (B) $y(t) = (t - 4)x(t + 1)$
- (C) **(Correct)** $y(t) = (t + 4)x(t - 1)$
- (D) $y(t) = (t + 5)x(t + 5)$

Correct Answer: (C)

Detailed Solution – Question 107

A system is casual if the output at any time depends only on values of the input at the present time and in the past.

Question 108: GATE EC 2007, Signals and Systems

MCQ

1 Mark

A Hilbert transformer is a

- (A) **(Correct)** non-linear system
- (B) non-causal system
- (C) time-varying system
- (D) low-pass system

Correct Answer: (A)

Detailed Solution – Question 108

The Hilbert transformer is characterised by the impulse response

$$h(t) = \frac{1}{\pi t} \quad t \in (-\infty, \infty)$$
$$h(t) \neq 0 \text{ for } t < 0$$

Thus, the Hilbert transformer is a non-causal system.

Question 109: GATE EC 2006, Signals and Systems

MCQ

1 Mark

A system with input $x[n]$ and output $y[n]$ is given as $y[n] = (\sin \frac{5}{6}\pi n) x[n]$. The system is

- (A) linear, stable and invertible
- (B) non-linear, stable and non-invertible
- (C) **(Correct)** linear, stable and non-invertible
- (D) linear, unstable and invertible

Correct Answer: (C)

Detailed Solution – Question 109

$$y(n) = \left(\sin \frac{5}{6}\pi n \right) x(n)$$

$$\text{Let } x(n) = 8(n)$$

$$\therefore y(n) = \sin 0 = 0 \text{ (bounded)}$$

BIBO stable

Question 110: GATE EC 2006, Signals and Systems

MCQ

1 Mark

The Dirac delta function $\delta(t)$ is defined as

(A)

$$\delta(t) = \begin{cases} 1 & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

(B)

$$\delta(t) = \begin{cases} \infty & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

(C)

$$\delta(t) = \begin{cases} 1 & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

$$\text{and } \int_{-\infty}^{\infty} \delta(t) dt = 1$$


(D) **(Correct)**

$$\delta(t) = \begin{cases} \infty & t = 0 \\ 0 & \text{otherwise} \end{cases}$$

$$\text{and } \int_{-\infty}^{\infty} \delta(t) dt = 1$$

Correct Answer: (D)

Detailed Solution – Question 110



Question 111: GATE EC 2005, Signals and Systems

MCQ

1 Mark

The power in the signal $s(t) = 8\cos(20\pi t - \frac{\pi}{2}) + 4\sin(15\pi t)$ is

(A) **(Correct)** 40

(B) 41

(C) 42

(D) 82

Correct Answer: (A)

Detailed Solution – Question 111



$$\begin{aligned} s(t) &= 8 \cos\left(\frac{\pi}{2} - 20\pi t\right) + 4 \sin 15\pi t \\ &= 8 \sin 20\pi t + 4 \sin 15\pi t \\ P &= \frac{8^2}{2} + \frac{4^2}{2} = 32 + 8 = 40 \end{aligned}$$

Question 112: GATE EC 2005, Signals and Systems

MCQ

1 Mark

The function $x(t)$ is shown in the figure. Even and odd parts of a unit step function $u(t)$ are respectively,






- (A) **(Correct)** $\frac{1}{2}, \frac{1}{2}x(t)$
- (B) $-\frac{1}{2}, \frac{1}{2}x(t)$
- (C) $\frac{1}{2}, -\frac{1}{2}x(t)$
- (D) $-\frac{1}{2}, -\frac{1}{2}x(t)$

Correct Answer: (A)

Detailed Solution – Question 112

$$\text{Even part} = \frac{u(t) + u(-t)}{2}$$

$$\text{Odd part} = \frac{u(t) - u(-t)}{2}$$



Question 113: GATE EC 2004, Signals and Systems

MCQ

1 Mark

Consider the sequence $x[n] = [-4 - j5, 1 + j2.5]$. The conjugate anti-symmetric part of the sequence is

(A) **(Correct)** $[-4 - j2.5, j2, 4 - j2.5]$

$-j2.5, 1, j2.5$

$-j5, j2, 0$

$-4, 1, 4$

Correct Answer: (A)

Detailed Solution – Question 113

$$\begin{aligned}x(n) &= [-4 - j5, 1 + j2, 4] \\x^*(-n) &= [4, 1 - j2, -4 + j5] \\x_{\text{CAS}}(n) &= \frac{x(n) - x^*(-n)}{2} \\&= [-4 - j2.5, j2, 4 - j2.5]\end{aligned}$$

$\uparrow$

Question 114: GATE EC 2003, Signals and Systems

MCQ

1 Mark

Let P be linearity, Q be time-invariance, R be causality and S be stability. A discrete time system has the input-output relationship,

$$y(n) = \begin{cases} x(n) & n \geq 1 \\ 0, & n = 0 \\ x(n+1) & n \leq -1 \end{cases}$$

where $x(n)$ is the input and $y(n)$ is the output. The above system has the properties

(A) **(Correct)** P, S but not Q, R

(B) P, Q, S but not R

(C) P, Q, R, S

(D) Q, R, S but not P

Correct Answer: (A)

Detailed Solution – Question 114

$$y(n - n_0) = x(n - n_0 + 1) \text{ (time varying)}$$

$$y(n) = x(n + 1) \text{ (depends on future)}$$

$$\text{i.e. } y(1) = x(2) \text{ (non causal)}$$

For bounded input, system has bounded output. So it is stable.

$$\begin{aligned} y(n) &= x(n), n \geq 1 \\ &= 0, n = 0 \\ &= x(n + 1), n \leq -1 \end{aligned}$$

So, system is linear.

Question 115: GATE EC 2001, Signals and Systems

MCQ

1 Mark

If a signal $f(t)$ has energy E , the energy of the signal $f(2t)$ is equal to

- (A) E
- (B) **(Correct)** $\frac{E}{2}$
- (C) $2E$
- (D) $4E$

Correct Answer: (B)

Detailed Solution – Question 115

$$\begin{aligned} E &= \int_{-\infty}^{\infty} f(t)^2 dt \\ E' &= \int_{-\infty}^{\infty} f(2t)^2 dt \\ &= \int_{-\infty}^{\infty} f(p)^2 - \frac{dp}{2} \left(2t = p; dt = \frac{dp}{2} \right) \\ E' &= \frac{E}{2} \end{aligned}$$

Question 116: GATE EC 2001, Signals and Systems

MCQ

1 Mark

Let $\delta(t)$ denote the delta function. The value of the integral $\int_{-\infty}^{\infty} \delta(t) \cos\left(\frac{3t}{2}\right) dt$ is

- (A) **(Correct)** 1
- (B) -1
- (C) 0

(D) $\frac{\pi}{2}$

Correct Answer: (A)

Detailed Solution – Question 116

$$\int_{-\infty}^{\infty} \delta(t) \cos\left(\frac{3t}{2}\right) dt = f(0) = \cos\left(\frac{3 \times 0}{2}\right) = \cos 0 = 1$$

Question 117: GATE EC 2015-SET-1, Signals and Systems

MCQ

2 Marks

Two sequences $[a, b, c]$ and $[A, B, C]$ are related as

$$\begin{bmatrix} A \\ B \\ C \end{bmatrix} = \begin{bmatrix} 1 & 1 & 1 \\ 1 & W_3^{-1} & W_3^{-2} \\ 1 & W_3^{-2} & W_3^{-4} \end{bmatrix} \begin{bmatrix} a \\ b \\ c \end{bmatrix} \text{ where } W_3 = e^{j\frac{2\pi}{3}}$$

If another sequence $[p, q, r]$ is derived as,

$$\begin{bmatrix} p \\ q \\ r \end{bmatrix} = \begin{bmatrix} 1 & 1 & 1 \\ 1 & W_3^1 & W_3^2 \\ 1 & W_3^2 & W_3^4 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 \\ 0 & W_3^2 & 0 \\ 0 & 0 & W_3^4 \end{bmatrix} \begin{bmatrix} A/3 \\ B/3 \\ C/3 \end{bmatrix}$$

then the relationship between the sequences $[p, q, r]$ and $[a, b, c]$ is

$p, q, r = [b, a, c]$

$p, q, r = [b, c, a]$

(A) **(Correct)** $[p, q, r] = [c, a, b]$

$p, q, r = [c, b, a]$

Correct Answer: (C)

Detailed Solution – Question 117

$$\begin{bmatrix} A \\ B \\ C \end{bmatrix} = \begin{bmatrix} a + b + c \\ a + bW_3^{-1} + cW_3^{-2} \\ a + bW_3^{-2} + cW_3^{-1} \end{bmatrix}$$
$$\begin{bmatrix} p \\ q \\ r \end{bmatrix} = \begin{bmatrix} 1 & w_3^2 & w_3^1 \\ 1 & w_3^1 w_3^2 & w_3^2 w_3^1 \\ 1 & w_3^2 w_3^2 & W_3^1 W_3^1 \end{bmatrix} \begin{bmatrix} \frac{a+b+c}{3} \\ \frac{a+bW_3^{-1}+cW_3^2}{3} \\ \frac{a+bW_3^{-2}+cW_3^{-1}}{3} \end{bmatrix}$$

where $W_3^4 = e^{j\frac{2\pi}{3}}$

$$W_3^2 = e^{j\frac{4\pi}{3}}$$

$$W_3^{-1} = e^{-j\frac{2\pi}{3}}$$

$$W_3^{-2} = e^{-j\frac{4\pi}{3}}$$

$$W_3^{-4} = W_3^{-1} = e^{-j\frac{2\pi}{3}}$$

$$\begin{bmatrix} p \\ q \\ r \end{bmatrix} = \begin{bmatrix} c \\ a \\ b \end{bmatrix}$$

Question 118: GATE EC 2014-SET-4, Signals and Systems

MCQ

2 Marks

The N -point DFT X of a sequence $x[n]$, $0 \leq n \leq N-1$ is given by,

$$X[k] = \frac{1}{\sqrt{N}} \sum_{n=0}^{N-1} x[n] e^{-j \frac{2\pi}{N} nk}, \quad 0 \leq k \leq N-1$$

Denote this relation as $X = \text{DFT}(x)$. For $N=4$, which one of the following sequences satisfies $\text{DFT}(\text{DFT}(x)) = x$?

(A)

$$x = [1 \quad 2 \quad 3 \quad 4]$$

(B) (Correct)

$$x = [1 \quad 2 \quad 3 \quad 2]$$

(C)

$$x = [1 \quad 3 \quad 2 \quad 2]$$

(D)

$$x = [1 \quad 2 \quad 2 \quad 3]$$

Correct Answer: (B)

Detailed Solution – Question 118

$$\text{DFT}(\text{DFT}(x)) = x$$

$$\text{Let, } x = [123]$$

$$\text{DFT}(x) = \frac{1}{\sqrt{4}} \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 1 \\ 2 \\ 3 \\ 2 \end{bmatrix}$$

$$= \frac{1}{2} \begin{bmatrix} 8 \\ -2 \\ 0 \\ -2 \end{bmatrix} = \begin{bmatrix} 4 \\ -1 \\ 0 \\ -1 \end{bmatrix}$$

$$\text{DFT}(\text{DFT}(x)) = \frac{1}{\sqrt{4}} \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 4 \\ -1 \\ 0 \\ -1 \end{bmatrix}$$

$$= \frac{1}{2} \begin{bmatrix} 2 \\ 4 \\ 6 \\ 4 \end{bmatrix} = \begin{bmatrix} 1 \\ 2 \\ 3 \\ 2 \end{bmatrix}$$

Question 119: GATE EC 2014-SET-4, Signals and Systems

NAT

1 Mark

The sequence $x[n] = 0.5^n u[n]$, where $u[n]$ is the unit step sequence, is convolved with itself to obtain $y[n]$. Then $\sum_{n=-\infty}^{+\infty} y[n]$ is -----.

Detailed Solution – Question 119

$$\begin{aligned}\text{Given } x[n] &= 0.5^n u[n] \\ y[n] &= x[n] * x[n] \\ &= \sum_{k=-\infty}^{\infty} x(k)h(n-k) \\ &= \sum_{k=-\infty}^{\infty} (0.5)^k u(k)(0.5)^{n-k} u(n-k) \\ &= (0.5)^n \left[\sum_{k=-\infty}^{\infty} u(k)u(n-k) \right]\end{aligned}$$

Also we know that $u[n] * u[n] = (n+1)u[n] \therefore$ Using the above formula, we get

$$\begin{aligned}y[n] &= (0.5)^n (n+1)u[n] \\ \text{Let } p &= \sum_{n=0}^{\infty} (0.5)^n (n+1) \\ \text{Also let } a &= 0.5 \\ \therefore p &= \sum_{n=0}^{\infty} a^n (n+1) \\ \rho &= a^0(1) + a^1(1+1) + a^2(2+1) + a^3(3+1) + \dots \\ ap &= a(1) + a^2(2) + a^3(3) + \dots \\ p - ap &= a^0 \cdot 1 + a^1 + a^2 + \dots \\ p(1-a) &= \frac{1}{1-a} \\ p &= \frac{1}{(1-a)^2} \\ a &= 0.5 \text{ or } \frac{1}{2} \\ p &= \frac{1}{(1-\frac{1}{2})^2} = \frac{1}{(\frac{1}{2})^2} = 4\end{aligned}$$

Question 120: GATE EC 2014-SET-4, Signals and Systems

NAT

1 Mark

A Fourier transform pair is given by

$$\left(\frac{2}{3}\right)^n u[n+3] \xleftrightarrow{FT} \frac{Ae^{-j6\pi f}}{1 - \left(\frac{2}{3}\right)e^{-j2\pi f}}$$

where $u[n]$ denotes the unit step sequence. The value of A is -----.

Detailed Solution – Question 120

$$\left(\frac{2}{3}\right)^n u(n+3) \xleftrightarrow{F.T.} \frac{Ae^{j6\pi f}}{1 - \left(\frac{2}{3}\right)e^{-j2\pi f}}$$

Let, $x[n] = \left(\frac{2}{3}\right)^n u(n+3)$ Discrete Fourier transform is given as

$$\begin{aligned} X(e^{j\omega}) &= \sum_{n=-\infty}^{\infty} x[n]e^{-j\omega n} \\ &= \sum_{n=-3}^{\infty} \left(\frac{2}{3}\right)^n e^{-j\omega n} \end{aligned}$$

Put, $n+3 = m$

$$\begin{aligned} \text{So, } x(e^{j\omega}) &= \sum_{m=0}^{\infty} \left(\frac{2}{3}\right)^{m-3} e^{-j\omega(m-3)} \\ &= \left(\frac{2}{3}\right)^{-3} \sum_{m=0}^{\infty} \left(\frac{2}{3}\right)^m e^{-j\omega m} e^{j\omega 3} \\ &= \left(\frac{3}{2}\right)^3 \sum_{m=0}^{\infty} \left(\frac{2}{3}e^{-j\omega}\right)^m \cdot e^{j\omega 3} \\ &= \frac{3.375 \cdot e^{j2\pi/3}}{1 - \frac{2}{3}e^{-j2\pi t}} \\ &= \frac{3.375e^{j\pi\pi f}}{1 - \frac{2}{3}e^{-j2\pi t}} \end{aligned}$$

So, $A = 3.375$

Question 121: GATE EC 2014-SET-2, Signals and Systems

MCQ

1 Mark

An FIR system is described by the system function $H(z) = 1 + \frac{7}{2}z^{-1} + \frac{3}{2}z^{-2}$ The system is

- (A) maximum phase
- (B) minimum phase
- (C) **(Correct)** mixed phase
- (D) zero phase

Correct Answer: (C)

Detailed Solution – Question 121

Minimum phase $\Rightarrow$ all zeroes are inside the unit circle.

For maximum phase, all the zeroes are outside the unit circle. $H(z) = 1 + \frac{7}{2}z^{-1} + \frac{3}{2}z^{-2} = 0$
 $2z^2 + 7z + 3 = 0$ $(2z+1)(z+3) = 0$ $z_1 = -\frac{1}{2}$ (inside the unit circle) $z_2 = -3$ (outside the unit circle) $\therefore$ Mixed phase.

Question 122: GATE EC 2014-SET-1, Signals and Systems

NAT

2 Marks

Consider a discrete time periodic signal $x[n] = \sin(\frac{\pi n}{5})$. Let a_k be the complex Fourier series coefficients of $x[n]$. The coefficients $\{a_k\}$ are non-zero when $k = Bm \pm 1$, where m is any integer. The value of B is -----.

Detailed Solution – Question 122

From discrete Fourier series definition

$$\begin{aligned} x[n] &= \sum_{K=0}^{N-1} a_K e^{jK(\frac{2\pi}{N})n} \\ &= a_{-1} e^{-j\frac{2\pi}{N}n} + a_0 + a_1 e^{j\frac{2\pi}{N}n} \quad \dots (i) \\ x[n] &= \frac{-1}{2j} e^{-i\frac{\pi}{5}n} + \frac{1}{2j} e^{i\frac{\pi}{5}n} \end{aligned}$$

Also given $x[n] = \sin(\frac{\pi n}{5})$ where $N = 10$ $[\frac{2\pi}{N} = \frac{\pi}{5} \Rightarrow N = 10]$ By comparison $a_1 = \frac{1}{2j}$ and $a_9 = a_{-1} = \frac{-1}{2j}$ As the TFS coefficient a_K is also periodic with period $N=10$.

$$a_1 = a_{11} = a_{21} \dots$$

$$a_{-1} = a_9 = a_{19} \dots$$

Given that a_K is non-zero for $K = Bm \pm 1$

$$\begin{array}{ccc} Bm \pm 1 = 1 & & 9 \dots \\ -1 & & 11 \dots \\ \text{For } m = 0 & \text{for} & m = 1 \end{array}$$

To satisfy this condition B must be '10' where 'm' is any integer.

Question 123: GATE EC 2013, Signals and Systems

MCQ

1 Mark

The DFT of a vector $[a \ b \ c \ d]$ is the vector

$$[\alpha \ \beta \ \gamma \ \delta]$$

. Consider the product

$$[p \ q \ r \ s] = [a \ b \ c \ d] \begin{bmatrix} a & b & c & d \\ d & a & b & c \\ c & d & a & b \\ b & c & d & a \end{bmatrix}$$

The DFT of the vector

$$[p \ q \ r \ s]$$

is a scaled version of

(A) (Correct)

$$[\alpha^2 \ \beta^2 \ \gamma^2 \ \delta^2]$$

(B)

$$[\sqrt{\alpha} \ \sqrt{\beta} \ \sqrt{\gamma} \ \sqrt{\delta}]$$

(C)

$$[\alpha + \beta \ \beta + \delta \ \delta + \gamma \ \gamma + \alpha]$$

(D)

$$[\alpha \quad \beta \quad \gamma \quad \delta]$$

Correct Answer: (A)

Detailed Solution – Question 123

$$\begin{aligned}\text{DFT}[pqrs] &= [abcd] * [abcd] \\ \text{So, DFT}[pqrs] &= [\alpha^2 \beta^2 \gamma^2 \delta^2]\end{aligned}$$

Question 124: GATE EC 2011, Signals and Systems

MCQ

1 Mark

The first six points of the 8-point DFT of a real valued sequence are 5, $1-j3$, 0, $3-j4$, 0 and $3+j4$. The last two points of the DFT are respectively

- (A) 0, $1-j3$
- (B) **(Correct)** 0, $1+j3$
- (C) $1+j3$, 5
- (D) $1-j3$, 5

Correct Answer: (B)

Detailed Solution – Question 124

$$\begin{aligned}x[n] &\rightarrow \text{real} \\ X[k] &\rightarrow \text{Conjugate symmetric} \\ \Rightarrow X[k] &= X^*[N-k] \\ N &= 8 \\ X[k] &= X^*[8-k] \\ \therefore X[6] &= X^*[8-6] = X^*[2] = 0 \\ X[7] &= X^*[8-7] = X^*[1] = 1+j3\end{aligned}$$

Question 125: GATE EC 2010, Signals and Systems

MCQ

1 Mark

For a N-point FFT algorithm $N = 2^m$, which one of the following statements is TRUE ?

- (A) It is not possible to construct a signal flow graph with both input and output in normal order
- (B) The number of butterflies in the m^{th} stage is N/m
- (C) In-place computation requires storage of only $2N$ data
- (D) **(Correct)** Computation of a butterfly requires only one complex multiplication.

Correct Answer: (D)

Detailed Solution – Question 125

For an N-point FFT algorithm with $N = 2^m$, computation of a butterfly requires only one complex multiplication and two complex additions

Question 126: GATE EC 2009, Signals and Systems

MCQ

1 Mark

The 4-point Discrete Fourier Transform (DFT) of a discrete time sequence 1,0,2,3 is

0, -2+2j, 2, -2-2j

2, 2+2j, 6, 2-2j

6, 1-3j, 2, 1+3j

(A) **(Correct)** [6, -1+3j, 0, -1-3j]

Correct Answer: (D)

Detailed Solution – Question 126

4-point DFT of sequence 1, 0, 2, 3 is given as

$$\begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -j & -1 & j \\ 1 & -1 & 1 & -1 \\ 1 & j & -1 & -j \end{bmatrix} \begin{bmatrix} 1 \\ 0 \\ 2 \\ 3 \end{bmatrix} = \begin{bmatrix} 1+2+3 \\ 1-2+3j \\ 1+2-3 \\ 1-2-3j \end{bmatrix} = \begin{bmatrix} 6 \\ -1+3j \\ 0 \\ -1-3j \end{bmatrix}$$

Question 127: GATE EC 2009, Signals and Systems

MCQ

1 Mark

A system with transfer function $H(z)$ has impulse response $h(\cdot)$ defined as $h(2)=1$, $h(3)=-1$ and $h(k)=0$ otherwise. Consider the following statements.

S1 : $H(z)$ is a low-pass filter.

S2 : $H(z)$ is an FIR filter.

Which of the following is correct?

(A) **(Correct)** Only S2 is true

(B) Both S1 and S2 are false

(C) Both S1 and S2 are true, and S2 is a reason for S1

(D) Both S1 and S2 are true, but S2 is not a reason for S1



Correct Answer: (A)

Detailed Solution – Question 127

$$h(2) = 1$$

$$h(3) = -1$$

$$h(k) = 0 \text{ otherwise}$$



It is finite impulse response. It is not low pass filter

Question 128: GATE EC 2008, Signals and Systems

MCQ

1 Mark

$x(n)$ is a real-valued periodic sequence with a period N . $x(n)$ and $X(k)$ form N -point Discrete Fourier Transform (DFT) pairs. The DFT $Y(k)$ of the sequence $y(n) = \frac{1}{N} \sum_{r=0}^{N-1} x(r)x(n+r)$ is

- (A) **(Correct)** $|X(k)|^2$
- (B) $\frac{1}{N} \sum_{r=0}^{N-1} X(r)X^*(k+r)$
- (C) $\frac{1}{N} \sum_{r=0}^{N-1} X(r)X(k+r)$
- (D) 0

Correct Answer: (A)

Question 129: GATE EC 2007, Signals and Systems

MCQ

1 Mark

A 5-point sequence $x[n]$ is given as $x[-3]=1$, $x[-2]=1$, $x[-1]=0$, $x[0]=5$ and $x[1]=1$. Let $X(e^{j\omega})$ denoted the discrete-time Fourier transform of $x[n]$. The value of $\int_{-\pi}^{\pi} X(e^{j\omega})d\omega$ is

- (A) 5
 (B) **(Correct)** 10π
 (C) 16π
 (D) $5 + j10\pi$

Correct Answer: (B)

Detailed Solution – Question 129


$$\begin{aligned}
 X(e^{j\omega}) &= e^{3/\omega} + e^{2/\omega} + 0 + 5 + e^{-j\omega} \\
 \therefore \int_{-\pi}^{\pi} e^{zi\omega} d\omega &= 0 \text{ if } a \neq 0 \\
 \int_{-\pi}^{\pi} X(e^{j\omega}) d\omega &= \left[\frac{e^{3/\omega}}{3j} + \frac{e^{2j\omega}}{2j} + 5\omega + \frac{e^{-j\omega}}{-j} \right]_{-\pi}^{\pi} \\
 &= 5\pi + 5\pi = 10\pi
 \end{aligned}$$

Question 130: GATE EC 2005, Signals and Systems

MCQ

1 Mark

A sequence $x(n)$ has non-zero values as shown in figure.



The Fourier transform of $y(2n)$ will be

- (A) $e^{-j2\omega} [\cos 4\omega + 2\cos 2\omega + 2]$
 (B) $\cos 2\omega + 2\cos \omega + 2$
 (C) **(Correct)** $e^{-j\omega} [\cos 2\omega + 2\cos \omega + 2]$

(D) $e^{j2\omega}[\cos 2\omega + 2\cos \omega + 2]$

Correct Answer: (C)

Detailed Solution – Question 130

$$y(2n) = x(n-1), \text{ seeing in graph}$$

$$f(n) = y(2n)$$

$$= \frac{1}{2}\delta(n+1) + \delta(n) + 2\delta(n-1) + \delta(n-2) + \frac{1}{2}\delta(n-3)$$

Taking z-transform

$$F(z) = \frac{1}{2}z + 1 + 2z^{-1} + z^{-2} + \frac{1}{2}z^{-3}$$

$$Z = e^{j\omega}$$

$$F(e^{j\omega}) = \frac{1}{2}e^{j\omega} + 1 + 2e^{-j\omega} + e^{-2j\omega} + \frac{1}{2}e^{-3j\omega}$$

$$= e^{-j\omega} \left(\frac{1}{2}e^{2j\omega} + e^{j\omega} + 2 + e^{-j\omega} + \frac{1}{2}e^{-2j\omega} \right)$$

$$= e^{-j\omega} \left[\frac{e^{2j\omega} + e^{-2j\omega}}{2} + e^{j\omega} + e^{-j\omega} + 2 \right]$$



$$f(n) = e^{-j\omega} [\cos 2\omega + 2\cos \omega + 2]$$

Question 131: GATE EC 2005, Signals and Systems

MCQ

1 Mark




A sequence $x(n]$ has non-zero values as shown in figure.




The sequence

$$y(n) = \begin{cases} X(\frac{n}{2} - 1), & \text{For } n \text{ is even} \\ 0, & \text{For } n \text{ is odd} \end{cases}$$

will be





(A) (Correct) A

(B) B

(C) C

(D) D

Correct Answer: (A)

Detailed Solution – Question 131

$$\begin{aligned}
 y(n) &= x\left(\frac{n}{2} - 1\right), n \text{ even} \\
 &= 0 \text{ for } n \text{ odd} \\
 n = 0, y(n) &= x(-1) = 1 \\
 n = 2, y(n) &= x(0) = 2 \\
 n = 4, y(n) &= x(1) = 1 \\
 n = 6, y(n) &= x(2) = 1/2
 \end{aligned}$$

Question 132: GATE EC 2005, Signals and Systems

MCQ

1 Mark

A signal $x(n) = \sin(\omega_0 n + \phi)$ is the input to a linear time-invariant system having a frequency response $H(e^{j\omega})$. If the output of the system is $Ax(n - n_0)$ then the most general form of $\angle H(e^{j\omega})$ will be

- (A) $-n_0\omega_0 + \beta$ for any arbitrary real β
- (B) **(Correct)** $-n_0\omega_0 + 2\pi k$ for any arbitrary integer k
- (C) $n_0\omega_0 + 2\pi k$ for any arbitrary integer k
- (D) $-n_0\omega_0 + \phi$

Correct Answer: (B)

Detailed Solution – Question 132

$$\begin{aligned}\sin(\omega_0 n + \phi) &= x(n) \leftrightarrow X(e^{j\omega}) \\ y(n) &= Ax(n - n_0) \\ (e^{j\omega}) &= Ae^{-j\omega} X(e^{j\omega}) \\ H(e^{j\omega}) &= \frac{Y(e^{j\omega})}{X(e^{j\omega})} = Ae^{-jn_0\omega} \\ \angle H(e^{j\omega}) &= -n_0\omega_0 + 2\pi k \quad (\text{at } \omega = \omega_0)\end{aligned}$$

Question 133: GATE EC 2005, Signals and Systems

MCQ

1 Mark

Match the following and choose the correct combination.

Group 1

E. Continuous and aperiodic signal

F. Continuous and periodic signal

G. Discrete and aperiodic signal

H. Discrete and periodic signal Group 2

1. Fourier representation is continuous and aperiodic

2. Fourier representation is discrete and aperiodic

3. Fourier representation is continuous and periodic

4. Fourier representation is discrete and periodic

- (A) E - 3, F - 2, G - 4, H - 1
- (B) E - 1, F - 3, G - 2, H - 4
- (C) **(Correct)** E - 1, F - 2, G - 3, H - 4
- (D) E - 2, F - 1, G - 4, H - 3

Correct Answer: (C)

Question 134: GATE EC 2005, Signals and Systems

MCQ

1 Mark

Let $x(n) = (\frac{1}{2})^n u(n)$, $y(n) = x^2(n)$ and $Y(e^{j\omega})$ be the Fourier transform of $y(n)$ then $Y(e^{j0})$

- (A) $\frac{1}{4}$
- (B) 2

(C) 4

(D) **(Correct)** $\frac{4}{3}$

Correct Answer: (D)

Detailed Solution – Question 134

$$x(n) = \left(\frac{1}{2}\right)^n \cdot u(n)$$

$$y(n) = x^2(n) = \left(\frac{1}{2}\right)^{2n} u^2(n)$$

$$y(n) = \left(\frac{1}{4}\right)^n u(n)$$

$$Y(z) = \frac{1}{1 - \frac{1}{4}z^{-1}}$$

Put, $z = e^{j\omega}$

$$Y(e^{j\omega}) = \frac{1}{1 - \frac{1}{4}e^{-j\omega}};$$

$$Y(e^{j0}) = \frac{1}{1 - \frac{1}{4}} = \frac{4}{3}$$

Question 135: GATE EC 2004, Signals and Systems

MCQ

1 Mark

The impulse response $h[n]$ of a linear time invariant system is given as

$$\begin{cases} -2\sqrt{2} & n = 1, -1 \\ 4\sqrt{2} & n = 2, -2 \\ 0 & \text{otherwise} \end{cases}$$

If the input to the above system is the sequence $e^{j\pi n/4}$, then the output is

(A) $4\sqrt{2}e^{j\pi n/4}$

(B) $4\sqrt{2}e^{-j\pi n/4}$

(C) $4e^{j\pi n/4}$

(D) **(Correct)** $-4e^{j\pi n/4}$

Correct Answer: (D)

Detailed Solution – Question 135

$$\begin{aligned}
 h(n) &= 4\sqrt{2}\delta(n+2) - 2\sqrt{2}\delta(n+1) \\
 &\quad - 2\sqrt{2}\delta(n-1) + 4\sqrt{2}\delta(n-2) \\
 x(n) &= e^{jn\pi/4} \\
 y(n) &= x(n)*h(n) \\
 &= 4\sqrt{2}\delta(n+2)*e^{jn\pi/4} + 4\sqrt{2}\delta(n-2)*e^{jn\pi/4} \\
 &\quad - 2\sqrt{2}\left[\delta(n+1)*e^{jn\pi/4} + \delta(n-1)*e^{jn\pi/4}\right] \\
 x(n)*\delta(n-a) &\rightarrow x(n-a) \\
 y(n) &= 4\sqrt{2}\left[e^{j\pi/4(n+2)} + e^{j\pi/4(n-2)}\right] \\
 &\quad - 2\sqrt{2}\left[e^{j\pi/4(n+1)} + e^{j\pi/4(n-1)}\right] \\
 &= e^{jn\pi/4}\left[4\sqrt{2}\left(e^{j\pi/2} + e^{-j\pi/2}\right)\right] \\
 &\quad - 2\sqrt{2}\left(e^{j\pi/4} + e^{-j\pi/4}\right) \\
 &= e^{jn\pi/4}[0 - 2\sqrt{2} \times 2\cos\pi/4] \\
 y(n) &= -4e^{jn\pi/4}
 \end{aligned}$$

Question 136: GATE EC 2014-SET-4, Signals and Systems

MCQ

1 Mark

A real-valued signal $x(t)$ limited to the frequency band $|f| \leq \frac{W}{2}$ is passed through a linear time invariant system whose frequency response is

$$H(f) = \begin{cases} e^{-j4\pi f}, & |f| \leq \frac{W}{2} \\ 0, & |f| > \frac{W}{2} \end{cases}$$

The output of the system is

- (A) $x(t+4)$
- (B) $x(t-4)$
- (C) $x(t+2)$
- (D) **(Correct)** $x(t-2)$

Correct Answer: (D)

Detailed Solution – Question 136

$$\text{Given: } H(f) = \begin{cases} e^{-j4\pi t}, & |f| \leq \frac{\omega}{2} \\ 0, & |f| > \frac{\omega}{2} \end{cases}$$

$$\text{So, } |H(f)| = 1$$

$$H(f) = e^{-j2.2\pi t}$$

$$H(\omega) = e^{j2\omega} \quad |f| \leq \frac{\omega}{2}$$

$$h(t) = \delta(t - 2)$$

As we know that

$$y(t) = x(t) * h(t)$$

$$\text{or } y(t) = X(\omega) \cdot H(\omega)$$

$$y(t) = x(t) * \delta(t - 2)$$

$$y(t) = x(t - 2)$$

Question 137: GATE EC 2014-SET-3, Signals and Systems

MCQ

1 Mark

The phase response of a passband waveform at the receiver is given by $\varphi(f) = -2\pi\alpha(f - f_c) - 2\pi\beta f_c$ where f_c is the centre frequency, and α and β are positive constants. The actual signal propagation delay from the transmitter to receiver is

- (A) $\frac{\alpha - \beta}{\alpha + \beta}$
- (B) $\frac{\alpha\beta}{\alpha + \beta}$
- (C) **(Correct)** α
- (D) β

Correct Answer: (C)

Detailed Solution – Question 137

Group delay is given by $= \frac{-1}{2\pi} \frac{d\phi(f)}{df} = \frac{-1}{2\pi} [-2\pi\alpha]$ Group delay $= \alpha$

Question 138: GATE EC 2014-SET-2, Signals and Systems

NAT

2 Marks

The value of the integral $\int_{-\infty}^{\infty} \text{sinc}^2(5t) dt$ is -----.

Detailed Solution – Question 138

$$\int_{-\infty}^{\infty} \sin^2(5t) dt$$

$$\begin{aligned} \text{Let, } f(t) &= \sin c(5t) \\ &= S_a(5\pi t) \quad [\because \sin c(t) = S_a(\pi t)] \end{aligned}$$

$$TSa\left(t \cdot \frac{T}{2}\right) \longleftrightarrow 2\pi G_T(\omega)$$



$$\frac{T}{2} = 5\pi \Rightarrow [T = 10\pi]$$

$$10\pi Sa(5\pi t) \longleftrightarrow 2\pi G_{10\pi}(\omega)$$

$$\Rightarrow F(\omega) = \frac{1}{5} G_{10\pi}(\omega)$$

$$ESD_f = |F(\omega)|^2$$

$$E_f = \int_{-\infty}^{\infty} f^2(t) dt = \frac{1}{2\pi} \int_{-\infty}^{\infty} ESD_f d\omega$$



$$\begin{aligned} \int_{-\infty}^{\infty} \sin^2(5t) dt &= \frac{1}{2\pi} \int_{-5\pi}^{5\pi} \left(\frac{1}{5}\right)^2 d\omega \\ &= \frac{1}{2\pi} \times \frac{1}{25} \times 10\pi = \frac{1}{5} \end{aligned}$$

Question 139: GATE EC 2014-SET-1, Signals and Systems

MCQ

2 Marks

For a function $g(t)$, it is given that $\int_{-\infty}^{+\infty} g(t)e^{-j\omega t} dt = \omega e^{-2\omega^2}$ for any real value ω . If $y(t) = \int_{-\infty}^t g(\tau) d\tau$, then $\int_{-\infty}^{+\infty} y(t) dt$ is

- (A) 0
- (B) (Correct) $-j$

(C) $-\frac{j}{2}$

(D) $\frac{j}{2}$

Correct Answer: (B)

Detailed Solution – Question 139

$$\begin{aligned}G(j\omega) &= \omega e^{-2\omega^2} \\ \int_{-\infty}^* g(t)dt &= G(j0) = 0 \\ y(t) &= g(t) * u(t) \\ \Rightarrow r(j\omega) &= G(j\omega)U(j\omega) \\ \Rightarrow \gamma(j\omega) &= G(j\omega) \left[\frac{1}{j\omega} + \pi\delta(\omega) \right] \\ &= \frac{\omega e^{-2\omega^2}}{j\omega} + \omega e^{-2\omega^2} \pi\delta(\omega) \\ \int_{-\infty}^* y(t)dt &= Y(j0) = \frac{1}{j} = -j\end{aligned}$$

Question 140: GATE EC 2014-SET-1, Signals and Systems

NAT

1 Mark

A continuous, linear time-invariant filter has an impulse response $h(t)$ described by

$$h(t) = \begin{cases} 3 & \text{for } 0 \leq t \leq 3 \\ 0 & \text{otherwise} \end{cases}$$

When a constant input of values 5 is applied to this filter, the steady state output is.....

Detailed Solution – Question 140

$$h(t) = \begin{cases} 3, & \text{for } 0 \leq t \leq 3 \\ 0, & \text{otherwise} \end{cases}$$

$$h(t) = 3[u(t) - u(t - 3)]$$

$$H(s) = 3 \left[\frac{1}{s} - \frac{e^{-3s}}{s} \right]$$

$$\therefore x(t) = 5$$

$$\text{Then } x(s) = \frac{5}{s}$$

We know that $Y(s) = H(s)X(s) = 3 \left[\frac{1}{s} - \frac{e^{-3s}}{s} \right] \cdot \frac{5}{s}$ Steady state output

$$\begin{aligned}&= \lim_{s \rightarrow 0} s \cdot Y(s) = \lim_{s \rightarrow 0} s \cdot \frac{15(1 - e^{-3s})}{s} \\&= 15 \cdot \lim_{s \rightarrow 0} 3e^{-3s} \quad [\because \text{L-Hospital's rule}] \\&= 45\end{aligned}$$

Question 141: GATE EC 2012, Signals and Systems

MCQ

1 Mark

The Fourier transform of a signal $h(t)$ is $H(j\omega) = (2\cos\omega)(\sin 2\omega) / \omega$. The value of $h(0)$ is

- (A) $1/4$
- (B) $1/2$
- (C) **(Correct)** 1
- (D) 2

Correct Answer: (C)



Detailed Solution – Question 141

$$\frac{2 \cos \omega \sin 2\omega}{\omega} = H(\omega)$$

$$H(\omega) = 2 \cos \omega \left(\frac{2 \sin 2\omega}{2\omega} - H_1(j\omega) \cdot H_2(j\omega) \right)$$

$$\text{where, } H_1(j\omega) = 2 \cos \omega$$

$$H_2(j\omega) = \frac{2 \sin 2\omega}{2\omega} = 2 \text{Sa}(2\omega)$$





$$H_1(j\omega) = 2 \cos \omega = (e^{j\omega} + e^{-j\omega}) = e^{j\omega t} + e^{j\omega(-1)}$$

So

$$H(j\omega) = 2 \cos \omega H_2(j\omega) = (e^{j\omega} + e^{-j\omega}) H_2(j\omega)$$

$$H(j\omega) = e^{j\omega} H_2(j\omega) + e^{-j\omega} H_2(j\omega) \Rightarrow h(t) = h_2(t+1) + h_2(t-1)$$



So, $h(0) = 1$

Question 142: GATE EC 2009, Signals and Systems

MCQ

1 Mark

Consider a system whose input x and output y are related by the equation $y(t) = \int_{-\infty}^{\infty} x(t - \tau)g(2\tau)d\tau$ where $h(t)$ is shown in the graph.



Which of the following four properties are possessed by the system ?

BIBO : Bounded input gives a bounded output.

Causal : The system is causal,

LP : The system is low pass.

LTI : The system is linear and time-invariant.





- (A) Causal, LP
- (B) **(Correct)** BIBO, LTI
- (C) BIBO, Causal, LTI
- (D) LP, LTI

Correct Answer: (B)

Detailed Solution – Question 142

$$y(t) = \int_{-\infty}^{\infty} x(t - \tau)h(2\tau)d\tau$$



It is not low pass filter.
But the system is LTI and BIBO.

Question 143: GATE EC 2009, Signals and Systems

MCQ

1 Mark

A function is given by $f(t) = \sin^2 t + \cos 2t$. Which of the following is true ?

- (A) f has frequency components at 0 and $\frac{1}{2\pi} Hz$
- (B) **(Correct)** f has frequency components at 0 and $\frac{1}{\pi} Hz$
- (C) f has frequency components at $\frac{1}{2\pi}$ and $\frac{1}{\pi} Hz$
- (D) f has frequency components at 0, $\frac{1}{2\pi}$ and $\frac{1}{\pi} Hz$

Correct Answer: (B)

Detailed Solution – Question 143

$f(t) = \frac{1}{2}(1 - \cos 2t) + \cos 2t$ frequency components are

$$f_1 = 0$$
$$f_2 = \frac{\omega_2}{2\pi} = \frac{2}{2\pi} = \frac{1}{\pi} \text{ Hz}$$

Question 144: GATE EC 2008, Signals and Systems

MCQ

1 Mark

The impulse response $h(t)$ of a linear time invariant continuous time system is given by $h(t) = \exp(-2t)u(t)$, where $u(t)$ denotes the unit step function

The output of this system, to the sinusoidal input $x(t) = 2\cos(2t)$ for all time t , is

- (A) 0
- (B) $2^{-0.25} \cos(2t - 0.125\pi)$
- (C) $2^{-0.5} \cos(2t - 0.125\pi)$
- (D) **(Correct)** $2^{-0.5} \cos(2t - 0.25\pi)$

Correct Answer: (D)

Detailed Solution – Question 144

Input $x(t) = 2 \cos(2t)$ Frequency response

$$X(\omega) = 2\pi[\delta(\omega - 2) + \delta(\omega + 2)]$$

$$H(\omega) = \frac{1}{2 + j\omega}$$

$$\text{output } Y(\omega) = H(\omega)X(\omega)$$

$$\begin{aligned} &= \frac{1}{2+j\omega} \cdot 2\pi[\delta(\omega - 2) + \delta(\omega + 2)] \\ &= \frac{2\pi}{2+j2} \delta(\omega - 2) + \frac{2\pi}{2-j2} \delta(\omega + 2) \\ &= \frac{2\pi}{8} [(2 - j2)\delta(\omega - 2) + (2 + j2)\delta(\omega + 2)] \\ &= \frac{\pi}{4} [2\{\delta(\omega - 2) + \delta(\omega + 2)\} + j2\{\delta(\omega + 2) - \delta(\omega - 2)\}] \\ &= \frac{\pi}{2} [\delta(\omega - 2) + \delta(\omega + 2)] - j\frac{\pi}{2} [\delta(\omega - 2) - \delta(\omega + 2)] \\ \therefore y(t) &= \frac{\cos 2t}{2} + \frac{\sin 2t}{2} \\ &= \frac{\sqrt{2}}{2} \left[\frac{1}{\sqrt{2}} \cos 2t + \frac{1}{\sqrt{2}} \sin 2t \right] \\ &= \frac{1}{\sqrt{2}} \cos(2t - 0.25\pi) \\ &= 2^{-0.5} \cos(2t - 0.25\pi) \end{aligned}$$

Question 145: GATE EC 2008, Signals and Systems

MCQ

1 Mark

The signal $x(t)$ is described by

$$x(t) = \begin{cases} 1 & \text{for } -1 \leq t \leq +1 \\ 0 & \text{otherwise} \end{cases}$$

Two of the angular frequencies at which its Fourier transform becomes zero are

- (A) **(Correct)** $\pi, 2\pi$
- (B) $0.5\pi, 1.5\pi$
- (C) $0, \pi$
- (D) $2\pi, 2.5\pi$

Correct Answer: (A)

Detailed Solution – Question 145

$$\begin{aligned}
 X(\omega) &= \int_{-\infty}^{\infty} x(t)e^{-j\omega t} dt \\
 &= \int_{-1}^1 e^{-j\omega t} dt = \left. \frac{e^{-j\omega t}}{-j\omega} \right|_{-1}^1 \\
 &= \frac{e^{-j\omega}}{-j\omega} - \frac{e^{j\omega}}{-j\omega} \\
 &= \frac{1}{j\omega} (e^{i0} - e^{-j\omega}) \\
 X(\omega) &= 0 \\
 \Rightarrow e^{j\omega} - e^{-i\omega} &= 0 \\
 \Rightarrow e^{j\omega} - \frac{1}{e^{i\omega}} &= 0 \\
 \Rightarrow e^{2i\omega} - 1 &= 0 \\
 \Rightarrow e^{2j\omega} &= 1 \\
 \Rightarrow e^{i\omega} &= \pm 1 \\
 \Rightarrow \omega &= \pi, 2\pi
 \end{aligned}$$

Question 146: GATE EC 2007, Signals and Systems

MCQ

1 Mark

The 3-dB bandwidth of the low-pass signal $e^{-t}u(t)$, where $u(t)$ is the unit step function, is given by

- (A) (Correct) $\frac{1}{2\pi} Hz$
- (B) $\frac{1}{2\pi} \sqrt{\sqrt{2} - 1} Hz$
- (C) ∞
- (D) $1 Hz$

Correct Answer: (A)

Detailed Solution – Question 146

Laplace transform of $e^{-t}u(t) = \frac{1}{s+1} \therefore$ magnitude at 3 dB frequency $= \frac{1}{\sqrt{2}}$

$$\begin{aligned}
 \Rightarrow \frac{1}{\sqrt{2}} &= \frac{1}{\sqrt{1 + \omega^2}} \\
 \omega &= 1 \text{ rad} \\
 f &= \frac{1}{2\pi} \text{ Hz}
 \end{aligned}$$

Question 147: GATE EC 2006, Signals and Systems

MCQ

1 Mark

Let $x(t) \leftrightarrow X(j\omega)$ be Fourier Transform pair. The Fourier Transform of the signal $x(5t - 3)$ in terms of $X(j\omega)$ is given as

(A) **(Correct)** $\frac{1}{5}e^{-\frac{j3\omega}{5}}X\left(\frac{j\omega}{5}\right)$

(B) $\frac{1}{5}e^{\frac{j3\omega}{5}}X\left(\frac{j\omega}{5}\right)$

(C) $\frac{1}{5}e^{-j3\omega}X\left(\frac{j\omega}{5}\right)$

(D) $\frac{1}{5}e^{j3\omega}X\left(\frac{j\omega}{5}\right)$

Correct Answer: (A)

Detailed Solution – Question 147

$$x(t) \leftrightarrow x(j\omega)$$

$$x\left[5\left(t - \frac{3}{5}\right)\right] = \frac{1}{5}e^{-\frac{j3\omega}{5}}X\left(\frac{j\omega}{5}\right)$$

Using scaling and shifting property.

Question 148: GATE EC 2005, Signals and Systems

MCQ

1 Mark

For a signal $x(t)$ the Fourier transform is $X(f)$. Then the inverse Fourier transform of $X(3f + 2)$ is given by

(A) $\frac{1}{2}x\left(\frac{1}{2}\right)e^{j3\pi t}$

(B) **(Correct)** $\frac{1}{3}x\left(\frac{1}{3}\right)e^{j3\pi t}$

(C) $3x(3t)e^{-4j\pi t}$

(D) $x(3t+2)$

Correct Answer: (B)

Detailed Solution – Question 148

$$x\left[3\left(t + \frac{2}{3}\right)\right] = \frac{1}{3}x\left(\frac{t}{3}\right)e^{-j4\pi t/3}$$

Applying scaling & shifting property.

Question 149: GATE EC 2005, Signals and Systems

MCQ

1 Mark

The output $y(t)$ of a linear time invariant system is related to its input $x(t)$ by the following equations: $y(t) = 0.5x(t - t_d + T) + x(t - t_d) + 0.5x(t - t_d + T)$ The filter transfer function $H(\omega)$ of such a system is given by

- (A) **(Correct)** $(1 + \cos \omega T)e^{-j\omega t_d}$
- (B) $(1 + 0.5\cos \omega T)e^{-j\omega t_d}$
- (C) $(1 + \cos \omega T)e^{j\omega t_d}$
- (D) $(1 - 0.5\cos \omega T)e^{-j\omega t_d}$

Correct Answer: (A)

Detailed Solution – Question 149

$$y(t) = 0.5x(t - t_d + T) + 0.5x(t - t_d - T) + x(t - t_d)$$

Taking Fourier transform

$$Y(\omega) = [0.5e^{j\omega(-t_d+T)} + 0.5e^{j\omega(-t_d-T)} + e^{-j\omega t_d}] X(\omega)$$

$$\frac{Y(\omega)}{X(\omega)} = e^{-j\omega t_d} [0.5e^{j\omega T} + 0.5e^{-j\omega T} + 1]$$

$$\frac{Y(\omega)}{X(\omega)} = e^{-j\omega t_d} [\cos \omega T + 1]$$


$$H(\omega) = (1 + \cos \omega T)e^{-j\omega t_d}$$


Question 150: GATE EC 2004, Signals and Systems

MCQ

1 Mark

Let $x(t)$ and $y(t)$ with Fourier transforms $X(f)$ and $Y(f)$ respectively be related as shown in Fig.





Then $Y(f)$ is

- (A) $-\frac{1}{2}X(f/2)e^{-j\pi f}$
- (B) **(Correct)** $-\frac{1}{2}X(f/2)e^{j2\pi f}$
- (C) $-X(f/2)e^{j2\pi f}$
- (D) $-X(f/2)e^{-j2\pi f}$

Correct Answer: (B)

Detailed Solution – Question 150



$$\begin{aligned}
 y(t) &= -x[2(t+1)] \\
 x(t-t_0) &\leftrightarrow x(f)e^{-j2\pi ft_0} \\
 t_0 &= -1 \\
 x(at) &= \frac{1}{|a|}X\left(\frac{t}{a}\right) \\
 a &= -2 \\
 \therefore Y(f) &= -\frac{1}{2}X\left(\frac{f}{2}\right)e^{j2\pi f}
 \end{aligned}$$

Question 151: GATE EC 2004, Signals and Systems

MCQ

1 Mark

A rectangular pulse train $s(t)$ as shown in the figure is convolved with the signal $\cos^2(4\pi \times 10^3 t)$. The convolved signal will be a



- (A) DC
- (B) 12 kHz sinusoid
- (C) 8 kHz sinusoid
- (D) **(Correct)** 14 kHz sinusoid


Correct Answer: (D)

Detailed Solution – Question 151


$$T_0 = 0.1 \times 10^{-3} = 10^{-4}$$

$$f_0 = \frac{1}{T_0} = 10^4 = 10\text{kHz}$$

$\cos^2(4\pi \times 10^3 t)$ has frequency = 4kHz



So only at '0', we get output after convolution. (Only odd harmonics are present.)



Question 152: GATE EC 2004, Signals and Systems

MCQ

1 Mark

The Fourier transform of a conjugate symmetric function is always

- (A) imaginary
- (B) conjugate anti-symmetric
- (C) **(Correct)** real
- (D) conjugate symmetric

Correct Answer: (C)

Question 153: GATE EC 2003, Signals and Systems

MCQ

1 Mark

The system under consideration is an RC low-pass filter (RC-LPF) with $R = 1 \text{ k}\Omega$ and $C = 1.0 \text{ }\mu\text{F}$. Let $t_g(f)$ be the group delay function of the given RC-LPF and $f_2 = 100 \text{ Hz}$. Then $t_g(f_2)$ in ms, is

- (A) (Correct) 0.717
- (B) 7.17
- (C) 71.7
- (D) 4.505

Correct Answer: (A)

Detailed Solution – Question 153

$$\begin{aligned}H(\omega) &= \frac{1}{1 + j\omega RC} \\ \theta(\omega) &= -\tan^{-1} RC\omega \\ t_g &= \frac{10^{-3}}{1 + 10^{-6} \times 4\pi^2 \times 10^4} \\ t_g &= 0.717\text{ms}\end{aligned}$$

Question 154: GATE EC 2003, Signals and Systems

MCQ

1 Mark

Let $x(t)$ be the input to a linear, time-invariant system. The required output is $4x(t-2)$. The transfer function of the system should be

- (A) $4e^{j4\pi f}$
- (B) $2e^{-j8\pi f}$
- (C) (Correct) $4e^{-j4\pi f}$
- (D) $2e^{j8\pi f}$

Correct Answer: (C)

Detailed Solution – Question 154

$$\begin{aligned}y(t) &= 4x(t-2) \\ Y(s) &= 4e^{-2s}X(s) \\ \frac{Y(s)}{X(s)} &= 4e^{-2s} \\ H(f) &= 4e^{-2xj.2\pi t} = 4e^{-j4\pi t}\end{aligned}$$

Question 155: GATE EC 2002, Signals and Systems

MCQ

1 Mark

A linear phase channel with phase delay T_P and group delay T_g must have

- (A) **(Correct)** $T_P = T_g = \text{constant}$
- (B) $T_P \propto f$ and $T_g \propto f$
- (C) $T_P = \text{constant}$ and $T_g \propto f$
- (D) $T_P \propto f$ and $T_g = \text{constant}$

Correct Answer: (A)

Detailed Solution – Question 155

$$\begin{aligned}\theta(\omega) &= -\omega\zeta_0 \\ T_P &= \frac{-\theta(\omega)}{\omega} = T_0 \\ T_g &= - \cdot \frac{d\theta(\omega)}{d\omega} = T_0 \\ T_P &= T_g = T_0 = \text{constant}\end{aligned}$$

Question 156: GATE EC 2002, Signals and Systems

MCQ

1 Mark

The Fourier transform $F\{e^{-1}u(t)\}$ is equal to $\frac{1}{1+j2\pi f}$. therefore, $F\{\frac{1}{1+j2\pi t}\}$ is

- (A) $e^f u(f)$
- (B) $e^{-f} u(f)$
- (C) **(Correct)** $e^f u(-f)$
- (D) $e^{-f} u(-f)$

Correct Answer: (C)

Detailed Solution – Question 156

$$\begin{aligned}f(t) &= e^{-t}u(t) \\ F(t) &= \frac{1}{1+j2\pi f} \\ \text{From duality, } F(t) &\xleftrightarrow{FT} f(-f) \\ \Rightarrow F(t) &= \frac{1}{1+j2\pi t} \\ f(-f) &= e^f u(-f) \\ F(t) &\xleftrightarrow{FT} e^f u(-f)\end{aligned}$$

Question 157: GATE EC 2015-SET-1, Signals and Systems

MCQ

1 Mark

The result of the convolution $x(-t) * \delta(-t - t_o)$ is

- (A) $x(t + t_0)$
- (B) $x(t - t_0)$
- (C) $x(-t + t_o)$
- (D) **(Correct)** $x(-t - t_o)$

Correct Answer: (D)

Detailed Solution – Question 157

$$x(t) * \delta(-t - t_0) = x(-t) * \delta(t + t_0) = x(-t - t_0)$$

Question 158: GATE EC 2014-SET-2, Signals and Systems

NAT

2 Marks

Consider a discrete-time signal

$$x[n] = \begin{cases} n & \text{for } 0 \leq n \leq 10 \\ 0 & \text{otherwise} \end{cases}$$

If $y[n]$ is the convolution of $x[n]$ with itself, the value of $y[4]$ is

Detailed Solution – Question 158

$$\begin{aligned} x[n] &= \begin{cases} n & \text{for } 0 \leq n \leq 10 \\ 0 & \text{otherwise} \end{cases} \\ y[n] &= \sum_{k=-\infty}^{\infty} x(k)x(n-k) \\ y[4] &= \sum_{k=0}^{10} x(k)x(4-k) \\ &= x(0)x(4) + x(1)x(3) + x(2)x(2) + x(3)x(1) + 0 \\ &= 0 + (1 \times 3) + (2 \times 2) + (3 \times 1) \\ &= 10 \end{aligned}$$

Question 159: GATE EC 2013, Signals and Systems

MCQ

1 Mark

Two systems with impulse responses $h_1(t)$ and $h_2(t)$ are connected in cascade. Then the overall impulse response of the cascaded system is given by

- (A) product of $h_1(t)$ and $h_2(t)$
- (B) sum of $h_1(t)$ and $h_2(t)$

- (C) **(Correct)** convolution of $h_1(t)$ and $h_2(t)$
- (D) subtraction of $h_2(t)$ from $h_1(t)$

Correct Answer: (C)

Detailed Solution – Question 159

The overall impulse response $h(t)$ of the cascade system is given by: $h(t) = h_1(t) * h_2(t)$

Question 160: GATE EC 2012, Signals and Systems

MCQ

1 Mark

Let $y[n]$ denote the convolution of $h[n]$ and $g[n]$, where $h[n] = (1/2)^n u[n]$ and $g[n]$ is a causal sequence. If $y[0] = 1$ and $y[1] = 1/2$, then $g[1]$ equals


- (A) **(Correct)** 0
- (B) $1/2$
- (C) 1
- (D) $3/2$

Correct Answer: (A)



Detailed Solution – Question 160

$$h[n] = \left(\frac{1}{2}\right)^n u[n]$$

$$g[n] = ??$$



$$y[n] = \sum_{k=-\infty}^{\infty} h[n-k]g[k]$$



$$y[0] = \sum_{k=-\infty}^{\infty} h[-k]g[k]$$

$$y[0] = h[0]g[0]$$

$$1 = 1g[0]$$

$$g[0] = 1$$

$$y[1] = \sum_{k=-\infty}^{\infty} h[1-k]g[k]$$

$$y[1] = h[1]g[0] + h[0]g[1]$$

$h[1-k]$ will be zero for $k > 1$ and $g[k]$ will be zero for $k < 0$ as it is a causal sequence.

$$\frac{1}{2} = \frac{1}{2} \cdot 1 + 1g[1]$$

$$g[1] = 0$$

Question 161: GATE EC 2011, Signals and Systems

MCQ

1 Mark

A system is defined by its impulse response $h(n) = 2^n u(n-2)$. The system is

- (A) stable and causal
- (B) **(Correct)** causal but not stable
- (C) stable but not causal
- (D) unstable and non-causal

Correct Answer: (B)

Detailed Solution – Question 161

$h(n) = 2^n u(n-2)$ For causal system $h(n) = 0$ for $n < 0$ Hence given system is causal. For stability: $\sum_{n=2}^{\infty} 2^n = \infty$, so given system is not stable.

Question 162: GATE EC 2008, Signals and Systems

MCQ

1 Mark

A discrete time linear shift-invariant system has an impulse response $h[n]$ with $h[0]=1$, $h[1]=-1$, $h[2]=2$, and zero otherwise. The system is given an input sequence $x[n]$ with $x[0]=x[2]=1$, and zero otherwise. The number of nonzero samples in the output sequence $y[n]$, and the value of $y[2]$ are respectively

- (A) 5, 2
- (B) 6, 2
- (C) 6, 1
- (D) **(Correct)** 5, 3


Correct Answer: (D)

Detailed Solution – Question 162

$L_1 = 3, L_2 = 3 \Rightarrow$ Number of samples in output $= L_1 + L_2 - 1 = 5$

$$y[n] = \sum_{k=-\infty}^{\infty} x[k]h[n-k]$$

$$y[2] = \sum_{k=-\infty}^{\infty} x[k]h[2-k]$$



$\Rightarrow y(2) = 3$

Question 163: GATE EC 2008, Signals and Systems

MCQ

1 Mark

The impulse response $h(t)$ of a linear time invariant continuous time system is described by $h(t) =$


$\exp(\alpha t)u(t) + \exp(\beta t)u(-t)$, where $u(-t)$ denotes the unit step function, and α and β are real constants. This system is stable if

- (A) α is positive and β is positive
- (B) α is negative and β is negative
- (C) α is positive and β is negative
- (D) **(Correct)** α is negative and β is positive

Correct Answer: (D)

Detailed Solution – Question 163

$h(t) = e^{\alpha t}u(t) + e^{\beta t}u(-t)$ For the system to be stable, $\int_{-\infty}^{\infty} h(t)dt < \infty$ For the above condition, $h(t)$ should be as shown below.





Question 164: GATE EC 2005, Signals and Systems

MCQ

1 Mark

Which of the following can be impulse response of a causal system ?





- (A) A
- (B) B
- (C) C
- (D) **(Correct)** D

Correct Answer: (D)

Detailed Solution – Question 164

For a causal system $h(t) = 0$ for $t < 0$

Question 165: GATE EC 2004, Signals and Systems

MCQ

1 Mark

The impulse response $h[n]$ of a linear time-invariant system is given by $h[n] = u[n+3] + u[n-2] - 2u[n-7]$ where $u[n]$ is the unit step sequence. The above system is

- (A) **(Correct)** stable but not causal
- (B) stable and causal
- (C) causal but unstable
- (D) unstable and not causal

Correct Answer: (A)

Detailed Solution – Question 165

$$\begin{aligned}\sum_{k=-\infty}^{\infty} h(k) &= \sum_{k=-3}^{\infty} u(k+3) + \sum_{k=2}^{\infty} u(k-2) \\ &\quad - 2 \sum_{k=7}^{\infty} u(k-7) \\ &= \sum_{k=-3}^6 1 + \sum_{k=2}^6 1 \\ &= 10 + 5 = 15 < \infty\end{aligned}$$

For bounded input, bounded output. So system is stable. Response depends on future value of input signal i.e. $u(n+3)$. So, system is not causal

Question 166: GATE EC 2002, Signals and Systems

MCQ

1 Mark

Convolution of $x(t+5)$ with impulse function $\delta(t-7)$ is equal to

- (A) $x(t-12)$
- (B) $x(t+12)$
- (C) **(Correct)** $x(t-2)$
- (D) $x(t+2)$

Correct Answer: (C)

Detailed Solution – Question 166

$$\begin{aligned}x(t+5) * \delta(t-7) &= x(t+5-7) \\ &= x(t-2)\end{aligned}$$

Question 167: GATE EC 2001, Signals and Systems

MCQ

1 Mark

The impulse response functions of four linear systems S1, S2, S3, S4 are given respectively by $h_1(t) = 1$, $h_2(t) = U(t)$, $h_3(t) = \frac{U(t)}{t+1}$, $h_4(t) = e^{-3t}U(t)$ where $U(t)$ is the step function. Which of these systems is time invariant, causal and stable?

- (A) S1
- (B) S2
- (C) S3
- (D) **(Correct)** S4

Correct Answer: (D)

Detailed Solution – Question 167

$h_1(t) \neq 0$ for $t < 0$ Therefore, is non causal

$$h_2(t) = u(t) = 0 \text{ for } t < 0$$
$$\int_{-\infty}^{\infty} n_2(t) dt = \int_{-\infty}^{\infty} u(t) dt = \int_0^{\infty} dt = \infty$$

Therefore s_2 is unstable and causal

$$h_3(t) = \frac{u(t)}{t+1}$$

at $t = -1$

$$h_f(t) = \infty, h_3(t) = 0 \text{ for } t < 0$$

Therefore s_3 is unstable and causal $h_4(t) = e^{-3t}u(t)$ s_4 is time invariant, causal and stable

Question 168: GATE EC 2015-SET-2, Signals and Systems

MCQ

1 Mark

The signal $\cos(10\pi t + \frac{\pi}{4})$ is ideally sampled at a sampling frequency of 15 Hz. The sampled signal is passed through a filter with impulse response $(\frac{\sin(\pi t)}{\pi t})\cos(40\pi t - \frac{\pi}{2})$. The filter output is

(A) **(Correct)** $\frac{15}{2}\cos(40\pi t - \frac{\pi}{4})$

(B) $\frac{15}{2}(\frac{\sin(\pi t)}{\pi t})\cos(10\pi t + \frac{\pi}{4})$

(C) $\frac{15}{2}\cos(10\pi t - \frac{\pi}{4})$

(D) $\frac{15}{2}(\frac{\sin(\pi t)}{\pi t})\cos(40\pi t - \frac{\pi}{4})$

Correct Answer: (A)

Detailed Solution – Question 168

$$x(t) = \cos(10\pi t + \frac{\pi}{4})$$
$$X(f) = \frac{1}{2}[\delta(f-5) + \delta(f+5)]e^{j\pi/4}$$

After sampling $x(t)$ by 15 Hz, we get $X_s(f) = 15 \sum_{n=-\infty}^{\infty} X(f-15n)$ Given,

$$h(t) = \left[\frac{\sin(\pi t)}{\pi t} \right] \cos\left(40\pi t - \frac{\pi}{2}\right)$$

$$H(f) = \frac{1}{2} \left[\text{rect}\left(\frac{f-20}{2\pi}\right) + \text{rect}\left(\frac{f+20}{2\pi}\right) \right] e^{-j\frac{\pi}{2}}$$

Output $Y(t) = X_s(f) \times H(f)$

$$y(t) = \frac{15}{2} \cos\left(40\pi t - \frac{\pi}{4}\right)$$

Question 169: GATE EC 2014-SET-4, Signals and Systems

MCQ

1 Mark

For a given sample-and-hold circuit, if the value of the hold capacitor is increased, then

- (A) droop rate decreases and acquisition time decreases
- (B) **(Correct)** droop rate decreases and acquisition time increases
- (C) droop rate increases and acquisition time decreases
- (D) droop rate increases and acquisition time increases

Correct Answer: (B)

Detailed Solution – Question 169

We know that

$$Q = CV = i \cdot t \quad \dots (i)$$

$$t = \frac{CV}{i} \quad \dots (ii)$$

From equation (ii) $t \propto C$ and it is clear that if value of capacitor increases then the acquisition time increases. For capacitor the drop rate is given as $\frac{dv}{dt}$

$$\begin{aligned} i &= C \frac{dv}{dt} \\ \frac{dv}{dt} &= \frac{i}{C} \\ \frac{dv}{dt} &\propto \frac{1}{C} \end{aligned}$$

From above relation it is clear that if capacitor value increases drop rate decreases.

Question 170: GATE EC 2014-SET-3, Signals and Systems

MCQ

1 Mark



Let $x(t) = \cos(10\pi t) + \cos(30\pi t)$ be sampled at 20 Hz and reconstructed using an ideal low-pass filter with cut-off frequency of 20 Hz. The frequency/ frequencies present in the reconstructed signal is/are

- (A) **(Correct)** 5 Hz and 15 Hz only
- (B) 10 Hz and 15 Hz only
- (C) 5 Hz, 10 Hz and 15 Hz only
- (D) 5 Hz only



Correct Answer: (A)

Detailed Solution – Question 170

$x(t) = \cos(10\pi t) + \cos(30\pi t)$ Given sampling frequency, $f_s = 20\text{Hz}$ $\omega_s = 40\pi\text{rad/sec}$



$Y(\omega) = \sum_{K=-\infty}^{\infty} X(\omega - K\omega_s)$ After sampling waveform will be



Applying an ideal low-pass filter of cut-off frequency of 20Hz or $40\pi\text{ rad/sec}$, we get the frequencies in reconstructed signal as 10π and $30\pi\text{ rad/sec}$. or 5Hz and 15Hz

Question 171: GATE EC 2014-SET-1, Signals and Systems

NAT

1 Mark

Consider two real valued signals, $x(t)$ band-limited to $[-500\text{ Hz}, 500\text{ Hz}]$ and $y(t)$ band-limited to $[-1\text{ kHz}, 1\text{ kHz}]$. For $z(t) = x(t) \cdot y(t)$, the Nyquist sampling frequency (in kHz) is

Detailed Solution – Question 171

Multiplication in time domain = convolution in frequency domain. $x_1(t) \cdot x_2(t) \leftrightarrow X_1(\omega) * X_2(\omega)$
So, highest frequency component contained by the convolved signal $z(t) = 1500\text{Hz}$ $\therefore$ Nyquist rate
 $= 2 \times 1500 = 3000\text{Hz} = 3\text{kHz}$

Question 172: GATE EC 2013, Signals and Systems

MCQ

1 Mark

A band-limited signal with a maximum frequency of 5 kHz is to be sampled. According to the sampling theorem, the sampling frequency which is not valid is

- (A) **(Correct)** 5 kHz
- (B) 12 kHz
- (C) 15 kHz
- (D) 20 kHz

Correct Answer: (A)

Detailed Solution – Question 172

$$\begin{aligned}(f_s)_{\min} &= 2f_m \\ (f_s)_{\min} &= 2 \times 5 = 10\text{kHz} \\ \text{So, } f_s &\geq 10\text{kHz}\end{aligned}$$

Question 173: GATE EC 2009, Signals and Systems



MCQ

1 Mark

An LTI system having transfer function $\frac{s^2+1}{s^2+2s+1}$ and input $x(t) = \sin(t+1)$ is in steady state. The output is sampled at a rate ω_s rad/s to obtain the final output $y(k)$. Which of the following is true ?

- (A) **(Correct)** $y(\cdot)$ is zero for all sampling frequencies ω_s
- (B) $y(\cdot)$ is nonzero for all sampling frequencies ω_s
- (C) $y(\cdot)$ is nonzero for $\omega_s > 2$, but zero for $\omega_s < 2$
- (D) $y(\cdot)$ is zero for $\omega_s > 2$, but nonzero for $\omega_s < 2$

Correct Answer: (A)



$$x(t) = \sin(t + 1)$$

$$\omega = 1 \text{ rad/sec}$$

$$X(s) = \frac{\omega}{(\omega)^2 + s^2} \cdot e^s = \frac{1}{1^2 + s^2} \theta^s = \frac{e^s}{s^2 + 1}$$

$$H(s) = \frac{Y(s)}{X(s)}$$

$$Y(s) = H(s)X(s)$$

$$Y(s) = \frac{s^2 + 1}{s^2 + 2s + 1} \times \frac{e^s}{s^2 + 1} = \frac{e^s}{s^2 + 2s + 1}$$

$$Y(s) = \frac{e^s}{(s + 1)^2}$$

$$y(t) = (t + 1)e^{(t+1)}$$

$$y(\infty) = \lim_{s \rightarrow 0} sY(s) = \lim_{s \rightarrow 0} \frac{se^s}{(s + 1)^2} = 0$$

So, at steady state y remains zero for all sampling frequencies ω_s

Question 174: GATE EC 2006, Signals and Systems



MCQ

1 Mark





A signal $m(t)$ with bandwidth 500 Hz is first multiplied by a signal $g(t)$ where $g(t) = \int_{R=-\infty}^{\infty} (-1)^k \delta(t - 0.5 \times 10^{-4}k)$. The resulting signal is then passed through an ideal lowpass filter with bandwidth 1 kHz. The output of the lowpass filter would be

- (A) $\delta(t)$
- (B) **(Correct)** $m(t)$
- (C) 0
- (D) $m(t)\delta(t)$

Correct Answer: (B)



$$m(t)g(t) \leftrightarrow M(f) * G(f)$$



Question 175: GATE EC 2004, Signals and Systems

MCQ

1 Mark

A 1 kHz sinusoidal signal is ideally sampled at 1500 samples/sec and the sampled signal is passed through an ideal low-pass filter with cut-off frequency 800 Hz. The output signal has the frequency.

- (A) zero Hz
- (B) 0.75 kHz
- (C) **(Correct)** 0.5 kHz
- (D) 0.25 kHz

Correct Answer: (C)

Detailed Solution – Question 175

$$f_s = 1.5\text{kHz}$$

$$f_m = 1\text{kHz}$$


Available frequency components are $nf_s \pm f_m$. So, 1kHz, 2.5kHz, 0.5kHz LPF has $f_c = 0.8\text{k}$ only 0.5 k will appear at output.


Question 176: GATE EC 2003, Signals and Systems

MCQ

1 Mark

Let $x(t) = 2 \cos (800\pi t) + \cos (1400\pi t)$. $x(t)$ is sampled with the rectangular pulse train shown in the figure. The only spectral components (in kHz) present in the sampled signal in the frequency range 2.5 kHz to 3.5 kHz are





- (A) 2.7, 3.4
- (B) 3.3, 3.6
- (C) 2.6, 2.7
- (D) **(Correct)** 2.7, 3.3

Correct Answer: (D)

Detailed Solution – Question 176

From Fourier series expansion,

$$C_n = \frac{1}{T_0} \int_{-T_0/6}^{T_0/6} A \cdot e^{-j\pi\omega_0 t} dt = \frac{A}{\pi n} \sin\left(\frac{n\pi}{3}\right)$$

$\therefore$ From C_n its clear that 1, 2, 4, 5, 7... harmonics are present. Freq of p(t) corr. to 1, 2, 4, 5, 7... are $10^3, 2 \times 10^3, 4 \times 10^3 \dots$ frequency components 0.7k and 0.4k (t) has' (t) gives $(1 \pm 0.7)k, (2 \pm 0.7)k, (4 \pm 0.7)k, (1 \pm 0.4)k, (2 \pm 0.4)k \dots$ Frequency present in range of 2.5k to 3.5k are 2.7, 3.3

Question 177: GATE EC 2015-SET-2, Signals and Systems

MCQ

2 Marks

Consider the differential equation $\frac{dx}{dt} = 10 - 0.2x$ with initial condition $x(0) = 1$. The response $x(t)$ for $t \geq 0$ is

- (A) $2 - e^{-0.2t}$
- (B) $2 - e^{0.2t}$
- (C) **(Correct)** $50 - 49e^{-0.2t}$
- (D) $50 - 49e^{0.2t}$

Correct Answer: (C)

Detailed Solution – Question 177

Applying Laplace transform

$$sX(s) - x(0) = \frac{10}{s} - 0.2X(s)$$
$$X(s) = \frac{10}{s(s+0.2)} + \frac{1}{(s+0.2)}$$

Applying inverse Laplace transform, we get $x = 50 - 49e^{(-0.2)t}$

Question 178: GATE EC 2015-SET-2, Signals and Systems

MCQ

1 Mark

Let the signal $f(t) = 0$ outside the interval $[T_1, T_2]$, where T_1 and T_2 are finite. Furthermore, $|f(t)| < \infty$. The region of convergence (RoC) of the signal's bilateral Laplace transform $F(s)$ is

- (A) a parallel strip containing the $j\Omega$ axis
- (B) a parallel strip not containing the $j\Omega$ axis
- (C) **(Correct)** the entire s-plane
- (D) a half plane containing the $j\Omega$ axis

Correct Answer: (C)

Detailed Solution – Question 178

ROC of a finite duration signal is entire s-plane.

Question 179: GATE EC 2015-SET-2, Signals and Systems

MCQ

1 Mark

The bilateral Laplace transform of a function

$$f(t) = \begin{cases} 1 & \text{if } a \leq t \leq b \\ 0 & \text{otherwise} \end{cases}$$

is

- (A) $\frac{a-b}{s}$
- (B) $\frac{e^{a(s-b)}}{s}$
- (C) **(Correct)** $\frac{e^{-as} - e^{-bs}}{s}$
- (D) $\frac{e^{s(a-b)}}{s}$

Correct Answer: (C)

Detailed Solution – Question 179

$$\begin{aligned} f(t) &= \begin{cases} 1 & \text{if } a \leq t \leq b \\ 0 & \text{otherwise} \end{cases} \\ &= U(t-a) - U(t-b) \\ \Rightarrow F(s) &= \frac{e^{-as} - e^{-bs}}{s} \end{aligned}$$

Question 180: GATE EC 2014-SET-4, Signals and Systems

NAT

2 Marks

A causal LTI system has zero initial conditions and impulse response $h(t)$. Its input $x(t)$ and output $y(t)$ are related through the linear constant-coefficient differential equation

$$\frac{d^2 y(t)}{dt^2} + \alpha \frac{dy(t)}{dt} + \alpha^2 y(t) = x(t)$$

Let another signal $g(t)$ be defined as

$$g(t) = \alpha^2 \int_0^t h(\tau) d\tau + \alpha h(t)$$

If $G(s)$ is the Laplace transform of $g(t)$, then the number of poles of $G(s)$ is-----.

Detailed Solution – Question 180

$\frac{d^2 y(t)}{dt^2} + \alpha \frac{dy}{dt} + \alpha^2 y(t) = x(t) \therefore (s^2 + \alpha s + \alpha^2) Y(s) = X(s)$ $H(s) = \frac{Y(s)}{X(s)} = \frac{1}{(s^2 + \alpha s + \alpha^2)}$ Let another signal $g(t)$ be defined as

$$\begin{aligned} G(s) &= \frac{\alpha^2}{s} H(s) + s H(s) + \alpha H(s) \\ G(s) &= \left(\frac{\alpha^2}{s} + s + \alpha \right) H(s) \\ &= \left(\frac{\alpha^2 + s^2 + s\alpha}{s} \right) \cdot \frac{1}{(s^2 + \alpha s + \alpha^2)} \\ &= \frac{(s^2 + s\alpha + \alpha^2)}{s(s^2 + \alpha s + \alpha^2)} = \frac{1}{s} \end{aligned}$$

So, number of poles of $G(s)$ is 1

Question 181: GATE EC 2014-SET-4, Signals and Systems

MCQ

2 Marks

A stable linear time invariant (LTI) system has a transfer function $H(S) = \frac{1}{s^2 + s - 6}$. To make this system causal it needs to be cascaded with another LTI system having a transfer function $H_1(S)$. A correct choice for $H_1(S)$ among the following options is

- (A) $s+3$
- (B) **(Correct)** $s-2$
- (C) $s-6$

(D) $s+1$

Correct Answer: (B)

Detailed Solution – Question 181

$H(s) = \frac{1}{(s^2+s-6)}$ The system is said to be causal if the output at any time depends only on present and/or past values of input or $h(t) = 0$ for $t > 0$ i.e. all poles must lie on LHS of S-plane. $H(s) = \frac{1}{(s+3)(s-2)}$ From the above expression it can be seen that $s=2$ is a pole which lies on RHS of s-plane. So, $H_1(s)$ system that needs to be cascaded should have one zero at $(s-2)$

$$\text{Thus, } H(s)H_1(s) = (s-2) \cdot \frac{1}{(s+3)(s-2)} = \frac{1}{(s+3)} \rightarrow \text{causal system}$$

Question 182: GATE EC 2014-SET-4, Signals and Systems

MCQ

2 Marks

The unilateral Laplace transform of $f(t)$ is $\frac{1}{s^2+s+1}$. Which one of the following is the unilateral Laplace transform of $g(t) = t \cdot f(t)$?

(A) $\frac{-s}{(s^2+s+1)^2}$

(B) $\frac{-(2s+1)}{(s^2+s+1)^2}$

(C) $\frac{s}{(s^2+s+1)^2}$

(D) **(Correct)** $\frac{2s+1}{(s^2+s+1)^2}$

Correct Answer: (D)

Detailed Solution – Question 182

Given $F(s) = \frac{1}{s^2+s+1}$ Laplace transform of $g(t) = t \cdot f(t)$

$$\begin{aligned} &= -\frac{dF(s)}{ds} = -\frac{d}{ds} \left[\frac{1}{(s^2+s+1)} \right] \\ &= \frac{(2s+1)}{(s^2+s+1)^2} \end{aligned}$$

Question 183: GATE EC 2014-SET-3, Signals and Systems

MCQ

2 Marks

Let $h(t)$ denote the impulse response of a causal system with transfer function $\frac{1}{s+1}$. Consider the following three statements.

S1 : The system is stable S2: $\frac{h(t+1)}{h(t)}$ is independent of $t > 0$ S3 : A non-causal system with the same transfer function is stable

For the above system

(A) **(Correct)** only S1 and S2 are true

- (B) only S2 and S3 are true
 (C) only S1 and S3 are true
 (D) S1,S2 and S3 are true


Correct Answer: (A)

Detailed Solution – Question 183

$$\text{Given } H(s) = \frac{1}{(s+1)}$$

$$h(t) = e^{-t}u(t)$$

$$\text{at } t = \infty, h(t) = 0$$



i.e. the system is stable as it converges to zero as $t \rightarrow \infty$. The system is causal as it can be seen from the graph that $h(t) = 0$ for $t < 0$. $\frac{h(t+1)}{h(t)} = \frac{e^{-(t+1)}}{e^{-t}} = \frac{e^{-t} \cdot e^{-1}}{e^{-t}} = e^{-1}$ i.e. independent of t . So, statements S_1 and S_2 are true.

Question 184: GATE EC 2014-SET-3, Signals and Systems

NAT

1 Mark

The input $-3e^{2t}u(t)$, where $u(t)$ is the unit step function, is applied to a system with transfer function $\frac{s-2}{s+3}$. If the initial value of the output is -2, then the value of the output at steady state is _____.

Detailed Solution – Question 184

Given, $x(t) = -3e^{-2t}$ Laplace transform of $x(t) \longleftrightarrow X(s)$ Where,

$$\begin{aligned}X(s) &= \frac{-3}{s+2} \\A \mid s0, H(s) &= \frac{s-2}{(s+3)} \\ \therefore Y(s) &= X(s)H(s) \\ \gamma(s) &= \frac{-3(s-2)}{(s+3)(s+2)}\end{aligned}$$

Using final value theorem, the steady state value of $Y(s)$ is

$$\begin{aligned}y(\infty) &= \lim_{s \rightarrow 0} sY(s) \\ &= 0\end{aligned}$$

Question 185: GATE EC 2014-SET-1, Signals and Systems

MCQ

2 Marks

A system is described by the following differential equation, where $u(t)$ is the input to the system and $y(t)$ is the output of the system. $\dot{y}(t) + 5y(t) = u(t)$ when $y(0) = 1$ and $u(t)$ is a unit step function, $y(t)$ is

- (A) $0.2 - 0.2^{-5t}$
- (B) $0.8 + 0.2^{-5t}$
- (C) $0.8 - 0.8^{-5t}$

Correct Answer: ()

Detailed Solution – Question 185

$\dot{y}(t) + 5y(t) = u(t)$ Taking the Laplace transform of the above equation

$$\begin{aligned}sY(s) - y(0) + 5r(s) &= \frac{1}{s} \\(s+5)r(s) - 1 &= \frac{1}{s} \\(s+5)r(s) &= \frac{s+1}{s} \\Y(s) &= \frac{(s+1)}{s(s+5)} \\ \frac{A}{s} + \frac{B}{(s+5)} &= \frac{(s+1)}{s(s+5)} \\ A &= 0.2 \\ B &= \frac{-4}{-5} = 0.8 \\ r(s) &= \frac{0.2}{s} + \frac{0.8}{(s+5)} \\ y(t) &= 0.2 + 0.8e^{-5t}\end{aligned}$$

Question 186: GATE EC 2013, Signals and Systems

MCQ

1 Mark

A system is described by the differential equation $\frac{d^2y}{dt^2} + 5\frac{dy}{dt} + 6y(t) = x(t)$. Let $x(t)$ be a rectangular pulse given by

$$x(t) = \begin{cases} 1 & 0 < t < 2 \\ 0 & \text{otherwise} \end{cases}$$

Assuming that $y(0) = 0$ and $\frac{dy}{dt} = 0$ at $t = 0$, the Laplace transform of $y(t)$ is

- (A) $\frac{e^{-2s}}{s(s+2)(s+3)}$
(B) **(Correct)** $\frac{1-e^{-2s}}{s(s+2)(s+3)}$
(C) $\frac{e^{-2s}}{(s+2)(s+3)}$
(D) $\frac{1-e^{-2s}}{(s+2)(s+3)}$

Correct Answer: (B)

Detailed Solution – Question 186

$$x(t) = u(t) - u(t-2)$$
$$X(s) = \frac{1}{s} - \frac{e^{-2s}}{s} = \frac{1-e^{-2s}}{s}$$

Given that $\frac{d^2y}{dt^2} + 5\frac{dy}{dt} + 6y(t) = x(t)$. Taking Laplace transform on both the sides


$$\left(y(0) = 0 \text{ and } \frac{dy}{dt} = 0 \text{ at } t = 0 \right)$$
$$s^2Y(s) + 5sY(s) + 6Y(s) = x(s)$$
$$Y(s) [s^2 + 5s + 6] = \frac{1-e^{-2s}}{s}$$
$$Y(s) = \frac{1-e^{-2s}}{s(s^2+5s+6)} = \frac{1-e^{-2s}}{s(s+2)(s+3)}$$

Question 187: GATE EC 2013, Signals and Systems

MCQ

1 Mark

Assuming zero initial condition, the response $y(t)$ of the system given below to a unit step input $u(t)$ is



- (A) $u(t)$

- (B) **(Correct)** $tu(t)$
- (C) $\frac{t^2}{2}u(t)$
- (D) $e^{-t}u(t)$

Correct Answer: (B)

Detailed Solution – Question 187

$x(t) = u(t)$ Apply Laplace transform

$$\begin{aligned} X(s) &= \frac{1}{s} \\ H(s) &= \frac{1}{s} \quad (\text{given}) \\ Y(s) &= H(s)X(s) \\ &= \frac{1}{s} \times \frac{1}{s} = \frac{1}{s^2} \end{aligned}$$

Taking inverse Laplace transform $y(t) = tu(t)$

Question 188: GATE EC 2013, Signals and Systems

MCQ

1 Mark

Which one of the following statements is NOT TRUE for a continuous time causal and stable LTI system?

- (A) All the poles of the system must lie on the left side of the $j\omega$ axis.
- (B) Zeros of the system can lie anywhere in the s-plane.
- (C) **(Correct)** All the poles must lie within $|s| = 1$
- (D) All the roots of the characteristic equation must be located on the left side of the $j\omega$ axis.

Correct Answer: (C)

Detailed Solution – Question 188

For a causal and stable LTI system the ROC must be right sided and it must include the $s = j\omega$ line ($\sigma = 0$). For all the poles must lie within $|s| = 1$ then all poles will lie between -1 to +1. We know that ROC does not include any pole, so in this case ROC will not be able to include $s = j0$ line ($\sigma = 0$). Thus the system will not be stable. Hence, this statement is NOT TRUE.

Question 189: GATE EC 2013, Signals and Systems

MCQ

1 Mark

The impulse response of a system is $h(t) = tu(t)$. For an input $u(t-1)$, the output is

- (A) $\frac{t^2}{2}u(t)$

(B) $\frac{t(t-1)}{2}u(t-1)$

(C) **(Correct)** $\frac{(t-1)^2}{2}u(t-1)$

(D) $\frac{t^2-1}{2}u(t-1)$

Correct Answer: (C)

Detailed Solution – Question 189

$$h(t) = tu(t)$$

Taking Laplace transform

$$H(s) = \frac{1}{s^2}$$

$$x(t) = u(t-1)$$

Taking Laplace transform

$$X(s) = \frac{e^{-s}}{s}$$

$$\frac{Y(s)}{X(s)} = H(s)$$

$$Y(s) = H(s)X(s)$$

$$Y(s) = \frac{1}{s^2} \cdot \frac{e^{-s}}{s} = \frac{e^{-s}}{s^3}$$

Taking the inverse Laplace transform

$$y(t) = \frac{(t-1)^2}{2}u(t-1)$$

Question 190: GATE EC 2012, Signals and Systems

MCQ

1 Mark

The unilateral Laplace transform of $f(t)$ is $\frac{1}{s^2+s+1}$. The unilateral Laplace transform of $tf(t)$ is

(A) $-\frac{s}{(s^2+s+1)^2}$

(B) $-\frac{2s+1}{(s^2+s+1)^2}$

(C) $\frac{s}{(s^2+s+1)^2}$

(D) **(Correct)** $\frac{2s+1}{(s^2+s+1)^2}$

Correct Answer: (D)

Detailed Solution – Question 190

If $L[f(t)] = \bar{f}(s)$ then

$$L[t^n f(t)] = (-1)^n \frac{d^n}{ds^n} \bar{f}(s)$$

In this problem, Given,

$$L[f(t)] = \frac{1}{s^2 + s + 1} = \bar{f}(s)$$

$$\begin{aligned} \text{We need } L[tf(t)] &= (-1)^1 \frac{d^1}{ds^1} \bar{f}(s) \\ &= -\frac{d}{ds} \bar{f}(s) \\ &= -\frac{d}{ds} \left[\frac{1}{s^2 + s + 1} \right] \\ &= -\left[\frac{-1}{(s^2 + s + 1)^2} \right] \times (2s + 1) \\ &= \left[\frac{2s + 1}{(s^2 + s + 1)^2} \right] \end{aligned}$$

Question 191: GATE EC 2011, Signals and Systems

MCQ

1 Mark

If $F(s) = L[f(t)] = \frac{2(s+1)}{s^2+4s+7}$ then the initial and final values of $f(t)$ are respectively

- (A) 0 , 2
- (B) **(Correct)** 2 , 0
- (C) 0 , 2/7
- (D) 2/7 , 0

Correct Answer: (B)

Detailed Solution – Question 191

$$F(s) = L[f(t)] = \frac{2(s+1)}{s^2 + 4s + 7}$$

Initial value,

$$\begin{aligned} \lim_{t \rightarrow 0} f(t) &= \lim_{s \rightarrow \infty} sF(s) = \lim_{s \rightarrow \infty} s \cdot \frac{2(s+1)}{s^2 + 4s + 7} \\ &= \lim_{s \rightarrow \infty} \frac{2s^2 \left(1 + \frac{1}{s}\right)}{s^2 \left(1 + \frac{4}{s} + \frac{7}{s^2}\right)} \\ &= \frac{2(1+0)}{(1+0+0)} = 2 \end{aligned}$$

Final value,

$$\begin{aligned} \lim_{t \rightarrow \infty} f(t) &= \lim_{s \rightarrow 0} sF(s) = \lim_{s \rightarrow 0} s \cdot \frac{2(s+1)}{s^2 + 4s + 7} \\ &= 0 \end{aligned}$$

Question 192: GATE EC 2011, Signals and Systems

MCQ

1 Mark

An input $x(t) = \exp(-2t)u(t) + \delta(t-6)$ is applied to an LTI system with impulse response $h(t) = u(t)$. The output is

$1 - \exp(-2t) \quad u(t) + u(t+6)$

$1 - \exp(-2t) \quad u(t) + u(t-6)$

(A) $0.5[1 - \exp(-2t)]u(t) + u(t+6)$

(B) **(Correct)** $0.5[1 - \exp(-2t)]u(t) + u(t-6)$

Correct Answer: (D)

Detailed Solution – Question 192

$$x(t) = e^{-2t}u(t) + \delta(t-6)$$

$$x(s) = \frac{1}{s+2} + e^{-6s}$$

$$H(s) = \frac{1}{s}$$

$$\therefore Y(s) = X(s) \cdot H(s)$$

$$\Rightarrow Y(s) = \frac{1}{s(s+2)} + \frac{1}{s}e^{-6s}$$

$$\Rightarrow Y(s) = \frac{1}{2} \left(\frac{1}{s} - \frac{1}{s+2} \right) + \frac{1}{s}e^{-6s}$$

Taking inverse Laplace transform, we have

$$y(t) = 0.5 (1 - e^{-2t}) u(t) + u(t-6)$$

Question 193: GATE EC 2011, Signals and Systems

MCQ

1 Mark

If the unit step response of a network is $(1 - e^{-at})$, then its unit impulse response is

(A) **(Correct)** αe^{-at}

(B) $\alpha^{-1} e^{-at}$

(C) $(1 - \alpha^{-1}) e^{at}$

(D) $(1 - \alpha) e^{-at}$

Correct Answer: (A)

Detailed Solution – Question 193

Unit step response $s(t) = (1 - e^{-\alpha t})$ So, unit impulse response is

$$\begin{aligned}h(t) &= \frac{ds(t)}{dt} = \frac{d}{dt} (1 - e^{-\alpha t}) \\&= \alpha e^{-\alpha t}\end{aligned}$$

Question 194: GATE EC 2010, Signals and Systems

MCQ

1 Mark

A continuous time LTI system is described by $\frac{d^2y(t)}{dt^2} + 4\frac{dy(t)}{dt} + 3y(t) = 2\frac{dx(t)}{dt} + 4x(t)$ Assuming zero initial conditions, the response $y(t)$ of the above system for the input $x(t) = e^{-2t}u(t)$ is given by

- (A) $(e^t - e^{3t})u(t)$
- (B) **(Correct)** $(e^{-t} - e^{-3t})u(t)$
- (C) $(e^{-t} + e^{-3t})u(t)$
- (D) $(e^t + e^{3t})u(t)$

Correct Answer: (B)

Detailed Solution – Question 194

$$\frac{d^2y(t)}{dt^2} + \frac{4dy(t)}{dt} + 3y(t) = \frac{2dx(t)}{dt} + 4x(t)$$

Taking Laplace transform on both sides (assuming zero initial conditions).

$$\begin{aligned}s^2Y(s) + 4sY(s) + 3Y(s) &= 2sX(s) + 4X(s) \\ \text{or } \frac{Y(s)}{X(s)} &= \frac{2s + 4}{s^2 + 4s + 3} \\ &= \frac{2(s + 2)}{(s + 1)(s + 3)}\end{aligned}$$

Given that

$$\begin{aligned}x(t) &= e^{-2t}u(t) \\ x(s) &= \frac{1}{s + 2} \\ Y(s) &= \frac{2(s + 2)}{(s + 1)(s + 3)(s + 2)} \\ &= \frac{2}{(s + 1)(s + 3)} \\ &= \frac{1}{s + 1} - \frac{1}{s + 3}\end{aligned}$$

Taking inverse Laplace transform on both sides. $y(t) = (e^{-t} - e^{-3t})u(t)$

Question 195: GATE EC 2010, Signals and Systems

MCQ

1 Mark

Given $f(t) = \mathcal{L}^{-1}\left[\frac{3s+1}{s^3+4s^2+(K-3)s}\right]$. If $\lim_{t \rightarrow \infty} f(t) = 1$, then the value of K is

- (A) 1
- (B) 2
- (C) 3
- (D) **(Correct)** 4

Correct Answer: (D)

Detailed Solution – Question 195

$\lim_{t \rightarrow \infty} f(t) = \lim_{s \rightarrow 0} sF(s)$ Given that,

$$\begin{aligned} F(s) &= \left[\frac{3s+1}{s^3+4s^2+(K-3)s} \right] \\ \lim_{t \rightarrow \infty} f(t) &= 1 \\ \Rightarrow \lim_{s \rightarrow 0} s \left[\frac{3s+1}{s^3+4s^2+(K-3)s} \right] &= 1 \\ \Rightarrow \lim_{s \rightarrow 0} \left[\frac{3s+1}{s^2+4s+(K-3)} \right] &= 1 \\ \Rightarrow \frac{1}{K-3} &= 1 \\ \Rightarrow K-3 &= 1 \\ \Rightarrow K &= 4 \end{aligned}$$

Question 196: GATE EC 2009, Signals and Systems

MCQ

1 Mark

Given that $F(s)$ is the one-side Laplace transform of $f(t)$, the Laplace transform of $\int_0^t f(\tau) d\tau$ is

- (A) $sF(s) - f(0)$
- (B) $\frac{1}{s}F(s)$
- (C) $\int_0^s F(\tau) d\tau$
- (D) **(Correct)** $\frac{1}{s}[F(s) - f(0)]$

Correct Answer: (D)

Detailed Solution – Question 196

$$\mathcal{L} \left[\int_0^t f(\tau) d\tau \right] = \frac{1}{s} [F(s) - f(0)]$$

Question 197: GATE EC 2007, Signals and Systems

MCQ

1 Mark

If the Laplace transform of a signal $y(t)$ is $Y(s) = \frac{1}{s(s-1)}$, then its final value is

- (A) -1
- (B) 0
- (C) 1
- (D) **(Correct)** Unbounded

Correct Answer: (D)

Detailed Solution – Question 197

Final value theorem is applicable only when all the poles of system lies in left half of s-plane.
 $\therefore s = 1$ is right S-plane pole. Therefore, final value theorem cannot be applied.

$$Y(s) = \frac{1}{s-1} - \frac{1}{s}$$
$$y(t) = (e^t - 1) u(t)$$

$\therefore$ Unbounded.

Question 198: GATE EC 2006, Signals and Systems

MCQ


1 Mark

Consider the function $f(t)$ having Laplace transform $F(s) = \frac{\omega_0}{s^2 + \omega_0^2}$ $Re[s] > 0$ The final value of $f(t)$ would be

- (A) 0
- (B) 1
- (C) **(Correct)** $-1 \leq f(\infty) \leq 1$
- (D) ∞

Correct Answer: (C)

Detailed Solution – Question 198



$$\begin{aligned} L^{-1}[F(s)] &= \sin \omega_0 t \\ f(t) &= \sin \omega_0 t \\ -1 &\leq f(\infty) \leq 1 \end{aligned}$$

Question 199: GATE EC 2005, Signals and Systems

MCQ

1 Mark

In what range should $\text{Re}(s)$ remain so that the Laplace transform of the function $e^{(a+2)t+5}$ exists.

- (A) **(Correct)** $\text{Re}(s) > a + 2$
- (B) $\text{Re}(s) > a + 7$
- (C) $\text{Re}(s) < 2$
- (D) $\text{Re}(s) > a + 5$

Correct Answer: (A)

Detailed Solution – Question 199

$$\begin{aligned} f(t)Y &= e^{(a+2)t+5} = e^5 \cdot e^{(a+2)t} \\ F(s) &= \left[\frac{1}{s - (a+2)} \right] e^5 \\ \therefore \text{ For } LT \text{ to exist, } \text{Re}(s) &> a + 2 \end{aligned}$$

Question 200: GATE EC 2003, Signals and Systems

MCQ

1 Mark

The Laplace transform of $i(t)$ is given by $I(s) = \frac{2}{s(1+s)}$ At $t \rightarrow \infty$ The value of $i(t)$ tends to

- (A) 0
- (B) 1
- (C) **(Correct)** 2
- (D) ∞

Correct Answer: (C)

Detailed Solution – Question 200

$$\begin{aligned}\lim_{t \rightarrow \infty} i(t) &= \lim_{s \rightarrow 0} sI(s) \\ &= \lim_{s \rightarrow 0} \frac{2}{s(1+s)} = 2\end{aligned}$$

Question 201: GATE EC 2002, Signals and Systems

MCQ

1 Mark

The Laplace transform of a continuous-time signal $x(t)$ is $X(s) = \frac{5-s}{s^2-s-2}$. If the Fourier transform of this signal exists, then $x(t)$ is

- (A) $e^{2t}u(t) - 2e^{-t}u(t)$
- (B) $-e^{2t}u(-t) + 2e^{-t}u(t)$
- (C) **(Correct)** $-e^{2t}u(-t) - 2e^{-t}u(t)$
- (D) $e^{2t}u(-t) - 2e^{-t}u(t)$

Correct Answer: (C)

Detailed Solution – Question 201

$$\begin{aligned}x(s) &= \frac{5-s}{s^2-s-2} = \frac{5-s}{(s+1)(s-2)} \\ \frac{5-s}{(s+1)(s-2)} &= \frac{A}{s+1} + \frac{B}{s-2} \\ 5-s &= A(s-2) + B(s+1) \\ s=2, 3 &= 3B \\ \Rightarrow B &= 1 \\ s=-1, 6 &= -3A \\ \Rightarrow A &= -2 \\ x(t) &= -2e^{-1}u(t) - e^{2t}u(-t) \\ \therefore -1 &< \sigma < 2\end{aligned}$$

Note: ROC of Laplace transform should include $\sigma = 0$ line.

Question 202: GATE EC 2001, Signals and Systems

MCQ

1 Mark

The transfer function of a system is given by $H(s) = \frac{1}{s^2(s-2)}$. The impulse response of the system is: (* denotes convolution, and $U(t)$ is unit step function)

- (A) $(t^2 * e^{-2t})U(t)$
- (B) **(Correct)** $(t * e^{2t})U(t)$
- (C) $(te^{-2t})U(t)$
- (D) $(te^{-2t})U(t)$

Correct Answer: (B)

Detailed Solution – Question 202

Impulse response of system is $L^{-1}[H(s)]$

$$\frac{1}{s^2(s-2)} = \frac{1}{s^2} \times \frac{1}{s-2} = (t * e^{+2t}) u(t)$$

Question 203: GATE EC 2015-SET-2, Signals and Systems

NAT

1 Mark

Two causal discrete-time signals $x[n]$ and $y[n]$ are related as $y[n] = \sum_{m=0}^n x[m]$. If the z-transform of $y[n]$ is $\frac{2}{z(z-1)^2}$, the value of $x[2]$ is -----.

Detailed Solution – Question 203



$$\begin{aligned} f(n) &= \sum_{m=0}^n x[m] = x[n] * u[n] \\ y(z) &= X(z) \cdot \left(\frac{z}{z-1} \right) \\ \text{Given } Y(z) &= \frac{2}{z(z-1)^2} = X(z) \cdot \frac{z}{z-1} \\ \Rightarrow A(z) &= \frac{2 \cdot z^{-2}}{z-1} = 2z^{-3} \left(\frac{z}{z-1} \right) \\ \Rightarrow x[n] &= 2u[n-3] \\ \text{Therefore, } x[2] &= 0 \end{aligned}$$

Question 204: GATE EC 2015-SET-1, Signals and Systems

MCQ

2 Marks

The pole-zero diagram of a causal and stable discrete-time system is shown in the figure. The zero at the origin has multiplicity 4. The impulse response of the system is $h[n]$. If $h[0] = 1$, we can conclude



- (A) **(Correct)** $h[n]$ is real for all n
- (B) $h[n]$ is purely imaginary for all n
- (C) $h[n]$ is real for only even n
- (D) $h[n]$ is purely imaginary for only odd n

Correct Answer: (A)

Detailed Solution – Question 204


$$\begin{aligned}
 H(z) &= \frac{z^4}{\left[\left(z - \frac{1}{2} \right)^2 + \frac{1}{4} \right] \left[\left(z + \frac{1}{2} \right)^2 + \frac{1}{4} \right]} \\
 \text{Poles} &= \frac{1}{2} \pm j\frac{1}{2}, -\frac{1}{2} \pm j\frac{1}{2} \\
 &= \frac{z^4}{\left(z^2 - z + \frac{1}{2} \right) \left(z^2 + z + \frac{1}{2} \right)} \\
 &= \frac{z^4}{z^4 + z^2 + \frac{1}{4} - z^2} \\
 H(z) &= \frac{z^4}{z^4 + \frac{1}{4}} \\
 &= \left(z^4 + \frac{1}{4} \right) z^4 \left(1 - \frac{1}{4} z^{-4} \dots \right. \\
 &\quad \left. \frac{z + \frac{1}{4}}{-\frac{1}{4}} \right)
 \end{aligned}$$

Question 205: GATE EC 2015-SET-1, Signals and Systems

MCQ

2 Marks

For the discrete-time system shown in the figure, the poles of the system transfer function are located at



- (A) 2, 3
- (B) 1/2, 3
- (C) **(Correct)** 1/2, 1/3
- (D) 2, 1/3

Correct Answer: (C)

Detailed Solution – Question 205

The difference equation of the system $x(n) - \frac{1}{6}y(n-2) + \frac{5}{6}y(n-1) = y(n)$

$$H(z) = \frac{Y(z)}{X(z)} = \frac{1}{1 + \frac{1}{6}z^{-2} - \frac{5}{6}z^{-1}}$$

Poles are at $z = \frac{1}{2}, \frac{1}{3}$

Question 206: GATE EC 2014-SET-3, Signals and Systems

NAT

2 Marks

The z-transform of the sequence $x[n]$ is given by $X(z) = \frac{1}{(1-2z^{-1})^2}$, with the region of convergence $|z| > 2$. Then, $x[2]$ is -----.

Detailed Solution – Question 206

$$\begin{aligned}\text{Given, } X(z) &= \frac{1}{(1-2z^{-1})^2}, \quad |z| > 2 \\ X(z) &= (1-2z^{-1})^{-2} \\ X(z) &= 1 + 4z^{-1} + 12z^{-2} + \dots \\ &\quad \text{(using binomial expansion)}\end{aligned}$$

Taking inverse z-transform, we get

$$\therefore x[n] = \{ 1, 4, 12, \dots \}$$

$$x[2] = 12$$

Question 207: GATE EC 2014-SET-3, Signals and Systems

NAT

2 Marks

Let $H_1(z) = (1 - pz^{-1})^{-1}$, $H_2(z) = (1 - qz^{-1})^{-1}$, $H(z) = H_1(z) + rH_2(z)$. The quantities p, q, r are real numbers. Consider $p = \frac{1}{2}$, $q = -\frac{1}{4}$, $|r| < 1$. If the zero of $H(z)$ lies on the unit circle, then $r =$ -----.

Detailed Solution – Question 207

$$\begin{aligned}\text{Here } H_1(z) &= \frac{1}{1 - pz^{-1}} \\ H_2(z) &= \frac{1}{1 - qz^{-1}} \\ \text{also } p &= \frac{1}{2}, \quad q = -\frac{1}{4} \\ \therefore H(z) &= H_1(z) + rH_2(z) \\ &= \frac{1}{1 - pz^{-1}} + \frac{r}{1 - qz^{-1}} \\ &= \frac{1}{1 - \frac{1}{2}z^{-1}} + \frac{r}{1 + \frac{1}{4}z^{-1}} \\ H(z) &= \frac{(1 + \frac{1}{4}z^{-1}) + r(1 - \frac{1}{2}z^{-1})}{(1 - \frac{1}{2}z^{-1})(1 + \frac{1}{4}z^{-1})} \quad \dots(i)\end{aligned}$$

zero of $H(z) \Rightarrow (1+r) - (q+pr)z^{-1} = 0 \quad \dots(ii)$ or $z = \frac{q+pr}{1+r}$ Since, the zero of $H(z)$ lies on the unit circle therefore $|z| = 1$ or $z = \pm 1$ Taking $z=1$, we get $z = \frac{q+pr}{1+r} = 1 \quad \dots(iii)$ By solving above expression with $p = \frac{1}{2}$ and $q = -\frac{1}{4}$, we get $r = -2.5$ But $|r| < 1$ or $-1 < r < 1$ Taking $z=-1$ in equation (iii), we get $r = -0.5$

Question 208: GATE EC 2014-SET-3, Signals and Systems

MCQ

1 Mark

For an all-pass system $H(z) = \frac{(z^{-1}-b)}{(1-az^{-1})}$, where $|H(e^{-j\omega})| = 1$, for all ω . If $\text{Re}(a) \neq 0$, $\text{Im}(a) \neq 0$, then b equals

- (A) a
- (B) **(Correct)** a^*
- (C) $1/a^*$
- (D) $1/a$

Correct Answer: (B)

Detailed Solution – Question 208

For the given system $H(z) = \frac{(z^{-1}-b)}{(1-az^{-1})}$ The pole lie at $z=a$ and the zero lie at $z = \frac{1}{b}$ also 'a' is complex in nature. Thus, $a = |a|e^{j\angle a}$ For an all pass system where $|H(e^{-j\omega})| = 1$, for all ω , if the pole lies at 'a' then the zero must be present at $\frac{1}{a^*}$

$$\therefore \left(\frac{1}{b}\right) = \frac{1}{|a|e^{-j\angle a}} = \frac{1}{a^*}$$

or $b = a^*$

Question 209: GATE EC 2014-SET-2, Signals and Systems

MCQ

2 Marks

The input-output relationship of a causal stable LTI system is given as $y[n] = \alpha y[n-1] + \beta x[n]$ If the impulse response $h[n]$ of this system satisfies the condition $\sum_{n=0}^{\infty} h[n] = 2$, the relationship between α and β is

- (A) **(Correct)** $\alpha = 1 - \beta/2$
- (B) $\alpha = 1 + \beta/2$
- (C) $\alpha = 2\beta$
- (D) $\alpha = -2\beta$

Correct Answer: (A)

Detailed Solution – Question 209

Input-output relation is given as

$$y[n] = \alpha y[n-1] + \beta x[n]$$

Taking Z-transform,

$$r(z) = \alpha z^{-1} Y(z) + \beta X(z)$$

$$Y(z) [1 - \alpha z^{-1}] = \beta X(z)$$

$$\frac{Y(z)}{X(z)} = H(z) = \frac{\beta}{1 - \alpha z^{-1}}$$

$$h[n] = \beta \cdot \alpha^n u[n]$$

$$\text{Also } \sum_{n=0}^{\infty} h[n] = 2 \Rightarrow \sum_{n=0}^{\infty} \beta \cdot \alpha^n u[n] = 2$$

$$\frac{\beta}{1 - \alpha} = 2 \Rightarrow \beta = 2 - 2\alpha$$

$$\Rightarrow 2\alpha = 2 - \beta$$

$$\alpha = 1 - \frac{\beta}{2}$$

Question 210: GATE EC 2014-SET-2, Signals and Systems

MCQ

1 Mark

Let $x[n] = x[-n]$. Let $X(z)$ be the z-transform of $x[n]$. If $0.5 + j0.25$ is a zero of $X(z)$, which one of the following must also be a zero of $X(z)$.

- (A) $0.5 - j0.25$
- (B) **(Correct)** $1/(0.5 + j0.25)$
- (C) $1/(0.5 - j0.25)$
- (D) $2 + j4$

Correct Answer: (B)

Detailed Solution – Question 210

Given $x[n] = x[-n]$ As we know that,

$$x[n] \xleftrightarrow{Z} X[z]$$

$$x[-n] \xleftrightarrow{Z} X[z^{-1}]$$

So, when $(0.5 + j0.25)$ is a zero of $X(z)$. Now $x[-n] \longleftrightarrow X(z^{-1})$ Zero of $X(z) = \frac{1}{(0.5 + j0.25)}$

Question 211: GATE EC 2014-SET-1, Signals and Systems

MCQ

2 Marks

Let $x[n] = (-\frac{1}{9})^n u(n) - (-\frac{1}{3})^n u(-n-1)$. The Region of Convergence (ROC) of the z -transform of x[n].

- (A) is $|z| > \frac{1}{9}$
- (B) is $|z| < \frac{1}{3}$
- (C) **(Correct)** is $\frac{1}{3} > |z| > \frac{1}{9}$
- (D) does not exist

Correct Answer: (C)

Detailed Solution – Question 211

$$x(n) = \frac{(-\frac{1}{9})^n u(n) - (-\frac{1}{3})^n u(-n-1)}{x_1(n)} \frac{1}{x_2(n)}$$

$$x_1(n) = \left(-\frac{1}{9}\right)^n u(n) \rightarrow \text{Right sided signal}$$

$$x_1(z) = \frac{1}{1 - (-\frac{1}{9}) z^{-1}}$$

$$\text{ROC } |z| \geq \left|\frac{1}{9}\right| \text{ or } |z| > \frac{1}{9}$$

$$x_2(n) = \left(-\frac{1}{3}\right)^n u(-n-1) \rightarrow \text{Left sided signal}$$

$$x_2(z) = \frac{1}{1 - (-\frac{1}{3}) z^{-1}}; \quad |z| \leq \frac{1}{3}$$

Now, when both the transforms are added using linearity property. ROC must be between $\frac{1}{3} > |z| > \frac{1}{9}$

Question 212: GATE EC 2012, Signals and Systems

MCQ

1 Mark

If $x[n] = (1/3)^{|n|} - (1/2)^n u[n]$, then the region of convergence (ROC) of its Z-transform in the Z-plane will be

- (A) $\frac{1}{3} < |z| < 3$
- (B) $\frac{1}{3} < |z| < \frac{1}{2}$
- (C) **(Correct)** $\frac{1}{2} < |z| < 3$
- (D) $\frac{1}{3} < |z|$

Correct Answer: (C)

Detailed Solution – Question 212

$$\begin{aligned}
 x[n] &= \left(\frac{1}{3}\right)^{|n|} - \left(\frac{1}{2}\right)^n u[n] \\
 x[n] &= \left(\frac{1}{3}\right)^n u[n] + \left(\frac{1}{3}\right)^{-n} u[-n-1] - \left(\frac{1}{2}\right)^n u[n] \\
 \left(\frac{1}{3}\right)^n u[n] &\longleftrightarrow \frac{1}{1 - \frac{1}{3}z^{-1}} \quad \text{ROC } |z| > \frac{1}{3} \\
 \left(\frac{1}{3}\right)^{-n} u[-n-1] &\longleftrightarrow \frac{-1}{1 - 3z^{-1}} \text{ROC } |z| < 3 \\
 \left(\frac{1}{2}\right)^n u[n] &\longleftrightarrow \frac{1}{1 - \frac{1}{2}z^{-1}} \quad \text{ROC } |z| > \frac{1}{2}
 \end{aligned}$$


So, overall ROC will be intersection of there ROC i.e. $\frac{1}{2} < |z| < 3$

Question 213: GATE EC 2011, Signals and Systems

MCQ

1 Mark

Two systems $H_1(z)$ and $H_2(z)$ are connected in cascade as shown below. The overall output $y(n)$ is the same as the input $x(n)$ with a one unit delay. The transfer function of the second system $H_2(z)$ is



- (A) $\frac{1-0.6z^{-1}}{z^{-1}(1-0.4z^{-1})}$
- (B) **(Correct)** $\frac{z^{-1}(1-0.6z^{-1})}{(1-0.4z^{-1})}$
- (C) $\frac{z^{-1}(1-0.4z^{-1})}{(1-0.6z^{-1})}$
- (D) $\frac{1-0.4z^{-1}}{z^{-1}(1-0.6z^{-1})}$

Correct Answer: (B)

Detailed Solution – Question 213

$y[n] = x[n - 1]$ Taking z-transform of both sides

$$r(z) = z^{-1}X(z)$$

$$\frac{r(z)}{X(z)} = z^{-1}$$

For cascaded system

$$H(z) = H_1(z) \cdot H_2(z)$$

$$z^{-1} = \frac{(1 - 0.4z^{-1})}{(1 - 0.6z^{-1})^{-1}(z)}$$

$$\therefore H_2(z) = \frac{z^{-1}(1 - 0.6z^{-1})}{(1 - 0.4z^{-1})}$$

Question 214: GATE EC 2010, Signals and Systems

MCQ

1 Mark

The transfer function of a discrete time LTI system is given by $H(z) = \frac{2 - \frac{3}{4}z^{-1}}{1 - \frac{3}{4}z^{-1} + \frac{1}{8}z^{-2}}$ Consider the following statements:

S1: The system is stable and causal for ROC: $|z| > 1/2$

S2: The system is stable but not causal for ROC: $|z| < 1/4$

S3: The system is neither stable nor causal for ROC: $1/4 < |z| < 1/2$

Which one of the following statements is valid ?

- (A) Both S1 and S2 are true
- (B) Both S2 and S3 are true
- (C) **(Correct)** Both S1 and S3 are true
- (D) S1, S2 and S3 are all

Correct Answer: (C)

Detailed Solution – Question 214

A discrete-time LTI system is causal if and only if the ROC of its system function is the exterior of a circle, including infinity.

A discrete-time LTI system is stable if and only if the ROC of its system function includes the unit circle, $|z| = 1$

$$H(z) = \frac{(1 - \frac{1}{4}z^{-1}) + (1 - \frac{1}{2}z^{-1})}{(1 - \frac{1}{4}z^{-1})(1 - \frac{1}{2}z^{-1})}$$

$$\text{or } H(z) = \frac{1}{1 - \frac{1}{4}z^{-1}} + \frac{1}{1 - \frac{1}{2}z^{-1}}$$

For ROC : $|z| > \frac{1}{2}$, the system is stable and causal.

For ROC : $|z| < \frac{1}{4}$, ROC does not include unit circle. So, system is not stable.

For ROC : $\frac{1}{4} < |z| < \frac{1}{2}$, ROC does not include unit circle. So, system is not stable. Also ROC is not the exterior of $|z| = \frac{1}{2}$. So, it is not causal.

Question 215: GATE EC 2010, Signals and Systems

MCQ

1 Mark

Two discrete time system with impulse response $h_1[n] = \delta[n - 1]$ and $h_2[n] = \delta[n - 2]$ are connected in cascade. The overall impulse response of the cascaded system is

- (A) $\delta[n - 1] + \delta[n - 2]$
- (B) $\delta[n - 4]$
- (C) **(Correct)** $\delta[n - 3]$
- (D) $\delta[n - 1]\delta[n - 2]$

Correct Answer: (C)

Detailed Solution – Question 215

$$h_1[n] = \delta[n - 1] \xrightarrow{Z} H_1(z) = z^{-1}$$

$$h_2[n] = \delta[n - 2] \xrightarrow{Z} H_2(z) = z^{-2}$$

Overall impulse response in z-domain,

$$\begin{aligned} H(z) &= H_1(z)H_2(z) \\ &= z^{-1}z^{-2} \\ &= z^{-3} \end{aligned}$$

Overall impulse response in discrete-time domain. $h[n] = \delta[n - 3]$

Question 216: GATE EC 2010, Signals and Systems

MCQ

1 Mark

Consider the z-transform $X(z) = 5z^2 + 4z^{-1} + 3; 0 < |z| < \infty$. The inverse z-transform $x[n]$ is

- (A) **(Correct)** $5\delta[n + 2] + 3\delta[n] + 4\delta[n - 1]$
- (B) $5\delta[n - 2] + 3\delta[n] + 4\delta[n + 1]$
- (C) $5u[n + 2] + 3u[n] + 4u[n - 1]$
- (D) $5u[n - 2] + 3u[n] + 4u[n + 1]$

Correct Answer: (A)

Detailed Solution – Question 216

$$\begin{aligned} \delta[n + n_0] &\xrightarrow{Z} z^{n_0} \\ X(z) &= 5z^2 + 4z^{-1} + 3; 0 < |z| < \infty \\ x(n) &= 5\delta(n + 2) + 4\delta(n - 1) + 3\delta(n) \end{aligned}$$

Question 217: GATE EC 2009, Signals and Systems

MCQ

1 Mark

The ROC of z -transform of the discrete time sequence $x(n) = (\frac{1}{3})^n u(n) - (\frac{1}{2})^n u(-n - 1)$ is

- (A) **(Correct)** $\frac{1}{3} < |z| < \frac{1}{2}$
- (B) $|z| > \frac{1}{2}$
- (C) $|z| < \frac{1}{3}$
- (D) $2 < |z| < 3$

Correct Answer: (A)

Detailed Solution – Question 217


$x(n] = (\frac{1}{3})^n u(n) - (\frac{1}{2})^n u(-n - 1)$ $(\frac{1}{3})^n u(n)$ is right sided signal, so ROC will be $|z| > 1/3$... (i) $-(\frac{1}{2})^n u(-n - 1)$ is left sided signal so ROC will be $|z| < 1/2$... (ii) from (i) and (ii) we see that ROC of the function will be $1/3 < |z| < 1/2$

Question 218: GATE EC 2008, Signals and Systems

MCQ

1 Mark

In the following network, the switch is closed at $t=0^-$ and the sampling starts from $t=0$. The sampling frequency is 10Hz.



The expression and the region of convergence of the z-transform of the sampled signal are

- (A) $\frac{5z}{z - e^{-5}}, |z| < e^{-5}$
- (B) $\frac{5z}{z - e^{-0.05}}, |z| < e^{-0.05}$
- (C) **(Correct)** $\frac{5z}{z - e^{-0.05}}, |z| > e^{-0.05}$

(D) $\frac{5z}{z-e^{-5}}, |z| > e^{-5}$

Correct Answer: (C)

Detailed Solution – Question 218

$$\begin{aligned} x(z) &= \sum_{n=0}^{\infty} 5e^{-0.05n} z^{-n} \\ &= 5 \sum_{n=0}^{\infty} (e^{-0.05} z^{-1})^n \\ \text{For } |e^{-0.05} z^{-1}| < 1 \text{ or } |z| > e^{-0.05} \\ x(z) &= \frac{5z}{z - e^{-0.05}} \end{aligned}$$

Question 219: GATE EC 2007, Signals and Systems

MCQ

1 Mark

The z-transform $X[z]$ of a sequence $x[n]$ is given by $X(z) = \frac{0.5}{1-2z^{-1}}$. It is given that the region of convergence of $X[z]$ includes the unit circle. The value of $x[0]$ is

- (A) -0.5
- (B) **(Correct)** 0
- (C) 0.25
- (D) 5

Correct Answer: (B)

Detailed Solution – Question 219

$$\begin{aligned} X(z) &= \frac{0.5}{1-2z^{-1}} \because \text{ROC includes unit circle} \Rightarrow \text{Left handed system} \Rightarrow x(n) = -(0.5)(2)^n u(-n-1) \\ \Rightarrow x(0) &= 0 \end{aligned}$$

Question 220: GATE EC 2006, Signals and Systems

MCQ

1 Mark

If the region of convergence of $x_1[n] + x_2[n]$ is $\frac{1}{3} < |z| < \frac{2}{3}$ then the region of convergence of $x_1[n] - x_2[n]$ includes

- (A) $\frac{1}{3} < |z| < 3$
- (B) $\frac{2}{3} < |z| < 3$
- (C) $\frac{3}{2} < |z| < 3$
- (D) **(Correct)** $\frac{1}{3} < |z| < \frac{2}{3}$

Correct Answer: (D)

Detailed Solution – Question 220

ROC remains the same for addition and subtraction in z-domain

Question 221: GATE EC 2006, Signals and Systems

MCQ

1 Mark

A low-pass filter having a frequency response $H(j\omega) = A(\omega)e^{j\phi(\omega)}$ does not produce any phase distortions if

- (A) $A(\omega) = C\omega^2, \phi(\omega) = k\omega^3$
- (B) **(Correct)** $A(\omega) = C\omega^2, \phi(\omega) = k\omega$
- (C) $A(\omega) = C\omega, \phi(\omega) = k\omega^2$
- (D) $A(\omega) = C, \phi(\omega) = k\omega^{-1}$

Correct Answer: (B)

Detailed Solution – Question 221

For distortionless transmission, $\frac{d\phi(\omega)}{d\omega} = \text{constant}$ Phase response should be linear $\phi(\omega) = k\omega$

Question 222: GATE EC 2005, Signals and Systems

MCQ

1 Mark

The region of convergence of z-transform of the sequence $(\frac{5}{6})^n u(n) - (\frac{6}{5})^n u(-n-1)$ must be

- (A) $|z| < \frac{5}{6}$
- (B) $|z| > \frac{5}{6}$
- (C) **(Correct)** $\frac{5}{6} < |z| < \frac{6}{5}$
- (D) $\frac{5}{6} < |z| < \infty$

Correct Answer: (C)

Detailed Solution – Question 222

$$\begin{aligned} & \text{z-transform of } \left(\frac{5}{6}\right)^n u(n) - \left(\frac{6}{5}\right)^n u(-n-1) \\ &= \frac{1}{1 - \frac{5}{6}z^{-1}} + \left[1 - \frac{1}{1 - (\frac{6}{5})^{-1}z} \right] \\ & \quad \text{(ROC)} \quad \text{(ROC)} \\ &= |z| > \frac{5}{6} \quad |z| < \frac{6}{5} \\ & \frac{5}{6} < |z| < \frac{6}{5} \end{aligned}$$

Question 223: GATE EC 2004, Signals and Systems

MCQ

1 Mark

A causal LTI system is described by the difference equation

$$2y[n] = \alpha y[n-2] - 2x[n] + \beta x[n-1]$$

The system is stable only if

- (A) $|\alpha| = 2, |\beta| < 2$
- (B) $|\alpha| > 2, |\beta| > 2$
- (C) **(Correct)** $|\alpha| < 2$, any value of β
- (D) $|\beta| < 2$, any value of α

Correct Answer: (C)

Detailed Solution – Question 223

$2y[n] = \alpha y[n-2] - 2x[n] + \beta x[n-1]$ Taking z-transform

$$\begin{aligned} 2Y(z) &= \alpha Y(z)z^2 - 2X(z) + \beta X(z)z^{-1} \\ Y(z) [2 - \alpha z^2] &= X(z) [\beta z^{-1} - 2] \\ \frac{Y(z)}{X(z)} &= \left(\frac{\beta z^{-1} - 2}{2 - \alpha z^{-2}} \right) \end{aligned}$$

For system to be stable, β can be of any value.

$$\begin{aligned} 2 - \alpha z^{-2} &= 0 \\ 2z^2 - \alpha &= 0 \\ z &= \sqrt{\frac{\alpha}{2}} < 1 \\ |\alpha| &< 2 \end{aligned}$$

For system to be stable all poles should be inside unity circle.

Question 224: GATE EC 2004, Signals and Systems

MCQ

1 Mark

The z-transform of a system is $H(z) = \frac{z}{z-0.2}$. If the ROC is $|z| < 0.2$, then the impulse response of the system is

- (A) $(0.2)^n u[n]$
- (B) $(0.2)^n u[-n-1]$
- (C) $-(0.2)^n u[n]$
- (D) **(Correct)** $-(0.2)^n u[-n-1]$

Correct Answer: (D)

Detailed Solution – Question 224

$$H(z) = \frac{z}{z - 0.2} = \frac{z}{z(1 - 0.2z^{-1})}$$

$$H(z) = \frac{1}{1 - 0.2z^{-1}}$$

ROC is $|z| < 0.2$ Comparing with, $-a^n u(-n-1) \rightarrow \frac{1}{1-az^{-1}}, |z| < a$ We get, $h(n) = -(0.2)^n u(-n-1)$

Question 225: GATE EC 2003, Signals and Systems

MCQ

1 Mark

A sequence $x(n)$ with the z -transform $X(z) = z^4 + z^2 - 2z + 2 - 3z^{-4}$ is applied as an input to a linear, time-invariant system with the impulse response $h(n) = 2\delta(n-3)$ where

$$\delta(n) = \begin{cases} 1, & n = 0 \\ 0, & \text{otherwise} \end{cases}$$

The output at $n = 4$ is

- (A) -6
- (B) **(Correct)** zero
- (C) 2
- (D) -4

Correct Answer: (B)

Detailed Solution – Question 225

$$Y(z) = H(z)X(z)$$

$$H(z) = 2z^{-3}$$

$$\begin{aligned} \therefore Y(z) &= 2z^{-3}(z^4 + z^2 - 2z + 2 - 3z^{-4}) \\ &= 2(z + z^{-1} - 2z^2 + 2z^3 - 3z^7) \end{aligned}$$

Taking inverse of z -transform

$$\begin{aligned} y(n) &= 2[\delta(n+1) + \delta(n-1) - 2\delta(n-2) \\ &\quad + 2\delta(n-3) - 3\delta(n-7)] \end{aligned}$$

$$\text{At } n = 4, y(4) = 0$$

Question 226: GATE EC 2002, Signals and Systems

MCQ

1 Mark

If the impulse response of a discrete-time system is $h[n] = -5^n u[-n-1]$, then the system function $H(z)$ is equal to

- (A) $\frac{-z}{z-5}$ and the system is stable
- (B) **(Correct)** $\frac{z}{z-5}$ and the system is stable
- (C) $\frac{-z}{z-5}$ and the system is unstable
- (D) $\frac{z}{z-5}$ and the system is unstable

Correct Answer: (B)

Detailed Solution – Question 226

$$\begin{aligned}
 h(n) &= -5^n u[-n-1] \\
 H(z) &= \sum_{n=-\infty}^{\infty} h(n) z^{-n} \\
 H(z) &= \sum_{n=-\infty}^{-1} -5^n z^{-n}, \text{ Let } n = -k \\
 &= - \sum_{k=\infty}^1 (5z^{-1})^{-k} \\
 &= 1 - \sum_{k=0}^{\infty} (5^{-1}z)^k \\
 &= 1 - \frac{1}{1 - 5^{-1}z}, |5^{-1}z| < 1, |z| < 5 \\
 &= 1 - \frac{5}{5-z} \\
 &= -\frac{z}{5-z} = \frac{z}{z-5}
 \end{aligned}$$

The system is stable because ROC includes unit circle.

Question 227: GATE EC 2001, Signals and Systems

MCQ

1 Mark

The region of convergence of the z-transform of a unit step function is

- (A) **(Correct)** $|z| > 1$
- (B) $|z| < 1$
- (C) (real part of Z) > 0

Correct Answer: (A)

Detailed Solution – Question 227

$$\begin{aligned}
 h(n) &= u(n) \\
 H(z) &= \sum_{n=0}^{\infty} 1 \cdot z^{-n}
 \end{aligned}$$


For the convergence of $H(z)$ $\sum_{n=0}^{\infty} (z^{-1})^n < \infty \therefore$ ROC is the range of values of z for which $|z^{-1}| < 1$ or $|z| > 1$

Question 228: GATE EC 2015-SET-2, Signals and Systems

MCQ

1 Mark

The magnitude and phase of the complex Fourier series coefficients a_k of a periodic signal $x(t)$ are shown in the figure. Choose the correct statement from the four choices given. Notation: $\mathbb{C}$ is the set of complex numbers, $\mathbb{R}$ is the set of purely real numbers, and $\mathbb{P}$ is the set of purely imaginary numbers.



- (A) **(Correct)** $x(t) \in \mathbb{R}$
- (B) $x(t) \in \mathbb{P}$
- (C) $x(t) \in (\mathbb{C} - \mathbb{R})$

(D) the information given is not sufficient to draw any conclusion about $x(t)$

Correct Answer: (A)

Detailed Solution – Question 228

$|a_k|$ – even symmetry

$\angle a_k$ – Odd symmetry (π can be $-\pi$)


$\Rightarrow x(t)$ is real.

Question 229: GATE EC 2014-SET-2, Signals and Systems



NAT

1 Mark

Consider the periodic square wave in the figure shown.



The ratio of the power in the 7^{th} harmonic to the power in the 5^{th} harmonic for this waveform is closest in value to



$$\begin{aligned}
 X(\omega) &= \sum_{K=-\infty}^{\infty} 2\pi a_K \delta(\omega - K\omega_0) \\
 a_K &= \frac{1}{2\pi} \int_0^2 x(t) e^{-jK\omega_0 t} dt \\
 &= \frac{1}{2\pi} \left\{ \int_0^1 1 \cdot e^{-jK\omega_0 t} dt - \int_1^2 1 \cdot e^{-jK\omega_0 t} dt \right\} \\
 &= \frac{1}{2\pi} \left[\frac{1}{-jK\omega_0} [e^{-jK\omega_0} - 1] - \frac{1}{-jK\omega_0} [e^{-j2K\omega_0} - e^{-jK\omega_0}] \right] \\
 &= \frac{1}{2\pi} \left[\frac{e^{-jK\omega_0/2}}{jK\omega_0} 2j \sin \frac{K\omega_0}{2} - \frac{1}{jK\omega_0} e^{-j\frac{3K\omega_0}{2}} \left(2j \sin \frac{K\omega_0}{2} \right) \right] \\
 &= \frac{1}{\pi} \left[\frac{\sin \frac{K\omega_0}{2}}{K\omega_0} (e^{-jK\omega_0/2}) \left(e^{j\frac{K\omega_0}{2}} - e^{-j\frac{3K\omega_0}{2}} \right) \right] \\
 &= \frac{1}{\pi} \left(\frac{\sin K\omega_0/2}{K\omega_0} \right) e^{-jK\omega_0/2} \times 2j \sin \left(\frac{K\omega_0}{2} \right) \\
 &= \frac{1}{\pi^2} \frac{(\sin K\frac{\pi}{2})^2}{K} 2j \times \cos K\pi
 \end{aligned}$$

$$7^{\text{th}} \text{ harmonic power} = (2\pi a_7)^2 \quad 5^{\text{th}} \text{ harmonic power} = (2\pi a_5)^2$$

$$Ratio = \left(\frac{a_7}{a_5} \right)^2 = \left(\frac{5}{7} \right)^2 = \frac{25}{49} = 0.51$$

Question 230: GATE EC 2011, Signals and Systems

MCQ

1 Mark

The trigonometric Fourier series of an even function does not have the

- (A) dc term
- (B) cosine terms
- (C) **(Correct)** sine terms
- (D) odd harmonic terms

Correct Answer: (C)

Detailed Solution – Question 230


Trigonometric Fourier series of an even function has de and cosine terms only.

Question 231: GATE EC 2010, Signals and Systems

MCQ

1 Mark

The trigonometric Fourier series for the waveform $f(t)$ shown below contains



- (A) only cosine terms and zero values for the dc components
- (B) only cosine terms and a positive value for the dc components
- (C) **(Correct)** only cosine terms and a negative value for the dc components
- (D) only sine terms and a negative value for the dc components

Correct Answer: (C)

Detailed Solution – Question 231

since $f(t)$ is an even function, its trigonometric Fourier series contains only cosine terms. D.C. component,

$$\begin{aligned}
 A_0 &= \frac{1}{T} \int_{-T/2}^{T/2} f(t) dt = \frac{2}{T} \int_0^{T/2} f(t) dt \\
 &= \frac{2}{T} \left[\int_0^{T/4} A dt + \int_{T/4}^{T/2} (-2A) dt \right] \\
 &= \frac{2}{T} \left[\frac{AT}{4} - 2A \left(\frac{T}{2} - \frac{T}{4} \right) \right] \\
 &= \frac{2}{T} \left[-\frac{AT}{4} \right] = -\frac{A}{2}
 \end{aligned}$$

Therefore, the trigonometric Fourier series for the waveform $f(t)$ contains only cosine terms and a negative value for the dc component.

Question 232: GATE EC 2009, Signals and Systems

MCQ

1 Mark

The Fourier series of a real periodic function has only (P) cosine terms if it is even

- (Q) sine terms if it is even
- (R) cosine terms if it is odd
- (S) sine terms if it is odd

Which of the above statements are correct ?

- (A) **(Correct)** P and S
- (B) P and R
- (C) Q and S
- (D) Q and R

Correct Answer: (A)

Detailed Solution – Question 232

The Fourier series of a real periodic function has only cosine terms if it is even and only sine terms if it is odd.

Question 233: GATE EC 2005, Signals and Systems

MCQ

1 Mark

Choose the function $f(t)$; $-\infty < t < \infty$ for which a Fourier series cannot be defined.

- (A) $3\sin(25t)$
- (B) $4\cos(20t+3)+2\sin(10t)$
- (C) **(Correct)** $\exp(-t)\sin(25t)$
- (D) 1

Correct Answer: (C)

Detailed Solution – Question 233

All other functions are either periodic or constant function.

Question 234: GATE EC 2003, Signals and Systems

MCQ

1 Mark

The Fourier series expansion of a real periodic signal with fundamental frequency f_0 is given by $g_p(t) = \sum_{n=-\infty}^{\infty} c_n e^{j2\pi n f_0 t}$. It is given that $c_3 = 3 + j5$. Then c_{-3} is

- (A) $5 + j3$
- (B) $-3 - j5$
- (C) $-5 + j3$
- (D) **(Correct)** $3 - j5$

Correct Answer: (D)

Detailed Solution – Question 234

$$\begin{aligned}c_{-k} &= c_k^* \\c_3 &= 3 + j5 \\c_{-3} &= c_k^* = 3 - j5\end{aligned}$$

Question 235: GATE EC 2002, Signals and Systems

MCQ

1 Mark

Which of the following cannot be the Fourier series expansion of a periodic signal?

- (A) $x(t) = 2\cos t + 3 \cos 3t$
- (B) **(Correct)** $x(t) = 2\cos \pi t + 7 \cos t$
- (C) $x(t) = \cos t + 0.5$

(D) $x(t) = 2\cos 1.5\pi t + \sin 3.5\pi t$

Correct Answer: (B)

Detailed Solution – Question 235

$$x(t) = 2\cos \pi t + 7\cos t$$

$$T_1 = \frac{2\pi}{(0)} = 2$$

$$T_2 = \frac{2\pi}{1} = 2\pi$$

$$\frac{T_1}{T_2} = \frac{1}{\pi} = \text{irrational}$$

$\therefore x(t)$ is not periodic and does not satisfy Dirichlet condition.


Question 236: Control Systems, Frequency Response Analysis


MCQ

1 Mark

The Nyquist plot of a system is given in the figure. Let $\omega_P, \omega_Q, \omega_R$ and ω_S be the positive frequencies at the points P, Q, R , and S , respectively.

Which one of the following statements is TRUE?





- (A) ω_S is the gain crossover frequency and ω_P is the phase crossover frequency
- (B) ω_Q is the gain crossover frequency and ω_S is the phase crossover frequency
- (C) ω_R is the gain crossover frequency and ω_S is the phase crossover frequency
- (D) **(Correct)** ω_S is the gain crossover frequency and ω_Q is the phase crossover frequency

Correct Answer: (D)

Detailed Solution – Question 236

From the Nyquist plot:

The gain crossover frequency is the frequency at which the Nyquist plot crosses the unit circle, i.e., the magnitude of the open-loop transfer function $|G(j\omega)H(j\omega)| = 1$.

The phase crossover frequency is the frequency at which the phase is -180° , i.e., the Nyquist plot crosses the negative real axis.

From the diagram:

Point S lies on the unit circle, so ω_S is the gain crossover frequency.

Point P lies on the negative real axis, hence ω_P is the phase crossover frequency.

Therefore, the correct statement is: ω_S is the gain crossover frequency and ω_P is the phase crossover frequency.


Question 237: Analog Circuits, Frequency Response of Amplifier

NAT

1 Mark

All the components in the bandpass filter given below are ideal. The lower -3dB frequency of the filter is 1 MHz .

The upper -3dB frequency (in MHz , rounded off to the nearest integer) is _____.



Detailed Solution – Question 237

We are given:

Lower cutoff (high-pass) $f_L = 1\text{ MHz}$ We can use the standard formulas for cutoff frequencies:

High-pass cutoff (lower -3dB):

$$f_L = \frac{1}{2\pi R_{\text{HP}} C_{\text{HP}}} = \frac{1}{2\pi R \cdot 10C}$$

$$f_L = \frac{1}{20\pi RC} \text{ Given } f_L = 1\text{ MHz} \Rightarrow RC = \frac{1}{20\pi \times 10^6}$$

Keep this for substitution.

Low-pass cutoff (upper -3dB):

$$f_H = \frac{1}{2\pi R_{\text{LP}} C_{\text{LP}}} = \frac{1}{2\pi \cdot 2R \cdot 0.1C} = \frac{1}{0.4\pi RC}$$

Now plug in $RC = \frac{1}{20\pi \cdot 10^6}$ into this:

$$f_H = \frac{1}{0.4\pi} \cdot \left(\frac{20\pi \cdot 10^6}{1} \right) = \frac{20\pi \cdot 10^6}{0.4\pi} = \frac{20}{0.4} \cdot 10^6 = 50 \cdot 10^6 = 50\text{ MHz}$$

Question 238: Control Systems, Frequency Response Analysis

MCQ

1 Mark

In the context of Bode magnitude plots, 40 dB/ decade is the same as _____

- (A) **(Correct)** 12 dB/ octave
- (B) 6 dB/ octave
- (C) 20 dB/ octave
- (D) 10 dB/ octave

Correct Answer: (A)

Detailed Solution – Question 238


$$\begin{aligned}20 \times \text{ndB/ decade} &= 6 \times \text{ndB/ octave} \\40 \text{ dB/ decade} &= 12 \text{ dB/ octave}\end{aligned}$$


Question 239: Analog Circuits, Frequency Response of Amplifier

MCQ

1 Mark

For the closed loop amplifier circuit shown below, the magnitude of open loop low frequency small signal voltage gain is 40. All the transistors are biased in saturation. The current source I_{SS} is ideal. Neglect body effect, channel length modulation and intrinsic device capacitances. The closed loop low frequency small signal voltage gain $\frac{V_{out}}{V_{in}}$ (rounded off to three decimal places) is _____.





- (A) (Correct) 0.976
 (B) 1
 (C) 1.025
 (D) 0.488

Correct Answer: (A)

Detailed Solution – Question 239

$$A_{OL} = 40$$

Given circuit is differential amplifier with current mirror active load.


$$\begin{aligned} V_f &= V_{out} \\ \frac{V_f}{V_{out}} &= \beta = 1 \\ A_{CL} &= \frac{A_{OL}}{1 + \beta A_{OL}} = \frac{40}{1 + 1 \times 40} \\ A_{CL} &= 0.976 \end{aligned}$$

Question 240: Control Systems, Frequency Response Analysis

NAT

2 Marks

The asymptotic magnitude Bode plot of a minimum phase system is shown in the figure. The transfer function of the system is $(s) = \frac{k(s+z)^a}{s^b(s+p)^c}$, where k, z, p, a, b and c are positive constants. The value of $(a + b + c)$ is ---
 (rounded off to the nearest integer).



Detailed Solution – Question 240

From the Bode magnitude plot, it is clear that there is one pole at origin, $\therefore b = 1$
 and at frequency ω_1 , system has a zero
 $\therefore a = 1$
 and at frequency ω_2 , system has a two poles



$$\begin{aligned}\therefore c &= 2 \\ \therefore a + b + c &= 1 + 1 + 2 \\ a + b + c &= 4\end{aligned}$$

Question 241: Control Systems, Frequency Response Analysis

MCQ



1 Mark

Consider a closed-loop control system with unity negative feedback and $KG(s)$ in the forward path, where the gain $K = 2$. The complete Nyquist plot of the transfer function $G(s)$ is shown in the figure. Note that the Nyquist contour has been chosen to have the clockwise sense. Assume $G(s)$ has no poles on the closed right-half of the complex plane. The number of poles of the closed-loop transfer function in the closed right-half of the complex plane is _____



- (A) 0
- (B) 1
- (C) (Correct) 2
- (D) 3

Correct Answer: (C)



For $K = 2$, point A will be $-0.8 \times 2 = -1.6$

Hence $N = -2$, $P = 0$

(By default Nyquist contour is considered in clockwise direction)

$P - N = 2$

Number of closed loop pole in right side of the complex plane.



Question 242: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The complete Nyquist plot of the open-loop transfer function $G(s)H(s)$ of a feedback control system in

the figure.



If $G(s)H(s)$ has one zero in the right-half of the s -plane, the number of poles that the closed-loop system will have in the right-half of the s -plane is

- (A) 0
- (B) 1
- (C) 4

(D) (Correct) 3

Correct Answer: (D)

Detailed Solution – Question 242


The given Nyquist plot is not matched according to the data given in the question.

Question 243: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The pole-zero map of a rational function $G(s)$ is shown below. When the closed counter Γ is mapped into the $G(s)$ -plane, then the mapping encircles.



- (A) the origin of the $G(s)$ -plane once in the counter-clockwise direction.
- (B) (Correct) the origin of the $G(s)$ -plane once in the clockwise direction.
- (C) the point $-1+j0$ of the $G(s)$ -plane once in the counter-clockwise direction.

(D) the point $-1+j0$ of the $G(s)$ -plane once in the clockwise direction.

Correct Answer: (B)

Detailed Solution – Question 243

s-plane contour is encircling 2-poles and 3-zeros in clockwise direction hence the corresponding $G(s)$ plane contour encircles origin 2-times in anti-clockwise direction and 3-times in clockwise direction.


Therefore, Effectively once in clockwise direction.

Question 244: Control Systems, Frequency Response Analysis

MCQ

1 Mark

For an LTI system, the Bode plot for its gain is as illustrated in the figure shown. The number of system poles N_p and the number of system zeros N_z in the frequency range $1\text{ Hz} \leq f \leq 10^7\text{ Hz}$ is



- (A) $N_p = 5, N_z = 2$
- (B) **(Correct)** $N_p = 6, N_z = 3$
- (C) $N_p = 7, N_z = 4$
- (D) $N_p = 4, N_z = 2$

Correct Answer: (B)

Detailed Solution – Question 244

Corner frequency (in Hz)	No. of poles (or) zeros
10	1 pole
10^2	2 poles
10^3	1 zero
10^4	2 zeros
10^5	2 poles
10^6	1 pole

Corner frequency (in Hz)	No. of poles (or) zeros
10	1 pole
10^2	2 poles
10^3	1 zero
10^4	2 zeros
10^5	2 poles
10^6	1 pole

Number of poles (N_P) = 6

Number of zeros (N_Z) = 3

Question 245: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The Nyquist stability criterion and the Routh criterion both are powerful analysis tools for determining the stability of feedback controllers. Identify which of the following statements is FALSE:

- (A) Both the criteria provide information relative to the stable gain range of the system.
- (B) The general shape of the Nyquist plot is readily obtained from the Bode magnitude plot for all minimum-phase systems.
- (C) The Routh criterion is not applicable in the condition of transport lag, which can be readily handled by the Nyquist criterion.
- (D) **(Correct)** The closed-loop frequency response for a unity feedback system cannot be obtained from the Nyquist plot.

Correct Answer: (D)

Question 246: Control Systems, Frequency Response Analysis

NAT

2 Marks

For a unity feedback control system with the forward path transfer function

$$G(s) = \frac{K}{s(s+2)}$$

The peak resonant magnitude M_r , of the closed-loop frequency response is 2. The corresponding value of the gain K (correct to two decimal places) is

Detailed Solution – Question 246

Maximum resonant peak,

$$M_r = \frac{1}{2\xi\sqrt{1-\xi^2}} = 2$$

$$2\xi\sqrt{1-\xi^2} = \frac{1}{2}$$

$$\xi^2(1-\xi^2) = \frac{1}{16}$$

$$\xi^4 - \xi^2 + \frac{1}{16} = 0$$

$$\xi^2 = \frac{1}{2} \pm \sqrt{\frac{1-\frac{1}{4}}{4}} = \frac{1}{2} \pm \frac{\sqrt{3}}{4}$$

$$\text{As } M_r = 2 > 1, \xi < \frac{1}{\sqrt{2}} \text{ and } \xi^2 < \frac{1}{2}$$

$$\text{So, } \xi^2 = \frac{1}{2} - \frac{\sqrt{3}}{4}$$

$$\text{Given, } G(s) = \frac{K}{s(s+2)} = \frac{\omega_n^2}{s(s+2\xi\omega_n)}$$

$$\text{So } \omega_n = \sqrt{K}$$

$$2\xi\sqrt{K} = 2$$

$$\sqrt{K} = \frac{1}{\xi}$$

$$K = \frac{1}{\xi^2} = \frac{1}{\left(\frac{1}{2} - \frac{\sqrt{3}}{4}\right)}$$

$$= \frac{4}{2 - \sqrt{3}} = 14.928$$


Question 247: Control Systems, Frequency Response Analysis

NAT

2 Marks

The figure below shows the Bode magnitude and phase plots of a stable transfer function $G(s) =$

$$\frac{n_0}{s^2 + d_2 s^2 + d_1 s + d_0}$$



Consider the negative unity feedback configuration with gain k in the feedforward path. The closed loop is stable for $k < k_o$. The maximum value of k_o is

Detailed Solution – Question 247

For $G(s)$ $M_{dB}(\omega_{pc}) = 20\text{dB}$ When cascaded with k ,

$$\begin{aligned} \text{GM}_{dB} &= -20\text{dB} - 20\log_{10}(k) > 0\text{dB} \\ 20 + 20\log_{10}(k) &< 0 \\ 20\log_{10}(k) &< -20 \\ k &< 10^{-1} = 0.10 \\ \text{So, } k_0 &= 0.10 \end{aligned}$$

Question 248: Analog Circuits, Frequency Response of Amplifier

MCQ

1 Mark

The Miller effect in the context of a Common Emitter amplifier explains

- (A) an increase in the low-frequency cutoff frequency
- (B) an increase in the high-frequency cutoff frequency
- (C) a decrease in the low-frequency cutoff frequency
- (D) **(Correct)** a decrease in the high-frequency cutoff frequency

Correct Answer: (D)

Detailed Solution – Question 248

Miller effect increases input capacitance and thereby decreases the higher cut-off frequency

Question 249: Control Systems, Frequency Response Analysis

MCQ

1 Mark

Consider a stable system with transfer function $G(s) = \frac{s^p + b_1 s^{p-1} + \dots + b_p}{s^q + a_1 s^{q-1} + \dots + a_q}$

where $b_1, \dots, b_p$ and $a_1, \dots, a_q$ are real valued constants. The slope of the Bode log magnitude curve of $G(s)$ converges to -60 dB/decade as $\omega \rightarrow \infty$. A possible pair of values for p and q is

- (A) **(Correct)** p=0 and q=3
- (B) p=1 and q=7
- (C) p=2 and q=3
- (D) p=3 and q=5

Correct Answer: (A)

Detailed Solution – Question 249

Final slope = -60 dB/decade, which indicates that, q-p=3
Among the given options, option (A) satisfies this condition

Question 250: Control Systems, Frequency Response Analysis

MCQ

2 Marks

The Nyquist plot of the transfer function

$$G(s) = \frac{K}{(s^2 + 2s + 2)(s + 2)}$$

does not encircle the point (1+j0) for K=10 but does encircle the point (-1+j0) for K=100. Then the closed loop system (having unity gain feedback) is

- (A) stable for K = 10 and stable for K = 100
- (B) **(Correct)** stable for K = 10 and unstable for K = 100
- (C) unstable for K = 10 and stable for K = 100
- (D) unstable for K = 10 and unstable for K = 100

Correct Answer: (B)

Detailed Solution – Question 250

Given that, $G(s) = \frac{K}{(s^2+2s+2)(s+2)}$ P= open loop poles in RHS of s-plane Z= closed loop poles in RHS of s-plane N= number of encirclements about the

point $(-1 + j0)$

For $K = 10$;

$N = P - Z = 0 \Rightarrow Z = 0$: stable

For $K = 100$;





$N = P - Z = 1 \Rightarrow Z \neq 0$: unstable

Question 251: Control Systems, Frequency Response Analysis

MCQ

2 Marks

A unity feedback control system is characterized by the open-loop transfer function $G(s) = \frac{10K(s+2)}{s^3+3s^2+10}$. The Nyquist path and the corresponding Nyquist plot of $G(s)$ are shown in the figures below.



If $0 < K < 1$, then the number of poles of the closed-loop transfer function that lie in the right half of the s-plane is

- (A) 0
- (B) 1
- (C) **(Correct)** 2

(D) 3

Correct Answer: (C)

Detailed Solution – Question 251

Given that, the open loop transfer function of a unity feedback system is, $G(s) = \frac{10k(s+2)}{s^3+3s^2+10}$ From the given Nyquist plot, for $0 < k < 1$ the encirclements about the point $(-1+j0)$ is,

$$N = 0$$
$$N = P - Z$$

P = number of open loop poles in the right half of s-plane Z = number of closed loop poles in the right half of s-plane To determine the value of P : Applying R-H criteria to $G(s)$ $G(s) = \frac{10k(s+2)}{s^3+3s^2+10}$

s^3		1	0
s^2		3	10
s^1		$-10/3$	0
s^0		10	0

Two sign changes are there in the first column of the RH table. So, two open loop poles are there in right half of s-plane.

So, $P = 2$

$$N = P - Z$$
$$0 = 2 - Z$$
$$Z = 2$$

Z=2 indicates, there are two closed loop poles in right half of s-plane.

Question 252: Control Systems, Frequency Response Analysis

MCQ

1 Mark

A closed-loop control system is stable if the Nyquist plot of the corresponding open-loop transfer function

- (A) **(Correct)** encircles the s-plane point $(-1 + j0)$ in the counterclockwise direction as many times as the number of right-half s-plane poles.
- (B) encircles the s-plane point $(0 - j1)$ in the clockwise direction as many times as the number of right-half s-plane poles.
- (C) encircles the s-plane point $(-1 + j0)$ in the counterclockwise direction as many times as the number of left-half s-plane poles
- (D) encircles the s-plane point $(-1 + j0)$ in the counterclockwise direction as many times as the number of right-half s-plane zeros.

Correct Answer: (A)

Detailed Solution – Question 252

$$N = P - Z$$

N = Number of encirclements of $(-1 + j0)$. It is positive if nyquist plot encircles the point $-1 + j0$ in counterclockwise direction.

Z = Number of closed loop poles lying in the right half of s -plane

P = Number of open loop poles lying in right half of s -plane

For stability $Z = 0 \Rightarrow N = P$

Question 253: Analog Circuits, Frequency Response of Amplifier

MCQ

1 Mark

Which one of the following statements is correct about an ac-coupled common-emitter amplifier operating in the mid-band region?

- (A) **(Correct)** The device parasitic capacitances behave like open circuits, whereas coupling and bypass capacitances behave like short circuits.
- (B) The device parasitic capacitances, coupling capacitances and bypass capacitances behave like open circuits.
- (C) The device parasitic capacitances, coupling capacitances and bypass capacitances behave like short circuits
- (D) The device parasitic capacitances behave like short circuits, whereas coupling and bypass capacitances behave like open circuits

Correct Answer: (A)

Question 254: Control Systems, Frequency Response Analysis



NAT

1 Mark

The number and direction of encirclements around the point $-1+j0$ in the complex plane by the Nyquist plot of $G(s) = \frac{1-s}{4+2s}$ is

Detailed Solution – Question 254

$G(s) = \frac{1-s}{4+2s}$ and $\angle G(s) = -\tan^{-1} \omega - \tan^{-1} \frac{\omega}{2}$ at $s = 0$, $|G(s)| = \frac{1}{4} = 0.25$ and $\angle G(s)|_{\omega=0} = 0^\circ$ at $s = \infty$, $|G(s)| = -\frac{1}{2} = -0.5$ and $\angle G(s)|_{\omega=\infty} = -180^\circ$ Nyquist plot is




Hence, number of encirclements of $(-1 + j0) = 0$

Question 255: Control Systems, Frequency Response Analysis

NAT

2 Marks

In the feedback system shown below $G(s) = \frac{1}{(s+1)(s+2)(s+3)}$



The positive value of k for which the gain margin of the loop is exactly 0 dB and the phase margin of the loop is exactly zero degree is

Detailed Solution – Question 255

$1 + G(s)H(s) = 1 + \frac{K}{(s+1)(s+2)(s+3)} = 0 \Rightarrow (s+1)(s^2 + 5s + 6) + K = 0 \Rightarrow s^3 + 5s^2 + 6s + s^2 + 5s + 6 + K = 0$
 $\Rightarrow s^3 + 6s^2 + 11s + 6 + K = 0$ Gain margin = 0dB and phase margin = 0° It implies marginal stable system By Routh Array

$$\begin{array}{c|cc}
 s^3 & 1 & 11 \\
 s^2 & 6 & (6+K) \\
 s & \frac{66-6-K}{6} & 0 \\
 s^0 & 6+K &
 \end{array}$$


For marginal stable system, $60 - K = 0 \Rightarrow K = 60$

Question 256: Control Systems, Frequency Response Analysis

NAT

2 Marks

The asymptotic Bode phase plot of $G(s) = \frac{1}{(s+0.1)(s+10)(s+p_1)}$, with k and p_1 both positive, is shown below. The value of p_1 is _____



Detailed Solution – Question 256

$$\begin{aligned}
 G(s) &= \frac{K}{(s + 0.1)(s + 10)(s + p_1)} \\
 \angle G(s) &= -\tan^{-1} \frac{\omega}{0.1} - \tan^{-1} \frac{\omega}{10} - \tan^{-1} \frac{\omega}{p_1} \\
 \angle G(s)|_{\omega=1} &= -\tan^{-1} \frac{1}{0.1} - \tan^{-1} \frac{1}{10} - \tan^{-1} \frac{1}{p_1} \\
 &= -135^\circ \\
 -\tan^{-1} 10 - \tan^{-1} 0.1 - \tan^{-1} \frac{1}{p_1} &= -135^\circ \\
 -84.28^\circ - 5.71^\circ - \tan^{-1} \frac{1}{p_1} &= -135^\circ \\
 -\tan^{-1} \frac{1}{p_1} &= -135^\circ + 90^\circ \\
 \tan^{-1} \frac{1}{p_1} &= 45^\circ \\
 \frac{1}{p_1} &= 1 \Rightarrow p_1 = 1
 \end{aligned}$$

Question 257: Control Systems, Frequency Response Analysis

MCQ

1 Mark



The polar plot of the transfer function $G(s) = \frac{10(s+1)}{s+10}$ for $0 \leq \omega < \infty$ will be in the

- (A) **(Correct)** first quadrant
- (B) second quadrant
- (C) third quadrant
- (D) fourth quadrant

Correct Answer: (A)

Detailed Solution – Question 257

$G(s) = \frac{10(s+1)}{(s+10)}$ For $\omega = 0 \Rightarrow M_1 = 1$ and $\phi_1 = 0^\circ$ $\omega = 0 \Rightarrow M_2 = 10$ and $\phi_2 = -\tan^{-1} \infty + \tan^{-1} \infty = 0^\circ \therefore$ Polar plot



As the zero is nearer to the imaginary axis hence the direction of polar plot is clockwise.

Question 258: Control Systems, Frequency Response Analysis

NAT

2 Marks

The transfer function of a mass-spring-damper system is given by

$$G(s) = \frac{1}{Ms^2 + Bs + K}$$

The frequency response data for the system are given in the following table.

ω in rad/s	$ G(j\omega) $ in dB	$\arg(G(j\omega))$ in deg
0.01	-18.5	-0.2
0.1	-18.5	-1.3
0.2	-18.4	-2.6
1	-16	-16.9
2	-11.4	-89.4
3	-21.5	-151
5	-32.8	-167
10	-45.3	-174.5

ω in rad/s	$ G(j\omega) $ in dB	$\arg(G(j\omega))$ in deg
0.01	-18.5	-0.2
0.1	-18.5	-1.3
0.2	-18.4	-2.6
1	-16	-16.9
2	-11.4	-89.4
3	-21.5	-151
5	-32.8	-167
10	-45.3	-174.5

The unit step response of the system approaches a steady state value of

Detailed Solution – Question 258

$\frac{\alpha(s)}{R(s)} = G(s) = \frac{1}{Ms^2 + Bs + K}$ Steady state value of response for unit step input

$$C(s) = \lim_{s \rightarrow 0} s \times \frac{1}{Ms^2 + Bs + K} \times \frac{1}{s} = \frac{1}{K}$$

Also

$$G(\approx 0) = \frac{1}{K} = -18.5\text{dB}$$

(as per the given table)


$$\therefore \frac{1}{K} = 10^{(-\frac{18.5}{20})} = 0.12$$


Question 259: Control Systems, Frequency Response Analysis

NAT

1 Mark

Consider the Bode plot shown in the figure. Assume that all the poles and zeros are real-valued.





The value of $f_H - f_L$ (in Hz) is

Detailed Solution – Question 259

As we know,

$$\begin{aligned} \text{Slope} &= \frac{y_2 - y_1}{x_2 - x_1} \\ \therefore 40\text{dB/dec} &= \frac{40 - 0}{\log 300 - \log f_L} \\ \text{or, } \log \left(\frac{300}{f_L} \right) &= \frac{40}{40} = 1 \Rightarrow f_L = 30\text{Hz} \end{aligned}$$

Similarly,

$$\begin{aligned} -40\text{dB/dec} &= \frac{40 - 0}{\log 900 - \log f_H} \\ \log \left(\frac{900}{f_H} \right) &= -1 \\ \text{or, } f_H &= 9000\text{Hz} \\ \text{Therefore, } f_H - f_L &= 9000 - 30 = 8970\text{Hz} \end{aligned}$$

Question 260: Control Systems, Frequency Response Analysis

NAT

1 Mark

The phase margin (in degrees) of the system $G(s) = \frac{10}{s(s+10)}$ is

Detailed Solution – Question 260

$$G(s) = \frac{10}{s(s+10)}$$

$$PM = 180^\circ + \angle G(\omega)H(\omega)|_{\omega=\omega_{gc}}$$

The gain cross over frequency can be calculated by

$$|G(\omega)H(\omega)| = 1$$

$$\frac{10}{\omega\sqrt{\omega^2 + 100}} = 1$$

$$\omega_{gc}^4 + 100\omega_{gc}^2 - 100 = 0$$

$$\text{Or } \omega_{gc}^2 = 0.99, \quad -100.99$$

$$\text{Or } \omega_{gc} = 0.99 \text{ rad/sec.}$$


$$\begin{aligned} \therefore PM &= 180^\circ + \left(-90^\circ - \tan^{-1} \frac{\omega_{gc}}{10}\right) \\ &= 180^\circ - 90^\circ - \tan^{-1} \frac{0.99}{10} \\ &\simeq 84.364^\circ \end{aligned}$$

Question 261: Control Systems, Frequency Response Analysis

MCQ


1 Mark

Consider the feedback system shown in the figure. The Nyquist plot of $G(s)$ is also shown. Which one of the following conclusions is correct ?



- (A) $G(s)$ is an all pass filter
- (B) $G(s)$ is a strictly proper transfer function
- (C) $G(s)$ is a stable and minimum phase transfer function
- (D) **(Correct)** The closed-loop system is unstable for sufficiently large and positive k

Correct Answer: (D)



From the Nyquist plot, it can be seen that it does not encircle the critical point $(-1, 0)$ $N = P \cdot Z$, $N = 0$

The closed loop-system is unstable for sufficiently large and positive K

Question 262: Control Systems, Frequency Response Analysis

NAT

2 Marks



The phase margin in degrees of $G(s) = \frac{1}{(s+0.1)(s+1)(s+10)}$ calculated using the asymptotic Bode plot is

Detailed Solution – Question 262

$$\frac{10}{0.7 \times 10 \left(\frac{s}{0.1} + 1 \right) \left(\frac{s}{1} + 1 \right) \left(\frac{s}{10} + 1 \right)}$$

$$= \frac{10}{\left(\frac{s}{0.1} + 1 \right) \left(\frac{s}{1} + 1 \right) \left(\frac{s}{10} + 1 \right)}$$

Amount of shift = $20 \log K = 20 \log 10 = 20 \text{ dB}$



$$-20 \text{ dB} = \frac{20 - 0}{\log 0.1 - \log \omega_{gc}}$$

or, $\omega_{gc} = 1 \text{ rad/sec}$... (i)

PM = $180^\circ + \angle GH(j\omega)|_{\omega=\omega_{gc}}$... (ii)

From the given transfer function,

$$\angle G(j\omega) = -\tan^{-1} \left(\frac{\omega_{gc}}{0.1} \right) - \tan^{-1} \left(\frac{\omega_{gc}}{1} \right)$$

$$- \tan^{-1} \left(\frac{\omega_{gc}}{10} \right)$$

$$\alpha \angle G(j(1)) = -84.289^\circ - 45^\circ - 5.711^\circ$$

$$= -135^\circ \quad \dots (iii)$$


∴ From equation (ii) and (iii) we get, Phase margin PM = $180^\circ - 135^\circ = 45^\circ$

Question 263: Control Systems, Frequency Response Analysis


NAT

2 Marks

The Bode asymptotic magnitude plot of a minimum phase system is shown in the figure



If the system is connected in a unity negative feedback configuration, the steady state error of the closed loop system, to a unit ramp input, is_____.



The open loop transfer function of the system

$$G(s)H(s) = \frac{K \left(\frac{s}{2} + 1 \right)}{s \left(\frac{s}{10} + 1 \right)} \quad \dots (i)$$

where, $26.02|_{\omega=0.1} = 20 \log K - 20 \log \omega \quad \dots (ii)$ Or, $K = 1.99 \simeq 2$ From equation (i) and (ii), we get $G(s) = \frac{20(s+2)}{2s(s+10)} \quad \dots (iii)$ Steady state error for ramp input is $e_{ss} = \frac{A}{K_V}$ where $K_V = \lim_{s \rightarrow 0} sG(s)$ From equation (iii), $K_V = \lim_{s \rightarrow 0} s \times \frac{10(s+2)}{s(s+10)} = 2 \therefore e_{ss} = \frac{1}{2} = 0.5$

Question 264: Control Systems, Frequency Response Analysis

MCQ

1 Mark

In a Bode magnitude plot, which one of the following slopes would be exhibited at high frequencies by a 4th order all-pole system ?

- (A) **(Correct)** -80dB/decade
- (B) -40dB/decade
- (C) $+40\text{dB/decade}$
- (D) $+80\text{dB/decade}$

Correct Answer: (A)

Detailed Solution – Question 264

A 4th order all-pole system means that the system must be having no zero or s-terms in numerator or and s^4 terms in denominator or 4 -poles.

i.e. $H(s) \propto \frac{1}{s^4}$



One pole exhibits -20 dB/decade slope, so 4 pole exhibits a slope of -80 dB/decade.

Question 265: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The Bode plot of a transfer function $G(s)$ is shown in the figure below.



The gain ($20 \log |G(s)|$) is 32 dB and -8 dB at 1 rad/s and 10 rad/s respectively. The phase is negative for all ω . Then $G(s)$ is

(A) $\frac{39.8}{s}$

(B) **(Correct)** $\frac{39.8}{s^2}$

(C) $\frac{32}{s}$

(D) $\frac{32}{s^2}$

Correct Answer: (B)

Detailed Solution – Question 265


10rad/s to 1rad/s is 1 decade $32 - (-8) = 40dB$ So, the slope is 40dB/decade it means there are two poles at origin, it means either option (B) or option (D) is correct put $\omega = 1\text{rad/sec}$ in both the options. $20 \log \left[\frac{39.8}{(1)^2} \right] = 32\text{dB}$ $20 \log \left[\frac{32}{(1)^2} \right] = 30.1\text{dB}$ So, option (B) is correct option = $\frac{39.8}{s^2}$

Question 266: Analog Circuits, Frequency Response of Amplifier

MCQ

1 Mark

The ac schematic of an NMOS common-source stage is shown in the figure below, where part of the biasing circuits has been omitted for simplicity. For the n-channel MOSFET M, the transconductance $g_m = 1\text{mA/V}$ and body effect and channel length modulation effect are to be neglected. The lower cutoff frequency in Hz of the circuit is approximately at



(A) **(Correct)** 8

(B) 32

- (C) 50
(D) 200

Correct Answer: (A)

Detailed Solution – Question 266

$$f_L = \frac{1}{2\pi RC} = \frac{1}{2 \times 3.14 \times (10k + 10k) \times 1\mu F} = 8Hz$$

Question 267: Control Systems, Frequency Response Analysis

MCQ

1 Mark

A system with transfer function $G(s) = \frac{(s^2+9)(s+2)}{(s+1)(s+3)(s+4)}$ is excited by $\sin(\omega t)$. The steady-state output of the system is zero at

- (A) $\omega=1$ rad/s
(B) $\omega=2$ rad/s
(C) **(Correct)** $\omega=3$ rad/s
(D) $\omega=4$ rad/s

Correct Answer: (C)

Detailed Solution – Question 267

Transfer function is

$$G(s) = \frac{(s^2 + 9)(s + 2)}{(s + 1)(s + 3)(s + 4)}$$

Input $X(s) = L \cdot T[\sin \omega t]$

$$X(s) = \frac{\omega}{s^2 + \omega^2}$$

So output

$$Y(s) = \frac{(s^2 + 9)(s + 2)}{(s + 1)(s + 3)(s + 4)} \cdot \frac{\omega}{(s^2 + \omega^2)}$$

Now

$$\lim_{t \rightarrow \infty} y(t) = \lim_{s \rightarrow 0} sY(s) = \lim_{s \rightarrow 0} s \frac{(s^2 + 9)(s + 2)}{(s + 1)(s + 3)(s + 4)} \cdot \frac{\omega}{(s^2 + \omega^2)}$$









this will be zero if $s^2 + \omega^2$ will cancel $(s^2 + 9)$ term as only then final value theorem will be applicable. So at $\omega^2 = 9 \Rightarrow \omega = 3\text{rad/sec}$, steady state output will be zero.

Question 268: Control Systems, Frequency Response Analysis

MCQ

1 Mark

For the transfer function $G(j\omega) = 5 + j\omega$, the corresponding Nyquist plot for positive frequency has the form



(A) (Correct) A

(B) B

(C) C

(D) D

Correct Answer: (A)

Detailed Solution – Question 268

$$G(j\omega) = 5 + j\omega$$

$$|G(j\omega)| = \sqrt{25 + \omega^2}$$

$$\text{At } \omega = 0$$

$$\text{At } |G(0)| = \sqrt{25 + 0} = 5$$

$$\text{At } \omega = \infty$$


$$|G(\infty)| = \infty$$

Question 269: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The input-output transfer function of a plant $H(s) = \frac{100}{s(s+10)^2}$. The plant is placed in a unity negative feedback configuration as shown in the figure below.



The gain margin of the system under closed loop unity negative feedback is

- (A) 0 dB
- (B) 20 dB
- (C) **(Correct)** 26 dB
- (D) 46 dB

Correct Answer: (C)

Detailed Solution – Question 269

$$G(s)H(s) = \frac{100}{s(s+10)^2}$$

$$\phi = -90^\circ - 2 \tan^{-1}(\omega/10)$$

For phase cross-over frequency, $\phi = -180^\circ$

$$\therefore -180 = -90^\circ - 2 \tan^{-1}(\omega/10)$$

$$\Rightarrow \omega = 10 \text{ rad/sec}$$

$$s = j\omega$$

$$\text{Put, } G(j\omega)H(j\omega) = \frac{100}{j\omega(j\omega + 10)^2}$$

$$|G(j\omega)H(j\omega)|_{\omega=10} = \frac{100}{\omega(\omega^2 + 100)}$$

$$= \frac{100}{10(200)} = \frac{1}{20}$$

$$\text{G.M.} = \frac{1}{|G(j\omega)H(j\omega)|} = 20$$

$$\text{G.M. in dB} = 20 \log 20 = 26 \text{ dB}$$

Question 270: Control Systems, Frequency Response Analysis

MCQ

1 Mark

A system with transfer function $\frac{Y(s)}{X(s)} = \frac{s}{s+p}$ has an output $y(t) = \cos(2t - \frac{\pi}{3})$ for the input signal $x(t) = p \cos(2t - \frac{\pi}{2})$. Then, the system parameter p is

(A) $\sqrt{3}$

(B) **(Correct)** $\frac{2}{\sqrt{3}}$

(C) 1

(D) $\frac{\sqrt{3}}{2}$

Correct Answer: (B)

Detailed Solution – Question 270

$$\phi = -\frac{\pi}{3} - \left(-\frac{\pi}{2}\right) = \frac{\pi}{6} = 30^\circ$$

and $\omega = 2\text{rad/s}$

From the transfer function,

$$\phi = 90^\circ - \tan^{-1} \frac{\omega}{p}$$

$$90^\circ - \tan^{-1} \frac{2}{p} = 30^\circ$$

$$\tan^{-1} \frac{2}{p} = 60^\circ$$

$$\frac{2}{p} = \tan 60^\circ = \sqrt{3}$$


$$p = \frac{2}{\sqrt{3}}$$

Question 271: Control Systems, Frequency Response Analysis

MCQ

1 Mark

For the asymptotic Bode magnitude plot shown below, the system transfer function can be



- (A) **(Correct)** $\frac{10s+1}{0.1s+1}$
- (B) $\frac{100s+1}{0.1s+1}$
- (C) $\frac{100s}{10s+1}$
- (D) $\frac{0.1s+1}{10s+1}$

Correct Answer: (A)

Detailed Solution – Question 271

system transfer function,

$$G(s)H(s) = \frac{K(1+\frac{s}{0.1})}{(1+\frac{s}{10})}$$

Here, $20 \log K = 0$

$$\Rightarrow K = 1$$



Therefore, $G(s)H(s) = \frac{10s+1}{0.1s+1}$

Question 272: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The Nyquist plot of a stable transfer function $G(s)$ is shown in the figure are interested in the stability of the closed loop system in the feedback configuration shown.



Which of the following statements is true ?

- (A) $G(s)$ is an all-pass filter
- (B) **(Correct)** $G(s)$ has a zero in the right-half plane
- (C) $G(s)$ is the impedance of a passive network
- (D) $G(s)$ is marginally stable

Correct Answer: (B)

Detailed Solution – Question 272

Nyquist plot will encircle the origin as many number of times as the difference between the number of right side poles and zeros of open loop transfer function.

$$\text{i.e. } N = P - Z$$

From the plot,

$$\begin{aligned} N &= -1 \\ \text{and } P &= 0 \quad (\text{Given}) \\ \therefore Z &= 1 \end{aligned}$$

Thus, one open loop zero in right half of s-Plane

Question 273: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The magnitude of frequency responses of an underdamped second order system is 5 at 0 rad/sec and peaks to $\frac{10}{\sqrt{3}}$ at $5\sqrt{3}$ rad/sec. The transfer function of the system is

- (A) **(Correct)** $\frac{500}{s^2+10s+100}$
- (B) $\frac{375}{s^2+5s+75}$
- (C) $\frac{720}{s^2+12s+144}$
- (D) $\frac{1125}{s^2+5s+225}$

Correct Answer: (A)

Detailed Solution – Question 273

$$\begin{aligned} M_r &= \frac{5}{2\xi\sqrt{1-\xi^2}} = \frac{10}{\sqrt{3}} \\ \text{or } \xi &= \frac{1}{2} \\ \text{Also, } \omega_r &= \omega_n\sqrt{1-2\xi^2} \\ 5\sqrt{2} &= \omega_n\sqrt{1-2\left(\frac{1}{4}\right)} \\ \text{or } \omega_n &= 10\text{rad/sec} \end{aligned}$$

Only option (A) satisfies the conditions.

Question 274: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The frequency response of a linear, time-invariant system is given by $H(f) = \frac{5}{1+j10\pi f}$. The step response of the system is

- (A) $5(1 - e^{-5t})u(t)$
- (B) **(Correct)** $5(1 - e^{-\frac{t}{5}})u(t)$
- (C) $1/5(1 - e^{-5t})u(t)$
- (D) $1/5(1 - e^{-t/5})u(t)$

Correct Answer: (B)

Detailed Solution – Question 274

$$\begin{aligned}
 H(f) &= \frac{5}{1 + j10\pi f} \\
 H(s) &= \frac{5}{1 + 5s} \\
 &= \frac{5}{5(s + \frac{1}{5})} = \frac{1}{s + \frac{1}{5}} \\
 \text{Step response} &= \frac{1}{S} \frac{1}{(s + \frac{1}{5})} \\
 \frac{1}{s} \times \frac{1}{(s + \frac{1}{5})} &= \frac{A}{s} + \frac{B}{s + \frac{1}{5}} \\
 \Rightarrow A \left(s + \frac{1}{5} \right) + Bs &= 1
 \end{aligned}$$

when $s = 0, A = 5$


$$\begin{aligned}
 \text{when } s &= -\frac{1}{5}, B = -5 \\
 Y(s) &= \frac{5}{s} - \frac{5}{s + \frac{1}{5}} \\
 \Rightarrow y(t) &= 5 \left[1 - e^{-t/5} \right] u(t)
 \end{aligned}$$


Question 275: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The asymptotic Bode plot of a transfer function is as shown in the figure. The transfer function $G(s)$ corresponding to this Bode plot is





- (A) $\frac{1}{(s+1)(s+20)}$
 (B) $\frac{1}{s(s+1)(s+20)}$
 (C) $\frac{100}{s(s+1)(s+20)}$
 (D) **(Correct)** $\frac{100}{s(s+1)(1+0.05s)}$

Correct Answer: (D)

Detailed Solution – Question 275

$$G(s) = \frac{K}{s(s+1)(s+20)} = \frac{K/20}{s(1+s)(1+\frac{s}{20})} \text{ Bode plot is in } (1+sT) \text{ form}$$

$$-20 \log \omega + 20 \log K = |60dB|_{\omega=0.1}$$

$$-20 \log 0.1 + 20 \log K = 60dB$$

$$20 \log K = 40dB$$

$$\Rightarrow K = 100$$

$$\therefore G(s) = \frac{100}{s(s+1)(1+0.05s)}$$

Question 276: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The open-loop function of a unity-gain feedback control system is given by $G(s) = \frac{K}{(s+1)(s+2)}$. The gain margin of the system in dB is given by

- (A) 0
 (B) 1
 (C) 20
 (D) **(Correct)** ∞

Correct Answer: (D)

Detailed Solution – Question 276


For 2nd order system G.M. = ∞

Question 277: Control Systems, Frequency Response Analysis

MCQ

1 Mark

In the system shown below, $x(t) = (\sin t)u(t)$. In steady-state, the response $y(t)$ will be



- (A) **(Correct)** $\frac{1}{\sqrt{2}}\sin(t - \frac{\pi}{4})$
- (B) $\frac{1}{\sqrt{2}}\sin(t + \frac{\pi}{4})$
- (C) $\frac{1}{\sqrt{2}}e^{-t}\sin t$
- (D) $\sin t - \cos t$

Correct Answer: (A)

Detailed Solution – Question 277

$$\begin{aligned}y(t) &= x(t) * h(t) \\Y(s) &= X(s) \cdot H(s) \\H(j\omega) &= \frac{1}{s+1} = \frac{1}{\sqrt{2}} \angle -45^\circ \\&= \frac{1}{\sqrt{2}} \angle -\frac{\pi}{4} \\x(t) &= \sin(t)u(t) \\\therefore y(t) &= \frac{1}{\sqrt{2}} \sin\left(t - \frac{\pi}{4}\right)\end{aligned}$$

Question 278: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The Nyquist plot of $G(j\omega) H(j\omega)$ for a closed loop control system, passes through $(-1, j0)$ point in the GH plane. The gain margin of the system in dB is equal to

- (A) infinite
- (B) greater than zero

- (C) less than zero
 (D) **(Correct)** zero

Correct Answer: (D)

Detailed Solution – Question 278

$$G.M = 20 \log \frac{1}{a} \text{dB}$$









$$a = 1 \quad \therefore G \cdot M = 0$$

Question 279: Control Systems, Frequency Response Analysis

MCQ

1 Mark

Which one of the following polar diagrams corresponds to a lag network ?



- (A) A
 (B) B
 (C) C

(D) (Correct) D

Correct Answer: (D)

Detailed Solution – Question 279


Let $\frac{1}{s+1}$ be a lag network At $\omega = 0$, $\text{Mag} = \infty$, $\angle = -\tan^{-1} 0 = 0$ $\omega = \infty$, $\text{Mag} = 0$, $\angle = -\tan^{-1} \infty = -90^\circ$ If in the direction of ω increasing phase shift is decreasing system is lag network.

Question 280: Control Systems, Frequency Response Analysis

MCQ



1 Mark

The polar diagram of a conditionally stable system for open loop gain $K = 1$ is shown in the figure. The open loop transfer function of the system is known to be stable. The closed loop system is stable for



- (A) $K < 5$ and $\frac{1}{2} < K < \frac{1}{8}$
- (B) (Correct) $K < \frac{1}{8}$ and $\frac{1}{2} < K < 5$
- (C) $K < \frac{1}{8}$ and $5 < K$
- (D) $K > \frac{1}{8}$ and $5 > K$

Correct Answer: (B)



System is stable in region -0.2 to -2 & on the left side of -8 as number of encirclement there is zero.

$$0.2K < 1 \Rightarrow K < 5$$

$$2K > 1 \Rightarrow K > 0.5$$

$$\therefore 0.5 < K < 5$$

$$1 > 8K$$

$K < \frac{1}{8}$ (negative sign only shows that it is on negative axis)

Question 281: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The open loop transfer function of a unity feedback is given by $G(s) = \frac{3e^{-2s}}{s(s+2)}$. The gain and phase crossover frequencies in rad/sec are, respectively

- (A) 0.632 and 1.26
- (B) 0.632 and 0.485
- (C) 0.485 and 0.632
- (D) **(Correct)** 1.26 and 0.632

Correct Answer: (D)

Detailed Solution – Question 281

Gain cross over frequency where gain is 1.

$$\begin{aligned}|G(s)| &= 1 \\ \Rightarrow \frac{3}{\omega(\omega^2 + 4)} &= 1 \\ \Rightarrow \frac{9}{\omega^2(\omega^2 + 4)} &= 1 \\ \Rightarrow \omega_g &= 1.26\end{aligned}$$

Phase cross over frequency


$$\begin{aligned}\text{Where } \angle GH &= -180^\circ \\ \Rightarrow \omega_{pc} &= 0.632 \left(\frac{\omega_\phi}{2} = \cot 2\omega_\phi \right)\end{aligned}$$


Question 282: Control Systems, Frequency Response Analysis

MCQ

1 Mark

Consider the Bode magnitude plot shown in the fig. The transfer function $H(s)$ is





- (A) $\frac{(s+10)}{(s+1)(s+100)}$
- (B) $\frac{10(s+10)}{(s+10)(s+100)}$
- (C) **(Correct)** $\frac{10^2(s+1)}{(s+10)(s+100)}$
- (D) $\frac{10^3(s+100)}{(s+1)(s+10)}$

Correct Answer: (C)

Detailed Solution – Question 282

$$\begin{aligned}
 20 \log K &= -20 \text{ dB} \\
 \Rightarrow K &= 10^{-1} = 0.1 \\
 \text{Zero at } \omega &= 1 \text{ \& poles at } \omega = 10, 100 \\
 H(s) &= \frac{K(s+1)}{\left(\frac{s}{10} + 1\right) \left(\frac{s}{100} + 1\right)} \\
 &= \frac{0.1(s+1) \times 10 \times 100}{(s+10)(s+100)} \\
 &= \frac{10^2(s+1)}{(s+10)(s+100)}
 \end{aligned}$$

Question 283: Analog Circuits, Frequency Response of Amplifier

MCQ

1 Mark

A bipolar transistor is operating in the active region with a collector current of 1 mA. Assuming that the β of the transistor is 100 and the thermal voltage (V_T) is 25 mV, the transconductance (g_m) and the input resistance (r_π) of the transistor in the common emitter configuration, are

- (A) $g_m = 25 \text{ mA/V}$ and $r_\pi = 15.625 \text{ k}\Omega$
- (B) $g_m = 40 \text{ mA/V}$ and $r_\pi = 4.0 \text{ k}\Omega$
- (C) $g_m = 25 \text{ mA/V}$ and $r_\pi = 2.5 \text{ k}\Omega$
- (D) **(Correct)** $g_m = 40 \text{ mA/V}$ and $r_\pi = 2.5 \text{ k}\Omega$

Correct Answer: (D)

Detailed Solution – Question 283

$$\begin{aligned}g_m &= \frac{I_C}{V_T} = \frac{1\text{mA}}{25\text{mV}} = 0.04 = 40\text{mA/V} \\h_{fe} &= g_m \cdot r_\pi, h_{fe} = \beta \\r_\pi &= \frac{\beta}{g_m} = \frac{100}{40 \times 10^{-3}} = 2.5\text{k}\Omega\end{aligned}$$

Question 284: Control Systems, Frequency Response Analysis

MCQ

1 Mark

A system has poles at 0.1 Hz, 1 Hz and 80 Hz; zeros at 5 Hz, 100 Hz and 200 Hz. The approximate phase of the system response at 20 Hz is

- (A) **(Correct)** -90°
- (B) 0°
- (C) 90°
- (D) -180°

Correct Answer: (A)

Detailed Solution – Question 284

Pole at 0.01 and 1 Hz gives -180° phase.


Zero at 5 Hz gives $+90^\circ$ phase $\therefore$ at $20\text{Hz} - 90^\circ$ phase shift is provided.


Question 285: Control Systems, Frequency Response Analysis

MCQ

1 Mark

Fig. shows the Nyquist plot of the open-loop transfer function $G(s)H(s)$ of a system. If $G(s)H(s)$ has one right-hand pole, the closed-loop system is





- (A) **(Correct)** always stable
- (B) unstable with one closed-loop right hand pole
- (C) unstable with two closed-loop right hand poles
- (D) unstable with three closed-loop right hand poles

Correct Answer: (A)

Detailed Solution – Question 285

The encirclement of critical point $(-1,0)$ in A.C direction is once.

$$\therefore N = 1, P = 1 \quad (\text{given})$$

$$Z = P - N = 0$$


No zero in RH of s-plane So system is stable.


Question 286: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The approximate Bode magnitude plot of a minimum phase system is shown in Fig. below. The transfer function of the system is





- (A) **(Correct)** $10^8 \frac{(s+0.1)^3}{(s+10)^2(s+100)}$
- (B) $10^7 \frac{(s+0.1)^3}{(s+10)(s+100)}$
- (C) $10^8 \frac{(s+0.1)^2}{(s+10)^2(s+100)}$
- (D) $10^9 \frac{(s+0.1)^2}{(s+10)(s+100)^2}$

Correct Answer: (A)

Detailed Solution – Question 286

$\omega = 0.1$ to 10 , $+120$ dB change $\therefore$ 3 zeroes at 0.1 $\omega = 10$ to 100 , -40 dB [i.e. $+60$ to $+20$] change So two poles at $\omega = 10$ $\omega = 100$, -20 dB change. $\therefore$ one pole at $\omega = 100$ $\therefore T(s) = \frac{K(s+0.1)^3}{(s+10)^2(s+100)}$
 $20 \log(K/\omega)|_{\omega=10} = 140$ $\frac{K}{\omega}|_{\omega=10} = 10^7 \therefore K = 10^8$

Question 287: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The gain margin and the phase margin of feedback system with $G(s)H(s) = \frac{s}{(s+100)^3}$ are

- (A) 0 dB, 0°
- (B) **(Correct)** ∞ , ∞
- (C) ∞ , 0°
- (D) 88.5 dB, ∞

Correct Answer: (B)

Detailed Solution – Question 287

$$G(s)H(s) = \frac{s}{(s+100)^3}$$

Calculating ω_{pc} ,

$$-180^\circ = +90 - 3 \tan^{-1} \frac{\omega_{pc}}{100}$$

$$-270^\circ = -3 \tan^{-1} \frac{\omega_{pc}}{100}$$

$$\text{or, } \omega_{pc} = \infty$$

$$\therefore \text{G.M.} = \infty$$

Hence cannot be determined. Calculating ω_{gc} From, $|G(s)H(s)| = 1$ ω_{gc} = negative value G.M. and P.M. of the system cannot be determined.

Question 288: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The phase margin of a system with the open-loop transfer function $G(s)H(s) = \frac{(1-s)}{(s+1)(s+2)}$ is

- (A) 0°
- (B) 63.4°
- (C) 90°
- (D) **(Correct)** ∞

Correct Answer: (D)

Detailed Solution – Question 288

$$PM = 180^\circ + \angle GH(j\omega)|_{\omega_{gc}}$$

$$\text{For } \omega_{gc}, |G(s)H(s)|_{\omega=\omega_{gc}} = 1$$

$$\left| \frac{1-s}{(1+s)(2+s)} \right| = \frac{\sqrt{1+\omega^2}}{\sqrt{1+\omega^2}\sqrt{4+\omega^2}} = 1$$

$$\sqrt{4+\omega^2} = 1$$

$$\Rightarrow 4 + \omega^2 = 1$$

$$\omega^2 = -3 \text{ (imaginary)}$$

So no gain crossover frequency $\therefore PM = \infty$

Question 289: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The system with the open loop transfer function $G(s)H(s) = \frac{1}{s(s^2+s+1)}$ has a gain margin of

- (A) - 6 dB

(B) (Correct) 0dB

(C) 3.5dB

(D) 6dB

Correct Answer: (B)

Detailed Solution – Question 289

$$G(s)H(s) = \frac{1}{s(s^2+s+1)} \quad \omega \text{ when } \angle G(s)H(s) = -180^\circ$$

$$-180 = -90 - \tan^{-1} \frac{\omega}{1 - \omega^2}$$

$$-90 = -\tan^{-1} \frac{\omega}{1 - \omega^2}$$

$$1 - \omega^2 = 0$$

$$\omega_{ac} = 1 \text{ rad/sec}$$

Value of gain at $\omega_{pc} = 1$

$$|G(s)H(s)| = \frac{1}{\sqrt{(1 - \omega^2)^2 + |j\omega|^2}}$$


$$\therefore G \cdot M = -20 \log 1 = 0$$


Question 290: Control Systems, Frequency Response Analysis

MCQ

1 Mark

The Nyquist plot for the open-loop transfer function $G(s)$ of a unity negative feedback system is shown in figure. If $G(s)$ has no pole in the right half of s-plane, the number of roots of the system characteristic equation in the right half of s-plane is





- (A) **(Correct)** 0
- (B) 1
- (C) 2
- (D) 3

Correct Answer: (A)

Detailed Solution – Question 290

$N = 0$ (1 encirclement in CW direction and other in ACW) $P = 0$ (no pole in right half) So, $N = P - Z$ $Z = P - N = 0$ $\therefore$ No roots on RH of s-plane.

Question 291: Analog Circuits, Frequency Response of Amplifier

MCQ

1 Mark

An npn BJT has $g_m = 38\text{ m A/V}$, $C_\mu = 10^{-14}\text{ F}$, $C_\pi = 4 \times 10^{-13}\text{ F}$ and DC current gain $\beta_0 = 90$. For this transistor f_T and f_β are

- (A) $f_T = 1.64 \times 10^8\text{ HZ}$ and $f_\beta = 1.47 \times 10^{10}\text{ HZ}$
- (B) **(Correct)** $f_T = 1.47 \times 10^{10}\text{ HZ}$ and $f_\beta = 1.64 \times 10^8\text{ HZ}$
- (C) $f_T = 1.33 \times 10^{12}\text{ HZ}$ and $f_\beta = 1.47 \times 10^{10}\text{ HZ}$
- (D) $f_T = 1.47 \times 10^{10}\text{ HZ}$ and $f_\beta = 1.33 \times 10^{12}\text{ HZ}$

Correct Answer: (B)

Detailed Solution – Question 291

$$\begin{aligned}f_T &= \frac{g_m}{2\pi (C_\mu + C_\pi)} \\&= \frac{38 \times 10^{-3}}{2\pi \times (10^{-14} + 4 \times 10^{-13})} \\&= \frac{38 \times 10^{-3}}{2\pi \times 10^{-13}(0.1 + 4)} = 1.47 \times 10^{10} \text{Hz} \\&= \frac{f_T}{\beta_0} = \frac{1.47 \times 10^{10}}{90} \\&= 1.64 \times 10^8 \text{Hz} \qquad (\beta_0 = h_1)\end{aligned}$$