

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Controller
Manufacturer: b+b Automations
Firmware Version: N/A
Model(s): EIB-Mediatechnic-Gateway

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_0_0	1/11/2017	Initial Version

Module Notes

- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

DimmerDiscrete	0 to 100 in steps of 1		
['Maingroup']	'0' – '15'		
['Midgroup']	'0' – '7'		
['Subgroup']	'0' – '255'		
DimmerStep	'Up'	'Down'	'Stop'
['Maingroup']	'0' – '15'		
['Midgroup']	'0' – '7'		
['Subgroup']	'0' – '255'		

Cable and Adapter Requirements:

Captive Screw to Female RS232 DB9 Serial Cable


Notes for the Device:

Serial communication:


Port Type: RS-232
Baud Rate: 38400
Data Bits: 8

Parity: None
Stop Bits: 1
Flow Control: None

Pin Assignments Diagram:



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



General Notes:

Appendix A. Set Commands

Dimmer Discrete 0 Maingroup 0 Midgroup 0 Subgroup 0	0/0/0=0\x0D
Dimmer Discrete 0 Maingroup 15 Midgroup 7 Subgroup 255	15/7/255=0\x0D
Dimmer Discrete 100 Maingroup 0 Midgroup 0 Subgroup 0	0/0/0=100\x0D
Dimmer Discrete 100 Maingroup 15 Midgroup 7 Subgroup 255	15/7/255=100\x0D
Dimmer Step Down Maingroup 0 Midgroup 0 Subgroup 0	0/0/0=1\x0D
Dimmer Step Down Maingroup 15 Midgroup 7 Subgroup 255	15/7/255=1\x0D
Dimmer Step Stop Maingroup 0 Midgroup 0 Subgroup 0	0/0/0=0\x0D
Dimmer Step Stop Maingroup 15 Midgroup 7 Subgroup 255	15/7/255=0\x0D
Dimmer Step Up Maingroup 0 Midgroup 0 Subgroup 0	0/0/0=9\x0D
Dimmer Step Up Maingroup 15 Midgroup 7 Subgroup 255	15/7/255=9\x0D