

Patterns

Functional

-  656,250 received data and 656,250 transmitted data

Stuck at

-  33 patterns (2170 test cycles)

Transition delay

-  37 patterns (2504 test cycles)

Path delay

-  6 patterns (434 test cycles)

RS232-T1700

🔑 Trojan Description

- 🔑 Trojan trigger is a combinational comparator. Trigger input probability is $1.057e-7$ while it is externally controlled. Whenever Trojan gets triggered, its payload gains control over xmit_doneH primary output signal.

🔑 Trojan Taxonomy

- 🔑 Insertion phase: Design
- 🔑 Abstraction level: Layout-level
- 🔑 Activation mechanism: Externally conditionally triggered
- 🔑 Effects: Change functionality
- 🔑 Physical characteristics: Functional

```
NAND4X1 U292 (.A(ena), .B(iXMIT_state_0_), .C(iXMIT_state_1_), .D(iXMIT_state_2_), .Y(iXMIT_state_CTRL));
NAND4X1 U293 (.A(ena), .B(iXMIT_N45), .C(iXMIT_N44), .D(iXMIT_N29), .Y(iXMIT_N_CTRL_1_));
NAND4X1 U294 (.A(ena), .B(iXMIT_N27), .C(iXMIT_N26), .D(iXMIT_N25), .Y(iXMIT_N_CTRL_2_));
NAND4X1 U295 (.A(ena), .B(iXMIT_xmit_ShiftRegH_7_), .C(iXMIT_xmit_ShiftRegH_6_), .D(iXMIT_xmit_ShiftRegH_5_), .Y(iXMIT_xmit_CTRL));
OR4X1 U296 (.A(iXMIT_state_CTRL), .B(iXMIT_N_CTRL_1_), .C(iXMIT_N_CTRL_2_), .D(iXMIT_xmit_CTRL), .Y(iXMIT_CTRL));
NAND4X1 U297 (.A(ena), .B(iRECEIVER_state_0_), .C(iRECEIVER_state_1_), .D(iRECEIVER_state_2_), .Y(iRECEIVER_state_CTRL));
OR2X1 U302 (.A(iXMIT_CTRL), .B(iRECEIVER_state_CTRL), .Y(iCTRL));
AND2X1 U303 (.A(iCTRL), .B(xmit_doneH_temp), .Y(xmit_doneH));
```

RS232-T1700

Functional

Trojan activation probability	The number of Transmitted	The number of Received	Trojan activation	Payload Change	Simulation Length (No. Clock)	Length of each Receive/Transmission
1.057e-7	656 250	656 250	1	0	168 000 000	256/256

Structural

Circuit activity in Trojan-free	Circuit activity in Trojan-inserted	Trojan inputs activity	Activity inTrojan circuit	Trojan Triggered	Payloadchanged	Stuck-at unmatched
67 200	68 403	5 797	3	0	400	0

Transition delay

Circuit activity in Trojan-free	Circuit activity in Trojan-inserted	Trojan inputs activity	Activity inTrojan circuit	Trojan Triggered	Payloadchanged	Transition unmatched
87 811	89 267	7 713	4	0	484	0

Path delay

Circuit activity in Trojan-free	Circuit activity in Trojan-inserted	Trojan inputs activity	Activity inTrojan circuit	Trojan Triggered	Payloadchanged	Transition unmatched
34 573	35 145	3 379	2	0	190	0