



Semester: July 2023 – Oct 2023		
Maximum Marks: 30 M	Examination: In-Semester Examination	Duration :1 Hr. 15 Min.
Programme code:01 Programme: B.Tech Computer Engineering	Class: FY/SY/TY/LY /MTECH	Semester: I/II/III/IV/V/VI/VII/VIII (SVU 2020)
Name of the Constituent College: K. J. Somaiya College of Engineering	Name of the department: COMP/ETRX/EXTC/IT/MECH	
Course Code: 116U01C502	Name of the Course:Computer Network	

Question No.		Max. Marks	CO Mapped	BT Level
Q1	Answer any TWO (5M each) - Compare between Connectionless and Connection Oriented Services - Compare between Switch and Router - Explain TCP/IP Model with the help of a suitable diagram.	10M	CO1	RE
Q2	A. Solve any ONE - A Eleven-bit Hamming code is received as 11111010110. Identify parity bit positions and values in the code. What is the corrected code? Assume Even Parity is used. - Calculate the Checksum stepwise for the following Dataword (in Hexadecimal) and generate the codeword FF23 2389 E3BA 1125 B. Explain the following scenarios for Selective Repeat ARQ with the help of a properly labeled flow diagram. Assume maximum possible sender and receiver window size with Sequence Number size is 3 Bits long. - What will be the sequence no and window size at transmitter and receiver end. - Sketch initial sender and receiver window. - Frame 0 and 1 are transmitted and ACK are received. - Frame 2 frame transmitted but ACK is lost. - Frame 3 and 4 are sent but frame 3 is lost.	5M	CO2	UN, AP
Q3	Identify the Class, Network Address and Broadcast address of the block to which following addresses belongs to: 181.18.81.8 221.21.21.12 /22	5M	CO3	AP

Details for your reference

Details for your reference

RE (Remember), UN (Understand), AP (Apply), AN (Analysis), EV (Evaluate) and CR (Create)