

Repositories

 EAIT source

info

Search this repository...



helpdesk

teamproject/2026s1_spec

<> Code

 Commits

 Branches

 Tags

 Search

 **Tree: f52e802** ▾

[teamproject/2026s1_spec](#)
/ [generated](#) / spec_engg3800.md

Update datasheets for both plug and socket of the terminal connector

Jeremy Herbert committed **f52e802** at 2026-03-13 19:59:14

spec_engg3800.md

 **Blame**

 **History**

 **Raw**

Power Meter

Team Project specification 2026, semester 1

Generated date: 2026-03-13 19:58:47

Course: **ENGG3800**

Notes:

- For the purposes of this document, we consider "code" or "software" to refer to programs which runs on a PC and/or on an embedded system.
- This document uses the words "should", "must" and so on interchangeably to indicate a requirement of particular

functionality. The use of "should" does not imply that functionality is optional.

- While we try our best to allow students to have the freedom to make their own design choices, it is not possible for the teaching staff to support every possible development system.
- This specification is a living document! Changes will occur and will be released throughout the semester. Some minor clarifications may appear on the discussion board only. You are expected to keep up to date with these.
- All assessment must only use PCBs which were ordered from ETSG (via [pinecone](#)). Please see the course profile for details.
- There are a number of grade hurdle requirements outlined in the course profile - please make sure you read these *carefully*.
- You must follow all other requirements outlined in the [TP-STD standards](#), otherwise your final product mark will be limited to a maximum of 50%.
- All assessment must only use parts from the approved suppliers! See TP-STD-003.
- You must individually commit to git in four weeks of the semester. See TP-STD-004 and Blackboard for further details.
- Did we mention that you should read the TP-STD documents? If you don't meet these requirements (as applicable), you will be limited to a maximum of 50% of the total marks available for the final demo.
- It is up to you to determine which parts are appropriate for your design (except where specific parts are required by this specification or the TP-STD documents). Not all parts available at ETSG will be suitable for use in your project, and some may appear to be useful while in reality not actually being useful at all. You should not expect ETSG to stock all parts needed to complete your design.
- We do not provide the final marksheet early in the semester, because we want you to read and digest the requirements in textual form (this is a learning outcome of this course). For this reason, the final marksheet will be

made available to you in approximately Week 6 or 7 of the semester.

- Unless stated otherwise, all AC measurements are provided as and expected as Root Mean Square (RMS) form.

Introduction and background

The goal of this project is to build a portable AC and DC power meter. The device is intended to measure AC (single phase) or DC power as well as a number of other metrics. The device must be able to display these metrics in real time and report the information to other devices.

Examples of commercially available power meters

- Power meters that plug into a single phase outlet: [1](#), [2](#), [3](#)
- [Panel mount power meter](#)
- DIN rail mounted power meters: [1](#), [2](#), [3](#)
- [Meter box power meter](#)

Device details

Physical user interface

The device contains a 128x64 pixel LCD module (ETSG part 24-05-03) for showing information to the user. The backlight of the display must be adjustable by the user to exactly 5 levels, where the lowest level turns the backlight totally off, and the highest level turns the backlight fully on.

You are permitted to have up to 6 momentary push buttons to allow the user to control the functions of the device. You may optionally use a multi-position momentary joystick-like switch as some of these buttons (for example, Digikey part EG4561-ND). You may optionally use a single rotary encoder in addition to these buttons.

Your device must contain a toggle/sliding power switch which totally disconnects the power supply from the device; this switch must be on the PCB itself and not external (on a cable, etc). In addition to this, your device must have a red power LED which is always on when power is supplied to the device.

Your device must have an LED (that is not red) which blinks every time a new measurement is completed.

In addition to the LEDs described in this specification, you may have additional LEDs for debugging purposes but these must be disabled or removed for the final demonstration.

Your device must operate normally if there is no connection to the PC.

DC measurement

Your device is required to measure and compute a number of DC-related measurements:

1. DC voltage (in V)
2. DC current (in A)
3. DC power (in W)

To measure DC power, all current for the device under test will be passed into **DC Current Input** and then out of **DC Current Output** (which will also be connected to GND). For voltage measurement purposes, the GND of the DC system also will be connected to **DC GND**. Note that the DC current may be negative if the current flows from **DC Current Output** to **DC Current Input** - you should consider this case in your design. A diagram of the connections is available along with this specification ([images/DC_Power_Measurement.svg](#)).

The largest voltage that will be applied to your device is +/- 10V DC. The largest current that will be sent through your device is +/- 2.2A. However, we only expect your device to be able to measure over +/- 9V and +/- 2A respectively.

Measurements must be completed at a rate of 1Hz or faster.

AC measurement

Your device is required to measure and compute a number of AC-related measurements:

1. AC voltage (in V)
2. AC current (in A)
3. AC frequency (in Hz)
4. AC phase difference between voltage and current waveform (in degrees)
5. AC real power (in W)
6. AC reactive power (in VAR)
7. AC apparent power (in VA)
8. AC power factor (unitless, between 0 and 1)
9. AC peak-to-peak voltage (in V, not RMS)
10. AC peak-to-peak current (in A, not RMS)
11. Total Harmonic Distortion (THD) of voltage (in %)
12. THD of current (in %)

For the purposes of calculating items 1-8 above (inclusive), you may assume that the waveform is sinusoidal. However, it is nonetheless possible that non-sinusoidal waveforms will be present on the input of your device. Although the measurements will not be correct for items 1-8 in this case, your device must not be damaged by this scenario and must continue to operate normally.

When performing AC measurements, it is possible that if the waveforms are small (or zero), it will not be possible to accurately calculate some measurements based on phase (for example, power factor). In this case, your device should show "UL" (Under Limit) to indicate that it isn't possible to calculate these quantities accurately.

For safety reasons, your device will operate through a provided transformer interface box that connects to 240V AC. This box contains a [Clamp or Current Transformer \(CT\)](#) that can be used to measure current, and a step-down transformer to reduce the voltage to a safe level (<20V AC). In a commercial device, this interface box would likely be integrated into the product itself.

The secondary side of [the step-down transformer](#) will be connected to **AC Input 1** and **AC Input 2** on the test harness, and [the CT](#) will be connected to **CT Input 1** and **CT Input 2**.

This means that in order to display to the user the actual voltage measurement, it will need to be multiplied by a user-configurable scaling factor (which is the turns ratio of the step-down transformer, N).

A diagram of the connections is available along with this specification ([images/AC_Power_Measurement.svg](#)).

The maximum voltage range that will be applied to the AC voltage input (ie after the step-down transformer) on your device is $\pm 10\text{V}$ (though closer to $\pm 9\text{V}$ is more likely to be what the device sees in almost all circumstances). The maximum AC current that will be monitored by the current clamp is $10\text{A} \pm 1\text{A}$ (though due to the [burden resistor](#) integrated into the clamp, this will be presented to your device as $\pm 1\text{V}$).

The intended AC frequency range applied to the input of the device will be between 20Hz and 100Hz . However, this frequency range only refers to the fundamental frequency of the waveform - you are expected to be able to monitor higher harmonics up to and including 500Hz . Your device does not need to report accurate measurements if the frequency is beyond this range, but it must not be damaged.

Your device must have both a hardware low and high current measurement range to allow more accurate measurement of current. In the low current range, the Full Scale Range (FSR) of the current input must be 0 to 1A , and in the high current range it must be 0A to 10A . The device must automatically switch between these ranges depending on the input from the CT without any user intervention. Your device must have a user interface item which indicates the range that the device is in (LED, icon on LCD, etc).

Measurements must be completed at a rate of 1Hz or faster.

If the input signal changes such that the current range needs to also change (ie, previous sample it was 0.5A , next sample it will be 2.5A), it is acceptable if there is a glitch/dropped measurement for a single measurement cycle as the range adjustment is performed.

LCD module interface

The display must have a measurement screen that is able to show any four of the measurements outlined above. There must be a mechanism for the user to choose which of these items to show and in which order, and it must be possible to adjust the system to view any combination of four items using the on-device controls only. The selected items must be stored in non-volatile memory; when input power is disconnected and reconnected to the device, the measurement configuration must remain the same.

Note that any combination of items may be visible on the display - your device must be able to measure/compute them all at the same time.

Each of these measurements should have a maximum error of $\pm 2.5\%$ (of the full input range) and be displayed to a minimum of two decimal places.

There must be a settings screen that allows the user to enter the transformer turns ratio (step-down ratio) for use in calculating the AC measurements. The user must be able to enter a 5 digit value (2 digits before the decimal place, and 3 digits after).

SD card logging

There must be a method for using the on-device interface to start or stop logging of all measurements (except the frequency spectra) to a microSD card. Each time that recording is started, a new log file should be created on the SD card filesystem. Data should be logged in CSV format such that it is visible in a spreadsheet editor (ie, Microsoft Excel), but the exact format is left undefined.

Power measurement interface

To connect to the sensor inputs, a 5.08mm pluggable screw terminal interface will be used (socket ETSG part will be provided soon, datasheet is [here](#)) as a connection/test harness. The pinout of this harness is as follows:

1. AC CT Input 1
2. AC CT Input 2
3. AC Voltage Input 1
4. AC Voltage Input 2
5. DC Current Input
6. DC Current Output
7. DC Voltage Input
8. DC Voltage GND

During the final demonstration, you will be provided with the pluggable block with these signals already connected.

The pin numbering for this connector can be found along with this specification ([images/screw_terminal_pinout.jpeg](#)).

PC communication

Your device must use the [polyglot-turtle-xiao](#) firmware with a Seeeduino Xiao (ETSG part 24-01-01), or alternatively a direct USB connection to an MCU, as the only means of wired communication with the PC.

In addition to this, your device must be able to communicate with the PC [via WiFi](#) using the [MQTT protocol](#). To do this, you must use an ESP32-C3 module running the [ESP-AT firmware](#) (ETSG part 26-04-01 - note that these modules are pre-flashed with the firmware, but modules purchased from an outside distributor are not).

Any communication must be possible over both USB and the WiFi interface.

The device needs to have a mechanism to select which of these interfaces is being used for communication to the PC software, and then only the selected interface should be used. It is acceptable if the device does some connection setup on both interfaces, as long as it is not directly communicating with the software (for example, connecting the WiFi module to the network and to the MQTT server, even if the USB interface is the selected one.)

No other form of communication with the PC is permitted.
When the device is connected to your PC software, the LCD

module must show a pictographic icon which is descriptive of this connection (for example, a USB logo). An icon should not be visible if there is no connection to the PC software.

Power supply

Your device must be powered entirely using a 3.7V nominal LiPo battery (ETSG part 28-11-05, uses a 2 pin JST PH connector). Your device must also integrate a charging circuit such that this battery can be charged over the USB interface. For the final submission, you will be required to include a cable which can be used with the battery simulator in the lab to simulate this battery (2 pin JST PH to bare wires is OK).

You must include a battery charging LED that indicates whether the battery is charging or not.

You may optionally power your device from the USB connection while the device is charging the battery - but your device must not rely on the USB cable being connected for the device to function.

There is no strict battery lifetime requirement other than that the battery must be able to last on a single charge for the entire final demo (approx 1hr). It must be possible to charge the battery while the device is being used.

Your device can only have a single USB port.

Real time clock

The device must have a real-time clock (RTC) to keep track of the date and time even when the device is not connected to a source of power. The time and date must always be visible on the LCD module, even if the time has not yet been set.

When the main battery is removed, the RTC is to be powered by a super capacitor. Note that this should not power the rest of the circuit when the device is not connected to a source of power, ie it should only power the RTC. It is acceptable if the RTC is powered by other sources of energy when available, and the super capacitor is used as a final backup.

You must include 2.54mm pin headers (with jumpers as necessary) to allow us to measure the voltage of the supercapacitor, as well as the current in to/out of the supercapacitor.

PC software

The PC software must be able to view all measurements that the device is performing (even those which are not visible on the LCD) in textual form and these should update live while the device remains connected. The user must also be able to select a single measurement (of the possible measurements) to be plotted live on a graph - the graph should have the measurement quantity on the Y axis, and the current time on the X axis (based on the RTC time, not the PC time). The update rate should be approximately as fast as the measurement rate on the device.

There must be controls to choose the number of points to be plotted (in the range of 10-3600), and once the number of points is reached, the oldest point is discarded when plotting a new one.

All measurements must be recorded in the background so that when the user selects a different measurement, the graph can show the most recent points.

There must be a button to send the current PC time to the device; the device should store this in the RTC if received.

The software must also display the frequency spectra being measured on two additional, separate plots (one for voltage spectrum, one for current spectrum) that can be hidden. The frequency spectrum must be computed with a non-interpolated resolution of at least 1Hz (ie 500 frequency bins per plot or higher).

The user must be able to select whether the communication that is being used is WiFi or USB.

Replay mode

Similar to the above, the software must be able to open a recording file from the microSD card and display the most recent points in the same format as the live view. The software does not need to literally replay them live (ie, at a rate of 1Hz), it just needs to show the final state with the most recent points up to the maximum number of points visible.

In the replay mode, the frequency spectra views should be disabled/hidden.

The normal mode and replay mode are mutually exclusive in terms of their visibility. Although it should be easy to change between them, they cannot be used by the user simultaneously.

Construction and physical dimensions

Your final product must be constructed using one or more custom designed PCBs. All components (display, buttons, batteries, etc) must be mounted on or to the PCB - no other mounting frames (3D printed, laser cut, etc) are permitted.

Submitting your product using any breadboards will result in your maximum mark for the final demo being limited to 50%. Please be aware that PCB submissions are only possible to [pinecone](#) up until the end of week 10, and you cannot use PCBs from other sources as part of your submission. As such, **you must submit a final PCB design (if you intend to submit with a PCB) to pinecone by the end of week 10** - no extensions of this manufacturing date are possible because it would impact the delivery of PCBs to other teams.

The following breakout boards are approved for use without triggering the grade hurdles outlined in the course profile:

- Seeeduino Xiao (running the polyglot-turtle-xiao firmware only)
- The display module mentioned previously
- The ETSG ESP32-C3 breakout board

Budget/Bill Of Materials (BOM)

Your final product must have a BOM total of \$150 AUD or less (excluding GST). Your team will have a \$200 AUD development budget available at ETSG; you can spend your ETSG development budget in one of three ways:

1. At the [ETSG store](#) (on campus in 50-S309), see also [How to use the ETSG store](#)
2. Using [pinecone](#) to order PCBs
3. Using [hazelnut](#) to order parts from [DigiKey](#)

Alternatively, you can order directly from any of the approved suppliers in the TP-STD documents (or a non-approved supplier as long as an equivalent part is available at an approved supplier), but **reimbursement will not be possible**.

You do not need to include the cost of the microSD card or USB cable in your BOM, but you must still provide them with your submission.

In your submission, you need to provide a suitable USB to microSD card reader that has been tested with your microSD card for the final demo (it will be returned to you after the demo). You do not need to include this in your BOM and it does not need to come from an approved supplier.

Any screws or mounting hardware that you have chosen for your product must be included in the BOM.

Components included in your locker

- The display module mentioned previously
- A Seeeduino Xiao to be used with the [polyglot-turtle](#) firmware.
- Various jumper wires
- STM32L432 Nucleo development board (ETSG part 28-11-04): <https://www.st.com/en/evaluation-tools/nucleo-l432kc.html>

Out of scope

The following items will not be tested deliberately during marking, but they may happen by accident in normal operation.

You should have a sensible way of dealing with these problems.

- Corrupted microSD cards
- Removing/inserting the microSD card while the device is powered on
- Attempting to use the device while the battery is unplugged

Other notes and recommendations

The following are not necessarily requirements for the project, rather they are hints and tips that may make things go more smoothly for you.

- You should be powering your MCU with 3.3V (or lower).
- You should search and peruse tp-info for further information on these topics.
- The mating terminal connector we will provide can be seen [here](#).
- Limiting the charging and discharging current of the supercapacitor may be desirable.

© 2012 - 2026 Powered by [GitList.org](https://gitlist.org)