



TUN and TUP

4.4 TUN AND TUP

MIKROELEKTRONIKA

As we previously said, many electronic devices work perfectly even if the transistor is replaced with a similar device. Because of this, many magazines use the identification TUN and TUP in their schematics. These are general purpose transistors. TUN identifies a general purpose NPN transistor, and TUP is a general purpose PNP transistor.

TUN = Transistor Universal NPN and TUP = Transistor Universal PNP.

These transistors have following characteristics:

U_{CEmax}	20V
I_{Cmax}	100mA
h_{FEmin}	110
P_{Cmax}	100mW
f_{Tmin}	100MHz

Some of the TUNs are:

BC107(8,9)	BC147(8,9)	BC207(8,9)
BC237(8,9)	BC317(8,9)	BC347(8,9)
BC547(8,9)	BC171(2,3)	BC182(3,4)
BC382(3,4)	BC437(8,9)	2N3856A
2N385	2N3860	2N3904
2N3947	2N4124	etc.

Some of the TUPs are:

BC157(8,9)	BC177(8,9)	BC204(5,6)
BC212(3,4)	BC251(2,3)	BC261(2,3)
BC307(8,9)	BC320(1,2)	BC350(1,2)
BC512(3,4)	BC557(8,9)	BC416
2N2412	2N3251	2N3906
2N4126	2N4291	etc.



4.4 TUN and TUP by MikroElektronika is licensed under a Creative Commons Attribution 4.0 International License, except where otherwise noted.

