
simple_earring — generated schematic


138 components / 87 nets / 4-layer JLCPCB stackup. Power rails (GND, 3V3, VBATT, VSYS, VLED, VBUS, VDD_CORE) are power symbols; only cross-block signals use global labels. Generated from scripts/circuit.py — do not hand-edit; rebuild with `python3 build.py --only schematic`.

USB-C receptacle / ESD / series R




J1 is a TYPE-C-31-M-12 right-angle receptacle. VBUS is charge-only: there is no VBUS->3V3 path, the MCU always runs from the cell.

3V3 LDO — EN = slide switch OR USB (diode-OR, clamped)




USB wake — VBUS feeds EN through R18




Rev 2: USB boots the board even with SW2 off. Against R17's pulldown EN sits at ~VBUS/2, and D2's second diode clamps it to VBATT+Vf (NCP730 abs max V_EN is VIN+0.3, even during precharge of a dead cell). Firmware then sees SW_ON=0 on the sense divider and shows charge status instead of running the show.


RUN / SWD



RP2350A




MCU decoupling — 100n on the 3V3 supply pins




IOVDD 38 and 1 share with C3/C4 — C5/C6 went to the core rail (see the regulator block)

QSPI flash (BOOTSEL strap on /CS)




Pico-style: QSPI_SS is both the flash /CS and the BOOTSEL strap.

IMU — LSM6DS3TR-C on I2C1 (addr 0x6A)




CS/SDx/SCx -> VDDIO selects I2C mode 1 and idles the aux master; SDO/SA0 -> GND sets address 0x6A.

USB cable present — 10k:10k tap on VBUS -> ADC1




CHRG and DONE both release at termination, so they cannot tell 'unplugged' from 'plugged in and full'. 10k:10k, not the 100k/1M used elsewhere: PWR_EN backfeeds through R18 and would float this node high, so the tap has to be stiff enough to swamp it (0.33V no cable, 2.2–2.75V with one). That is also what holds Q2's gate low enough to keep the battery path on.

VLED high-side load switch (LEDs draw zero when off)




R10 holds the switch off until firmware drives LED_EN high.

Li-ion charger (LGS4056H, ~41mA) + RJD2032C1 cell




CHRG / DONE are open-drain -> GPIO with internal pull-up (low = active); software owns the charge indicator.

Switch / battery sense -> ADC




1M:1M divider off SW_ON, the switch common (rev 2 — was VBATT). Switch ON: VBAT/2 battery telemetry as before. Switch OFF + USB: reads 0, telling firmware to show charge status instead of running the show. GPIO29/ADC3.

Ambient light sensor -> ADC0 (rev 2)




ALS-PT19 visible-light phototransistor; 22k load -> ~0.33V @ 100 lux, saturates ~900 lux. Reads on GPIO26/ADC0.

12MHz crystal




ABM8-272-T3. CL 10pF / ESR<=50R — the 15p caps and R1 are matched to it; do not retune.

power path — VBUS runs the board when a cable is in




Rev 2: VBATT is the cell alone, VSYS runs the board, so the charger's whole 41mA reaches the cell in either switch position. Q2's SOURCE is VSYS and its drain VBATT — a P-FET body diode conducts drain->source, so that way round it blocks USB from back-feeding the cell past the charger.

RP2350 core buck regulator (ds §6.3.8)




L1 dot on the VOUT (pad 1) side — ds Fig 23. C11 CIN: C12 COUT at L1: C13 the 2nd 4u7 at DVDD 23 (§6.3.8.1). C5/C6 are the 100n pair §6.1.3 wants on the two DVDD pins nearest the regulator — they already sat there, netted to 3V3. R13+C22 filter VREG_AVDD.

LED ring bypass — 100n VLED-GND, one per two LEDs




C30..C74, distributed around the ring next to their LEDs

Addressable LED ring — 45 x SK6805-EC10 daisy chain



Chain runs LED1 -> LED45 in board order; each row break carries on through LED_D<n>. VLED is the switched battery rail, so the ring is dark until LED_EN goes high.

LED data level shifter — open-drain into the ring



The ring's VIH is 0.7*VLED. On the cell that peaked at 2.94V and the MCU drove pixel 1 directly; on VSYS it is 3.29V (3.5V at a 5.25V port), past anything a 3.3V pad can output. Q3 inverts into R23's pull-up, so the swing is a full VLED rail whatever VLED is — 3.0V cell or 5.0V cable. Only pixel 1 needs it: every DI after that is driven by the previous DO. Firmware must set gpio_set_outover(LED_DATA, GPIO_OVERRIDE_INVERT) — the pad override sits after the PIO, so the NeoPixel program is untouched.