

Module 1 - Front-End Web Development

HTML/CSS Exercise

Overview

Master CSS Grid and Flexbox by creating a dynamic image gallery with filtering capabilities and responsive layout.

Instructions:

1. Create two files:

- gallery.html
- style.css

2. HTML Requirements:

- Create a gallery page with:
 - Filter buttons (Landscapes, Portraits, Architecture)
 - Image grid with at least 12 images
 - Image cards containing:
 - Image
 - Title
 - Category tag
 - Overlay with description

3. CSS Requirements:

- Layout:
 - Use Grid for main gallery layout
 - Use Flexbox for filter buttons
 - Use Grid for card layouts
- Responsive Design:
 - Desktop: 4 columns
 - Tablet: 2 columns
 - Mobile: 1 column
- Interactive Elements:
 - Hover effects on cards
 - Active states for filter buttons
 - Smooth transitions between layouts

4. Add CSS transitions for filtering animations

Submission:

After completing your code, upload your files to the LMS. Display the webpage in your browser and demonstrate your working solution to your lecturer for review.