

Triac Triggers (Diacs) by American Microsemiconductor:

The ST2 (diac) is a silicon bi-directional diode which may be used for triggering triacs or SCR's.

The ST4 is an asymmetrical AC trigger integrated circuit for use in triac phase control applications.

AMS Type	V_{s2} Switching Voltage		V_{s1} Switching Voltage		I_{s2}, I_{s1} Switching Current Max. (μA)	Pulse Output Min. (V)
	Min. (V)	Max. (V)	Min. (V)	Max. (V)		
ST2	28	36	28	36	200	3.0
ST4	7	9	14	18	80	3.5