

BANGLADESH UNIVERSITY OF ENGINEERING AND TECHNOLOGY

CSE 321: Computer Networks

Time: 25 minutes

Class Test – 3

Total: 20 Marks

Name: _____

Student ID: _____

Question 1

10 Marks

Consider a generator polynomial $G = 11011$ that has been selected for some CRC calculation. Now answer the following:

- (a) Why can G be used to detect any single bit error?
- (b) What length of burst error can G detect? Justify your answer.

Answer:

Question 2

10 Marks

Station A needs to send a message consisting of 9 frames to Station B using Go-Back-N protocol with a window size of 3. All frames are ready and immediately available for transmission. If every 5th frame that A transmits gets lost (but no ACKs from B ever get lost), then what is the number of frames that A will transmit for sending the message to B? Show necessary simulation/calculation.

Answer: