COMPUTER SCIENCE & ENTREPRENEURSHIP 9

UNIT 2: SYSTEM DESIGN & TROUBLESHOOTING (COMPLETE NOTES)

Topic 1: Digital Systems & Types of Signals

Question 1: What are digital systems?

Digital systems are the foundational building blocks of modern electronics, processing all information by converting it into binary form consisting of 0s and 1s. They are widely used in computers, mobile phones, and advanced digital devices.

Question 2: Define analog signal and give examples. Give details.

An analog signal is a continuous wave where electrical values change smoothly over time, taking any value within a specific range. Common examples include human voice sound waves, temperature variations, and radio transmission signals.

Question 3: What is a digital signal?

A digital signal is a discrete electrical or optical pulse that represents information using two distinct binary states (0 and 1). These signals are vital in modern computing for precise and error-free data processing.

Question 4: What is the main difference between analog and digital signals?

The fundamental difference is that analog signals are continuous with infinite possible values, whereas digital signals are discrete and strictly limited to two binary states (0 or 1), making them reliable for computers.

Question 5: What is the function of an Analog-to-Digital Converter (ADC)?

An ADC is an essential electronic circuit that takes continuous real-world analog signals (such as microphone voice inputs) and converts them into digital binary code so that microprocessors can process them.

Question 6: What is the function of a Digital-to-Analog Converter (DAC)?

A DAC is a converter that transforms processed digital binary data back into continuous analog waveforms, enabling humans to perceive information through senses, such as hearing audio via speakers.

Question 7: Why are ADC and DAC converters needed?

Since physical environment information like sound, light, and temperature exists purely in analog form while computers understand only binary digits, converters are required to bridge this communication gap.

Question 8: How does the ADC and DAC process work in microphones and speakers?

When speaking, a microphone converts sound waves from analog to digital via ADC; the CPU processes the data, and DAC converts the binary results back into audible sound waves through the speaker.

Question 9: Define Boolean Algebra.

Boolean algebra is a specialized branch of mathematical logic where variables can only take two truth values: True (represented by 1) and False (represented by 0). It forms the mathematical foundation of digital circuits.

Question 10: What are Boolean functions and expressions?

Boolean functions are mathematical expressions that define logical relationships between binary variables using operators like AND, OR, and NOT, describing the exact operational behavior of logic circuits.

Question 11: What are binary variables and logic operations?

Binary variables are logical quantities that can hold only two states (0 or 1). Logic operations refer to the fundamental mathematical manipulations performed on these variables, such as conjunction, disjunction, and negation.

Topic 2: Boolean Algebra, Logic Operators & Gates

Question 12: Define AND operator and build its truth table.

The AND operator is a basic logical operator that produces a True (1) output only when all of its inputs are simultaneously True (1). Otherwise, the output is False (0).

AND Truth Table:

A	B	A AND B
0	0	0
0	1	0
1	0	0
1	1	1

Question 13: Define OR operator and build its truth table.

The OR operator is a logical operator that yields a True (1) output if at least one of its input signals is True (1). The output is 0 only when all inputs are 0.

OR Truth Table:

A	B	A OR B
0	0	0
0	1	1
1	0	1
1	1	1

Question 14: Define NOT operator and build its truth table.

The NOT operator (inverter) reverses the logical state of its input; if input is 1, output is 0, and if input is 0, output is 1. Its mathematical notation is A'.

NOT Truth Table:

A	NOT A (A')
0	1
1	0

Question 15: What are Logic Gates and name their primary types?

Logic gates are electronic circuits built on Boolean principles acting as core building blocks of digital hardware. Their main types include AND gate, OR gate, NOT gate, NAND gate, and XOR gate.

Question 16: What is an AND gate? Explain its symbol and function.

An AND gate is a logic circuit taking multiple inputs and producing a high output (1) only when all inputs are high. Its graphical symbol resembles a capital letter 'D' with inputs on the flat side.

Question 17: Explain the symbol and working mechanism of an OR gate.

An OR gate is a logic gate that outputs a high signal (1) if any of its input terminals receive a high signal. Its schematic symbol is characterized by a curved input edge and pointed output.

Question 18: Describe the schematic symbol and utility of a NOT gate.

A NOT gate is a single-input digital circuit that inverts the signal. Its symbol is a triangle pointing forward with a small inversion bubble at the output tip.

Question 19: Define a NAND gate and illustrate its schematic structure.

An NAND gate is a combination of an AND gate followed by a NOT gate. The inversion bubble at the output of an AND gate creates NAND, producing inverted outcomes of standard AND.

Question 20: What is the unique characteristic of an XOR gate?

An XOR (Exclusive-OR) gate produces a True output only when its inputs are unequal (one is 0 and the other is 1). If inputs are identical, its output is strictly 0.

Question 21: What is the meaning of 1 + 1 in binary logic?

In binary logic, 1 + 1 does not mean arithmetic addition equaling 2; rather, it represents Boolean OR logic where having one or both inputs high results in a constant high output of 1.

Question 22: What does the construction of a Boolean function involve?

Construction of a Boolean function involves taking logical specifications or truth tables and implementing them into physical electronic circuits using combinations of logic gates.

Topic 3: Solving Boolean Expressions and Laws

Question 23: What does simplifying a Boolean function mean?

Simplifying a Boolean function means reducing a complex logic expression to its minimal form using algebraic laws, resulting in cheaper, smaller, and faster digital circuits.

Question 24: Write the names of fundamental laws of Boolean algebra.

The fundamental laws of Boolean algebra include Identity Laws, Null Laws, Idempotent Laws, and Commutative Laws, which govern logical variable manipulations.

Question 25: State the remaining important Boolean laws.

Other crucial laws include Associative Laws, Distributive Laws, Absorption Laws, and De Morgan's Theorems, essential for circuit optimization.

Question 26: Why is simplification of Boolean functions necessary?

Complex circuits require more components, consume more power, and cost more. Simplification minimizes gate count, reduces cost, and optimizes overall processing speed.

Question 27: Example 1: Simplify the expression A + A.B.

Answer solution:
$A + A.B = A(1 + B)$ (Distributive Law)
$= A.1 = A$ (Applying Null and Identity laws yields final output A).

Question 28: Example 2: Simplify the expression (A + B).(A + B').

Answer solution:
$(A + B).(A + B') = A + B.B'$ (Distributive Law)
$= A + 0 = A$ (Since B.B' equals 0 by Complement Law).

Question 29: Example 3: Simplify the expression A + B.A.

Answer solution:
$A + B.A = A(1 + B) = A.1 = A$
(Solved via Absorption Law, yielding final simplified output A).

Question 30: Example 4: Simplify the expression (A + B).(A' + B).

Answer solution:
$(A + B).(A' + B) = A.A' + B$
$= 0 + B = B$
(Simplified using distributive and complement rules to get final output B).

Question 31: What is a logic diagram?

A logic diagram is a graphical schematic representing a Boolean expression using standard logic gate symbols to display circuit interconnections.

Question 32: What is the benefit of analyzing or building a logic diagram?

Analyzing logic diagrams helps engineers understand circuit operation principles, trace wiring faults, verify logic accuracy, and enhance hardware efficiency.

Topic 4: System Troubleshooting & Hardware Issues

Question 33: What is System Troubleshooting?

Troubleshooting is a systematic logical process of identifying hardware or software faults in computing systems, diagnosing root causes, and implementing effective corrective solutions.

Question 34: How many and what are the key steps of troubleshooting?

There are 6 key sequential steps: 1. Identify the problem, 2. Establish a theory of probable cause, 3. Test the theory, 4. Create an action plan, 5. Implement the solution, 6. Document findings.

Question 35: Explain the first three steps of troubleshooting in detail.

1. Identify the exact problem symptoms, 2. Formulate a logical theory regarding what might be causing the failure, and 3. Test the theory to check if the initial assumption is valid.

Question 36: Explain the final steps of troubleshooting.

4. Prepare a step-by-step action plan, 5. Implement the solution on the system, 6. Verify that the issue is fully resolved, and 7. Document the solution for future reference.

Question 37: Why is troubleshooting necessary in computing systems?

Troubleshooting is vital because it maintains optimal system performance, minimizes unexpected downtime, and resolves minor component issues before they cause total system failure.

Question 38: What is Downtime?

Downtime refers to the unproductive period during which a computer or network system is out of service or unavailable due to technical failures. Troubleshooting aims to minimize this duration.

Question 39: What is the role of troubleshooting in Data Integrity and Security?

Troubleshooting ensures that stored data remains accurate, consistent, and uncorrupted, while identifying potential security vulnerabilities to protect confidential files against breaches.

Question 40: Why does Cable Disconnection happen and how is it resolved?

Physical cables often become loose due to vibrations, accidental pulls, or worn-out connectors. Resolution involves checking all data and power cables and securing them firmly.

Question 41: What causes Computer Overheating and how can it be prevented?

Overheating is caused by processor cooling fan failure or heavy dust accumulation blocking heat sinks. Prevention includes cleaning dust regularly and placing systems in well-ventilated areas.

Question 42: What causes Peripheral Devices to malfunction?

Peripherals like keyboards or mice fail due to outdated drivers, faulty USB ports, or loose connectors. Resolution involves reconnecting devices or updating respective software drivers.

Question 43: What diagnostic tools are used in modern troubleshooting?

Modern technicians utilize specialized software diagnostic suites such as Windows Memory Diagnostic, CrystalDiskInfo, and Memtest86 to check hardware health.

Topic 5: Hardware Diagnostics & Software Maintenance

Question 44: What are the symptoms of RAM failure and how is it diagnosed?

RAM failure symptoms include frequent system freezes, random reboots, and Blue Screen of Death (BSOD) errors. Diagnosis is performed using Windows Memory Diagnostic.

Question 45: What are the symptoms of Hard Drive failure and health monitoring tools?

Failing hard drives exhibit sluggish system performance, clicking noises, and read errors. Health monitoring tools like CrystalDiskInfo and S.M.A.R.T utilities track drive status.

Question 46: How is RAM upgraded or replaced?

First, determine motherboard compatibility and maximum capacity, purchase matching memory modules, power off the system safely, and insert the RAM stick firmly into the designated slot.

Question 47: What is the proper procedure to replace a hard drive?

Power down the computer completely, disconnect power and data cables, unscrew the old drive chassis, install the replacement drive securely, and restore data from a recent backup.

Question 48: Why is software maintenance necessary?

Software maintenance is essential to patch security vulnerabilities, install system updates, clear junk files, and maintain high operational speed and stability.

Question 49: What are the benefits of regular updates and software uninstallation?

Regular updates eliminate dangerous bugs and security exploits, while removing unused programs frees up storage space and reduces system overhead.

Question 50: How are Software Conflicts resolved?

Software conflicts occur when concurrent applications compete for identical system resources. Resolution requires identifying conflicting apps and updating or uninstalling them.

Question 51: What is the primary purpose of antivirus and firewall protection?

Antivirus and firewalls protect computing systems by detecting and blocking malicious software like viruses, trojans, spyware, and cyber attacks such as ransomware.

Exercise Short Questions (Unit 2)

Question 1: Define Boolean function.

Answer: Boolean functions are mathematical expressions that represent the presence of logic operators in the processing of binary variables, playing a fundamental role in designing digital circuits.

Question 2: What is the importance of a truth table in digital logic?

Answer: A truth table in digital logic helps visualize how a Boolean function behaves for all possible input combinations, ensures correct design, simplifies Boolean expressions, and is essential for verifying and analyzing digital circuits.

Question 3: Explain the working of a NOT gate with its truth table.

Answer: A NOT gate is a basic digital logic gate that inverts the input. It outputs the reverse of the input value: if input is high (1), output is low (0), and if input is low (0), output is high (1).

NOT Truth Table:

Input (A)	Output (A')
0	1
1	0

Question 4: State the purpose of ADC and DAC.

Answer: ADC (Analog-to-Digital Converter) converts continuous signals into discrete signals so they can be processed by digital devices like computers and smartphones, while DAC (Digital-to-Analog Converter) converts digital signals back into analog signals.

Question 5: Write the truth table for an AND operation with two variables.

Answer: The AND operation is a fundamental logic operation producing a high output (1) only when all its inputs are 1.

AND Truth Table:

A	B	A AND B (P)
0	0	0
1	0	0
0	1	0
1	1	1

Question 6: What is the first step in the systematic troubleshooting process?

Answer: The first step in troubleshooting is identifying and defining the problem. This is important because it provides clear guidance on understanding the issue and prevents unnecessary steps.

Question 7: After identifying a problem, what is the next step in troubleshooting?

Answer: After identifying a problem, the next troubleshooting step is gathering details about the issue. This helps understand what is going wrong and aids in finding the correct solution.

Question 8: Explain the importance of testing a theory during troubleshooting. Provide an example.

Answer: Testing a theory is important because it helps verify whether the probable cause of the problem is correct. For example, if a computer is not turning on, checking if the power plug is connected tests the power supply theory to confirm if that is the issue.

Question 9: Explain what is included in the 'implement the solution' step of troubleshooting.

Answer: The 'implement the solution' step involves putting the executed solution into practice to resolve the identified problem. This may include making repairs, replacing components, correcting system configuration, or updating software, followed by verifying proper operation.

Question 10: Why is it important to verify full system functionality after implementing a solution?

Answer: Verifying full system functionality ensures that the problem has been completely resolved and no new issues have arisen. For example, after fixing a computer, checking that all programs run smoothly confirms everything operates as expected.

Additional Short Questions

Question 1: Define analog signal and give examples.

Answer: An analog signal is a continuous wave where electrical values change smoothly over time. Examples include human voice sound waves and temperature variations.

Question 2: What is a digital signal?

Answer: Digital signals are discrete signals limited to two specific physical states or values (0 and 1) used for accurate data processing.

Question 3: Define OR operator and build its truth table.

Answer: The OR operator yields a True output if at least one input is True.

OR Truth Table:

A	B	A OR B
0	0	0
0	1	1
1	0	1
1	1	1

Question 4: What are Logic Gates and name their primary types?

Answer: Logic gates are electronic circuits operating on Boolean principles. Types include AND, OR,NOT, NAND, and XOR gates.

Question 5: What is the purpose of simplifying a Boolean function?

Answer: Simplifying a Boolean function reduces expressions using minimal logic gates to make circuits cheaper and faster.

Question 6: What is Downtime?

Answer: Downtime is the unproductive period when a computer or network system fails to operate due to technical faults.

Question 7: What are the symptoms of RAM failure?

Answer: Symptoms of RAM failure include frequent system crashes and Blue Screen of Death (BSOD) errors.

Question 8: Why is software maintenance necessary?

Answer: Software maintenance is essential to protect computer software from virus attacks, obtain security patches, and maintain overall system performance.

Question 9: What does the Domain Name System (DNS) do?

Answer: DNS translates human-readable website names into computer-understandable IP addresses.

H.M. Shakeel Abbas GHS 40A/4L