

1 Ans: B

$$\frac{1}{R} = \frac{1}{R_1} + \frac{1}{R_2} \text{ or } R = \frac{R_1 R_2}{R_1 + R_2}$$

From 1st principle,

$$\min R_1 = 195 \, \Omega, \max R_1 = 205 \, \Omega$$

$$\min R_2 = 795 \, \Omega, \max R_2 = 805 \, \Omega$$

$$\min R = \frac{(195)(795)}{195 + 795} = 156.6 \, \Omega$$

$$\max R = \frac{(205)(805)}{205 + 805} = 163.4 \, \Omega$$

$$\Delta R = (\max R - \min R)/2 = (163.4 - 156.6)/2 = 3.4 \, \Omega$$

2 Ans: C