













PIDAC Cheatsheet - Week 1

Poort	Rechthoekige notatie	Alternatieve notatie	Waarheidstabel	Boole algebra
AND			$\begin{array}{cc c} y & z & Q \\ \hline 0 & 0 & 0 \\ 0 & 1 & 0 \\ 1 & 0 & 0 \\ 1 & 1 & 1 \end{array}$	$Q = y \cdot z$
OR			$\begin{array}{cc c} y & z & Q \\ \hline 0 & 0 & 0 \\ 0 & 1 & 1 \\ 1 & 0 & 1 \\ 1 & 1 & 1 \end{array}$	$Q = y + z$
XOR			$\begin{array}{cc c} y & z & Q \\ \hline 0 & 0 & 0 \\ 0 & 1 & 1 \\ 1 & 0 & 1 \\ 1 & 1 & 0 \end{array}$	$Q = y \oplus z$
Inverter			$\begin{array}{c c} y & Q \\ \hline 0 & 1 \\ 1 & 0 \end{array}$	$Q = \bar{y}$
NAND			$\begin{array}{cc c} y & z & Q \\ \hline 0 & 0 & 1 \\ 0 & 1 & 1 \\ 1 & 0 & 1 \\ 1 & 1 & 0 \end{array}$	$Q = \overline{y \cdot z}$
NOR			$\begin{array}{cc c} y & z & Q \\ \hline 0 & 0 & 1 \\ 0 & 1 & 0 \\ 1 & 0 & 0 \\ 1 & 1 & 0 \end{array}$	$Q = \overline{y + z}$

PIDAC Cheatsheet - Week 2

Rekenregels

1. $z + z = z$
2. $z \cdot z = z$
3. $\overline{\overline{z}} = z$
4. $z + \overline{z} = 1$
5. $z \cdot \overline{z} = 0$
6. $\overline{0} = 1$
7. $\overline{1} = 0$
8. $z + 0 = z$
9. $z + 1 = 1$
10. $z \cdot 0 = 0$
11. $z \cdot 1 = z$

Associativiteit

12. $(x + y) + z = x + (y + z)$
13. $(x \cdot y) \cdot z = x \cdot (y \cdot z)$

Commutativiteit

14. $y + z = z + y$
15. $y \cdot z = z \cdot y$

Distributieve wetten

16. $x \cdot y + x \cdot z = x \cdot (y + z)$
17. $(x + y) \cdot (x + z) = x + y \cdot z$

Absorptie, De Morgan en XOR

18. $y + \overline{y} \cdot z = y + z$
 19. $\overline{y \cdot z} = \overline{y} + \overline{z}$
 20. $y \cdot \overline{z} + \overline{y} \cdot z = y \oplus z$
-