







ICDFA-PLC-Engineering-v1.0 (LAB01-START) [Running] - Oracle VirtualBox

File Machine View Input Devices Help





Explanation of the Start, Stop, latch and MotorOutput elements.

For the motor output (**MotorOutput coil**) to energize, the circuit conditions must allow power flow from the left power rail to the right power rail. The **Stop contact must remain closed**, allowing current to pass through the circuit. When the **Start contact is activated**, it closes and allows the control signal to reach the MotorOutput coil.

Once the MotorOutput coil becomes energized, the **MotorOutput latch contact** closes and creates a holding circuit. This keeps the motor running even after the Start button is released.

Industrial I/O Classification Table

I/O Type	Explanation	Industrial Example
Discrete Input	A digital signal with only two states: ON or OFF (1 or 0).	Start push button, emergency stop switch, limit switch
Analog Input	A continuously varying signal used to measure physical conditions.	Temperature sensor, pressure sensor, level sensor
Discrete Output	A digital output used to switch devices ON or OFF.	Motor relay, indicator lamp, solenoid valve
Analog Output	A variable output signal used to control equipment levels.	Variable frequency drive speed control, valve position control signal

Reflection: Network Connected PLCs and Cybersecurity Considerations

Programmable Logic Controllers (PLCs) are important components in industrial automation because they allow machines and processes to be monitored and controlled efficiently. When PLCs are connected to networks, organizations gain several operational benefits, including remote monitoring, faster troubleshooting, improved data collection, and better coordination between industrial systems.

However, network-connected PLCs also introduce cybersecurity considerations. Traditional PLC systems were often designed mainly for reliability and continuous operation rather than security. Connecting them to networks can expose them to unauthorized access, malware, incorrect configuration, and possible disruption of industrial processes.

To reduce these risks, organizations should apply security measures such as network segmentation, strong authentication, regular software updates, access control, and continuous monitoring of industrial networks. Personnel should also receive cybersecurity training to reduce human-related risks.

A balance between operational efficiency and cybersecurity protection is necessary in modern industrial environments. Properly secured PLC networks allow industries to benefit from automation technologies while reducing the possibility of operational failures and security incidents.

Knowledge Check

1. What is the difference between an input module and an output module?

Input modules receive signals from sensors and switches and send them to the PLC.
Output modules send signals from the PLC to control devices like motors and valves.

2. Why is a normally closed contact commonly associated with stop or emergency-stop logic?

A normally closed contact is used for stop or emergency-stop logic because it keeps the circuit active during normal operation and opens immediately when the stop button is pressed, breaking the circuit and stopping the machine.

3. Give one example of a discrete I/O signal and one example of an analog I/O signal.

Discrete I/O signal: A push button (ON/OFF signal).

Analog I/O signal: A temperature sensor (continuous value signal).

4. What operational risk can arise when industrial automation devices become network-connected?

A risk is unauthorized access or cyberattacks that can disrupt industrial operations and affect system safety.