

Dasha's microphone keeps cutting out during sound check. The sound engineer (you) thinks something is wrong with the voltage regulator on the equipment. Professional audio equipment is designed with precise voltage requirements. Write a quick script to check the tolerances with your voltmeter. You will have to truncate the values before you enter them in your test suite though, as they only accept values to specific decimal lengths.



Input

You will receive between 3 and 10 lines. The first line will be the number of decimals your test equipment can handle. The rest of the numbers will be various voltages that have been recorded in the surge protection system recently. 000 on a line by itself ends input.

```
2
19770525.4444
19800521.55555
19830525.6
000
```

Output

Truncate (cut off) the decimals at the length specified. If the number's decimals are already at the specified length, or shorter, do nothing. **DO NOT ROUND**

```
19770525.44
19800521.55
19830525.6
```

Discussion

Note, it is a *mistake* to treat the inputs as floats/doubles, as not all of the decimal lengths given in your datasets can be *reliably* stored at those lengths in standard floats/doubles. Some of the numeric values will also be too large to store in a standard int-32, just FYI. If you would like to listen to our TED talk about number issues in programming languages, and have 3 hours free, we have a lot to say about this topic. (◡ ◡◡◡) ◡ ◡◡◡

Additional Examples

[illegible]

Input 3	Output 3
7 151218.70000000700000007000000070000007 20171215.88888888 20191220.999999999999999999999999999999 000	151218.70000000 20171215.88888888 20191220.99999999