

Telnet Insecure Lab Topology

Use:

PC ---- Switch ---- Router

Step 1: Configure PC

Desktop → IP Configuration

IP Address: 192.168.1.2

Subnet Mask: 255.255.255.0

Default Gateway: 192.168.1.1

Step 2: Configure Router for TELNET

Use this configuration:

enable

configure terminal

hostname R1

interface g0/0

ip address 192.168.1.1 255.255.255.0

no shutdown

exit

! Router enable password

enable secret snit

! Configure Telnet access

line vty 0 4

password telnetsnit

login

transport input telnet

exit

```
! Encrypt passwords
service password-encryption
```

```
end
write
```

Step 3: Test Telnet from PC

On PC Command Prompt:

```
telnet 192.168.1.1
```

Router asks:

Password:

Enter:

```
telnet>snit
```

Successful login proves Telnet works.

Step 4: Why Telnet is NOT Secure

Now explain:

Problem 1: No Encryption

Tell students:

“Telnet sends all data in plain text. Usernames and passwords can be captured by attackers.”
