

Bagara N 1.1

10  $\rightarrow$  16

$$\begin{array}{r|l}
 12345678 & 16 \\
 \hline
 12345664 & 771604 & 16 \\
 \hline
 14 & 771600 & 48225 & 16 \\
 (E) & 4 & 48224 & 3014 & 16 \\
 & & 1 & 3008 & 188 & 16 \\
 & & & 6 & 176 & 11 \\
 & & & & 12 & (B) \\
 & & & & & (C)
 \end{array}$$

Orbit: BC614E<sub>16</sub>

Bagara N 1.2

10  $\rightarrow$  16

$$\begin{array}{r|l}
 1000000 & 16 \\
 \hline
 1000000 & 62500 & 46 \\
 \hline
 0 & 62496 & 3906 & 16 \\
 & 4 & 3904 & 244 & 16 \\
 & & 2 & 240 & 15 \\
 & & & 4 & (F)
 \end{array}$$

Orbit: F4240

Bagara N 2.1

16  $\rightarrow$  10

12345678

$$\begin{aligned}
 & 1 \cdot 16^7 + 2 \cdot 16^6 + 3 \cdot 16^5 + 4 \cdot 16^4 + 5 \cdot 16^3 + 6 \cdot 16^2 + \\
 & + 7 \cdot 16^1 + 8 \cdot 16^0 = 268435456 + 33554432 + 3145728 +
 \end{aligned}$$



$$+ 262\,144 + 20\,480 + 15\,36 + 112 + 8 = \boxed{305\,419\,896}$$

Задача №2.2.

$$16 \rightarrow 10$$

1 000 000

$$1 \cdot 16^6 + 0 = \boxed{16\,777\,216}$$

Задача №4.1.

$$A \rightarrow B = \neg A \vee B$$

| A | B | $A \rightarrow B$ | $\neg A \vee B$ |
|---|---|-------------------|-----------------|
| 0 | 0 | 1                 | 1               |
| 0 | 1 | 1                 | 1               |
| 1 | 0 | 0                 | 0               |
| 1 | 1 | 1                 | 1               |

Задача №4.2.

$$A \leftrightarrow B = (A \& B) \vee (\neg A \& \neg B)$$

| A | B | $A \leftrightarrow B$ | $A \& B$ | $\neg A \& \neg B$ | = |
|---|---|-----------------------|----------|--------------------|---|
| 0 | 0 | 1                     | 0        | 1                  | 1 |
| 0 | 1 | 0                     | 0        | 0                  | 0 |
| 1 | 0 | 0                     | 0        | 0                  | 0 |
| 1 | 1 | 1                     | 1        | 0                  | 1 |



Задача № 6.

$$\begin{aligned} X &= (B \rightarrow A) (\overline{A+B}) \cdot (A \rightarrow C) = \\ &= (\overline{B} + A) \cdot \overline{A} \cdot \overline{B} \cdot (\overline{A} + C) = \\ &= \overline{B} \cdot (\overline{B} + A) \cdot \overline{A} \cdot (\overline{A} + C) = \\ &= \overline{B} \cdot \overline{B} + \overline{B} \cdot A \cdot \overline{A} \cdot \overline{A} + \overline{A} \cdot C = \\ &= \overline{B} + \overline{B} \cdot A \cdot \overline{A} + \overline{A} \cdot C = \\ &= (\overline{B} + \overline{B}) \cdot (\overline{B} + A) \cdot (\overline{A} + \overline{A}) \cdot (\overline{A} \cdot C) = \\ &= \overline{B} + \overline{B} \cdot 0 + \overline{A} \cdot C = \overline{B} + \overline{A} \cdot C \end{aligned}$$



View all by July

+ Follow July

+ Add To



$$X = !A * !B + A * B + !A$$



| A | B | $!A * !B$ | $A * B$ | $!A$ | X |
|---|---|-----------|---------|------|---|
| 0 | 0 | 1         | 0       | 1    | 1 |
| 0 | 1 | 0         | 0       | 1    | 1 |
| 1 | 0 | 0         | 0       | 0    | 0 |
| 1 | 1 | 0         | 1       | 0    | 1 |





DEC 76

HEX

↓

BIN

▲

4

▼

▲

C

▼

0

1

0

0

1

1

0

0

View all b

+ Follow

+ A







XXXXXXXXXXXXXXXXXXXX  
HEX C9

DEC



BIN



-

0

5

5



1

1

0

0

1

0

0

1