utility10_03-fridge-door-guard

Fridge Door Guard: manufacturing manual

> **Status: design only.** Nothing here has been built or tested as hardware. This manual tells you exactly what to make, buy, assemble, program and test, and how to accept or reject a unit; expect to correct it after the first prototype run (5 units).

Product summary. A reed switch and magnet stick on the door gap. Quiet for 60 s, then a chirp every 10 s, continuous after 3 min; closing silences it. It also counts openings and total open time (for kids' door habits).

Product line / price in the plan: Tier B · low-voltage electronics · prototype Rs 610 · price Rs 599. Status: designed and verified as far as a computer can; no prototype built, nothing field-tested.

1. What you are building: deliverables

Deliverable	Where	State
PCB: Gerbers, BOM, CPL, KiCad project	`utility10/pcb/release/fridge/`	**order-ready: every automatic check passes** (DRC errors 0, netlist match True)
Firmware (`boards/fridge_guard.hex`)	`utility10/firmware/release/4MHz/boards/fridge_guard.hex`, source `utility10/firmware/src/main_board.cpp` (seeti: `seeti_prod.cpp`), drivers `board_drivers.h`, engine `utility10/firmware/lib/utilcore.c`	engine host-tested (115 checks); board firmware compiles but is **not yet run on hardware** (see section 6)
Enclosure STL (prototype shell)	`utility10/03-fridge-door-guard/enclosure_body.stl`, `enclosure_lid.stl` and the board's `4_enclosure/`	prototype shell only
Mechanical / bought-in parts	section 3	listed
Test sheet	`manuals/templates/eol_test_sheet.md`	template

2. Before you start

- Read `manuals/STANDARD_PROCEDURES.md` (sections A-F, J, K).
- Tools: soldering iron, flux, multimeter, USBasp programmer + avrdude, calipers, 3D printer or print service, bench supply with current limit.
- Power source for this product: **2 x AAA**.

3. Bill of materials

3a. Circuit board parts (21 parts, 3 test points)

SMD parts marked `SMT (JLC)` are assembled by the fab from the JLC BOM; parts marked `hand/THT` are soldered by you. Every LCSC number was checked against an LCSC/JLCPCB listing on 2026-11-01; re-check stock on the day you order.

Ref	Value	Package	Part (manufacturer)	LCSC	Assembly
U1	ATmega328P-AU	TQFP-32_7x7mm_P0.8mm	ATMEGA328P-AU	C14877	SMT (JLC)
C1	100n	C_0603_1608Metric	0603 100nF X7R	C14663	SMT (JLC)
C2	100n	C_0603_1608Metric	0603 100nF X7R	C14663	SMT (JLC)
C3	100n	C_0603_1608Metric	0603 100nF X7R	C14663	SMT (JLC)
R7	10k	R_0603_1608Metric	0603 10k 1%	C25804	SMT (JLC)
J2	ISP	PinHeader_2x03_P2.54mm_Vertical	ZHOURI 2.54-2*3	C5116479	hand/THT
J1	BATT 2xAAA	JST_PH_B2B-PH-K_1x02_P2.00mm_Vertical	JST B2B-PH-K-S(LF)(SN)	C131337	hand/THT
SW1	Power	SW_SPDT_PCM12	C&K PCM12SMTR	C221841	SMT (JLC)
Q2	AO3401A	SOT-23	AO3401A	C15127	SMT (JLC)
C4	10u	C_0805_2012Metric	0805 10uF X5R	C15850	SMT (JLC)
BZ1	Buzzer	Buzzer_12x9.5RM7.6	YUEXIN KC1206 16 ohm passive magnetic 12x9.5 mm (2048 Hz)	C781869	hand/THT
Q1	MMBT3904	SOT-23	MMBT3904	C20526	SMT (JLC)
D2	1N4148WS	D_SOD-323	1N4148WS	C2128	SMT (JLC)
R6	1k	R_0603_1608Metric	0603 1k 1%	C21190	SMT (JLC)
D1	Green	LED_0603_1608Metric	Everlight 19-217/GHC-YR1S2/3T (LCSC showed it out of stock on the search day: check)	C72043	SMT (JLC)
R5	1k	R_0603_1608Metric	0603 1k 1%	C21190	SMT (JLC)
SW2	Silence	SW_SPST_B3U-1000P	Omron B3U-1000P	C231329	SMT (JLC)
J3	Reed switch	JST_PH_B2B-PH-K_1x02_P2.00mm_Vertical	JST B2B-PH-K-S(LF)(SN)	C131337	hand/THT
R8	1k	R_0603_1608Metric	0603 1k 1%	C21190	SMT (JLC)
C9	10n	C_0603_1608Metric	0603 10nF X7R	C57112	SMT (JLC)

Ref	Value	Package	Part (manufacturer)	LCSC	Assembly
D4	TVS 5V bidir	D_SOD-323	Nexperia PESD5V0S1BA,115	C19224	SMT (JLC)

3b. Bought-in and mechanical items (estimates for about 2,000 units; replace with quotes)

Item	Rs
MCU (small)	30
Reed switch + magnet	15
Buzzer	12
PCB	20
2×AAA holder	15
Stick-on enclosure	25
Packaging	20
Assembly + test	25

4. Step 1: fabricate the PCB

Upload `utility10/pcb/release/fridge/1_fabrication/fridge_door_guard_gerbers.zip` with the settings in STANDARD_PROCEDURES section A. Finish: HASL lead-free. Board size and layer list are in `utility10/pcb/release/fridge/README.md`.

5. Step 2: assemble the board

1. Order SMT assembly as in STANDARD_PROCEDURES section B (or hand-solder the SMD parts in section D order).
2. Solder the through-hole parts listed `hand/THT` in 3a.
3. Clean, inspect under magnification, and compare with `2_assembly/*_assembly_top.pdf`.

6. Step 3: program the microcontroller

1. Connect a USBasp to the 6-pin ISP header J2 (pin 1 = square pad) with the board powered (2 x AAA).
2. Set fuses: `avrdude -p m328p -c usbasp -U lfuse:w:0xE2:m -U hfuse:w:0xD9:m -U efuse:w:0xFE:m` (internal 8 MHz RC, CKDIV8 off, brown-out 1.8 V; the firmware then divides the clock to 4 MHz (2 x AAA supply may fall to 2.0 V)).
3. Flash and verify: `avrdude -p m328p -c usbasp -U flash:w:utility10/firmware/release/4MHz/boards/fridge_guard.hex:i` then `-U flash:v:utility10/firmware/release/4MHz/boards/fridge_guard.hex:i`.
4. Remove the programmer, power-cycle the board, and confirm the start-up behaviour (section 9).

If you change the supply type (for example USB instead of batteries) use the hex built for that clock (`4MHz` for 2 x AAA, `8MHz` for every other tool).

Firmware pin map (generated from the PCB spec, so firmware and board agree):

Arduino pin	ATmega pin	Net
D3	1	REED
D7	11	LED

Arduino pin	ATmega pin	Net
D9	13	BUZ
D2	32	BTN

What is verified: the control logic (`utilcore.c`) passes 115 host tests. **What is not:** the display, OLED, RTC and HX711 drivers and the button flows in `main_board.cpp` were written from datasheets and only compile-checked. Budget bring-up time for them on the first prototype.

7. Step 4: electrical bring-up

1. Magnet next to reed: REED (TP3) low; remove: high and INT1 wakes the unit.
2. After 60 s open: chirp every 10 s; after 180 s: continuous; closing silences.

8. Step 5: sensors, cables and mechanical assembly

- **Reed switch and magnet.** Solder the reed switch (J3) to a 20 cm 2-core lead and fix it in the housing edge; glue a small neodymium magnet into a second housing piece; mounting is by 3M adhesive so the two halves face each other across the door gap with under 5 mm separation (alignment tolerance is not verified: test with the real fridge).

9. Step 6: enclosure and final assembly

1. Print the shell (STANDARD_PROCEDURES section G). Enclosure: `enclosure_body.stl` / `enclosure_lid.stl` (60×30×18 mm, 2.4 mm walls, watertight): a simple prototype shell; production tooling needs a proper design.
2. Place the board on the standoffs (4 mm), fasten with M2.5 screws (6 mm), route cables through the cut-outs, close the lid.
3. Label: serial number, rev, battery type/polarity, warnings.

10. Step 7: calibration

- None. Verify that the reed closes reliably at the real door gap and magnet distance (try 2, 4 and 6 mm).

11. Step 8: end-of-line functional test (every unit)

1. Magnet near the reed: silent; magnet away 65 s: chirp; 185 s: continuous alarm; magnet back: silent.
2. Count the openings logged after 11 short opens: no warning should have sounded.

Record results on `manuals/templates/eol_test_sheet.md`. Accept only if every line passes.

12. Packaging, documents, compliance

- In the box: unit, batteries or note on the required adapter, mounting accessories, quick-start card (`manuals/templates/quick_start_card.md`), warranty card.
- Compliance items to verify before sale: Battery safety, BIS requirement for any bought-in adapter, EMC, e-waste EPR, Legal Metrology labelling; no safety claims..
- Labelling: STANDARD_PROCEDURES K.

13. Troubleshooting (product specific)

Symptom	Cause / action
Alarm sounds with the door closed	magnet too far or reed contact stuck: replace the reed
Battery empties early	check sleep behaviour; battery life is not measured

General issues: STANDARD_PROCEDURES section L.

14. Known limits and risks

Host tests: quiet in the first minute, chirps then continuous alarm at the thresholds, closing silences and logs time, 11 short opens never warn, millis() wrap-safe. Not verified: magnet alignment tolerance and battery life.

Price pressure (₹150–300 door alarms exist), needs strong differentiation (open-time log, loudness, battery life).

Nothing in this manual replaces testing with real users, a design review by a PCB engineer, and the compliance checks above.