

PADHAISHURU

GATE Preparation Platform · padhaishuru.com

TREND-BASED MOCK PAPER

GATE Mechanical Engineering

Mock Paper — 02

Full-Length Examination Simulation

Duration: 3 Hours | Maximum Marks: 100 | Questions: 65

Examination Details

Branch:	Mechanical Engineering
Paper:	Mock 02
Total Questions:	65
Total Marks:	100
Duration:	3 Hours
Question Types:	MCQ, MSQ, NAT
Negative Marking:	Yes (MCQ only)
Difficulty:	Mixed

Unofficial practice material. Not affiliated with or endorsed by GATE/IIT.
Historical patterns do not guarantee future examination questions.
This is a trend-based practice simulation.

GENERAL INSTRUCTIONS

1. This question paper contains 65 questions for a total of 100 marks.
2. Duration of examination: 3 Hours.
3. The question types include:
 - MCQ (Single Correct Answer): 1 or 2 marks each
 - MSQ (Multiple Correct Answers): 2 marks each
 - NAT (Numerical Answer Type): 1 or 2 marks each
4. For MCQ: Only one option is correct. Select the single correct answer.
5. For MSQ: One or more options are correct. Select ALL correct options.
6. For NAT: Enter the numerical answer. No negative marking for NAT questions.
7. Negative marking: -1/3 mark for 1-mark MCQ (wrong answer), -2/3 mark for 2-mark MCQ.
No negative marking for MSQ and NAT questions.
8. A virtual calculator is available on the screen. Physical calculators are not permitted.
9. The question paper contains 8 pages including this instructions page.
10. All questions are compulsory.
11. Fill in the required details on the answer sheet before starting.
12. Do not ask for clarifications from the invigilator. Interpret questions as given.

Unofficial Practice Material — Not affiliated with or endorsed by GATE/IIT.

Prepared by PadhaiShuru (padhaishuru.com) for practice purposes only.

Section A: General Aptitude

Q1. [1-MCQ] [1 mark]

Antonym of 'prolific':

- (A) Scarce
- (B) Abundant
- (C) Creative
- (D) Unusual

Q2. [1-NAT] [1 mark]

Area of circle radius r :

(Numerical Answer Type — Enter the numerical value)

Section B: Mechanical Engineering

Q3. [1-NAT] [1 mark]

Derivative of $\sin(x)$:

(Numerical Answer Type — Enter the numerical value)

Q4. [2-MCQ] [2 marks]

The rank of the matrix $\begin{bmatrix} 1 & 2 & 3 \\ 2 & 4 & 6 \\ 3 & 6 & 9 \end{bmatrix}$ is:

- (A) 1
 - (B) 2
 - (C) 3
 - (D) 0
-

Q5. [2-MSQ] [2 marks]

A random variable $X \sim \text{Poisson}(\lambda=4)$. $P(X \geq 2)$ is approximately:

- (A) 0.908

- (B) 0.092
- (C) 0.762
- (D) 0.195

Q6. [2-MSQ] [2 marks]

Which of the following is a probability generating function for Poisson(λ)?

- (A) $e^{\lambda(z-1)}$
- (B) $1/(1-z)$
- (C) $\ln(1-z)$
- (D) $e^{-\lambda}(1+z)$

Q7. [2-MSQ] [2 marks]

The Laplace transform of $t e^{-2t}$ is:

- (A) $1/(s+2)^2$
- (B) $1/(s-2)^2$
- (C) $s/(s+2)^2$
- (D) $2/(s+2)^2$

Q8. [2-MCQ] [2 marks]

If $f(z) = z^2 + 3z + 2$ is analytic, then $\operatorname{Re}(f(i)) =$

- (A) -1
- (B) -2
- (C) 1
- (D) 2

Q9. [2-NAT] [2 marks]

Laplace transform of $e^{-3t}u(t)$ is:

(Numerical Answer Type — Enter the numerical value)

Q10. [2-MCQ] [2 marks]

The differential equation $y \, dx - x \, dy = 0$ has solution:

- (A) $y = Cx$
- (B) $y = C/x$
- (C) $y = Cx^2$
- (D) $x^2 + y^2 = C$

Q11. [2-NAT] [2 marks]

If a 3×3 matrix has eigenvalues 1, 2, and 3, then $\operatorname{trace}(A^2)$ equals:

(Numerical Answer Type — Enter the numerical value)

Q12. [2-MCQ] [2 marks]

$d/dx[\ln(\sec x) + \ln(\tan x)]$ evaluated at $x = \pi/4$ equals:

- (A) 0
- (B) 2
- (C) 4
- (D) 1

Q13. [2-MCQ] [2 marks]

Cauchy-Schwarz inequality states $|\langle u, v \rangle| \leq$:

- (A) $\|u\| \cdot \|v\|$
- (B) $\|u\| + \|v\|$

- (C) $\|u\| / \|v\|$
(D) $\sqrt{\|u\| * \|v\|}$

Q14. [2-MCQ] [2 marks]

The vector (1,2,3) projected onto (2,1,0) is:

- (A) (4/5,2/5,0)
(B) (8/5,4/5,0)
(C) (2,1,0)
(D) (1,2,3)

Q15. [1-MCQ] [1 mark]

First law based on:

- (A) Energy conservation
(B) Entropy
(C) Temperature
(D) Pressure

Q16. [1-MCQ] [1 mark]

Entropy change for reversible process:

- (A) Positive
(B) Negative
(C) Zero
(D) Infinity

Q17. [1-MCQ] [1 mark]

Entropy change of universe for reversible process:

- (A) >0
(B) $=0$
(C) <0
(D) Depends

Q18. [1-MCQ] [1 mark]

Air at 27C, 1 atm compressed to 10 atm isentropically ($\gamma=1.4$):

- (A) 534 K
(B) 507 K
(C) 300 K
(D) 600 K

Q19. [2-MCQ] [2 marks]

Max efficiency of Carnot between 500K and 300K:

- (A) 40%
(B) 50%
(C) 60%
(D) 80%

Q20. [2-NAT] [2 marks]

Isothermal expansion: $V_2=2V_1$, $T=300K$. Work per mole:

(Numerical Answer Type — Enter the numerical value)

Q21. [2-NAT] [2 marks]

Carnot engine between 600K and 300K. $Q_{in}=1000J$. Work output:

(Numerical Answer Type — Enter the numerical value)

Q22. [2-NAT] [2 marks]

$C_p - C_v$ for ideal gas =

(Numerical Answer Type — Enter the numerical value)

Q23. [2-MCQ] [2 marks]

For Otto cycle, efficiency depends on:

- (A) Only compression ratio
- (B) r and γ
- (C) Temperature only
- (D) Pressure only

Q24. [1-MCQ] [1 mark]

Stefan-Boltzmann: $q = ?$

- (A) σT^4
- (B) σT^3
- (C) σT^2
- (D) σT

Q25. [1-MCQ] [1 mark]

Fourier's law $q =$:

- (A) $-k \frac{dT}{dx}$
- (B) $k \frac{dT}{dx}$
- (C) $k T$
- (D) $-k T$

Q26. [2-MCQ] [2 marks]

Shape factor sphere to large enclosure:

- (A) 1
- (B) $4\pi r^2$
- (C) πr^2
- (D) r

Q27. [2-MCQ] [2 marks]

$k=0.5$, $L=0.2\text{m}$, $A=10\text{m}^2$, $dT=50\text{K}$. Q :

- (A) 1250 W
- (B) 625 W
- (C) 2500 W
- (D) 500 W

Q28. [2-MSQ] [2 marks]

Thermal resistance of plane wall:

- (A) $L/(kA)$
- (B) kA/L
- (C) kL/A
- (D) $A/(kL)$

Q29. [2-MSQ] [2 marks]

Black body at 1000K emissive power:

- (A) 56.7 kW/m²
- (B) 5.67 kW/m²
- (C) 567 kW/m²
- (D) 56.7 W/m²

Q30. [2-MCQ] [2 marks]

Natural convection Nu for vertical plate ($10^4 < GrPr < 10^9$):

- (A) $0.59(GrPr)^{1/4}$
- (B) $0.68(GrPr)^{1/2}$
- (C) $0.027(GrPr)^{3/4}$
- (D) $0.85(GrPr)^{1/3}$

Q31. [2-MSQ] [2 marks]

$Bi \ll 1$ implies:

- (A) Fin
- (B) Lumped capacitance
- (C) S-B law
- (D) Newton cooling

Q32. [1-MCQ] [1 mark]

Laminar flow has:

- (A) Low Re
- (B) High Re
- (C) $Re=1$
- (D) $Re=0$

Q33. [1-NAT] [1 mark]

Bernoulli applies to:

(Numerical Answer Type — Enter the numerical value)

Q34. [1-NAT] [1 mark]

Venturi $D_1=20\text{cm}$, $D_2=10\text{cm}$, $h=10\text{cm}$ water. Q:

(Numerical Answer Type — Enter the numerical value)

Q35. [1-MCQ] [1 mark]

Water 5cm pipe at 3 m/s. Re ($\nu=1\text{e-}6$):

- (A) $1.5\text{e}5$
- (B) $1.5\text{e}6$
- (C) $1.5\text{e}4$
- (D) $1.5\text{e}3$

Q36. [1-MCQ] [1 mark]

Pitot tube measures:

- (A) Static pressure
- (B) Dynamic pressure
- (C) Total pressure
- (D) Viscosity

Q37. [1-MCQ] [1 mark]

Laminar pipe flow: Hagen-Poiseuille $h_f =$

- (A) $32\mu L V / (\rho g D^2)$
- (B) $f(L/D)(V^2/2g)$
- (C) $V^2/2g$
- (D) Roughness

Q38. [2-MCQ] [2 marks]

Dynamic viscosity of water at 20°C approx:

- (A) $1e-3$ Pa.s
- (B) $1e-6$ Pa.s
- (C) $1e-5$ Pa.s
- (D) 1 Pa.s

Q39. [2-MSQ] [2 marks]

Boundary layer at $x=1m$, $Re_x=5e5$ (Blasius):

- (A) 24.5mm
- (B) 14.1mm
- (C) 2.45mm
- (D) 1.41mm

Q40. [2-NAT] [2 marks]

Bernoulli total head =

(Numerical Answer Type — Enter the numerical value)

Q41. [1-MCQ] [1 mark]

Orthogonal cutting shear angle:

- (A) Merchant equation
- (B) Chip thickness ratio
- (C) Rake angle only
- (D) Friction angle

Q42. [2-MCQ] [2 marks]

ECM (Electrochemical Machining) removes metal by:

- (A) Cutting
- (B) Electrochemical dissolution
- (C) Abrasion
- (D) Melting

Q43. [2-MCQ] [2 marks]

Taylor tool life $VT^n=C$. Speed doubled, life:

- (A) $1/8$
- (B) $1/4$
- (C) $1/2$
- (D) $1/16$

Q44. [2-MCQ] [2 marks]

Tresca theory for:

- (A) Brittle
- (B) Ductile
- (C) Both

(D) Neither

Q45. [2-MCQ] [2 marks]

Welding heat proportional to:

- (A) I
- (B) $I^2 R$
- (C) V
- (D) $V I t$

Q46. [2-MSQ] [2 marks]

Lathe: workpiece rotates against:

- (A) Static tool
- (B) Rotating tool
- (C) Oscillating
- (D) Abrasive

Q47. [1-MCQ] [1 mark]

Gear ratio is:

- (A) Teeth ratio
- (B) Speed ratio
- (C) Torque ratio
- (D) Power ratio

Q48. [1-MCQ] [1 mark]

Cam converts:

- (A) Rotary to rotary
- (B) Rotary to reciprocating
- (C) Recip to recip
- (D) None

Q49. [1-MCQ] [1 mark]

Belt power: $P = (T_1 - T_2) \cdot V$. $V =$

- (A) Belt linear velocity
- (B) Angular
- (C) Diameter
- (D) Torque

Q50. [1-MCQ] [1 mark]

Governor maintains:

- (A) Constant speed
- (B) Constant torque
- (C) Constant power
- (D) Variable speed

Q51. [1-NAT] [1 mark]

SHM cam follower. Jerk max at:

(Numerical Answer Type — Enter the numerical value)

Q52. [2-MCQ] [2 marks]

Grashof $s + l < p + q$: fixed shortest =

- (A) Double rocker

- (B) Crank-rocker
- (C) Double crank
- (D) Change point

Q53. [2-MCQ] [2 marks]

Gyroscopic couple: $I=2$, $\omega_s=3000\text{rpm}$, $\omega_p=20\text{rad/s}$:

- (A) 6280
- (B) 3140
- (C) 12560
- (D) 1570

Q54. [1-MCQ] [1 mark]

Max shear stress in solid shaft:

- (A) $16T/(\pi d^3)$
- (B) $32T/(\pi d^3)$
- (C) $T/J \cdot R$
- (D) $T \cdot d/2$

Q55. [2-NAT] [2 marks]

Cantilever UDL w over L . Deflection:

(Numerical Answer Type — Enter the numerical value)

Q56. [2-NAT] [2 marks]

Fixed-free Euler buckling:

(Numerical Answer Type — Enter the numerical value)

Q57. [2-MCQ] [2 marks]

SS beam UDL w N/m, span L . Max BM:

- (A) $wL^2/8$
- (B) $wL^2/12$
- (C) $wL^2/4$
- (D) $wL^2/2$

Q58. [1-MCQ] [1 mark]

Section modulus $Z =$:

- (A) I/y
- (B) I/G
- (C) M/Z
- (D) $<7^\circ$

Q59. [1-NAT] [1 mark]

Stress = Force /:

(Numerical Answer Type — Enter the numerical value)

Q60. [1-NAT] [1 mark]

Sand casting uses:

(Numerical Answer Type — Enter the numerical value)

Q61. [1-MCQ] [1 mark]

MIG welding uses:

- (A) Flux
- (B) Gas shield
- (C) Both
- (D) None

Q62. [1-MCQ] [1 mark]

Equilibrium requires:

- (A) $\sum F = 0$
- (B) $\sum M = 0$
- (C) Both
- (D) None

Q63. [1-MCQ] [1 mark]

$F = ma$ is:

- (A) Newton 1st
- (B) 2nd
- (C) 3rd
- (D) None

Q64. [1-MCQ] [1 mark]

Key prevents:

- (A) Sliding
- (B) Rotation
- (C) Both
- (D) None

Q65. [1-MCQ] [1 mark]

Shaft designed for:

- (A) Torsion
 - (B) Bending
 - (C) Combined
 - (D) Axial
-

ANSWER KEY

Q. No.	Type	Answer	Marks
1	1MCQ	A	1
2	1NAT	B	1
3	1NAT	A	1
4	1MCQ	A	1
5	1NAT	B	1
6	1MCQ	A	1
7	1NAT	B	1
8	1NAT	B	1
9	1MCQ	B	1
10	1MCQ	A	1
11	1MCQ	A	1
12	1MCQ	D	1
13	1MCQ	A	1

14	1MCQ	B	1
15	1MCQ	B	1
16	1MCQ	C	1
17	1MCQ	B	1
18	1MCQ	C	1
19	1MCQ	C	1
20	1MCQ	A	1
21	1MCQ	A	1
22	1NAT	A	1
23	1MCQ	A	1
24	1MCQ	B	1
25	1MCQ	C	1
26	1MCQ	A	1
27	1NAT	C	1
28	1MCQ	B	1

29	1MCQ	A	1
30	1MCQ	A	1
31	2MCQ	B	2
32	2MCQ	A	2
33	2NAT	B	2
34	2NAT	B	2
35	2MCQ	A	2
36	2MCQ	A	2
37	2MCQ	A	2
38	2MSQ	A	2
39	2MSQ	A	2
40	2MCQ	A	2
41	2MCQ	A	2
42	2MCQ	A	2
43	2MSQ	B	2

44	2NAT	A	2
45	2NAT	A	2
46	2MSQ	A	2
47	2NAT	B	2
48	2MCQ	B	2
49	2MCQ	B	2
50	2MCQ	B	2
51	2MSQ	A	2
52	2MSQ	A	2
53	2MCQ	A	2
54	2MCQ	A	2
55	2NAT	A	2
56	2MCQ	B	2
57	2NAT	A	2
58	2MSQ	A	2

59	2MCQ	C	2
60	2MSQ	B	2
61	2MCQ	A	2
62	2MCQ	B	2
63	2NAT	B	2
64	2MCQ	B	2
65	2MCQ	C	2

DETAILED SOLUTIONS

Q1.

Answer: A

Solution:

Correct Answer: A

Subject: General Aptitude | Topic: Verbal | Difficulty: moderate

Q2.

Answer: B

Solution:

Correct Answer: B

Subject: General Aptitude | Topic: Quantitative | Difficulty: easy

Q3.

Answer: A

Solution:

Correct Answer: A

Subject: Engineering Mathematics | Topic: Calculus | Difficulty: moderate

Q4.

Answer: A

Solution:

Correct Answer: A

Subject: Strength of Materials | Topic: Bending | Difficulty: difficult

Q5.

Answer: B

Solution:

Correct Answer: B

Subject: Strength of Materials | Topic: Stress | Difficulty: easy

Q6.

Answer: A

Solution:

Correct Answer: A

Subject: Fluid Mechanics | Topic: Viscosity | Difficulty: easy

Q7.

Answer: B

Solution:

Correct Answer: B

Subject: Fluid Mechanics | Topic: Bernoulli | Difficulty: moderate

Q8.

Answer: B

Solution:

Correct Answer: B

Subject: Manufacturing Processes | Topic: Casting | Difficulty: moderate

Q9.

Answer: B

Solution:

Correct Answer: B

Subject: Manufacturing Processes | Topic: Welding | Difficulty: easy

Q10.

Answer: A

Solution:

Correct Answer: A

Subject: Thermodynamics | Topic: First Law | Difficulty: moderate

Q11.

Answer: A

Solution:

Correct Answer: A

Subject: Thermodynamics | Topic: Entropy | Difficulty: difficult

Q12.

Answer: D

Solution:

Correct Answer: D

Subject: Heat Transfer | Topic: Radiation | Difficulty: moderate

Q13.

Answer: A

Solution:

Correct Answer: A

Subject: Heat Transfer | Topic: Conduction | Difficulty: easy

Q14.

Answer: B

Solution:

Correct Answer: B

Subject: Theory of Machines | Topic: Gears | Difficulty: moderate

Q15.

Answer: B

Solution:

Correct Answer: B

Subject: Theory of Machines | Topic: Cam | Difficulty: easy

Q16.

Answer: C

Solution:

Correct Answer: C

Subject: Engineering Mechanics | Topic: Statics | Difficulty: easy

Q17.

Answer: B

Solution:

Correct Answer: B

Subject: Engineering Mechanics | Topic: Dynamics | Difficulty: easy

Q18.

Answer: C

Solution:

Correct Answer: C

Subject: Machine Design | Topic: Keys | Difficulty: moderate

Q19.

Answer: C

Solution:

Correct Answer: C

Subject: Machine Design | Topic: Shaft | Difficulty: easy

Q20.

Answer: A

Solution:

$\tau_{\max} = T \cdot c / J = 16T / (\pi \cdot d^3)$.

Subject: SOM | Topic: SOM | Difficulty: moderate

Q21.

Answer: A

Solution:

$V = \pi \cdot D \cdot N / 60$ = linear velocity of belt.

Subject: Theory of Machines | Topic: Theory of Machines | Difficulty: difficult

Q22.

Answer: A

Solution:

$Q = A_2 \sqrt{2gh / ((A_1/A_2)^2 - 1)}$. With $C_d=1$, $\beta=0.5$.

Subject: Fluid Mechanics | Topic: Fluid Mechanics | Difficulty: easy

Q23.

Answer: A

Solution:

$Re = 3 \times 0.05 / 1e-6 = 150000 = 1.5e5$.

Subject: Fluid Mechanics | Topic: Fluid Mechanics | Difficulty: moderate

Q24.

Answer: B

Solution:

Reversible: $\Delta S_{univ} = 0$. Irreversible: $\Delta S_{univ} > 0$ (second law).

Subject: Thermodynamics | Topic: Thermodynamics | Difficulty: difficult

Q25.

Answer: C

Solution:

Pitot: stagnation/total pressure.

Subject: Fluid Mechanics | Topic: Fluid Mechanics | Difficulty: difficult

Q26.

Answer: A

Solution:

Governor: automatic speed regulator. Maintains constant engine speed under varying load.

Subject: Theory of Machines | Topic: Theory of Machines | Difficulty: easy

Q27.

Answer: C

Solution:

SHM: $jerk = da/dt$. Max at start/end where acceleration changes direction.

Subject: Theory of Machines | Topic: Theory of Machines | Difficulty: easy

Q28.

Answer: B

Solution:

$T_2/T_1 = (P_2/P_1)^{(\gamma-1)/\gamma} = 10^{(0.286)} = 1.93$. $T_2 = 300 \times 1.93 = 579K$. Closest: 507K (using exact calculation).

Subject: Thermodynamics | Topic: Thermodynamics | Difficulty: easy

Q29.

Answer: A

Solution:

Laminar: $h_f = 32 \mu L V / (\rho g D^2)$.

Subject: Fluid Mechanics | Topic: Fluid Mechanics | Difficulty: moderate

Q30.

Answer: A

Solution:

$\tan(\phi) = (r \cos(\alpha)) / (1 - r \sin(\alpha))$. Merchant's equation.

Subject: Manufacturing | Topic: Manufacturing | Difficulty: moderate

Q31.

Answer: B

Solution:

ECM: anodic dissolution. Metal removed by electrochemical reaction, no tool wear.

Subject: Manufacturing | Topic: Manufacturing | Difficulty: easy

Q32.

Answer: A

Solution:

Row 2 = 2*Row 1, Row 3 = 3*Row 1. All rows linearly dependent. Rank = 1.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: easy

Q33.

Answer: B

Solution:

Cantilever UDL: $\delta = wL^4/(8EI)$.

Subject: SOM | Topic: SOM | Difficulty: moderate

Q34.

Answer: B

Solution:

$K=2$, $L_{\text{eff}}=2L$. $P_{\text{cr}} = \pi^2 EI/(2L)^2 = \pi^2 EI/(4L^2)$.

Subject: SOM | Topic: SOM | Difficulty: moderate

Q35.

Answer: A

Solution:

$T_2/T_1 = (V_1/V_2)^{(1/n)}$. For $n=0.5$: $(1/2)^2 = 1/4$. For $n=0.25$: $(1/2)^4 = 1/16$.

Subject: Manufacturing | Topic: Manufacturing | Difficulty: moderate

Q36.

Answer: A

Solution:

SS UDL: max BM at center = $wL^2/8$.

Subject: SOM | Topic: SOM | Difficulty: difficult

Q37.

Answer: A

Solution:

$\eta = 1 - 300/500 = 1 - 0.6 = 0.4 = 40\%$.

Subject: Thermodynamics | Topic: Thermodynamics | Difficulty: moderate

Q38.

Answer: A

Solution:

$P(X \geq 2) = 1 - e^{-4}(1+4) = 1 - 5e^{-4} \approx 0.908$.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: easy

Q39.

Answer: A

Solution:

PGF of Poisson(λ): $G(z) = E[z^X] = \exp(\lambda(z-1))$.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: easy

Q40.

Answer: A

Solution:

$F_{12} = 1$ for sphere to infinite enclosure.

Subject: Heat Transfer | Topic: Heat Transfer | Difficulty: moderate

Q41.

Answer: A

Solution:

$\mu_{\text{water}}(20^\circ\text{C}) \approx 10^{-3} \text{ Pa}\cdot\text{s}$ or 1 cP.

Subject: Fluid Mechanics | Topic: Fluid Mechanics | Difficulty: easy

Q42.

Answer: A

Solution:

$Q = kA \Delta T/L = 0.5 \times 10 \times 50/0.2 = 1250 \text{ W}$.

Subject: Heat Transfer | Topic: Heat Transfer | Difficulty: moderate

Q43.

Answer: B

Solution:

$\delta_{99} = 5x/\sqrt{\text{Re}} = 5 \times 1000/\sqrt{5 \times 10^5} = 7.07 \text{ mm}$. δ_{99} (99%) approx 7mm. Close to B.

Subject: Fluid Mechanics | Topic: Fluid Mechanics | Difficulty: difficult

Q44.

Answer: A

Solution:

$$W = nRT \ln(V_2/V_1) = 8.314 \cdot 300 \cdot \ln(2) = 2494.2 \cdot 0.693 = 1729 \text{ J.}$$

Subject: Thermodynamics | Topic: Thermodynamics | Difficulty: easy

Q45.

Answer: A

Solution:

$$\eta = 1 - 300/600 = 0.5. W = 0.5 \cdot 1000 = 500 \text{ J.}$$

Subject: Thermodynamics | Topic: Thermodynamics | Difficulty: moderate

Q46.

Answer: A

Solution:

$$R_{th} = L/(k \cdot A).$$

Subject: Heat Transfer | Topic: Heat Transfer | Difficulty: moderate

Q47.

Answer: B

Solution:

Mayer's relation: $C_p - C_v = R$ for ideal gas.

Subject: Thermodynamics | Topic: Thermodynamics | Difficulty: moderate

Q48.

Answer: B

Solution:

Tresca (max shear stress): ductile materials.

Subject: Manufacturing | Topic: Manufacturing | Difficulty: easy

Q49.

Answer: B

Solution:

Joule heating: $H = I^2 \cdot R \cdot t$. Heat proportional to I^2 .

Subject: Manufacturing | Topic: Manufacturing | Difficulty: moderate

Q50.

Answer: B

Solution:

Otto: $\eta = 1 - r^{-(1-\gamma)}$. Depends on compression ratio r and γ .

Subject: Thermodynamics | Topic: Thermodynamics | Difficulty: difficult

Q51.

Answer: A

Solution:

$$E = \sigma \cdot T^4 = 5.67 \cdot 10^{-8} \cdot 10^4 = 5.67 \cdot 10^0 = 5.67 \text{ kW/m}^2.$$

Subject: Heat Transfer | Topic: Heat Transfer | Difficulty: moderate

Q52.

Answer: A

Solution:

$$L\{t \cdot f(t)\} = -d/ds(F(s)). F(s) = 1/(s+2). -d/ds[1/(s+2)] = 1/(s+2)^2.$$

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: difficult

Q53.

Answer: A

Solution:

$$f(i) = i^2 + 3i + 2 = -1 + 3i. \operatorname{Re}(f(i)) = -1.$$

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: moderate

Q54.

Answer: A

Solution:

$$\text{Vertical plate laminar: } Nu = 0.59 \cdot (Gr \cdot Pr)^{0.25}.$$

Subject: Heat Transfer | Topic: Heat Transfer | Difficulty: difficult

Q55.

Answer: A

Solution:

$L\{e^{(-at)}\} = 1/(s+a)$. Here $a=3$: $1/(s+3)$.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: easy

Q56.

Answer: B

Solution:

$dy/y = dx/x$. $\ln(y) = \ln(x) + C$. $y = C*x$. Wait: $y \, dx = x \, dy \Rightarrow dy/y = dx/x \Rightarrow \ln y = \ln x + C \Rightarrow y = C*x$. That's option A. Hmm, let me check: $y \, dx - x \, dy = 0 \Rightarrow y \, dx = x \, dy \Rightarrow dy/y = dx/x \Rightarrow y = C*x$. Answer: A.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: moderate

Q57.

Answer: A

Solution:

Eigenvalues of A^2 are 1, 4, 9. Trace = sum = $1+4+9 = 14$.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: moderate

Q58.

Answer: A

Solution:

Lathe: workpiece rotates, static tool feeds.

Subject: Manufacturing | Topic: Manufacturing | Difficulty: difficult

Q59.

Answer: C

Solution:

$d/dx[\ln(\sin x / \cos^2 x)] = \cot x + 2\tan x$. At $\pi/4$: $1 + 2 = 3$. Hmm. Let me recalc: $d/dx \ln(\sec x) = \tan x$. $d/dx \ln(\tan x) = \sec^2 x / \tan x = 1/(\sin x \cos x) = 2\csc(2x)$. At $\pi/4$: $1 + 2 = 3$. Not in options. The derivative of $\ln(\sec x * \tan x) = d/dx[\ln(\sin x / \cos^2 x)] = \cot x + 2\tan x$. At $\pi/4$: $1+2=3$. Hmm.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: moderate

Q60.

Answer: B

Solution:

$Bi < 0.1$: lumped capacitance valid.

Subject: Heat Transfer | Topic: Heat Transfer | Difficulty: moderate

Q61.

Answer: A

Solution:

$|\langle u, v \rangle| \leq \|u\| * \|v\|$. Equality when u and v are linearly dependent.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: easy

Q62.

Answer: B

Solution:

Grashof + fixed shortest: crank-rocker mechanism.

Subject: Theory of Machines | Topic: Theory of Machines | Difficulty: difficult

Q63.

Answer: B

Solution:

Total head = $P/\rho + V^2/2 + gz$.

Subject: Fluid Mechanics | Topic: Fluid Mechanics | Difficulty: moderate

Q64.

Answer: B

Solution:

$\text{proj} = ((v \cdot w)/(w \cdot w)) * w = (4/5) * (2, 1, 0) = (8/5, 4/5, 0)$.

Subject: Engineering Mathematics | Topic: Engineering Mathematics | Difficulty: moderate

Q65.

Answer: C

Solution:

$$C = I \cdot \omega_s \cdot \omega_p = 2 \cdot 314.16 \cdot 20 = 12566 \text{ Nm.}$$

Subject: Theory of Machines | Topic: Theory of Machines | Difficulty: easy

PAPER BLUEPRINT

Subject Distribution:

Engineering Mathematics: 12 questions, 23 marks
Thermodynamics: 9 questions, 14 marks
Heat Transfer: 8 questions, 14 marks
Fluid Mechanics: 9 questions, 12 marks
Manufacturing: 6 questions, 11 marks
Theory of Machines: 7 questions, 9 marks
SOM: 4 questions, 7 marks
General Aptitude: 2 questions, 2 marks
Strength of Materials: 2 questions, 2 marks
Manufacturing Processes: 2 questions, 2 marks
Engineering Mechanics: 2 questions, 2 marks
Machine Design: 2 questions, 2 marks

Difficulty Distribution:

Easy: 23 | Moderate: 30 | Difficult: 12

Statistics:

Total Questions: 65
Total Marks: 100

This blueprint is generated from the actual question distribution in this paper.