ESP32 WROOM 32E + Camera Extension Pinout												
	IO13	IO12	IO14	1027	1026	1025	1033	1032	135	134	139	136
PWM Output												
Input/Output												
Input Only												
Analog	ADC2_4	ADC2_5	ADC2_6	ADC2_7	ADC2_9	ADC2_8	ADC1_5	ADC1_4	ADC1_7	ADC1_6	ADC1_3	ADC1_0
<b>Touch Sensor</b>	TOUCH_4	TOUCH_5	TOUCH_6	TOUCH_7			TOUCH_8	TOUCH_9				
DAC					DAC_2	DAC_1						
I2C												
UART												
SPI	H_MOSI	H_MISO	H_CLK									
LED												
Strapping												
SD	DAT3	DAT2	CLK									
Camera												
Pull-up 47K Resistor												
Pull-up 4.7K resistor												
Pull-down 1K resistor												

ESP32 WROOM 32E + Camera Extension Pinout												
	IO15	102	100	104	105	IO18	IO19	1021	RXD	TXD	1022	1023
PWM Output												
Input/Output												
Input Only												
Analog	ADC1_0	ADC2_3	ADC2_2	ADC2_1	ADC2_0							
<b>Touch Sensor</b>	TOUCH_3	TOUCH_2	TOUCH_1	TOUCH_0								
DAC												
I2C								SDA			SCL	
UART									RXD	TXD		
SPI	H_CS				V_CS	V_CLK	V_MISO					V_MOSI
LED		LED										
Strapping												
SD	CMD	DAT0		DAT1								
Camera												
Pull-up 47K Resistor												
Pull-up 4.7K resistor												
Pull-down 1K resistor												