

Exp No: 1

Flashing of led using at89c51 microcontroller using proteus

AIM:

To Write an assembly language program to flash the LED using AT89C51

SOFTWARES REQUIRED:

- Proteus software

PROGRAM

```
ORG 0000H
```

```
UP: SETB P2.0
```

```
ACALL DELAY
```

```
CLR P2.0
```

```
ACALL DELAY
```

```
SJMP UP
```

```
DELAY: MOV R4,#35
```

```
H1:MOV R3,#255
```

```
H2:DJNZ R3,H2
```

```
DJNZ R4,H1
```

```
RET
```

```
END
```

OUTPUT

