Rajalakshmi Engineering College

Name: syed mohammed hussain

Email: 241801288@rajalakshmi.edu.in

Roll no: 241801288 Phone: 9363281289

Branch: REC

Department: I AI & DS FD

Batch: 2028

Degree: B.E - AI & DS



NeoColab_REC_CS23231_DATA STRUCTURES

REC_DS using C_Week 3_COD_Question 3

Attempt : 1 Total Mark : 10 Marks Obtained : 10

Section 1: Coding

1. Problem Statement

Sharon is developing a programming challenge for a coding competition.

The challenge revolves around implementing a character-based stack data structure using an array.

Sharon's project involves a stack that can perform the following operations:

Push a Character: Users can push a character onto the stack.Pop a Character: Users can pop a character from the stack, removing and displaying the top character.Display Stack: Users can view the current elements in the stack.Exit: Users can exit the stack operations application.

Write a program to help Sharon to implement a program that performs the given operations.

Input Format

The input consists of integers corresponding to the operation that needs to be performed:

Choice 1: Push the character onto the stack. If the choice is 1, the following input is a space-separated character, representing the character to be pushed onto the stack.

Choice 2: Pop the character from the stack.

Choice 3: Display the characters in the stack.

Choice 4: Exit the program.

Output Format

The output displays messages according to the choice and the status of the stack:

- 1. If the choice is 1, push the given character to the stack and display the pushed character having the prefix "Pushed: ".
- 2. If the choice is 2, undo the character from the stack and display the character that is popped having the prefix "Popped: ".
- 3. If the choice is 2, and if the stack is empty without any characters, print "Stack is empty. Nothing to pop."
- 4. If the choice is 3, print the elements in the stack having the prefix "Stack elements: ".
- 5. If the choice is 3, and there are no characters in the stack, print "Stack is empty."
- 6. If the choice is 4, exit the program.
- 7. If any other choice is entered, print "Invalid choice"

Refer to the sample output for formatting specifications.

Sample Test Case

Input: 2

4

Output: Stack is empty. Nothing to pop.

Answer

#include <stdio.h>

```
24,801288
                                                    24,180,1288
    #include <stdbool.h>
#define MAX_SIZE 100
    char items[MAX_SIZE];
    int top = -1;
    void initialize() {
      top = -1;
    bool isFull() {
       return top == MAX_SIZE - 1;
                                                                              241801288
    bool isEmpty() {
      return top == -1;
    void push(char ch) {
      if (top >= MAX_SIZE - 1) {
         printf("Stack overflow\n");
         return;
      items[++top] = ch;
                                                                              24,80,1288
                                                    241801288
      printf("Pushed: %c\n", ch);
    void pop() {
      if (top == -1) {
         printf("Stack is empty. Nothing to pop.\n");
      } else {
         printf("Popped: %c\n", items[top--]);
      }
    }
241801288
                                                    241801288
        printf("Stack is empty.\n");
```

```
24,180,1288
         printf("Stack elements: ");
          for (int i = top; i >=0; i--) {
            printf("%c ", items[i]);
          printf("\n");
       }
     }
     int main() {
        initialize();
        int choice;
        char value;
        while (true) {
       scanf("%d", &choice);
          switch (choice) {
            case 1:
               scanf(" %c", &value);
               push(value);
               break;
            case 2:
               pop();
               break;
            case 3:
               display();
break case 4:
               break;
                                                        24,180,1288
               return 0;
               printf("Invalid choice\n");
        }
        return 0;
     }
```

Status: Correct Marks: 10/10

24,180,1288

24,301,288

24,180,1288

24,80,1288

241801288

24,180,1288