Register maps

BACnet points by controller · built Nov 13, 2026

BACnet points by controller

What each T3 model exposes as BACnet objects, and how many of each. The object names are the ones the controller publishes, so they can be matched against a point list read from the device.

T3-BB

Item	Value	Notes
Controller	T3-BB Big Brother	Range
Total Channels	56	
Universal Input	32	
ANALOG_INPUT1 (IN1)	Select "Analog Units" or "No Units"for the corresponding Inputs	ANALOG_INPUT32 (IN32)
BINARY_INPUT1 (IN1)	Select "Digital Units" for the corresponding Inputs	BINARY_INPUT32 (IN32)
Relay Output	12	
BINARY_OUTPUT1 (OUT1)	Select "Digital Units"for the corresponding Outputs	BINARY_OUTPUT12 (OUT12)
Analog Output	12	
ANALOG_OUTPUT13 (OUT13)	Select "Analog Units"for the corresponding Outputs	ANALOG_OUTPUT24 (OUT24)
Variable	128	
ANALOG_VALUE1 VAR1	Select "Analog Units"for the corresponding VAR	ANALOG_VALUE128 VAR128
BINARY_VALUE1 VAR1	Select "Digital Units"for the corresponding VAR	BINARY_VALUE128 VAR128

T3-LB

Item	Value	Notes
Controller	T3-LB Little Brother	Range
Total Channels	26	
Universal Input	16	
ANALOG_INPUT1 (IN1)	Select "Analog Units" or "No Units"for the corresponding Inputs	ANALOG_INPUT16 (IN16)
BINARY_INPUT1 (IN1)	Select "Digital Units" for the corresponding Inputs	BINARY_INPUT16 (IN16)
Relay Output	6	
BINARY_OUTPUT1 (OUT1)	Select "Digital Units"for the corresponding Outputs	BINARY_OUTPUT6 (OUT6)
Analog Output	4	
ANALOG_OUTPUT7 (OUT7)	Select "Analog Units"for the corresponding Outputs	ANALOG_OUTPUT10 (OUT10)
Variable	128	
ANALOG_VALUE1 VAR1	Select "Analog Units"for the corresponding VAR	ANALOG_VALUE128 VAR128
BINARY_VALUE1 VAR1	Select "Digital Units"for the corresponding VAR	BINARY_VALUE128 VAR128

T3-TB

Item	Value	Notes
Controller	T3-TB Tiny Brother	Range
Total Channels	22	
Universal Input	8	
ANALOG_INPUT1 (IN1)	Select "Analog Units" or "No Units"for the corresponding Inputs	ANALOG_INPUT32 (IN32)
BINARY_INPUT1 (IN1)	Select "Digital Units" for the corresponding Inputs	BINARY_INPUT32 (IN32)
Relay Output	8	
BINARY_OUTPUT1 (OUT1)	Select "Digital Units"for the corresponding Outputs	BINARY_OUTPUT8 (OUT8)
Analog Output	6	
ANALOG_OUTPUT9 (OUT9)	Select "Analog Units"for the corresponding Outputs	ANALOG_OUTPUT14 (OUT14)
Variable	128	
ANALOG_VALUE1 VAR1	Select "Analog Units"for the corresponding VAR	ANALOG_VALUE128 VAR128
BINARY_VALUE1 VAR1	Select "Digital Units"for the corresponding VAR	BINARY_VALUE128 VAR128