



Tertiary Infotech Academy Pte Ltd

UEN: 201200696W

LEARNER GUIDE

For

Internet of Things (IoT) Fundamental for Beginners

TGS Ref No: TGS-2020504020

Conducted by

Tertiary Infotech Academy Pte Ltd

UEN: 201200696W

Version 13

DOCUMENT VERSION CONTROL RECORD

Version Number	Effective Date of Release	Summary of Included Changes	Author
12	1 March 2025	Previous release — ThingSpeak/ESP8266/Node-RED based courseware.	Dr. Alfred Ang
13	6 July 2026	Revamped to the IoTFlow platform (iot.tertiaryinfotech.com): 6 labs covering device registration, MQTT/HTTP telemetry, virtual-pin remote control, dashboards and n8n + AI automation.	Dr. Alfred Ang

TABLE OF CONTENTS

Introduction.....	4
Skills Framework.....	4
Course Learning Outcomes.....	4
Key IoT Concepts at a Glance.....	5
Before You Start — IoTFlow Platform Setup.....	5
Topic 01 — Overview of Internet of Things (IoT) (A1, K1, K4).....	6
Topic 02 — Collect and Post Data to Cloud (A2, K3).....	6
Lab 1 — Register Your First Device on IoTFlow.....	6
Lab 2 — Send Sensor Readings to the Cloud (HTTP & MQTT).....	8
Topic 03 — Read Data and Remote Control from Cloud (A3, K2).....	10
Lab 3 — Read Device Data from the Cloud (REST API & MQTT).....	11
Lab 4 — Remote Control a Device with Dashboard Virtual Pins.....	12
Topic 04 — IoT Data Analytics and Visualization (A4, K5, K6).....	14
Lab 5 — Build a Real-Time IoT Dashboard.....	14
Lab 6 — Automate with n8n — Triggers, Workflows and AI.....	16
After the Course.....	18
Glossary.....	18

Introduction

This Learner Guide accompanies the WSQ course Internet of Things (IoT) Fundamental for Beginners (TGS-2020504020), conducted by Tertiary Infotech Academy Pte Ltd. It provides step-by-step instructions for all 6 hands-on labs, organised by the four course topics. Every lab runs on our IoT platform IoTFlow (<https://iot.tertiaryinfotech.com>) and mirrors an official platform tutorial (<https://iot.tertiaryinfotech.com/tutorials>), so you can repeat the same steps any time after class.

Use this guide alongside the course slides and the lab files in the labs/ folder of the course repository. No hardware is required — every lab can be completed with cURL or Python from any terminal — but an ESP32/ESP8266 or Raspberry Pi makes the experience real.

Course page: <https://www.tertiarycourses.com.sg/wsq-internet-of-things-iot-fundamental-for-beginners.html>

Skills Framework

This course is mapped to the Skills Framework TSC Internet of Things Application (PTP-TEM-3002-1.1).

TSC Abilities

- A1: Conduct briefings on the uses and functions of IoT technologies adopted by the organisation
- A2: Review IoT testing results and identify areas for improvement
- A3: Integrate information from multiple data sources
- A4: Review data to produce insights of business value

TSC Knowledge

- K1: Concept of Internet of Things (IoT)
- K2: Types and functionalities of IoT devices
- K3: Types of circuits and sensors within devices
- K4: Types of wireless communication technologies
- K5: Data analytics techniques
- K6: Concept of cybersecurity

Course Learning Outcomes

- LO1: Understand the uses and functions of IoT technologies
- LO2: Post sensor data to cloud for IoT review
- LO3: Control devices from cloud data sources
- LO4: Data analytics and visualization on cloud to gain business insight

Key IoT Concepts at a Glance

- **Devices** — Hardware — sensors, gadgets, appliances and machines — that collect and exchange data over the internet.
- **Sensors** — The input side: they measure a physical quantity (temperature, humidity, motion, gas, light).
- **Actuators** — The output side: relays, motors, pumps, valves and LEDs that act on the physical world.
- **Triggers** — Rules that turn readings into events — a threshold crossed or a device going offline fires an action.
- **n8n automation** — A low-code workflow tool: device events fire flows that notify, log, call AI or control devices back.
- **Workflows** — Chains of n8n nodes wired together — each node does one job (trigger, transform, notify, store, AI).
- **AI** — AI nodes inside workflows summarise readings, detect anomalies and recommend actions — analytics with zero code.
- **Dashboard for control** — Web/mobile panels of widgets: display widgets show data; control widgets write virtual pins to command devices.

Before You Start — IoTFlow Platform Setup

What you need

- A free account on IoTFlow — sign up at <https://iot.tertiaryinfotech.com>.
- A modern browser. The dashboard is an installable PWA that also works on your phone.
- Optional hardware: ESP32 / ESP8266 / Raspberry Pi with a DHT temperature-humidity sensor.
- Access to an n8n instance for Lab 6 (cloud or self-hosted).

How the platform works

- **Connect** — flash the wizard snippet to your ESP32 / Arduino / Pi. It streams data over MQTT or HTTP.
- **Visualise & Control** — compose a dashboard of charts, gauges, buttons & sliders, on web and mobile.
- **Automate with n8n** — device events fire n8n flows that notify, control devices back, log data or call AI.

Conventions used in every lab

- Your device token (dev_...) is shown ONCE at registration — store it safely and never share it.
- Every API call authenticates with the header: Authorization: Bearer dev_XXXXXXXXXXXX

- MQTT broker: iot.tertiaryinfotech.com, port 1883. REST endpoint: `/api/telemetry`.
- Each lab mirrors a platform tutorial at <https://iot.tertiaryinfotech.com/tutorials> — revisit them any time.

Topic 01 — Overview of Internet of Things (IoT) (A1, K1, K4)

What is IoT · Devices, Sensors & Actuators · Triggers · Wireless Technologies · Use Cases

Key concepts

- IoT is the network of physical devices embedded with sensors, software and connectivity that collect and exchange data over the internet.
- A device senses the world with sensors (input) and acts on it with actuators (output) — a trigger turns a reading into an event that starts an action.
- Wireless technologies (Wi-Fi, Bluetooth, Zigbee, LoRaWAN, NB-IoT, 5G) connect constrained devices to the cloud.
- IoT powers smart homes, agriculture, healthcare, manufacturing, logistics, retail and smart cities.

Note: This topic is delivered through concepts, diagrams and trainer demonstrations — the hands-on labs begin in Topic 02.

Topic 02 — Collect and Post Data to Cloud (A2, K3)

Cloud & IoT Platforms · IoTFlow · Device Registration · MQTT & HTTP Telemetry

Key concepts

- The cloud stores and processes IoT data at scale — devices stream telemetry to an IoT platform instead of a single computer.
- IoTFlow (iot.tertiaryinfotech.com) is our low-code IoT platform: connect ESP32/Arduino/Pi over MQTT or HTTP, visualise, control and automate.
- Every device authenticates with a device token (Authorization: Bearer dev_...) issued once at registration.
- Telemetry is a simple JSON document of metric key-value pairs, e.g. `{"temperature": 22.5, "humidity": 60}`.

Lab 1 — Register Your First Device on IoTFlow

Learning outcome: Post sensor data to cloud for IoT review — register a device (LO2).

Goal: The learner signs in to the IoTFlow platform, creates a project workspace, runs the Add Device wizard, chooses a protocol (HTTP or MQTT) and obtains the device token used to authenticate every message the device sends.

What you'll build

A registered IoT device in your own IoTFlow project, with its device token saved (Uses: IoTFlow projects, Add Device wizard, device tokens, MQTT & HTTP protocols.)

IoTFlow

Features How it works Tutorials Blog Industries Contact

Log in Sign up

← All tutorials

Tutorial 1 of 5 ~2 min

Add your first device

Register a device and get the token it uses to talk to the platform.

- 1 Pick or create a project**

Every device lives in a project — a self-contained workspace with its own dashboard, alerts, map and automations. Use the project switcher at the top of the sidebar to pick one, or create a new project first.
- 2 Open the Add Device wizard**

Click Add Device in the sidebar and give your device a friendly name (e.g. "Living Room Sensor"). The 6-step wizard walks you through the rest.

The guided Add Device wizard.
- 3 Choose a protocol**

Pick HTTP (simplest — POST JSON to a REST endpoint) or MQTT (lightweight pub/sub, ideal for many devices and real-time control). You can change this later; both are always available.
- 4 Copy the device token**

When the device is created you get a device token (starts with dev_). Copy it now — it is shown only once. Your device sends this token to authenticate every message.

Authorization: Bearer dev_XXXXXXXXXX

Next
Send your first reading →

© 2026 Tertiary Infotech Academy Pte Ltd. All rights reserved. · UEN 201200696W · Powered by Tertiary Infotech Academy Pte Ltd

Platform walkthrough for Lab 1 — Register Your First Device on IoTFlow

Step-by-step

1. Open the IoTFlow platform and sign up for a free account (or log in).

<https://iot.tertiaryinfotech.com> → Sign up → Log in

2. Pick or create a project — a self-contained workspace with its own dashboard, alerts, map and automations. Use the project switcher at the top of the sidebar.
3. Click Add Device in the sidebar and give your device a descriptive name.

Device name: `Living Room Sensor`

4. Follow the six-step guided wizard and choose a protocol: HTTP — simplest, POST JSON to a REST endpoint; or MQTT — lightweight pub/sub, ideal for many devices and real-time control. Both remain available later.
5. Copy the device token shown when the device is created — it is displayed only once.

`dev_XXXXXXXXXXXX`

6. Understand how the token authenticates every message your device sends.

Authorization: `Bearer dev_XXXXXXXXXXXX`

Test it

The new device appears in your project's device list, and the Integrate page shows code snippets pre-filled with your endpoint and device token.

Note: This lab mirrors the platform tutorial at <https://iot.tertiaryinfotech.com/tutorials/add-your-first-device> — the full lab sheet is `labs/lab-01-register-your-first-device-on-iotflow.md` in the course repository.

Lab 2 — Send Sensor Readings to the Cloud (HTTP & MQTT)

Learning outcome: Post sensor data to cloud for IoT review — send telemetry (LO2).

Goal: The learner pushes sensor values to the IoTFlow telemetry API three ways — cURL from any terminal, the Python client, and an ESP32/ESP8266 over MQTT — and watches the readings appear live on the dashboard.

What you'll build

Live temperature & humidity telemetry streaming into IoTFlow from terminal, Python and ESP32 (Uses: Telemetry REST API, Python `iotflow` client, ESP32/ESP8266 Arduino library, MQTT broker (port 1883).)


[Features](#)
[How it works](#)
[Tutorials](#)
[Blog](#)
[Industries](#)
[Contact](#)


[Log in](#)
[Sign up](#)

[← All tutorials](#)



Tutorial 2 of 5
1~5 min

Send your first reading

Push a sensor value from an ESP32, Arduino or Raspberry Pi — or from any terminal — and watch it appear live.

- Open the Integrate guide**

Inside the app, the Integrate page gives you copy-paste snippets with your endpoint already filled in — cURL, Python and ESP32.


- Send over HTTP (works from anything)**

The simplest test: POST a JSON body with your device token. Run this from any terminal.

```
curl -X POST https://YOUR-HOST/api/telemetry \
-H "Authorization: Bearer dev_YOUR_DEVICE_TOKEN" \
-H "Content-Type: application/json" \
-d '{"temperature": 22.5, "humidity": 60}'
```
- Or use the one-file Python client**

On a Raspberry Pi or PC, download `iotflow.py` (no pip install needed for HTTP) and send readings in two lines.

```
from iotflow import IoTFlow
iot = IoTFlow("https://YOUR-HOST", "dev_YOUR_DEVICE_TOKEN", "your-device-id")
iot.send(temperature=22.5, humidity=60)
```
- Or ESP32 / ESP8266 over MQTT**

With the optional IoTFlow Arduino library, report readings with `virtualWrite()` — bind a widget to the metric name (e.g. temperature).

```
iot.setServer("BROKER_HOST", 1883);
iot.setDevice("your-device-id", "dev_YOUR_DEVICE_TOKEN");
iot.begin();
iot.virtualWrite("temperature", 22.5);
```

Platform walkthrough for Lab 2 — Send Sensor Readings to the Cloud (HTTP & MQTT)

Step-by-step

- Open the Integrate page for your device — every snippet comes pre-filled with your endpoint and device token.
- Send your first reading from any terminal with cURL (HTTP POST).

```
curl -X POST https://iot.tertiaryinfotech.com/api/telemetry \
-H "Authorization: Bearer dev_XXXXXXXXXXXX" \
```

```
-H "Content-Type: application/json" \  
-d '{"temperature": 22.5, "humidity": 60}'
```

9. Open the Dashboard — the reading appears under Latest Telemetry within seconds (widgets auto-refresh every 5 s).
10. Send readings from Python using the lightweight `iotflow.py` client (plain HTTP — no `pip` install needed).

```
client = IoTFlow(host, device_token, device_id)  
client.send(temperature=23.1, humidity=58)
```

11. For real hardware: flash the ESP32/ESP8266 Arduino sketch — set your Wi-Fi SSID/password, the broker host (port 1883) and your device credentials.

```
IoTFlow.virtualWrite("temperature", t); // metric name binds to dashboard  
widgets
```

12. Let the device publish continuously and confirm the values update live on the dashboard.

Test it

Each value you send appears in the Dashboard's Latest Telemetry within seconds, and the device's telemetry history grows with every reading.

Note: This lab mirrors the platform tutorial at <https://iot.tertiaryinfotech.com/tutorials/send-your-first-reading> — the full lab sheet is `labs/lab-02-send-sensor-readings-to-the-cloud-http-mqtt.md` in the course repository.

Topic 03 — Read Data and Remote Control from Cloud (A3, K2)

Read via REST API & MQTT · Virtual Pins · Dashboard Control · Alerts & Triggers

Key concepts

- Reading from the cloud integrates data sources: REST GET for state and history, MQTT subscribe for real-time push.
- Virtual pins (V1, relay, pump ...) are named keys that dashboard control widgets write to — buttons, switches, sliders and terminals.
- Devices receive downlink commands on the MQTT topic `devices/<id>/down`, or by HTTP-polling GET `/api/device/state`.
- Alert rules fire on metric thresholds or device-offline, and can hand off to an n8n automation.


Lab 3 — Read Device Data from the Cloud (REST API & MQTT)

Learning outcome: Control devices from cloud data sources — read data (LO3).

Goal: The learner reads device data back out of the cloud — the latest state over the REST API, real-time messages by subscribing to the device's MQTT topics, and per-device telemetry history on the platform — integrating data from multiple sources.

What you'll build

A terminal and Python session reading live device state and streaming MQTT messages (Uses: REST API (GET /api/device/state), MQTT subscribe (devices/<id>/down), telemetry history.)



Platform walkthrough for Lab 3 — Read Device Data from the Cloud (REST API & MQTT)

Step-by-step

13. Read your device's latest state from any terminal over the REST API.

```
curl https://iot.tertiaryinfotech.com/api/device/state \
-H "Authorization: Bearer dev_XXXXXXXXXXXXX"
```

14. Inspect the JSON reply — the platform returns the current value of every metric and virtual pin.

15. Subscribe to your device's MQTT downlink topic to watch commands and data arrive in real time.

```
mosquitto_sub -h iot.tertiaryinfotech.com -p 1883 \
  -u device -P dev_XXXXXXXXXXXX -t "devices/<id>/down" -v
```

16. Send a fresh reading (Lab 2) and watch it flow through — uplink telemetry vs downlink commands.
17. Open the device page on IoTFlow and review its per-device telemetry history and active alerts.
18. Read the same state from Python and print the values — this is how any external app integrates IoT data.

```
r = requests.get(f"{host}/api/device/state",
  headers={"Authorization": f"Bearer {token}"})
print(r.json())
```

Test it

The REST call returns the same values shown on the dashboard, and the MQTT subscription prints messages the moment they are published.

Note: This lab mirrors the platform tutorial at <https://iot.tertiaryinfotech.com/tutorials> — the full lab sheet is `labs/lab-03-read-device-data-from-the-cloud-rest-api-mqtt.md` in the course repository.

Lab 4 — Remote Control a Device with Dashboard Virtual Pins

Learning outcome: Control devices from cloud data sources — remote control (LO3).

Goal: The learner adds Control widgets (button, switch, slider, terminal) bound to virtual pins, implements the device-side command handler, and flips a relay/LED live from the dashboard — Blynk-style two-way control.

What you'll build

A dashboard switch and slider that control a relay/LED on the device in real time (Uses: Control widgets (Button, Switch, Slider, Terminal), virtual pins, MQTT downlink, HTTP polling.)


[Features](#)
[How it works](#)
[Tutorials](#)
[Blog](#)
[Industries](#)
[Contact](#)


[Log in](#)
[Sign up](#)

[← All tutorials](#)




Tutorial 4 of 5
5 min

Control a device

Flip a relay or LED, or set a value, straight from the dashboard using Blynk-style virtual pins.

- ### Add a control widget

On the Dashboard → Add widget, choose a Control type: Button (momentary), Switch (toggle), Slider (value) or Terminal (text).




Control widgets live in the same Add widget dialog.
- ### Choose a virtual pin

Give the control a virtual pin name — e.g. V1, relay or pump. This is the key your device listens on. For a slider, set the min and max.
- ### Make your device react

Your device receives commands on MQTT topic devices/<id>/down, or HTTP-only devices poll GET /api/device/state. Act on the (pin, value) message — the equivalent of Blynk's BLYNK_WRITE.

```
void onCommand(const String& pin, float value, const String& text) {
  if (pin == "V1") digitalWrite(RELAY_PIN, value > 0 ? HIGH : LOW);
}
```
- ### Toggle from the dashboard

Flip the Switch or drag the Slider — the command is persisted and delivered to your device instantly (and it also fires a COMMAND automation you can hook into n8n).



Platform walkthrough for Lab 4 — Remote Control a Device with Dashboard Virtual Pins

Step-by-step

- On the Dashboard click Add widget and choose a Control type: Button (momentary), Switch (toggle), Slider (value) or Terminal (text).
- Assign the virtual pin the widget writes to — e.g. V1, relay or pump. For a slider also set the min/max range.

Virtual pin: V1

21. Understand the downlink path — devices receive commands via MQTT on their command topic, or by HTTP polling.

MQTT topic: `devices/<id>/down` HTTP: `GET /api/device/state`

22. Implement the command handler in your device sketch and map pins to GPIO outputs.

```
void onCommand(const String& pin, float value, const String& text) {  
    if (pin == "V1") digitalWrite(RELAY_PIN, value > 0 ? HIGH : LOW);  
}
```

23. Flip the switch and move the slider on the dashboard — commands are delivered to the device immediately.

24. Observe the relay/LED respond, and note that the same events can also trigger automations (Lab 6).

Test it

Toggling the dashboard switch changes the relay/LED state within a second, and the slider value arrives in the `onCommand` handler as you drag it.

Note: This lab mirrors the platform tutorial at <https://iot.tertiaryinfotech.com/tutorials/control-a-device> — the full lab sheet is `labs/lab-04-remote-control-a-device-with-dashboard-virtual-pins.md` in the course repository.

Topic 04 — IoT Data Analytics and Visualization (A4, K5, K6)

Dashboards & Widgets · n8n Workflow Automation · AI Analytics · IoT Cybersecurity

Key concepts

- Dashboards turn raw readings into number cards, gauges, line/bar charts, LED indicators and maps that auto-refresh.
- n8n is a low-code workflow automation tool: a device event triggers a flow of nodes that notify, log, call AI or control devices back.
- AI nodes in a workflow summarise readings, detect anomalies and generate recommendations — analytics with zero code.
- IoT security matters because the cyber and physical worlds converge: spoofing, tampering, eavesdropping, DoS and elevation of privilege.

Lab 5 — Build a Real-Time IoT Dashboard

Learning outcome: Data analytics and visualization on cloud — dashboards (LO4).

Goal: The learner turns raw readings into a live dashboard — number cards, gauges, line/bar charts, LED indicators, device status and maps — arranged on a responsive grid that auto-refreshes.

What you'll build

A monitoring dashboard with a number card, gauge, chart, LED indicator and map
(Uses: Display widgets: number card, gauge, line/bar chart, LED, device status, alert list, map.)

The screenshot displays the IoTFlow web interface. At the top, there's a navigation bar with the IoTFlow logo, links for Features, How it works, Tutorials, Blog, Industries, and Contact, and buttons for Log in and Sign up. Below this, a breadcrumb trail shows 'All tutorials' and 'Tutorial 3 of 5' (estimated 3 minutes). The main heading is 'Build a dashboard', with a subtext 'Turn raw readings into number cards, gauges, charts, LEDs and maps.'.

The tutorial is divided into four numbered steps:

- Click "Add widget"**
On the Dashboard, click Add widget. Widgets are grouped into Display (show data) and Control (send commands).
The screenshot shows a modal window titled 'Add widget' with a 'Widget type' dropdown set to 'Number card'. It also has fields for 'Title (optional)' (e.g., Warehouse Temp) and 'Device' (a dropdown menu). Buttons for 'Cancel' and 'Add widget' are at the bottom.
- Choose a display type**
Pick a Number card, Gauge, Line/Bar chart, LED indicator, Device status, Alert list or Map — whatever suits the reading.
- Bind a device and metric**
Select the device and the metric to show (e.g. temperature). For gauges you can set a min and max. Give the widget a title and add it.
- Arrange your dashboard**
Add as many widgets as you like — they tile into a responsive grid and refresh automatically. Remove one with the trash icon on its card.

The bottom part of the screenshot shows the final dashboard layout. It features a sidebar with navigation options like Warehouse Monitoring, Tutorial, Dashboard, Projects, Devices, Add Device, Integrate, Telemetry, Alerts, Automations, Maps, API Keys, Settings, Admins, Users, Enquiries, and Email & Alerts. The main area displays a 'Welcome back, Demo' message and a grid of widgets: 'Total devices' (3), 'Online' (2), 'Offline' (1), 'Active alerts' (1), 'Latest telemetry' (showing data for Cold Room Monitor, Pump Station 4, and Warehouse Sensor A), and 'Recent activity' (showing an alert for Warehouse Sensor A).

Step-by-step

25. On the Dashboard click Add widget — widgets are grouped into Display (show data) and Control (send commands).
26. Add a Number card: select your device, choose the metric (temperature) and give the widget a title.
27. Add a Gauge for humidity and set sensible min/max bounds (e.g. 0–100 %).
28. Add a Line chart to plot the temperature history over time.
29. Add an LED indicator (on/off state) and a Map widget if your device reports a location.
30. Arrange the layout — widgets snap into a responsive grid, refresh automatically, and can be removed with the trash icon.

Test it

Send fresh readings (Lab 2) and watch every widget — card, gauge and chart — update live within the 5-second auto-refresh.

Note: This lab mirrors the platform tutorial at <https://iot.tertiaryinfotech.com/tutorials/build-a-dashboard> — the full lab sheet is `labs/lab-05-build-a-real-time-iot-dashboard.md` in the course repository.

Lab 6 — Automate with n8n — Triggers, Workflows and AI

Learning outcome: Data analytics and visualization on cloud — n8n automation & AI insight (LO4).

Goal: The learner connects IoTFlow to n8n with a webhook, picks a trigger (telemetry, alert, online/offline, command), then builds a no-code workflow that notifies, logs to a sheet, calls AI for insight and even controls the device back.

What you'll build

An n8n workflow fired by device events: threshold alert → notify + log + AI summary (Uses: IoTFlow Automations, n8n Webhook node, alert rules, Email/Telegram, Google Sheets, AI nodes.)


[Features](#)
[How it works](#)
[Tutorials](#)
[Blog](#)
[Industries](#)
[Contact](#)


[Log in](#)
[Sign up](#)

[← All tutorials](#)



Tutorial 5 of 5
~8 min


Automate with n8n

Run no-code logic when a device event happens — notify, control devices back, log data or call AI.

- Create a webhook in n8n**

In your n8n instance, add a Webhook node to a workflow, activate it, and copy its Production URL. This is where IoTFlow will send matching events.
- Create an automation**


In IoTFlow → Automations → New automation. Give it a name and choose the event that should fire it (Telemetry received, Alert, Device online/offline, or Command).



Linking a device event to an n8n webhook.
- Filter and paste the webhook URL**

Optionally filter by device and metric (e.g. only temperature), then paste the n8n webhook Production URL and save. IoTFlow will POST a normalized event envelope to it.
- Test it, then go live**

Click Test on the automation card to send a sample event — you'll see the delivery status and n8n will run the flow. After that, real device events trigger it automatically. n8n flows can call back to control devices, notify Slack/Email/WhatsApp, log to Sheets, or run AI.



Platform walkthrough for Lab 6 — Automate with n8n — Triggers, Workflows and AI

Step-by-step

- In n8n, add a Webhook node to a new workflow, activate the workflow, and copy the webhook's Production URL.
- In IoTFlow, create a new Automation and choose the trigger type: telemetry received, alert fired, device online/offline, or command sent.
- Optionally narrow the trigger by device and metric (e.g. only temperature), then paste the n8n webhook URL and save.

34. Create an alert rule on a threshold (e.g. temperature > 30) or device-offline, and hand it off to the automation.

Alert rule: `temperature > 30 → fire automation (n8n webhook)`

35. Use Test to send a sample payload to n8n, inspect the JSON the webhook receives, then enable live triggering.
36. In n8n, branch the flow: send an Email/Telegram/WhatsApp notification and append the reading to Google Sheets.
37. Add an AI node to summarise the readings and recommend an action — AI-powered analytics with zero code.
38. Close the loop: add an HTTP Request node that sends a downlink command back to the device (e.g. switch a fan on).

```
POST {host}/api/device/command { "pin": "V1", "value": 1 }
```

Test it

Pushing a reading above the threshold fires the n8n flow: the notification arrives, a row is appended to the sheet, the AI summary is generated, and the device reacts to the command sent back.

Note: This lab mirrors the platform tutorial at <https://iot.tertiaryinfotech.com/tutorials/automate-with-n8n> — the full lab sheet is `labs/lab-06-automate-with-n8n-triggers-workflows-and-ai.md` in the course repository.

After the Course

- Your IoTFlow account and projects remain yours — keep experimenting at <https://iot.tertiaryinfotech.com>.
- Revisit the tutorials at <https://iot.tertiaryinfotech.com/tutorials> to repeat any lab.
- Connect a real ESP32 or Raspberry Pi at home using the Integrate page snippets.
- Extend your n8n flow: WhatsApp alerts, Google Sheets logging, AI agents.
- Assessment: WA (SAQ, 1 hour) + PP (practical, 1 hour), open book, on Day 2 from 4:30 pm.

Glossary

- **IoT** — Internet of Things — the network of physical objects with sensors, software and connectivity that exchange data over the internet.
- **IIoT** — Industrial IoT — IoT applied to industrial sectors such as manufacturing and energy.
- **Telemetry** — The stream of metric readings a device sends to the cloud, as JSON key-value pairs.

- **Device token** — The secret (dev_...) issued once at registration that authenticates every message a device sends.
- **MQTT** — A lightweight publish/subscribe messaging protocol for constrained devices; a broker routes messages by topic.
- **REST API** — An HTTP interface — POST /api/telemetry to write data, GET /api/device/state to read it.
- **Uplink / Downlink** — Uplink = device → cloud telemetry. Downlink = cloud → device commands.
- **Virtual pin** — A named key (V1, relay, pump) that dashboard control widgets write to and device code reacts to — Blynk-style.
- **Widget** — A dashboard building block: number card, gauge, chart, LED, map (display) or button, switch, slider, terminal (control).
- **Trigger** — A rule that fires on an event — telemetry received, threshold crossed, device offline, command sent.
- **Alert rule** — A trigger on a metric threshold or device-offline that tracks active alerts and can hand off to n8n.
- **n8n** — A low-code workflow automation tool with 400+ integrations; flows start from a webhook and run nodes.
- **Webhook** — A URL that starts an n8n workflow when the platform POSTs an event payload to it.
- **Workflow** — A set of n8n nodes wired together that runs automatically on every trigger event.
- **AI node** — A workflow node that calls a language model to summarise, classify or recommend actions from your data.
- **PWA** — Progressive Web App — install the dashboard on your phone's home screen for mobile control.