


rdt_send(data)

```
if (nextseqnum < base+N) {  
    sndpkt[nextseqnum] = make_pkt(nextseqnum,data,chksum)  
    udt_send(sndpkt[nextseqnum])  
    if (base == nextseqnum)  
        start_timer  
    nextseqnum++  
}  
else  
    refuse_data(data)
```

Λ
base=1
nextseqnum=1

rdt_rcv(rcvpkt)
&& corrupt(rcvpkt)



timeout
start_timer
udt_send(sndpkt[base])
udt_send(sndpkt[base+1])
...
udt_send(sndpkt[nextseqnum-1])

rdt_rcv(rcvpkt) &&
notcorrupt(rcvpkt)
base = getacknum(rcvpkt)+1
If (base == nextseqnum)
 stop_timer
else
 start_timer