



It has a body made of brass, a water impeller and a Hall sensor. When water flows through the impeller, it moves the impeller shaft. Its speed changes at different flow rates. The Hall sensor sends a corresponding pulse signal. It can be applied to water heaters, automatic water dispensers mounted on 3/4-inch diameter pipe or other industrial automation projects.

Power	5-18 VDC
Output	NO, OC transistor output (10mA) min. 4.7 VDC (input voltage 5 VDC)
Material	Brass
Assembly	External thread 3/4" Inch
Minumum flow	2L/min
Maximum flow	45L/min
Wire lengh	30 cm
Working pressure	≤ 1,75 MPa - (17 bar)
Working conditions	0 ~ 80°C
Vulume converter	477 imp/L ± 10%

Dimensions

