

ASSIGNMENT 4

Title : Write an Embedded C program to interface PIC18FXXX with LED and blinking it using specified delay

Problem Statement : Write an Embedded C program to interface PIC 18FXXX with LED and blinking it using specified delay

Input:

```
#include<xc.h>

void delay(unsigned int time)
{
    unsigned int i,j;

    for(i=0;i<time;i++)
        for(j=0;j<5000;j++){           //5000 is time in micro seconds
            }
}

void main(void)
{
    TRISB =0x00;      //PORTB set as output port
    LATB  =0xFF;      //0xFF=1

    while(1)          //infinite loop
    {
        LATB=~LATB;
        delay(200);
    }
}
```