

Switching Voltage Regulator PCB Design Report

Assignment II: 12V to 5V Buck Converter

Yanis MAILLARD

June 2, 2026

Contents

1	Introduction	2
2	Working Principle of the Buck Converter	2
3	Component Selection	2
4	Low-Noise PCB Layout Rationale	2
4.1	Short High-Current Loops	3
4.2	Switch Node Optimization	3
4.3	Massive Ground Plane	3
5	Manufacturing Deliverables	3
6	Conclusion	3

1 Introduction

This document details the design, component selection, and PCB layout rationale for a compact step-down (buck) converter power supply, fulfilling the requirements of Assignment II. The objective is to efficiently convert a 12V DC input to a stable 5V DC output using a switching regulator, specifically the LM2596. Special emphasis is placed on mitigating electromagnetic interference (EMI) through low-noise design practices and minimizing high-current loop areas.

2 Working Principle of the Buck Converter

Unlike a linear regulator that dissipates excess voltage as heat, a buck converter operates by rapidly switching the input voltage on and off. The core components form a dynamic energy transfer system:

- **The Switch (LM2596):** Operates at a fixed frequency (150 kHz), generating a pulse-width modulated (PWM) square wave.
- **The Inductor (L1):** When the switch is closed, current flows through the inductor to the load, storing energy in a magnetic field. When the switch opens, the magnetic field collapses, maintaining current flow to the load.
- **The Catch Diode (D1):** Provides a safe return path (freewheeling) for the inductor current when the switch is open.
- **The Output Capacitor (C2):** Smooths the resulting ripple current into a stable DC voltage.

The output voltage is determined by the duty cycle (D) of the switch: $V_{out} \approx V_{in} \times D$.

3 Component Selection

To achieve a compact design, Surface Mount Devices (SMD) were utilized for all active and passive components, excluding the structural input/output terminal blocks.

- **Regulator IC (U1):** Texas Instruments **LM2596S-5.0** (TO-263-5 package). The fixed 5.0V version was selected to minimize external component count (eliminating the feedback resistor divider) and reduce PCB area.
- **Catch Diode (D1): SS34 Schottky Diode** (SMC package). A standard silicon diode cannot react fast enough to 150 kHz switching. The SS34 provides a fast recovery time, a low forward voltage drop, and safely handles the 3A maximum current.
- **Inductor (L1):** 33 μH Power Inductor (12 $\times$ 12 mm footprint). Sized according to the manufacturer's datasheet for a 12V to 5V conversion at 3A.
- **Filter Capacitors (C1, C2):** Low-ESR electrolytic capacitors (680 μF input, 220 μF output) to properly absorb switching transients without overheating.

4 Low-Noise PCB Layout Rationale

The primary engineering challenge in switching converters is managing Electromagnetic Interference (EMI). Rapidly changing currents (di/dt) create magnetic noise, and rapidly changing voltages (dv/dt) create capacitive coupling noise. The PCB layout was strictly engineered to mitigate these issues:

4.1 Short High-Current Loops

The most critical path in a buck converter is the input loop (Input Capacitor $\rightarrow$ Switch $\rightarrow$ Diode $\rightarrow$ Ground). This loop sees the most violent, discontinuous current pulses. To minimize parasitic inductance and prevent the circuit from acting as a loop antenna:

1. The components were placed in a strict **Left-to-Right linear flow** ($J2 \rightarrow C1 \rightarrow U1/D1/L1 \rightarrow C2 \rightarrow J1$).
2. The input capacitor ($C1$) was placed immediately adjacent to the V_{in} pin of the LM2596.
3. The Schottky diode ($D1$) was positioned intimately close to the Switch Node (Pin 2) and the Ground (Pin 3).

4.2 Switch Node Optimization

The copper area connecting Pin 2 of the IC, the cathode of the diode, and the inductor is the noisiest part of the board. The trace was kept wide enough to handle 3A, but physically constrained to the smallest possible surface area to prevent it from radiating EMI.

4.3 Massive Ground Plane

Instead of routing thin traces for the ground connections, a continuous copper pour (F.Cu) was utilized across the entire board. This serves three vital functions:

1. Provides the lowest possible impedance path for return currents.
2. Acts as an electromagnetic shield.
3. Serves as an integrated heatsink for the LM2596's TO-263 thermal tab.

5 Manufacturing Deliverables

The layout was finalized with commercial manufacturing standards in mind:

- **Trace Widths:** Power traces were widened (minimum 1.5 mm - 2.0 mm) to safely carry continuous high currents without thermal degradation.
- **Silkscreen Labels:** Clear polarity markings and “IN 12V” / “OUT 5V” labels were added to the F.Silkscreen layer to prevent user error during installation.
- **Mounting:** Four 3.2mm M3 mounting holes were integrated into the corners of the board for secure mechanical enclosure integration.

All required Gerber files, Excellon drill files, and the Bill of Materials (BOM) have been generated and committed to the project repository.

6 Conclusion

The step-down converter was successfully designed to meet both the electrical and physical constraints of the assignment. By strictly adhering to low-noise layout practices and utilizing a compact SMD architecture, the resulting PCB is robust, thermally efficient, and ready for fabrication.