

**AC-ENTRY**

Diagram illustrating AC-ENTRY protection components and connections:

- Path 1 (Left):** N\_ACDC\_1 → JACL1 → STUD-M8 → JACL2 → STUD-M8 → JACL3 → STUD-M8.
- Path 2 (Middle):** PE → JPE → STUD-M8.
- Path 3 (Right):** N\_ACDC\_1 → F1 → FUSE-gG-690V → LF1.
- Path 4 (Right):** N\_ACDC\_2 → F2 → FUSE-gG-690V → LF2.
- Path 5 (Right):** N\_ACDC\_3 → F3 → FUSE-gG-690V → LF3.

**SURGE**

Diagram illustrating SURGE protection components and connections:

- Path 1 (Left):** N\_ACDC\_4 → GDT1 → PE.
- Path 2 (Middle):** N\_ACDC\_5 → GDT2 → PE.
- Path 3 (Right):** N\_ACDC\_6 → GDT3 → PE.
- Path 4 (Left):** LF1 → MOV1 → S20K550 → LF2.
- Path 5 (Middle):** LF2 → MOV2 → S20K550 → LF3.
- Path 6 (Right):** LF3 → MOV3 → S20K550 → LF1.

**AC-ENTRY**

Diagram illustrating AC Entry Protection components and connections:

- Input 1:** N\_ACDC\_1 connects to JACL1, then through STUD-M8 to JPE, and finally through FUSE-gG-690V (F1) to LF1.
- Input 2:** N\_ACDC\_2 connects to JACL2, then through STUD-M8 to JPE, and finally through FUSE-gG-690V (F2) to LF2.
- Input 3:** N\_ACDC\_3 connects to JACL3, then through STUD-M8 to JPE, and finally through FUSE-gG-690V (F3) to LF3.

**SURGE**

Diagram illustrating Surge Protection components and connections:

- Input 4:** N\_ACDC\_4 connects to MOV3, then through S20K550 to LF1.
- Input 5:** N\_ACDC\_5 connects to MOV1, then through S20K550 to LF2.
- Input 6:** N\_ACDC\_6 connects to MOV2, then through S20K550 to LF3.

**EMI-FILTER**

**CMC1**

LF1 1 A1  
AC1M 2 B1  
LF2 3 A2  
AC2M 4 B2  
LF3 5 A3  
AC3M 6 B3

CMC-3PH-2mH-SKU

**CMC2**

AC1M 1 A1  
AC1D 2 B1  
AC2M 3 A2  
AC2D 4 B2  
AC3M 5 A3  
AC3D 6 B3

CMC-3PH-2mH-SKU

**CX11**  
2.2uF  
AC1M 1 2 AC2M

**CX12**  
2.2uF  
AC2M 1 2 AC3M

**CX13**  
2.2uF  
AC3M 1 2 AC1M

**CX21**  
2.2uF  
AC1 1 2 AC2

**CX22**  
2.2uF  
AC2 1 2 AC3

**CX23**  
2.2uF  
AC3 1 2 AC1

**CY1**  
4.7nF  
AC1 1 2 PE

**CY2**  
4.7nF  
AC2 1 2 PE

**CY3**  
4.7nF  
AC3 1 2 PE

**LDM1**  
DM-22u-SKU  
AC1D 1 2 AC1

**LDM2**  
DM-22u-SKU  
AC2D 1 2 AC2

**LDM3**  
DM-22u-SKU  
AC3D 1 2 AC3

DC-Modules – 30 kW module

Sheet: /

File: acdc-INPUT-EMI.kicad\_sch

**Title: 30kW ACDC 1of6 INPUT-EMI**

|                     |                  |          |
|---------------------|------------------|----------|
| Size: User          | Date: 2026-09-05 | Rev: D.1 |
| KiCad E.D.A. 10.0.6 |                  | Id: 1/1  |

Id: 1/1