

## **Exp No: 3- 7-Segment Display using AT89C51**

### **Objectives:**

1. To interface a 7-segment display with the AT89C51.
2. To display decimal digits using a 7-segment display.
3. To understand output display interfacing.

### **Program:**

ORG 000H

UP:MOV P2,#0C0H

ACALL DELAY

MOV P2,#0F9H

ACALL DELAY

MOV P2,#0A4H

ACALL DELAY

MOV P2,#0B0H

ACALL DELAY

MOV P2,#99H

ACALL DELAY

MOV P2,#92H

ACALL DELAY

MOV P2,#82H

ACALL DELAY

MOV P2,#0F8H

ACALL DELAY

MOV P2, #80H

ACALL DELAY

MOV P2,#90H

ACALL DELAY

DELAY: MOV R5,#10

H1:MOV R4,#180

H2:MOV R3,#255

H3:DJNZ R3,H3

DJNZ R4,H2

DJNZ R5,H1

RET

END

**Output:**

