

Fault Code: 4688

Water in Fuel Indicator Sensor Circuit - Voltage Above Normal or Shorted to High Source

 Printable Version

Overview

Codes	Reason	Effect
Fault Code: 4688 PID(P): SPN: 97 FMI: 3 Lamp: Maintenance SRT:	Water in Fuel Indicator Sensor Circuit - Voltage Above Normal or Shorted to High Source. High voltage detected at the water in fuel indicator circuit.	None on performance. No water in fuel warning available.



Water in Fuel Indicator Sensor Circuit

Circuit Description

The water in fuel indicator sensor is fitted by the original engine manufacturer (OEM). The water in fuel indicator sensor sends a signal to the engine control module (ECM) when a set volume of water has accumulated in the fuel filter. The water in fuel indicator sensor circuit contains two wires: a water in fuel indicator RETURN (sensor return 1) ground wire and a water in fuel indicator SIGNAL wire.

Component Location

The water in fuel indicator sensor is mounted by the original equipment manufacturer (OEM). Refer to the OEM service manual.

Shoptalk

There are multiple ECMs for the engine models included in this manual. Each ECM has an individual source address that displays when INSITE™ electronic service tool is connected. . When troubleshooting a fault code, use the source address displayed in INSITE™ electronic service tool to determine which ECM and circuit is affected.

Possible causes of this fault code include:

- Open return or signal circuit in the harness, connectors, or sensor
- SIGNAL wire shorted to sensor supply or battery voltage.

Refer to Troubleshooting Fault Code t05-4688. (</qs3/pubsys2/xml/en/procedures/122/122-t05-4688.html>)