

Module : ARM

Total Marks : 25

A) MCQ's

1) _____ register classifies each of the 32 interrupt requests as contributing to FIQ or IRQ.

a) VICIntEnable b) VICVectAddr c) VICIntSelect d) None of these

Ans: c

2) The start condition followed by the _____ sequence of bits leads to 10 bit addressing mode in I2C.

a) 1010 b) 11110 c) 10110 d) 11111

Ans: b

3) In ARM7 register set _____ is Stack Pointer.

a) R15 b) R14 c) R13 d) None of these

Ans : c

4) How to select 8N1 frame in UART0 ?

a) U0LCR=0x03 b) U0LCR=0x01 c) U0LCR=0x80 d) None of these

Ans : a

5) _____bit allows differentiation between standard and extended frames.

a) DLC b) SOF c) IDE d) RB0

Ans : c

6) External interrupts are triggered in_____ modes in LPC2129.

- a) 7 b) 4 c) 8 d) 32

Ans : b

7) In CAN extended data frame , the message id is _____ bits.

- a) 11 b) 13 c) 29 d) 3

Ans : c

8) How to select raising-edge sensitivity for external interrupt0 in LPC2129?

- | | |
|---------------------------------------|---------------------------------------|
| a) EXTMODE=0x01;
EXTPOLAR=0x00; | b) EXTMODE=0x01;
EXTPOLAR=0x01; |
| c) EXTMODE=0x00;
EXTPOLAR=0x00; | b) EXTMODE=0x00;
EXTPOLAR=0x01; |

Ans : b

9) How to select P0.0 as TXD0 and P0.1 as RXD0 in UART ?

- a) PINSEL0=0x0000 0001 b) PINSEL1=0x0000 0005
c) PINSEL0=0x0000 0005 d) PINSEL1=0x0000 0001

Ans : c

10) The current state of the port pins can always be read from _____ register, regardless of pin direction and mode.

- a) IOSET b) IOCLR c) IOPIN d) All of these

Ans : c

11) CG RAM is _____ bytes , allowing for _____ 5x8 pixel, character patterns to be defined in LCD.

a) 80, 64 b) 64, 80 c) 64,8 d) 80,8

Ans : c

12) CAN protocol is using _____ and _____ layers of OSI.

Ans : data link and physical

13) _____ register holds the address of the ISR for Non-vectorized IRQ's.

Ans : VICDefVectAddr

14) To generate the delay of 500milliseconds _____ value to be loaded into T0PR.

Ans : 7500000

15) To clear the EINT1 Flag in _____ register _____ bit has to be set.

Ans : EXTINT, 1st bit

16) Explain Decode stage in pipelining.

Ans : Identifies the type of instruction.

17)What happens when T0TCR is loaded with 0x01 ?

Ans : T0PC and T0TC are enabled for counting.

18) _____ is the command for Display On , Cursor On in LCD.

Ans : 0x0E

19) Allocate slot 2 to external interrupt1 in LPC2129 (2M)

Ans) VICVectCntl2 = (0x20)|15;

C) Descriptive

5M

1) Write an ECP to repeatedly transmit 'A' serially through UART0 using Interrupt Method ?

