RAJALAKSHMI ENGINEERING COLLEGE

Vijay Karthick S 251001301-2025-IT

V2

Started on	Wednesday, 5 August 2026, 9:12 AM
State	Finished
Completed on	Wednesday, 19 August 2026, 9:23 AM
Time taken	14 days
Marks	1.00/1.00
Grade	**10.00** out of 10.00 (**100**%)

Question 1 | Correct Mark 1.00 out of 1.00

Convert the following algorithm into a program and find its time complexity using the counter method.

```
void func(int n)
{
    if(n==1)
    {
      printf("*");
    }
    else
    {
     for(int i=1; i<=n; i++)
     {
       for(int j=1; j<=n; j++)
       {
          printf("*");
          printf("*");
          break;
       }
     }
   }
 }
```

Note: No need of counter increment for declarations and scanf() and count variable printf() statements.

Input:

A positive Integer n

Output:

Print the value of the counter variable

Answer: (penalty regime: 0 %)

```c
#include<stdio.h>

void func(int n){
    int count=0;

    if(n==1){
        //printf("*");
    }
    else{
        count++;
        for(int i=1;i<=n;i++){
            count++;
            count++;
            for(int j=1;j<=n;j++){
                count++;
                //printf("*");
                //printf("*");
                count++;
                break;
            }
            count++;
        }
        count++;

    }
    printf("%d",count);

}
```

```
29 int main(){
30     int n;
31     if(scanf("%d",&n)==1){
32         func(n);
33     }
34     return 0;
35 }
```

	Input	Expected	Got	
✔	2	12	12	✔
✔	1000	5002	5002	✔
✔	143	717	717	✔

Passed all tests! ✔

Correct

Marks for this submission: 1.00/1.00.

Back to Course