

Exp No: 18 GENERATION OF PWM USING TIMER INTERRUPT

DATE: 18/08/2026

PROGRAM:

C:\Keil_v5\C51\Examples\HELLO\EMBEDDED C\EXP11\EXP18.uvproj - µVision

File Edit View Project Flash Debug Peripherals Tools SVCS Window Help

Project: EXP18

- Target 1
 - Source Group 1

```
1 #include<reg51.h>
2 sbit PWM=P1^0;
3 unsigned char count=0;
4 unsigned char duty=150;
5 void timer0_ISR(void) interrupt 1
6 {
7     TH0=0xFC;
8     TL0=0x66;
9     count++;
10    if(count<duty)
11        PWM=1;
12    else
13        PWM=0;
14    if(count>=200)
15        count=0;
16 }
17 void main()
18 {
19     TMOD=0x01;
20     TH0=0xFC;
21     TL0=0x66;
22     IE=0x82;
23     TR0=1;
24     while(1);
25 }
```

Build Output

linking...
Program Size: data=11.0 xdata=0 code=213
".\Objects\EXP18" - 0 Error(s), 0 Warning(s).
Build Time Elapsed: 00:00:00

