

Task: Simple Banking Operations using switch Case

Create a Java program that simulates simple banking operations like checking balance, depositing money, and withdrawing money using a switch case statement.

Requirements:

Use the Scanner class to accept user input

Use switch case to perform operations based on the user's menu choice.

Maintain a balance variable that gets updated based on operations

Handle invalid inputs gracefully

Sample Output:

Welcome to ABC Bank

1. Check Balance

2. Deposit Money

3. Withdraw Money

4. Exit

Enter your choice: 2

Enter amount to deposit: 5000

Deposit successful!

Enter your choice: 1 Your current balance is: ₹5000

Enter your choice: 3

Enter amount to withdraw: 2000 Withdrawal successful

Enter your choice: 1 Your current balance is: 3000

Enter your choice: 4 Thank you for using ABC Bank!

```
package wirpotra;

import java.awt.Choice;

import java.util.Scanner;

public class Task2 {

    public static void main(String[] args) {

        Scanner sc=new Scanner(System.in);

        int balance=0;

        int choice;

        System.out.println("Welcome to ABC bank");

        System.out.println("1. check balance");

        System.out.println("2. Deposit money");

        System.out.println("3. withdraw money");

        System.out.println("4. Exit");

        System.out.println("Enter your choice");

        do {

            choice=sc.nextInt();

            switch(choice)

            {

                case 1:

                    System.out.println("your current balance"+balance);

                    break;

                case 2:

                    System.out.println("enter amount to deposit:");

                    int amount=sc.nextInt();

                    balance=balance+amount;

                    System.out.println("Deposite successful");

                    break;

                case 3:

                    System.out.println("Enter amount to withdraw:");

                    int withdraw=sc.nextInt();

                    balance=balance-withdraw;

                    System.out.println("Withdraw successfull");

                    break;

                case 4:
```

```
System.out.println("Thank youb using ABC Bank!");

    break;

default:

    System.out.println("Invalid choic");

}

}while(choice!=4);

sc.close();

}

}
```