

Exp No: 1

FLASHING OF LED USING AT89C51 MICROCONTROLLER USING PROTEUS

OBJECTIVES

- To understand the working of the AT89C51 microcontroller.
- To write and execute an assembly language program for LED flashing.
- To simulate and verify the LED blinking operation using Proteus 8.

PROGRAM

ORG 0000H

UP: SETB P2.0

ACALL DELAY

CLR P2.0

ACALL DELAY

SJMP UP

DELAY: MOV R4,#35

H1:MOV R3,#255

H2:DJNZ R3,H2

DJNZ R4,H1

RET

END

OUTPUT

