Network Cable And Connectors


1. Cat6 Ethernet Cable Diagram (T568B Standard & RJ-45 Pins)

The diagram below details the pin order (Pins 1–8), the T568B color codes, and the RJ-45 8P8C modular connector contacts:

T568B Wire Sequence Table

Pin #	Wire Color Code	Signal Role (Gigabit Full-Duplex)
Pin 1	**White / Orange Stripe**	Transmit Positive (Tx+)
Pin 2	**Solid Orange**	Transmit Negative (Tx-)
Pin 3	**White / Green Stripe**	Receive Positive (Rx+)
Pin 4	**Solid Blue**	Bi-directional / PoE
Pin 5	**White / Blue Stripe**	Bi-directional / PoE
Pin 6	**Solid Green**	Receive Negative (Rx-)
Pin 7	**White / Brown Stripe**	Bi-directional / PoE
Pin 8	**Solid Brown**	Bi-directional / PoE

- **Orientation Tip:** Hold the RJ-45 plug with the gold contact pins facing up toward you and the plastic latch pointing down away from you. **Pin 1 is always on the far left**.



2. Three Types of Network Cables, Real-World Devices & Justification

Cable Type	Real-World App / Device	Why It Is Used
1. Cat5e Copper UTP	**Zomato POS Terminal / Billing Counter**	POS terminals and receipt printers only transfer lightweight transaction payloads (a few kilobytes). Cat5e provides up to 1 Gbps over distances under 100 meters at the lowest cable cost.
2. Cat6 / Cat6a UTP	**Home / Office Wi-Fi 6 Router & Gaming Rigs**	Cat6 features tighter wire twists and a central spline separator to reduce crosstalk. It supports 1 Gbps to 10 Gbps bandwidth at 250 MHz, ensuring low ping and no packet loss for 4K streaming and low-latency gaming.
3. Fiber Optic (Single-Mode / Multi-Mode)	**IPL Live Streaming Cloud Servers / ISP CDN**	Streaming high-definition cricket to millions of concurrent viewers demands massive aggregate throughput (10 to 100+ Gbps). Fiber optic cables carry light pulses over glass, allowing multi-gigabit data to travel kilometers without signal degradation or electromagnetic interference.

3. Step-by-Step RJ-45 Crimping Process & Common Mistakes

Step-by-Step Process:

1. **Strip the Outer Jacket:** Use the wire stripper on the crimping tool to score and remove approximately 1.5 inches1.5\text{ inches}1.5 inches (3–4 cm3\text{–}4\text{ cm}3–4 cm) of the outer PVC cable jacket, taking care not to nick the inner copper wire insulation.
2. **Untwist & Cut the Spline:** Cut away the central plastic cross-spline and rip-cord. Untwist all 4 wire pairs and straighten each individual wire.
3. **Arrange in T568B Order:** Line the wires flat and side-by-side in the T568B sequence:

White-Orange →*rightarrow*→ *Orange* →*rightarrow*→ *White-Green* →*rightarrow*→ *Blue* →*rightarrow*→ *White-Blue* →*rightarrow*→ *Green* →*rightarrow*→ *White-Brown* →*rightarrow*→ *Brown*.

4. **Trim the Wires Flush:** Holding the aligned wires firmly between your thumb and forefinger, use the cutter blade on the crimper to cut the wires straight across, leaving roughly 0.5 inches0.5\text{ inches}0.5 inches (1.2 cm1.2\text{ cm}1.2 cm) of exposed parallel wires.
5. **Insert into RJ-45 Plug:** Slide the wires into the RJ-45 modular connector until all 8 wire ends firmly hit the front edge of the plug underneath the copper pins. Ensure the outer cable jacket enters past the rear strain-relief wedge.
6. **Crimp & Validate:** Insert the RJ-45 plug into the 8P8\text{P}8P crimping die. Squeeze the crimper handles with firm, steady pressure until the ratchet releases, driving the gold-plated pins into the conductors. Test the cable using a network cable continuity tester (all 8 LED lights must flash in sequential order from 1 to 8 on both units).

Two Common Mistakes to Avoid:

1. **Splitting the Pair Order (Pins 3 & 6 Mismatch):** Mixing up **Pin 3 (White-Green)** and **Pin 6 (Solid Green)** around the Blue pair is the most common error. If Green is placed next to White-Green (like the Orange pair), the cable fails Gigabit transmission tests.
2. **Stripping Too Much Jacket (Exposed Conductors Outside the Plug):** If more than 0.5 inches0.5\text{ inches}0.5 inches of jacket is stripped, the outer jacket will sit outside the connector rather than under the internal retaining wedge. Over time, tugging on the cable will pull the conductors out of their pins.


4. Scenario: Gaming Zone for an IPL Screening Event

- **Selected Cable Type: Category 6 (Cat6) Shielded / High-Grade UTP Ethernet Cable**.
- **Selected Connector Type: RJ-45 (8P8C) Modular Connectors with Strain-Relief Boots** (and **High-Speed HDMI 2.1** for direct video feeds to large displays).

Technical Justification:

- **High Throughput & Low Latency:** A gaming zone with multiple consoles (PlayStation/Xbox/PCs) requires low-latency packet transmission to avoid in-game lag and input delay. Cat6 handles 1 Gbps1\text{ Gbps}1 Gbps to 10 Gbps10\text{ Gbps}10 Gbps with 250 MHz250\text{ MHz}250 MHz bandwidth, easily supporting simultaneous multiplayer games and local network matches.
- **Resistance to Interference (Crosstalk):** Running dozens of cables alongside heavy power cords for large screening displays and sound amplifiers generates electromagnetic interference (EMI). Cat6 includes internal pair separation (spline), ensuring clean signal transmission without packet drops.
- **Durability & Quick On-Site Repair:** Standard RJ-45 terminations can be custom-cut to exact lengths on site and repaired quickly with an inexpensive crimping tool if a cable is tripped over or damaged during the event.

5. Network Cable in Real-World Use (Photo Documentation)



The documentation and photo breakdown below illustrate a network cable in active use:

- **Cable Type: Category 6 (Cat6) Unshielded Twisted Pair (UTP) Ethernet Cable** (blue PVC jacket, 23 AWG 4-pair solid copper).
- **Connector Type:** Clear **RJ-45 (8P8C)** modular plug with an integrated snagless strain-relief boot.
- **Devices Being Connected:**
    - **Device 1 (Source):** The Gigabit Ethernet LAN port of an optical fiber ONT modem.
    - **Device 2 (Destination):** The dedicated blue **WAN (Internet)** port of a home Wi-Fi 6 router.
- **Description of Function:** The cable transfers the incoming high-speed internet data stream from the fiber modem directly to the Wi-Fi router's WAN port. The router then executes Network Address Translation (NAT), handles DHCP addressing, and broadcasts the bandwidth wirelessly to household smartphones, laptops, and smart TVs. Solid green link LEDs above the connector indicate an active, negotiated 1000 Mbps1000\text{ Mbps}1000 Mbps (Gigabit) uplink.