Name: G.Mukkesh Reg No: 17BCE1128 Faculty: Prof. Thoma Abraham

OS LAB WEEK – 6 Kernel Manipuation

Objective: To create our own Kernel Module, and insert it into the operating system. We also view the log file entries to check for the modified kernel's printed message.

Code for the kernel file (17bce1128.c):

Now, to compile this into the KO file, we need to write a Makefile.

Makefile code:

```
obj-m += 17bce1128.o
all:
    make -C /lib/modules/$(shell uname -r)/build M=$(PWD) modules
clean:
    make -C /lib/modules/$(shell uname -r)/build M=$(PWD) clean
```

When make is executed on the terminal, the 17bce1128.ko file is created. This is our compiled kernel code. Now, we can insert this by using the insmod command, and remove it by using the rmmod command. These methods will also lead to the printk() values being stored in the log files. They can be viewed by the dmesg | tail -1 method.

Additionally, the Kernel's info can be viewed by the modinfo command.

Name: G.Mukkesh Reg No: 17BCE1128 Faculty: Prof. Thoma Abraham

Output:

```
root@mex:/home/mukkesh/Desktop# make
make -C /lib/modules/4.15.0-20-generic/build M=/home/mukkesh/Desktop modules
make[1]: Entering directory '/usr/src/linux-headers-4.15.0-20-generic'
  CC [M] /home/mukkesh/Desktop/17bce1128.o
  Building modules, stage 2.
 MODPOST 1 modules
        /home/mukkesh/Desktop/17bce1128.mod.o
 CC
 LD [M] /home/mukkesh/Desktop/17bce1128.ko
make[1]: Leaving directory '/usr/src/linux-headers-4.15.0-20-generic'
root@mex:/home/mukkesh/Desktop# insmod 17bce1128.ko
root@mex:/home/mukkesh/Desktop# dmesg | tail -1
[ 1971.886263] Hello. This is the work of G.Mukkesh (17BCE1128)
root@mex:/home/mukkesh/Desktop# modinfo /home/mukkesh/Desktop/17bce1128.ko
               /home/mukkesh/Desktop/17bce1128.ko
filename:
description:
               Modified kernel
              G.Mukkesh 17BCE1128
author:
license:
              GPL
srcversion:
              12704A8D3F95B53E6F31D03
depends:
retpoline:
name:
               17bce1128
               4.15.0-20-generic SMP mod unload
vermagic:
root@mex:/home/mukkesh/Desktop# rmmod 17bce1128.ko
root@mex:/home/mukkesh/Desktop# dmesg | tail -1
[ 2070.001366] Removing all
```