

Mnemônico	Opcode [4..0]					N	Z	WrPC	SelA1	SelA0	SelB	WrAcc	OpSel
HLT	0	0	0	0	0	X	X	0	X	X	X	0	X
STO	0	0	0	0	1	X	X	1	X	X	X	0	X
LD	0	0	0	1	0	X	X	1	0	0	X	1	X
LDI	0	0	0	1	1	X	X	1	0	1	X	1	X
ADD	0	0	1	0	0	X	X	1	1	0	0	1	0
ADDI	0	0	1	0	1	X	X	1	1	0	1	1	0
SUB	0	0	1	1	0	X	X	1	1	0	0	1	1
SUBI	0	0	1	1	1	X	X	1	1	0	1	1	1
BEQ	0	1	0	0	0	X	0	1	X	X	X	0	X
	0	1	0	0	0	X	1	1	X	X	X	0	X
BNE	0	1	0	0	1	X	0	1	X	X	X	0	X
	0	1	0	0	1	X	1	1	X	X	X	0	X
BGT	0	1	0	1	0	0	0	1	X	X	X	0	X
	0	1	0	1	0	0	1	1	X	X	X	0	X
	0	1	0	1	0	1	0	1	X	X	X	0	X
	0	1	0	1	0	1	1	1	X	X	X	0	X
BGE	0	1	0	1	1	0	X	1	X	X	X	0	X
	0	1	0	1	1	1	X	1	X	X	X	0	X
BLT	0	1	1	0	0	0	X	1	X	X	X	0	X
	0	1	1	0	0	1	X	1	X	X	X	0	X
BLE	0	1	1	0	1	0	0	1	X	X	X	0	X
	0	1	1	0	1	0	1	1	X	X	X	0	X
	0	1	1	0	1	1	0	1	X	X	X	0	X
	0	1	1	0	1	1	1	1	X	X	X	0	X
JMP	0	1	1	1	0	X	X	1	X	X	X	0	X